HP 3000 Computer Systems

HEWLETT PACKARD

MPE V Tables Manual for MPE V/E, Version G.00.00



HP 3000 Computer Systems

MPE V TABLES MANUAL
for MPE V/E, Version G.00.00

HEWLETT PACKARD
19447 PRUNERIDGE AVENUE, CUPERTINO, CA 95014

Part No. 32033-90010
E2412

Printed in U.S.A. 09/84

CAUTION

The normal checks and limitations that apply to the standard MPE users are bypassed in Privileged Mode. It is possible for a Privileged Mode program to destroy file integrity including the MPE operating system software itself. Upon request Hewlett-Packard will investigate and attempt to resolve problems resulting from the use of Privileged Mode code. This service is available on a time and materials billing basis. However, Hewlett-Packard will not support, correct, or attend to any modifications of the MPE operating system software.

NOTICE

The information contained in this manual is proprietary and may not be disclosed to third parties. The terms and conditions of release of this information to the recipient are governed by the agreement executed at and between Hewlett-Packard and the recipient regarding the HP 3000 internal MPE V System Table Structures, including the MPE V Tables Manual for MPE V Operating System.

Hewlett-Packard does not warrant the accuracy or completeness of the information contained in this manual. Hewlett-Packard may make revisions to the MPE operating system or CPU firmware that may affect the information and specifications contained herein. Hewlett-Packard shall have no obligation to provide the recipient with notification of revisions, corrections, or updates regarding the information contained herein.

Hewlett-Packard shall not be responsible for any loss or damage to the recipient, its customers, or any third party caused by the recipient's use of the information provided herein.

LIST OF EFFECTIVE PAGES

The List of Effective Pages gives the date of the current edition, and lists the dates of all changed pages. Unchanged pages are listed as "ORIGINAL". Within the manual, any page changed since the last edition is indicated by printing the date the changes were made on the bottom of the page. Changes are marked with a vertical bar in the margin. If an update is incorporated when an edition is reprinted, these bars and dates remain. No information is incorporated into a reprinting unless it appears as a prior update.

First Edition . . . . . September 1984

Effective Pages	Date
ALL	SEP 1984

PRINTING HISTORY

New editions are complete revisions of the manual. Update packages, which are issued between editions, contain additional and replacement pages to be merged into the manual by the customer. The date on the title page and back cover of the manual changes only when a new edition is published. When an edition is reprinted, all the prior updates to the edition are incorporated. No information is incorporated into a reprinting unless it appears as a prior update.

The software date code number printed alongside the date indicates the version level of the software product at the time the manual edition or update was issued. Many product updates and fixes do not require manual changes, and conversely, manual corrections may be done without accompanying product changes. Therefore, do not expect a one-to-one correspondence between product updates and manual updates.

First Edition . . . . . SEP 1984 . . . . . G.00.00

CONTENTS

CONTENTS (Continued)

CONTENTS (Continued)

CHAPTER 6 FILE SYSTEM

CHAPTER 7 PROCESS TABLES

CONTENTS (Continued)

CHAPTER 8 JOB TABLES

CHAPTER 9 RELOCATABLE OBJECT CODE

CHAPTER 10 PREPARED OBJECT CODE

CHAPTER 11 LOADER

CONTENTS (Continued)

CHAPTER 14 SPOOLING

CONTENTS (Continued)

CONTENTS (Continued)

CONTENTS (Continued)

CONTENTS (Continued)

CHAPTER 22 DISC FREE SPACE MAP

CHAPTER 23 MPE DISC CACHING

PREFACE

This manual describes the internal table organization of the MPE V operating system, release G.00.00. The Tables Manual is an informational reference for the technically sophisticated user with Privilege Mode capability. We strongly discourage modifying the table structure because you may destroy the operating system. The following caution applies:

CAUTION

> The normal checks and limitations that apply to the standard MPE users are bypassed in Privileged Mode. It is possible for a Privileged Mode program to destroy file integrity including the MPE operating system software itself. Upon request Hewlett-Packard will investigate and attempt to resolve problems resulting from the use of Privileged Mode code. This service is available on a time and materials billing basis. However, Hewlett-Packard will not support, correct, or attend to any modifications of the MPE operating system software.

The table structure of MPE V is significantly expanded from MPE IV. The operating system reflected in the table structure is the Fundamental Operating Software (FOS) version of MPE V. Your table structure may look different depending on the applications and uses of your system.

The information is presented in several different formats. This reflects the combined knowledge of several divisions and groups within Hewlett-Packard. Instead of taking the time to consolidate all the various formats, we chose to release the information quickly.

We hope you will find this edition informative. Your comments and suggestions are welcome via the "Reader Comment Sheet" at the back of this manual.

CHAPTER 1 MEMORY LAYOUT

Fixed Low Memory (Series 44/48/64/68)

%		DEC
0	CSTB (BASE OF CST TABLE)**	0
1	XCSTB (POINTER TO CURRENT EXECUTING PROGRAM BLOCK)	1
2	DSTB (BASE OF DST TABLE)**	2
3	0	3
4	CPCB (CURRENT PCB INDEX)**	4 >PCB REL
5	QI (INITIAL Q FOR ICS)**	5
6	ZI (INITIAL Z FOR ICS)**	6
7	SYSTEM INTERRUPT MASK WORD**	7
10	DRTBANK (BANK OF DRT TABLE)	8
11	DRTADDR (BASE OF DRT TABLE)	9
12	DBBANK (FOR INITIAL'S STACK) *	10
13	DB (FOR INITIAL'S STACK) *	11
14		12
15		13
16		14
17		15
20		16
21	LR (INTERRUPT INTERVAL)+	17
22	TEMPLR (TEMP STORAGE OF LIMIT REG)+	18
23	LR (SYSTEM CLOCK LIMIT REGISTER) **	19
24	//	20

Fixed Low Memory (Series 44/48/64/68) (Cont.)

25	TR (TIME SINCE LAST SOFT TIMER INTERRUPT)**	21
26	SCST (SYSTEM CLOCK STATUS)**	22
27	SCLC (SYSTEM CLOCK LAST COUNT)**	23
30-37		24-31

NOTE: All pointers are absolute addresses.

LEGEND: ** Needed by Firmware and/or by System, always
* Needed during INITIAL
\+ Needed by MPE, set up by INITIAL or PROGENITOR.

System Global Area

OCTAL	1 2 3 4 5 6 7 8 9 10 11 12 13 14 15	NAME
0	SYSGLOB	
1	CST BASE	CST
2	DST BASE	DST
3	PCB BASE	PCB
4	SWAPTAB BASE	SLL
5	IOQ BASE	IOQ
6	SBUF BASE	BUF
7	ICS QI	ICS
10	LPDT BASE	LPDT
11	SMON BASE	SMON
12	TRL BASE	TRL
13	JCUT BASE	SIR
14	SIR BASE	SOCTAB
15	JPCNT BASE	JPCNT
16	TBUF BASE	BUF
17	DISC REQUEST BASE	DRQ
20 21	FIRST FREE MEMORY ADDRESS	
22 23	TIME OF LAST CYCLE	
24	RESERVED	
25	Break Point Flag	BPTF

System Global Area (Cont.)

26	VDSMTAB BASE	VDSMTAB
27	STATIC FENCE	
30	CURRENT CST BLOCK INDEX	CSTBX
31	MEASIO BASE	MEASIO
32	DISPLACEMENT TO CODE =@CST(0)-@DST(0)	OFC
33	DISPLACEMENT TO SHARABLE = @CST(LAST)-@DST(0)	OFS
34	Smon Index	
35	ABS ADDRESS (SYSDIT(8))	DIT8
36	Reserved	SBANK
37	ABS ADR OF PMBC TABLE FOR LST/STT CHECKING	SBASE
40	RESERVED FOR INITIAL (VDSENTRY)	
41	RESERVED FOR INITIAL (VDSMAP)	
42	SRTTAB BASE	SRTTAB
43	SPECO HEAD	SPECOHEAD
44	Number of Available Regions	HOLECOUNT
45	# PAGES IN LARGEST CURRENTLY AVAILABLE REGION	MAXAVAILREG
46	MAKE OVERLAY CANDIDATE INFORMATION	MOCINFO
47	NUMBER OF MEMORY BANKS CONFIGURED -1	NBANKS
50	SCHEDULER TO AWAKE MESSAGE	SCHEDTOAWAKEMSG
51	POINTER TO CSTBLK TABLE	CSTXBLCKPOINTER
52	AWAKE TO SCHEDULER MESSAGE	AWAKETOSCHEDMSG
53	WAIT TO SCHEDULER MESSAGE	
54	CURRENT ACTIVITY'S PRIORITY	CURACTPRI

System Global Area (Cont.)



System Global Area (Cont.)



System Global Area (Cont.)



System GIobal Area (Cont.)



System Global Area (Cont.)

LOGGING	210	(TOTAL # LOG RECORDS MISSED)	
	211	(DUE TO LOG FAILURE)	
	212	TOTAL# RECORDS MISSED - "JOB INITIATION" LOSS	
	213	TOTAL# RECORDS MISSED - "JOB TERMINATION" LOSS	
	214	OPERATOR CONSOLE JOBSESSION $ RT STARTUP	
	215 216 217	RESERVED FOR KERNEL USE	
	220	MAPPING FIRMWARE FLAG (NON-ZERO=MPE V/E UCODE)	
	221 222	BANK AND ADDRESS OF MAPPING DST (INITIALIZED BY DISPATCHER DURING LAUNCHING A PROCESS)	
	223	TOTAL SEGMENT NUMBER OF CURRENT PROCESS	
	224	TOTAL FREE PHYSICAL DST ENTRIES	
	225	HEAD OF FREE PHYSICAL DST LINK	
	226	XLST DST NUMBER	
	227 247	RESERVED	
	250	HOLE LIST HEAD (BANK)	HLHEAD
	251	HOLE LIST HEAD (ADDRESS)	
	252	HOLE LIST TAIL (BANK)	HLTAIL
	253	HOLE LIST TAIL (ADDRESS)	

System Global Area (Cont.)

SEGMENT TRACE	254	CURRENT WORD COUNT	XOSCOUNT
	255	BUFFER SIZE	BUFFSIZE
	256	MAG TAPE LDEV	LDEV
	257	TRACE SEGMENT EXTERNAL LABEL	TLABEL
	260	STMON	
	261	MEASINFOTABPTR	
	262	MEASUREMENT STATISTICS CLASS MASK	GCLASSENABLED
	263	CLASS 0 STATISTICS BANK NUMBER	MEASSTATXOSBANK
	264	CLASS 0 STATISTICS ADDRESS	MEASSTATXOSBASE
	265 266	SCRH POINT	
	267	MEASFLAGS	**
	270		
KERNEL	271	INDEX OF PCB AT HEAD OF DISPATCHING Q	SYSDISQHEAD
	272	INDEX OF PCB AT TAIL OF DISPATCHING Q	SYSDISPQTAIL
	273	DST # OF CDT TABLE (DISC CACHING)	
	274	BANK # OF THE CDT TABLE (DISC CACHING)	
	275	ADDRESS OF CDT TABLE (DISC CACHING)	
	276	HELP LOGICAL DEVICE NUMBER	
	277	CURRENT LOGON DST	DSTLOGON
	300 301	(STOP) (BITS) (see p. 2-15)	
	302	# PROCESS ENTRIES	
	303		

System Global Area (Cont.)

	304	DEVREC PIN | 2	
	305	%20	
	306	UCOP PIN | 0	
	307	%20	
PROCESS STOP TABLE	310	LOG PIN | 1	
	311	%20	
	312	IOMESS PIN | 3	
	313	%20	
	314	MEMLOG PIN | 4	
	315	%20	
	316	RESERVED	
	317	Reserved	
	320	OS GLOBAL ANTR SEGMENT DST NUMBER	
	321	RESERVED FOR OS/3000 (SET TO ZERO)	
	322	RESERVED FOR OS/3000 (SET TO ZERO)	
	323	SOS LDEV FLABEL	
OS	324	RESERVED FOR OS/3000 (SET TO ZERO)	
	325	RESERVED FOR OS/3000 (SET TO ZERO)	
	326	RESERVED FOR OS/3000 (SET TO ZERO)	
	327	RESERVED FOR OS/3000 (SET TO ZERO)	
	330	DISC STATUS	LAST DISC SIO ERROR
	331	LDEV | DISC	
	332	RONESS	
	333	MAXQUEUE	JOBPRI
	334	DEFAULTQUEUE	

System Global Area (Cont.)

	335	OSCHECK PLABEL	
	336	OSOPEN PLABEL	
	337	OSCLOSE PLABEL	
	340	MRMRGEWRITE CONV. PLABEL	
	341	CONSOLINE' PLABEL	
	342	CXREMOTE PLABEL	
	343	CXOSLINE PLABEL	
	344	CXRFR PLABEL	
	345	OSIMRGE PLABEL	
	346	DEFAULT LABEL TYPE | TAPE LBL AUTO REC FUN	
	347	SYSDB PTR TO TERM INIT CHNL PGM (S30/33 ONLY)	
	350	MP | |SD|	SOFTDEATH FLAG MEM PRESSURE
	351 352	LAST CYCLE DURATION	
	353 354	CYCLE THRESHOLD	
	355	BUG CATCH ENABLE CELL	
	356	MONITOR BUFFER | TIMESTAMP	MONBUFTD
	357	MONITOR BUFFER | TIMESTAMP	MONBUFT1
	360	OSBREAK PLABEL	
	361	Bank of last memory word	LAST MEMORY
	362	Base of last memory word	ADDRESS
	/363	PVPROC PIN	
PRIVATE< VOLUMES	364	PV RECOGNITION COUNT	
	365	VMOUNT FLAGS |AUTO|RLL|ON|	

System Global Area (Cont.)



1401 = DUMPDEVOAT
02 = X
03 = OL
04 = OB - BANK
05 = OB
06 = Q
07 = S

1410 = S - BANK
11 = Z
12 = STATUS
13 = PB - BANK
14 = PB
15 = P
16 = PL
17 = CIR

1420 = MEMORY SIZE
21 = SYSTEM HALT #
22 = ISR

SysGlob Extension

%200 words long; Pointer found at SysOB + %377





SysGlob Extension (Cont.)



SysGlob Extension (Cont.)



* MIOCNT = MEASIOCOUNT (3 BITS)
** MEASFLAGS (15:1) = 1 ==> MONITOR ENABLED

(14:1) = 1 ==> BUFFER FLIP/FLOP
(13:1) = 1 ==> EOT ON MONITOR TAPE

SYSDB Words

System tables may be accessed by using the LST/SST instructions. Pointers have the following format:



Address is the whole word with "Bank" masked out to 00000.

Systems that have MPE V/E microcode (all 6X systems, 4X systems with new boards) can have a non-zero bank number. Systems running pre-MPE V/E microcode can only use bank 0, therefore the pointer will look like:



SysGlob Word Definitions

ADDRESS	NAME	FUNCTION
DB+55	BUSY	- SYSDB relative pointer to BUSY TABLE for I/O resources
DB+56	HEAD	- SYSDB relative pointer to table containing head pointers to I/O resource queues
DB+57	TAIL	- SYSDB relative pointer to table containing head pointers to tail of I/O resource queues
DB+60	SID COUNT	- Number of I/O Programs currently executing
DB+72	POWER FAIL	- 0-no power fail 1-system disc recovery 2-all other disc recovery 3-all other device recovery
DB+73	SYSUP	- System is up and operable
DB+74	CONSLDEVN	- System console logical device number
DB+400	CPU NUMBER	- Set when system aborts

JOBSYNCH job synchronization via jobsynch (sysglob+121(B))

(13:1) - JDBSAEADY - set by DEVREC & MDRGUE (via procedure STRATDEVICE) indicating a ready job. This prevents UCOP from going to a wait state when a job is just made ready.

(15:1) - DEVFREED - set by DEALLOCATE when device count goes to 0.

NOTE - Both bits above used for synchronization of job-made-ready or devicefreed when UCOP is running.

(14:1) - JDBSWAITING- set by UCOP just before waiting if any job is waiting for list device. Signals DEALLOCATE to awake UCOP when a device is freed.

Allow Mask Format

The Allow mask for MPE V is expanded to six words. There is a mask in each user's JIT and in the SYSGLOB area. The Allow mask contains enough bits for a one-to-one correspondence to every present OPERATOR type command, or any future OPERATOR command. When a user is ALLOWed any OPERATOR command or ASSOCIATEd to a device (which will use OPERATOR type commands) then the corresponding bit(s) in the mask in that user's JIT for that command is set. If the ALLOW or ASSOCIATE was done on a global scale, then the bit(s) in the mask of the SYSGLOB area is/are updated.

The following EQUATEs define the mask bit for each operator command.

The first set of commands define the operator commands dealing with devices.

When adding a new command to this set of EQUATEs, be sure to add a corresponding move statement in LOGIMAGE, even if the command will not be logged.

	Word	Bit	#
ABORTIO	0	0	0
ACCEPT	0	1	1
DOWN	0	2	2
GIVE	0	3	3
HEADOFF	0	4	4
HEADON	0	5	5
REFUSE	0	6	6
REPLY	0	7	7
STARTSPOOL	0	B	8
TAKE	0	9	9
UP	0	10	10
MPLINE	0	11	11
OSCONTROL	0	12	12

UPPER LIMIT->DEVICE COMMANDS

ABORTJOB	0	13	13
ALLOW	0	14	14
ALTFILE	0	15	15
ALTJOB	1	0	16
BREAKJOB	1	1	17
DELETE	1	2	18
DISALLOW	1	3	19
JOBFENCE	1	4	20
LIMIT	1	5	21
STOPSPOOL	1	6	22
SUSPENDSPOOL	1	7	23
OUTFENCE	1	B	24
RECALL	1	9	25
RESUMEJOB	1	10	26
RESUMESPOOL	1	11	27
STREAMS	1	12	28
CONSOLE	1	13	29

Allow Mask (Cont.)

	Word	Bit	#
WARN	1	14	30
WELCOME	1	15	31
MOM	2	0	32
MOFF	2	1	33
VMOUNT	2	2	34
LMOUNT	2	3	35
LDISMOUNT	2	4	36
MRJECONTROL	2	5	37
JOBSECURITY	2	6	38
DOWNLOAD	2	7	39
MIOENABLE	2	8	40
MIODISABLE	2	9	41
LOG	2	10	42
FOREIGN	2	11	43
IMF	2	12	44
SHOWCOM	2	13	45
OPENQ	2	14	46
SHUTQ	2	15	47
OISCAPS	3	2	4B

Logging Related Locations



STATE = 0 if respective buffer empty
1 if respective buffer is current
2 if respective buffer is full

FLAGX



SF = 1 if soft failure
HF = 1 if hard failure
BUF = 0 if current log buffer is buffer 0
= 1 if current log buffer is buffer 1
SL = 1 to indicate a switch in log buffers (from 0 to 1 or from 1 to 0)
SO = 1 to indicate shutdown in progress

Process Stop List General Layout



Entry Format



Preassigned Entries

entry #	process	stop bit #
1	devrec	2
2	ucop	0
3	log	1

Initial Memory Allocation

This section is a description of the method used by INITIRL to allocate memory for MPE tables and code segments in MPE V/E. All memory allocated by INITIRL is permanently allocated. All non-core resident code and data is put on disc before exiting INITIRL.

At the most basic level INITIRL will try to build memory to look exactly as diagramed below. There are, however, several ways in which to deviate from this structure. Before going into the sources of these deviations, it is necessary to point out which portions of memory are used by INITIRL during the restart and therefore cannot be used by MPE until INITIRL has finished.

Before INITIRL begins to allocate any memory space, it relocates its core resident code, its code segment swapping area and its stack to the highest configured memory space. Additionally, it uses the last %326 words of bank 0 on series 4x machines for its I/O buffer area and temporary code segment table. After INITIRL has built all of core resident MPE (tables and code), it builds the disc resident MPE tables. Since some of the disc resident tables may be too large to be built in INITIRL's stack, these tables are built in unused memory space. Therefore, in addition to the memory space required for INITIRL's code, INITIRL's stack and core resident MPE, there must be enough space left in which to build the largest of the disc resident tables.

For Series 6x machines with the MPE V/E firmware, INITIRL will build the tables with ">" signs by them out of Bank 0 if necessary. For all other tables, INITIRL will essentially build memory in the order shown below. There may be an unused fragment of memory between the DRT's and the system global area which INITIRL will fill with the smaller tables. Neither the tables marked with an asterisk nor the code segments will ever be put in this area. NOTE: INITIRL will build all tables on 32-word boundaries.

If the system being built by INITIRL is configured with 128K words or 160K words of memory then INITIAL's stack will be in bank 1 (the code also on a 128K word memory size). If INITIRL is occupying part of bank 1 and the space is needed for a core resident MPE code segment or to build a disc resident table then INITIRL will print the error message "ERROR #350 OUT OF MEMORY".

Except for the exceptions stated above, for every allocation of memory INITIRL will first try to allocate any remaining space between the DRT's and SYSDB. It will then try the next available space in bank 0, then the next available space in bank 1. If it were necessary it could continue searching until all all banks were checked for available space.

Immediately before exiting INITIRL, INITIRL lays down all the memory region headers and trailers as shown below. For any one bank of memory there will only be one block of core resident MPE, regardless of its contents. The only block of core resident MPE that does not have a reserved region global header is in bank 0. It does have the reserved region global trailer though. Before placing any code outside bank 0 the first 24 words of every bank (except bank 0) is reserved for the region global header.

Bank 0



Bank 0 (Cont.)



NOTE: The > means these tables can move out of Bank 0 if necessary.

Bank 1



CHAPTER 2 MEMORY MANAGEMENT TABLES

Segment Table Structure

The current location and state of each data segment and loaded code segment is maintained in the Segment Table. This table is partitioned into three separate tables as shown in Figure 2-1. The partitions are based on the segment classes: a segment is a data segment, a segment is a system SL segment, or a segment is part of a program. The structure and format of each partition is described in the following.



Overall ST Structure

Pointers and DST #'s of Segment Table Components

i. DST

% 2 absolute address of entry 0 of the DST. %1002 sysbase relative index of entry 0 of DST. DST number 2 is the OST Table dst #.

ii. CST

% 0 absolute address of entry 0 of System SL. %1001 sysbase relative index of entry 0 of System SL. %1D32 displacement from OST base of entry 0 of System SL (i.e. @CST(last) - @DST(0) = OFS). DST number 4 is the CSTX Table OST #.

iii. CSTX

% 1 absolute address of entry 0 of current program. %1033 displacement from OST base to first CSTX entry SL. OST number 4 is the CSTX Table OST #.

iv. CSTXMAP

%1051 sysbase relative index of entry 0 of CSTXMAP. DST number 43 (%72) is CSTXMAP Table DST #.

Standard Object Identifier Format




```
DBJIDENTIFIER(D).(D:4) ==> TYPE
                        = 0 Object is a Data segment
                        = 1 Object is an SL segment
                        = 2 Object is a Program segment
                        = 3 Object is a Cache Domain

DBJIDENTIFIER(0).(4:12) ==> Program index into CSTXBLK
DBJIDENTIFIER(1).(0:16) ==> Number field:
                                DST, CST, CSTX, or CDT number
```

DST Entry Formats

DST/CST Entry 0 Format



DST General Entry Format

Case (i) OST Entry for a Present Data Segment



Case (ii) DST Entry for an Absent Data Segment



CST Entry Formats

CST General Entry Format

Case (i) CST Entry for a Present SL Segment or CSTX Segment



CASE (ii) CST Entry For Rn Rbsent Segment SL or CSTX Segment



Case (iii) DST/CST Free Entry



Refer to the Logical Segment Table Format in Chapter 11 for more information on XCST.

ST Entry Field Descriptions

R = 1 ==> segment absent
M = 1 ==> segment privileged
R = 1 ==> segment has been referenced
T = 1 ==> segment is being traced
DCV = 1 ==> disc copy is valid
STK = 1 ==> segment is a stack
MOD = 1 ==> a segment modification (exp., contr.) is pending
FWIP= 1 ==> a forced write of this segment is in progress
WMPAGECNT = # of virtual memory pages allocated to this segment
ROC = 1 ==> segment is recoverable overlay candidate
IMI = 1 ==> segment is in motion in
SYS = 1 ==> segment is a system segment
CORE= 1 ==> segment is core resident
WD= 1 ==> write disabled

CSTBLK Format



The table is initialized to minus one in each entry. When selected, the entry is replaced by a DST-relative index to the entry NO of the CST extension block. This is the the overhead entry for the associated program.

Program Blocks and the CSTXMAP

Since programs can be dynamically loaded and unloaded, the segment table must be kept packed or Fragmentation would occur. Thus, the block of ST entries for a program segment begins at an ST entry number that changes if a program which was loaded before it gets unloaded. To manage this dynamic structure, an auxiliary structure, the CSTXMAP is used. A program is identified by its index, CSTXEIX, into this map. The program's current beginning physical ST entry number is equal to equal to CSTMAP (CSTXEIX).

Entry Format - CST Extension Block



The value of CSTXEIX is established when a CST extension block is allocated. This index into the array CSTXMAP is maintained in the PCB of each process sharing the block.

Fixed DST Entry Assignments

DCTRL		DECIMRL	TRBLE NAME
0		0	
1	CST	1	CST
2	DST	2	DST
3	PCB	3	PCB
4	CSTX	4	CSTX
5	SYSTEM GLOBAL AREA	5	SYS
6	CORE	6	CORE
7	ICS	7	ICS
10	SYSTEM BUFFERS	8	SBUF
11	UCOP REQUEST QUEUE	9	UCRQ
12	PROCESS-PROCESS COMMUNICATION TABLE	10	PPCOM
13	I/O QUEUE	11	IOQ
14	TERMINAL BUFFERS	12	TBUF
15	LOGICAL-PHYSICAL DEVICE TABLE	13	LPDT
16	LOGICAL DEVICE TABLE	14	LDT
17	DRIVER LINKAGE TABLE	15	DLT
20	I/O RESOURCE TABLES	16	BUSY, NERD, TRIL
21	SECONDARY MSG TABLE	17	SECMSGTAB
22	LORDER SEGMENT TABLE	18	LST
23	TIMER REQUEST LIST	19	TAL
24	DIRECTORY	20	DDS

DST (Cont.)

OCTAL		DECIMAL	TABLE NAME
25	DIRECTORY SPACE	21	
26	RIN TABLE	22	RIN
27	SWRPTABLE (SLL)	23	SWRPTRB
30	JOB PROCESS COUNT	24	JPCNT
31	JOB MASTER TABLE	25	JMRT
32	TAPE LABEL TABLE	26	VOD
33	LOG TABLE	27	LOGTAB
34	REPLY INFORMATION TABLE	28	RIT
35	VOLUME TABLE	29	VTAB
36	BREAKPOINT TABLE	30	STOP
37	LOG BUFFER1	31	
40	LOG BUFFER2	32	
41	LOG IO TABLE	33	LIOTRB
42	ASSOCIATE TABLE	34	
43	CST BLOCK	35	CSTBLK
44	JOB CUTOFF TABLE	36	JCUT
45	SYSTEM JIT	37	SJIT
46	SPECIRL REQ TABLE	38	SRT
47	VIRTURL DISC SPACE MANAGEMENT TABLE	39	VDSMTAB
50	DEVICE CLASS TABLE	40	DEVCLASS
51	Reserved Kernel	41	

DST (Cont.)

OCTAL		DECIMAL	TABLE NAME
52	ILT	42	ILT
53	SIA TABLE	43	SIA
54	FMAVT	44	FMAVT
55	INPUT DEVICE DIRECT	45	IDD
56	OUTPUT DEVICE DIRECT	46	DDD
57	WELCOME MESSAGE #1	47	LOGONDSTN1
60	WELCOME MESSAGE #2	48	LOGONDSTN2
61	CS DRTR SEGMENT	49	CSTAB
62	PROCESS-JOB CROSS REFERENCE	50	PJXREF
63	SYSTEM JDT	51	SYSJDT
64	COMMAND LOGON OST	52	CILOGDST
65	MOUNTED VOL. SET TRBLE	53	MVTAB
66	PRI.VOL. USER TABLE	54	PVUSER
67	RESERVED KERNEL	55	
70	DISC REQUEST TABLE	56	DISCREQTAB
71	MSG HARBOR TABLE	57	MSGHARBTAB
72	PRIMARY MESSAGE TABLE	58	PRIMMSGTAB
73	MEASUREMENT INFO TABLE	59	MEASINFOTAB
74	FIRST FREE DST	60	

Swap Tables

The SWRPTRB is a core resident memory management table used to keep track of the locality lists of the competing processes. The PCB entry for a process has a SWRPTAB relative pointer to the header entry for the process.

SWAPTAB DST# = 23 (%27)

%1004 System table pointer to SWAPTRB entry 0.

NOTE: The number of entries configured will be 3 greater than the number configured via SYSDUMP. (Entry 0 consumes 3 entries).

SWAPTAB Entry 0 Format

	0 1 2 3 4 5 6 7 8 9 10 11 12 13 14 15	
0	# ENTRIES CONFIGURED	0
1	ENTRY SIZE (6)	1
2	# AVAILABLE ENTRIES	2
3	TABLE RELATIVE INDEX OF FIRST FREE ENTRY	3
4	TABLE RELATIVE INDEX OF LAST FREE ENTRY	4
5	HIGH WATER MARK	5
6	# PRIMARY ENTRIES (D)	6
7	HEAD OF IMPEDED QUEUE (PCB RELATIVE)	7
8	TAIL OF IMPEDED QUEUE (PCB RELATIVE)	10
9	# CURRENTLY IMPEDED PROCESSES	11
10	MAX # OF IMPEDED PROCESSES	12
11	CUMULATIVE # OF IMPEDED PROCESSES	13
12	. . .	14
17		21

SWAPTAB Unassigned Entry Format

	0 1 2 3 4 5 6 7 8 9 10 11 12 13 14 15
0	%100000
1	TABLE RELATIVE INDEX OF NEXT FREE ENTRY
2	TABLE RELATIVE INDEX OF PREV. FREE ENTRY
3	0
4	0
5	0

An assigned entry in the swaptab is a process' SLL header or a member of a process' SLL. These formats are now described.

Segment Locality Lists (SLL)

The system maintains for each process a segment locality list (SLL) of the segments belonging to that process' current working set. The process' SLL consists of a header and a list of entries. The header and list entries are taken from the SWAPTRB.

R process' SLL is located via the process' PCB entry. PCB01 contains the SLL relative index of the process' SLL header.



SLL Header Format



SLL(SLLHERDINX+0)
.(1:1) SWREQ, Swap Required Flag
.(2:1) NASMEM, Nas Memory Flag
.(3:1) INTLOC, Initialize locality to minimum
.(4:1) PARTIN, Process partially swapped in
.(5:1) STRTOV, Start swap over flag
.(6:1) SWIP, Swap In Progress Flag
.(8:8) IOCNT, Segment read completions until awake

SLL List Entry Format



SLL(SLLINX+0) NEXTIMPPIN, next make present deferred queue PCB Index

SLL(SLLINX+1) NEXTINX, next SLL entry

SLL(SLLINX+2) PREVINX, previous SLL entry

SLL(SLLINX+3) SLL'OBJDESC, 1st word of object identifier

SLL(SLLINX+4) SLL'OBJNUM, 2nd word of object identifier

SLL(SLLINX+5)
.(0:1) MRPSEG, process' CST napping segment (LSTT)
.(1:1) STK, process' stack entry
.(2:1) DISCIDSEG, disc I/O pending on this segment
.(3:1) LOCKED, segment locked in memory
.(4:1) BLKLK, request for blocked lock
.(5:1) FRDZE, segment frozen in memory
.(6:1) SLLIMI, process queued for this segment
.(7:1) TOSS, Toss this entry
.(8:1) FRZREQ, request segment to be frozen
.(9:1) LKREQ, request to lock segment in memory
.(10:1) DECCNTFLAG,
.(11:5) PREFETCNCOUNT,

NOTE:
The Swap Table will be configured with at least twice the number of configured PCBs.

Special Request Table

Used for passing data segment size change info and for keeping a list of devices waiting for a segment to arrive in memory.

%1042 - SRT relative index to entry N 0
%1043 - SRT relative index to the head of the queue

NOTE: The number of entries configured will be 3 greater than the number configured via SYSDUMP. (Entry #0 consumes 3 entries).

SRT Entry 0 Format



The following entry format is for data segment size changes:



The following is the format for devices waiting on a segment: (The region header for the segment contains an SRT relative index to this entry. If more that 5 devices are waiting on this segment, another entry will be linked to this entry.)



NOTE:
The number of primary configured entries will be equal to the total number of LDEVs configured. The number of secondary entries will be configured to be at least the same as the number of PCBs configured. Data segment change entries are secondary type, while devices queued entries will be primary entries.

Main Memory Region Headers and Trailers

Main memory is partitioned into regions. Each region is in one of three states: available, reserved, or assigned.

An available region is available for consumption by the free space allocation mechanism. An available region consists of neighboring subregions, each of which is either a hole or an overlay candidate. An available region is linked into the available region list.

A reserved region is a main memory region which is in the transition state from available to assigned. A reserved region has been cleaned, and there is a pending disc read of a segment into the region.

Assigned regions are occupied by present segments. Available and reserved regions consist of one or more adjacent subregions. Region headers and trailers are partitioned into global and local components. The global region header/trailer is only valid for the first/last subregion in regions consisting of more than one subregion.

The region headers and trailers of available, reserved, and assigned regions contain the state and control information pertaining to the current or planned contents of the region.

Cache domains are another form of assigned regions and are designated as such in the subregion header. If the cache domain is "napped" - has I/O pending against it - then the object identifier will have a non-zero value in the second word of the segment identifier field. If the second word of the segment identifier field is zero, then this region is a cache domain that is unmapped. (Refer to Chapter 23 for further information regarding Disc Caching.)

Header length = 24
Trailer length = 4

Global Region Trailer



Global Region Header (Available Regions)



Subregion Header (Available Regions)



Global Region Header (Reserved Regions)



Subregion Header (Reserved Regions)



Subregion Header (Cached Regions)



Region Header and Trailer Field Descriptions

RRS, Region Rssignment State
- .(0:1) Region Rssigned Flag
- .(1:1) Region Reserved Flag
- .(2:1) Region Available Flag
- .(3:1) Region Cleaned Flag
- .(4:1) Size Change Pending Flag
- .(5:1) Region Locked Flag
- .(6:1) Region Frozen Flag
- .(7:1) Region I/O Frozen Flag
- .(8:1) LSTT segment
- .(9:6) Not used
- .(15:1) Blocked Lock Migration in Progress Flag

IOCRT, On-Going I/O Count
= N of on-going I/O's in the region which must complete before the initiation message can be processed.

INITMSG, Initiation Message
- .(0:1) Message Processed Toggle Switch
- .(1:1) Message Externally Disabled Flag
- .(2:1) Message On-going I/O Disabled Flag
- .(3:1) Queue Segment Read Disc Request Flag
- .(4:1) Incore Move Request Flag
- .(5:1) Expansion Request Flag
- .(6:1) Garbage Collection Flag
- .(7:1) Message Aborted Flag
- .(8:1) Release Residual Pages Flag
- .(9:1) Ok to start completion flag
- .(10:5) Not used
- .(15:1) Message Valid Flag

INITINFD, Initiation Message Ruxiliary Information
= ORQ relative index of segment read disc request if INITMSG. OREADREQ=1
or
= +/- Displacement to initiation message for Moves and expansions.

COMPMSG, Completion Message

- .(0:1) Message Processed Toggle Switch
- .(1:1) Segment Modification Required
- .(2:1) Block Lock Request
- .(3:1) Send Scheduler A Message
- .(4:1) Awaken A Device
- .(5:1) Message Aborted
- .(6:9) Available
- .(15:1) Message Valid Flag

MPQLINK PCB relative index of the HEAD of the make present queue.

PAGECNT, Release Page Count
=# of extra pages to release before processing initiation message.

SPECREQTABPTR, A Special Request Table relative index to the list of devices queued on this segment.

SRS, Subregion Assignment State
.(0:1) Cached region
.(1:1) Referenced
.(2:1) Recover Overlay Candidate
.(13:3) I/O Status from region fetch

SS, Subregion Size

SD, Subregion Displacement
.(0:1) Displacement Count Valid Flag
.(1:15) # Pages to Base of Region

WREQP, Write Request Pointer
= DAQ Relative Index of Disc Write Request when the Data Segment in the Subregion is in Motion Out When the region belongs to a cashed domain which is mapped (i. e. OBJIDENT = 30000/non zero number) this word is non zero. If the cashed domain is not mapped WREQP is zero.

OBJIDENT, Object Identifier- has standard object identifier format

LKFZCNT, Lock and freeze count
.(0:8) Number of times region has been frozen
.(8:8) Number of times region has been locked

WDIOFZCNT, Iofreeze count
.(0:8) Not used
.(8:8) Number of times region has been iofrozen

For regions belonging to cashed domains, the above two words contain the absolute address of the PD field in the previous region belonging to a cashed domain.

NDDR, High order disc address in virtual memory of this region

LODR, Low order disc address in virtual memory of this region

ND, Next cashed domain link for cashed domain regions only. Contains the absolute address of the ND field of the next cashed region.(2 words)

ARRTIME, Arrival time, contains the time at which the segment contained in the region became present

CACDADISP Valid only for regions containing a cashed domain, this word represents the disc address (in one word) of the segment contained in the region. This word which exists in each member of a linked list of cashed domains, is used as the target word during the LLSN instruction.

Space Allocation Structures

As of MPE V/P and V/E, one doubly linked list structure is used instead of the multiple lists ordered by size as in MPE IV. Sysglob locations %250 through %253 contain the respective head and tail (bank & address) of the available region list. These four words have in essence replaced the ARSBM and ARL data structures in MPE IV. Memory allocation and deallocation is handled through PUTONARL and TAKEOFFARL. The search for an available region of the desired size is done via the LLSN instruction. The format of the list is the following :

Sysglob %250 & %251 points to the absolute address of the NEXT LINK field (two words) in the first available region on the list. The NEXT LINK field in the first available region points to the absolute address of the NEXT LINK field in the second available region and so on. It is worth mentioning that in addition to having a NEXT LINK field, each available region also contains a PREVIOUS LINK pointer, which makes management of the list both easier and faster.

CHAPTER 3 DISC LAYOUT

System Disc Layout



System Disc Layout (Cont.)



System Disc Layout (Cont.)



Disc Label (Sector 0 of Disc)

System Volume



System Volume (Cont.)



Serial Volume



Serial Volume (Cont.)



Master Volume



Master Volume (Cont.)



Slave Volume



Slave Volume (Cont.)



Defective Tracks Table (Sector 1 of Disc)
(Not Used On CS-80 Discs)



DTC	(DEFECTIVE TRACK CODE)
0	suspect
1	suspect alternate
2	deleted
3	reassigned

NOTE: The situation where there are two entries for the same track, n, one having a DTC of 0 (suspect) and the other having a DTC 3 (reassigned) results from a situation where the disc driver could not "read" (unreadable) the address of the particular track.

Defective Sector Table (DSCT -- Sector 1 of Disc)
(the DSCT exists on device type 3 (CS-80) discs)



Unlike the DTT, entries in the DSCT are not permanent. Once a suspect sector is handled by INITIAL or VINIT, its entry is removed from the table. Thus, this table contains only unprocessed suspect sectors.

Reserved Area Bit Map (Sector 4 of the System Disc)

The first 400 sectors of the system disc are reserved for Initial'e use. This area contains permanent data structures for the boot. It is also used as a temporary storage area for data during sparing. All other system volumes and private volumes reserve only the first 10 sectors of the disc. They do not have a reserved area bit map.

The bit map contains 1 bit per sector. A '1' means the sector is free.



Disc Cold Load Information Table (Sectors 28-39)



Disc Cold Load Information Table (Cont.)



Disc Cold Load Information Table (Cont.)

SIZE IN WORDS		FAEFTR+0 <--------
MEMORY ADDRESS	*DRIVER TABLE	
DISC ADDRESS		
SIZE IN WORDS		FAEFTR+5
MEMORY ADDRESS	*CTABO	
DISC ADDRESS		
SIZE IN WORDS		FAEFTR+10
MEMORY ADDRESS	*CTAB	
DISC ADDRESS		
SIZE IN WORDS	* COMMUNICATION SUB-SYSTEM DRIVER TABLE	FAEFTR+15
MEMORY ADDRESS		
DISC ADDRESS		
SIZE IN WORDS	* COMMUNICATION SUB-SYSTEM DEFINITION TABLE	FAEFTR+20
MEMORY ADDRESS		
DISC ADDRESS		

Disc Cold Load Information Table (Cont.)

SIZE IN WORDS		FAEFTR+25
MEMORY ADDRESS	COMMUNICATION SUBSYSTEM TABLE	
DISC ADDRESS		
SIZE IN WORDS		FAEFTR+30
MEMORY ADDRESS	LOGICAL-PHYSICAL DEVICE TABLE	
DISC ADDRESS		
SIZE IN WORDS		FAEFTR+35
MEMORY ADDRESS	LOGICAL-DEVICE TABLE	
DISC ADDRESS		
SIZE IN WORDS		FAEFTR+40
MEMORY ADDRESS	DEVICE CLASS TABLE	
DISC ADDRESS		
SIZE IN WORDS		FAEFTR+45
MEMORY ADDRESS	VOLUME TABLE	
DISC ADDRESS		

Disc Cold Load Information Table (Cont.)

SIZE IN WORDS		FAEFTR+50
MEMORY ADDRESS	LOGICAL DEVICE TABLE EXTENSION	
DISC ADDRESS		
STACK SIZE		FAEFTR+55
MEMORY ADDRESS	INITIAL's STACK	
DISC ADDRESS		
SIZE IN WORDS		FAEFTR+60
MEMORY ADDRESS	DEVICE CLASS TABLE HEADER	
DISC ADDRESS		
SIZE IN WORDS		FAEFTR+65
MEMORY ADDRESS	TERMINAL DESCRIPTOR TABLE	
DISC ADDRESS		
SEGMENT SIZE		FAEFTR+70
MEMORY ADDRESS	INITIAL/SYSDUMP COMMUNICATION RECORD	
DISC ADDRESS		

Disc Cold Load Information Table (Cont.)

SEGMENT SIZE		FAEFTR+75
MEMORY ADDRESS	INITIAL's SEGMENTS	
DISC ADDRESS		
(MORE SEGMENTS OF INITIAL) ININ		

INITIAL Program CST Map

LOGICAL CST#	PHYSICAL CST#	SEGMENT NAME	
0	1	ININ	\
1	2	BOOTSTRAP	|----> core resident
2	3	RESIDENT	/
3	4	MAINSEG1	\
4	5	MAINSEG1A		
5	6	CONFIGURE			noncore resident
6	7	DEFCTRACKS			but present in core
7	10	SETUP	|------| |at completion of
10	11	TAPEIO			cold load
11	12	FILEIO			
12	13	DISCSPACE	/	
13	14	DIRECTORY1		
14	15	DIRECTORY2		
15	16	SL PROGRAM		
16	17	PROCESS		
17	20	MAINSEG1B		
20	21	MAINSEG2		
21	22	MAINSEG3		
22	23	MAINSEG4		

*code segment swapping starts at completion of MAINSEG1

SYSDUMP/Initial Communication Record

0	MIT VERSION
1	MIT UPDATE
2	MIT FIX
3	VERSION
4	UPDATE
5	FIX
6	EXP SYSTEM NR.
7	HIGHEST DRT
8	HIGHEST LDEV
9	HIGHEST VOL/# OF VOLS
10	# OF ADD'L DRIVERS
11	COLD LOAD COUNT
12	FILES DUMPED
13	SERIAL DISC LOAD
14	TAPE RECORD SIZE
15	DISC COLD LOAD ENTRY
16	MAX INITIAL SEG SIZE
17	SPARE
18	SPARE
19	SPARE
20	DEV CLASS TAB SIZE
21	TERM DESCRIPTOR SIZE
22	OLD VTAB SIZE
23	OLD INFO SIZE
24	CS TABLE SIZE

SYSDUMP/Initial Communication Record (Cont.)

25	SPARE
26	SPARE
27	SPARE
28	SPARE
29	SPARE
30	CONVERSION BITS WORD 1
31	CONVERSION BITS WORD 2
32	CONVERSION BITS WORD 3
33	CONVERSION BITS WORD 4
34	SPARE
35	SPARE
36	SPARE
37	SPARE
38	SPARE
39	SPARE
40	LOG FILE NUMBER

Cold Load Information Table Extension

The Cold Load Information Table Extension is a part of the Cold Load Information Table that has no use in booting the system. It exists for different system level processes to hold information that would only be created during a RELOAD. A good example of this is the system log file number. This is only created on a RELOAD, and changed whenever a log file is full or a boot (other than a RELOAD) is performed.

In order to protect the Cold Load Info Table, the extension was created. In this way NO I/Os should be performed to the Cold Load Information Table during MPE operation. However to process data into the Cold Load Info Extension a process must use the access routine "PROCESS'COLD'LOAD'INFO". The exact calling sequence can be found in KERNELD.

The Cold Load Information Extension is 2 sectors long and immediately follows the SYSDUMP/Initial Communication Record starting at sector address #31 on logical device 1.

The assigned entries are as follows:

	0
RESERVED FOR FUTURE SYSTEM USE	2
	20
SYSTEM LOGGING FILE NUMBER	21
NETWORK MANAGEMENT LOGGING FILE NUMBER	22
NETWORK MANAGEMENT TRACE FILE NUMBER	23
FULL/PARTIAL COMMAND DUMP DATE	24
	25
	26
NOT CURRENTLY ASSIGNED	27
	28
	255

Virtual Disc Space Management Structures

Disc space for data segments is allocated from reserved regions of system volumes which have been assigned the virtual memory supporting (VMS) attribute. The data structure used for accounting and management of the virtual disc space of the various VMS volumes is the Virtual Disc Space Table (VDSMTAB). This structure consists of a circular list of entries, one for each VMS volume. Each entry contains the information defining the state of the virtual memory region on that volume.

Virtual Disc Space Management Table

```
VDSMTAB DSTN = 39 (X47)
VDSMTABPTR   = Absolute(X1D26) = SYSGLOB X26
```

General Structure



VDSMTAB Entry 0 Format



VOSMTAB General Entry Format



***COMMENT: A bit on in a device's VM8IT MAP
==> Corresponding VM page is free.

Volume Table

SIA #22=X26
OST #29=X35



Typical Private Volume Entry



Typical System Volume Entry



CHAPTER 4 DIRECTORY

Introduction to the Directory

SYSGLOB cells:

DIRBASE <----absolute disc addr of base [SYSGLOB+X130 AND X131]

Directory on disc consists of a contiguous area:



The capacities for accounts/groups/users/files are dependent on their block sizes.

*	SYSSAIBSIZE	System acct index block size (3 sectors)
	SYSRUIBSIZE	Acct. user index block size (1-3 sectors)
	SYSRGIBSIZE	Acct. group index block size (1-3 sectors)
	SYSGFIBSIZE	Group file index block size (2 sectors)
	SYSGVSIBSIZE	Group volume set definition ind. blk. size(1 sector)
*	SYSAEBSIZE	Acct. entry block size (3 sectors)
	SYSUEBSIZE	User entry block size (2 sectors)
	SYSGEBSIZE	Group entry block size (2 sectors)
	SYSFEBSIZE	File entry block size (2 sectors)
	SYSVSEBSIZE	Volume set definition entry block size (1 sector)
	SYSMRXBSIZE	Maximum of above. (used to initialize DDS.)

*These values are used once for the creation of the (root) system, account index or new systems. This root index is always at address DIRBASE+3.

Overview of Directory



Overview of Directory

Directory Data Segment



Directory Data Segment (Cont.)



Directory Pointer Rrea [DR or DB] DST=20(10) SIR=8(10)



Directory Space Data Segment (DIRSDS)

DST=21 (X25)

SIR=B
10

DST = 21 (X25)

	0 1 2 3 4 5 6 7 8 9	1 1 1 1 1 1 0 1 2 3 4 5	
0	Logical device	Bit map	
1	baee sector addreee		DS'BRSE
2	Ptr to last avail word in buff		DS'LAST'WORD
3	Ptr to firet word in buffer		DS'FIRST'WORD
4	Size in eectore of directory		DS'DIR'SIZE
5	D|E|S|P|		DS'FLAGS
6	First current sector in buff		DS'CUR'SECTDR
7	Disc address of currsnt part		OS'ADDR
10	of bit map in the buffer		
11	Size of buffer in words		DS'SIZE
12	Next rsquested sector		DS'REQ'SECTOR
13	Last sector in bit map		DS'LAST'SECTOR
14	Systen saved pntr to last		DS'SYS'LAST
15	Systen eaved pntr to firet		DS'SYS'FIRST
16	Systen saved currsnt sector		DS'SYS'CUR
17	Saved directory size		DS'SYS'SIZE
20	LDEV that last error occurred		DS'ERROR'LDEV
21	Type of error that occurred		DS'ERRDR'TYPE

This section of the bit map DST ie occupied by up to 3 eectors of bit map. It is swapped in 3 sectors at a time as needed. DS'FIRST'WORD ie updated to search for space in the bit map. When it reachee DS'LAST'WORD for the second pase, the next 3 sectors of bit map will be swapped in.

Partial definitione:

```
DS'LDEV         =  DS'BRSEO.(0:B)
DS'DIRTY        =  DS'FLAGS.(0:1)
DS'ERR'IN'PROG  =  DS'FLAGS.(1:1)
DS'DIR'DISRBLED=   DS'FLAGS.(2:1)
DS'PERM'DISABLE=   DS'FLAGS.(3:1)
```

Descriptions:

DS'ADDR

This is the addrsss of the eection of bit map that is currently in the buffers. For example, this addrese uill usually be the same as DS'BASE. If we need to page in more sectors of bit map than the first three, then thie addrsse uill be eubsequently larger than DS'BASE.

DS'BRSE

This is the base addrsse of the directory bit map. If the directory is greater than 6112 sectors, then this address will be 29 eectors less than the address found in the Cold Load Information table on diec.

DS'CUR'SECTDR

This ie the current bit map sector number of the first sector in the buffer area. Its value can range from 1 to 30. Thie number minus one added to DS'BRSE will reeult in DS'RDDR.

DS'DIR'DISRBLED

If this bit is on, the directory allocation and deallocation is off and only a WARMSTRRT will turn this bit off. The bit is turned on if an I/D error occurs on a dirsctory bit map sector or if we find data integrity problems with the bit map, i.e. if we attempt to deallocate a eector that is already deallocated.

DS'OIR'SIZE

This ie the eize (sectors) of the directory area. This eize includes only the laet 3 eectors of the bit map. If the dirsctory is greater than 6112 sectors, then thie eize doee not include the extra 29 eectore of bit map. It can also be thought of as the number of bits in the bit map.

DS'DIRTY

This bit is eet if the bit map sectors in the buffer have been modified in any way. When more sectors must be brought into the buffers, or if we switch to a differsnt domain (system to PV, PV to system) this bit is interrogated to determine if the sectors prssently in the buffers must be firet written to disc.

DS'ERROR'LDEV

The LDEV in which the last directory error occurred.

DS'ERROR'TYPE

This word describes the type of directory bit map error that occurred. Ite legal values are:

0 - No error
1 - I/D error on a write
2 - I/D error on a read
3 - Attempting to deallocate space that is already deallocated
4 - Dirsctory space management is already disabled

DS'ERR'IN'PROGRESS

R directory space management error is currsntly in progress.

DS'FIRST'WDRD

R DST relative pointer to the word in the bit map buffer that we will interrogate next when directory space is needed. When the syeten first cones up, this word is always initialized to DS'NERDER+2 (i.e. to point to the first word in the bit map). On subsequent bit map sector reads, it is set to DS'NERDER since subsequent eectore will not have the 2 word overhead that exists in the first sector of the bit map.

DS'FLAGS

This word contains numerous flags. See individual descriptions.

DS'LAST'SECTOR

This is the total number of active bit map sectors. This number will range from 1 to 32.

DS'LAST'WORD

This is the current number of bit map word in the buffer. It can range from 1 to %577 + DS'HEADER. If there exists 3 full sectors in the buffer, then it will have the value %600 + DS'HEADER - 1 or %621. It is compared to DS'FIRST'WORD to determine if we have hit the end of the current buffer area.

DS'PERM'DISABLE

If this bit is set, then directory allocation/deallocating is permanently disabled. This bit should not be set.

DS'REQ'SECTOR

This is the next sector to begin reading in up to 3 bit map sectors. It is updated by 2 or 3 and the read procedure will bring in up to 3 sectors starting from this sector. If this sector is set to be greater than DS'LAST'SECTOR, then it is reset to 1. After the sectors are read in, DS'CUR'SECTOR is set the DS'REQ'SECTOR.

DS'SIZE

This is the size in words of the bit map buffer area. It is always a multiple of a sector (128 words). It will usually have the value of %600. Legal values are %200, %400 and %600.

DS'SYS'LAST, DS'SYS'FIRST, DS'SYS'CUR & DS'SYS'SIZE

The values of DS'LAST'WORD, DS'FIRST'WORD, DS'CUR'SECTOR and DS'SIZE will be stored in these locations when the directory space management switches from the system directory to a private volume directory. And, of course, when DSM switches back to system domain, the above mentioned values are reinitialized with these values.

Directory Structure



The Index Block prefix points back to the previous higher level. The Index Block entries point to the entry blocks.

Directory Definitions

>PAGE - smallest allocatable record ("phys.recd")-currently sector.
>BLOCK - integral# of pages; contains contiguous indices or entries.
>INDEX - pointer to entry block, containing name of 1st entry.
>ENTRY - information-containing "object" may contain pointer to an index block.
>POINTER - 15-bit positive relative page number (relative to directory base).
>DDS - directory data segment.
>ELEMENT - a generic name for index or entry.

Index Block Prefix (10 Words)



*The count is incremented by each access that uses and relies upon a pointer to the index block, i.e., it is guaranteed not to be purged while the count is not = 0.

Index Entry (6 Words)



Account Entry (%36 Words)



Account Entry (Cont.)



P PURGE flag

S If 1, systen level UDC's exist (only in "SYS" account)
A If 1, account level UDC's exist for account

Group Entry (251 Words)



Group Entry (Cont.)



GLINKAGE



Group Entry (Cont.)

GLINKAGE (0:1) = 0; MVS is in System Domain
(0:1) = 1; MVS is in Private Volume Domain
(8:8) = 0; If not PV or Not Bound
(8:8) <>0; If PV and Bound

GROUP SECURITY MASK



File Entry (File Pointer)(6 Words)



B - Bad file label
(0:1) = 0 - not defective
= 1 - defective

User Entry (19 Words)



User Attributes/Capability



Volume Set Definition Entry



TY = 0 VOLUME SET DEFINITION
= 1 VOLUME CLASS
MVTABX: MOUNTED VOLUME TABLE INDEX (IF MOUNTED)
VOL COUNT: NO. OF VOLUMES
VMASK: VOLUME MASK
M = 0 NOT MOUNTED
= 1 MOUNTED
VTABX: VOLUME TABLE INDEX

GVSLINKAGE

T - TYPE
0 = Volume Set Definition
1 = Volume Set Class
R - ALLOCATING FLAG
0 = not initially allocating (not 1st user of set)
1 = 1st user of set allocating resources (transitional)
MVTABX - Mounted Volume Table Index
0 if volume set not logically mounted

GVSINFO

VOLCNT - Number of members in set
VSMASK - Bit mask of volume member usage
Order is from right to left
i.e., bit 15 is 1st member, bit 14 is 2nd member ...

GVSVOLFLAGS

M - Member Mounted Flag
0 = not mounted
1 = mounted

GVSVOLINFO

DISC PSEUDO-SUBTYPE = (Actual type *16) + actual subtype.
VTABX - Volume Table Index

Volume Set Class Entry



G V C L I N K A G E



T - TYPE
1 = Volume Set Definition
0 = Volume Set Class

G V C I N F O



VOLCNT - Number of members in set
VCMASK - Bit mask of volume member usage (VOLUME CLASS MASK)
Order is from right to left
i.e. bit 15 is 1st member, bit 14 is 2nd member ...

Volume Mask Format

- USED IN MVTAB, PVUSER, FILE CONTROL BLOCK (FCB), VOLUME SET/CLASS DEFINITION, VOLUME SET VTAB.
- 8-BIT MASK.



0: NOT MOUNTED OR NON-MEMBER 1: MOUNTED OR MEMBER

CHAPTER 5 LOCK RESOURCES

SIR# Allocation DST 253

Sir's Ordered by Sir Number

SIR #	RANK	SIR NAME
1	10	LOAD PROCESS
2	335	CACHE CONTROL
3	91	IDD
4	92	ODD
5	50	PROCESS TREE STRUCTURE
6	60	SCHEDULING QUEUE
7	70	CST ENTRIES
8	80	SYSTEM DIRECTORY
9	90	LPDT
10	B5	LDT
11	110	STORAGE IN OVERLAY AREA
13	130	JPCNT
14	140	JCUT
15	27	JMAT
16	5	FMAVT
17	22	LOADER SEGMENT TABLE
18	180	VDD
19	190	SPOOL
20	200	MESSAGE CATRLOGUE
21	210	RIT
22	220	VOLUME TABLE
23	230	WELCOME MESSAGE SIR
24	240	ASSOCIRTION TABLE
25	250	CS RLLOCATE
26	260	LOGGING BUFFER
27	83	PV MVTAB
28	280	MERSSIR
29	290	PV USER TABLE
30	300	IMAGE
31	310	KSAM
32	320	USER LOGGING
33	330	DEBUG BREAKPOINT TRBLE
34	340	PCB
35	350	SUB-QUEUE MAPPING TRBLE
36	360	CILOG
37	25	FILE INTEGRITY
38	380	RIN
39	390	TAPE LABELS
40	B7	DEVICE CLASS TABLE
41	400	Reserved
42	401	Cold Load SIR
43		1st JOB
44		2nd JOB
.	.	.
.	.	.

Sir's Ordered by Ranking

RANK	SIR #	SIR NAME
5	16	FMAVT
10	1	LOAD PROCESS
22	17	LOADER SEGMENT TABLE
25	37	FILE INTEGRITY
27	15	JMAT
50	5	PROCESS TREE STRUCTURE
60	6	SCHEDULING QUEUE
70	7	CST ENTRIES
80	8	SYSTEM DIRECTORY
83	27	PV MVTAB
85	10	LDT
87	40	DEVICE CLASS TRBLE
90	9	LPDT
91	3	IDD
92	4	ODD
110	11	STORAGE IN OVERLAY AREA
130	13	JPCNT
140	14	JCUT
180	18	VDD
190	19	SPOOK
200	20	MESSAGE CATALOG
210	21	RIT
220	22	VOLUME TABLE
230	23	WELCOME MESSAGE
240	24	ASSOCIATION TABLE
250	25	CS ALLOCATE
260	26	LOGGING BUFFER
280	28	MERASSIR
290	29	PV USER TABLE
300	30	IMAGE
310	31	KSAM
320	32	USER LOGGING
330	33	DEBUG BREAKPOINT TABLE
335	2	CACHE CONTROL
340	34	PCB
350	35	SUB-QUEUE MAPPING TABLE
360	36	CILOG
380	38	RIN
390	39	TAPE LABELS
400	41	Reserved

SIR Table Information

The system internal resource table is located in non-linked memory (resident table). The SIR table is used to protect critical system elements against access by more than one process, i.e., it provides a "lock out" mechanism. Each critical system resource (usually a table) is assigned a specific SIR number. Procedures are provided within MPE to lock (GETSIR) and unlock (RELSIR) the SIR. Processes attempting to obtain a SIR that is not available are impeded by the system. The SIR table entries form the head of a linked list in this case. If more than one process becomes impeded, word 15 of the PCB entry is used to add the "new" process to the growing list. The method of unimpeding the process depends on the SIR type.

A SIR does not respect process priority and operates in a FIFO manner. As processes become impeded on behalf of a SIR the new entries are entered at the tail of the impeded list. When the current holder of the SIR releases it, on the first process in the list (pointed at by the head pointer) is unimpeded. The linked list head and all pointers are then updated and the newly unimpeded process will obtain the SIR.

SIR Entry Formats



P = PIN#
PIN = PCB table entry number
SIR QUEUE LENGTH- number of processes queued for this SIR

The SIR table is indexed by SIR#, with each SIR# corresponding to a unique, pre-assigned system internal resource. Entry #0 is not used. Impeded lists are established by using the SIR table entry (2) as the head of the list and PCB(15) for elements. PINs are always used as pointers, with 0 indicating end of list.

CHAPTER 6 FILE SYSTEM

This chapter describes the MPE V file system. The second section describes the basic concepts. The third section describes the table structures used.

File System Overview

I/O to files is done by reference to file numbers, which are assigned by calling the FOPEN intrinsic. This establishes an initial "point of attachment", which may be described as a connection between a program (i.e., process) and that particular point in a particular file at which the next FREAD or FWRITE would cause data to be transferred. A point of attachment is described by a control block, of which there are several different kinds (described later). Control blocks may exist in the process's own stack or in an extra data segment assigned by the file system. In order to find control blocks quickly, a pointer scheme called vectors is used. A control block is uniquely described by a vector, which consists of two words with the first word containing a segment number and the second word containing a word offset into the control table of the vector table entry which describes the location of the control block within that segment. The entire assemblage, consisting of eight overhead words, the vector table, and all of the control blocks to which it points, comprises the entire segment; if in a stack, it occupies part of the PXFILE part of the PCBX.

The point of attachment is described by a "physical access control block", or PACB, which will exist as a result of an FOPEN to any file (except $NULL). Any required I/O buffers are associated with the PACB; refer to Section 2.1.

All FOPENs specifying "multi-access" for all processes running under a single job use a single PACB for references to a multi-access file. Although all these are attached to a single point in the file, the type of attachment (i.e., ROPTIONS) may be different. So, each FOPEN specifying a multi-access file establishes a "logical access control block", or LACB, which contains the point-of-attachment local values. The use of a single buffer (i.e., PACB) ensures that references by various processes or against various FOPENs within one process are dealt with in strict sequential order. Note that references to a file by other jobs, or by other processes not specifying multi-access, will be through other PACBs, whose buffers will be read or written at the pleasure of the file system; in order to ensure any sort of coherence to such shared references, the jobs must use global RINS and FLOCK and FUNLOCK the file. $STDIN, $STDLIST, and spoolfiles are opened multi-access automatically.

In the case of disc files, there is another kind of control block: the file control block (FCB). It contains copies of information read from the file label, such as the end-of-file pointer, the extent map, and the record and block structure. The EOF pointer is updated in the FCB as the file is written, and all changes made to the FCB are posted to the file label when the file is closed. An FCB is shared by all jobs in the system which reference the file.

The file number assigned by an FOPEN is an index into the Available File Table (AFT), a table of six-word entries which is at the end of the PXFILE part of the PCBX. Two double words are vectors to the PACB and (if it exists) the LACB.

AFT entries can also reside in a global AFT extra data segment. If the file was opened Global AFT (specified in the ROPTIONS) and the program is privileged, then the AFT is placed into this global AFT DST. Any accesses to the file are identical to local AFT's. All accesses to the file opened global must be done from privilege mode code. The file system intrinsics distinguish this file by a negative file number. Again, these files are identical in every other way except for where the AFT entry resides.

Because control blocks are shared among processes, it is necessary to have a scheme for coordinating access to them. A control block is "locked" by a process which requires exclusive access to it for a time. Other processes which attempt to lock the block will find it already locked, and will be impeded and queued. It may also be necessary to lock an entire control block table so that a process can create or destroy a control block in it, or lock or unlock an existing control block in the table.

Another table used by FOPEN is the File Multi-Access Vector Table (FMAVT). This table exists in a system extra data segment and is used by all jobs and processes in the system. When a file is being FOPENed with multi-access specified, the FMAVT is searched; if the file is already open, the FMAVT gives the PACB vector for the prior reference for each job.

Buffers

A bit in ROPTIONS specifies, when a file is opened, whether access is to be buffered or unbuffered. If unbuffered, data is transferred directly between the I/O device and the user's buffer (usually in his stack), which will be frozen in memory for the duration of the transfer. If buffered, the data is moved between the user's buffer and a file system buffer to which the I/O is actually done.

Buffers are associated with the PACB, attached to it as an appendage.

Table Formats

This section gives a detailed discussion of the main tables constructed and used by the file system. The location and overall structure of each table is given, in addition to the table format and a discussion of each field in the table. Table indices at the right of the table are in octal. Index names apply to the entire word; if in parentheses, the names are defined in the file system listing but not explicitly used there.

File System Section of PCBX (PXFILE)

The PXFILE area is a subsection of the PCBX. It is a contiguous, expandable and contractible block of storage that is managed by the file system primarily for its own use. Other subsystems, namely CS and DS, also make use of the PXFILE section. In doing so they must conform to the conventions of the file system.

The overall structure of the PXFILE area is:



Overhead

The part labeled Overhead contains information that pertains to the entire section. It is addressed via the pointer at DL-3.

0 1 7 8 15		
PXFILE SIZE IN WORDS	0	PXFSIZE
LAST OOPEN ERROR NO. | LAST COPEN ERROR NO.	1	
N |	2	
LAST OF AFT	3	
SLAVE AFT NUMBER	4	
LAST KOPEN ERROR NUMBER | LAST FOPEN ERROR NUMBER	5	
AFT SIZE IN WORDS	6	PXAFTSIZE
CS TRACE FILE INFO	7 8	(PXCTRINFO)
LAST RESPONDING NO-WAIT I/O AFT ENTRY NUMBER	9	PXFLEFTOFF
1ST USER (NOBUF) CONTROL BLOCK TABLE DST NUMBER	10	PXFCBT1
2ND USER (NOBUF) CONTROL BLOCK TABLE DST NUMBER	11	(PXFCBT2)
3RD USER (NOBUF) CONTROL BLOCK TABLE DST NUMBER	12	(PXFCBT3)
4TH USER (NOBUF) CONTROL BLOCK TABLE DST NUMBER	13	(PXFCBT4)
5TH USER (NOBUF) CONTROL BLOCK TABLE DST NUMBER	14	(PXFCBT5)
6TH USER (NOBUF) CONTROL BLOCK TABLE DST NUMBER	15	(PXFCBT6)
7TH USER (NOBUF) CONTROL BLOCK TABLE DST NUMBER	16	(PXFCBT7)
8TH USER (NOBUF) CONTROL BLOCK TABLE DST NUMBER	17	(PXFCBT8)

Partial word field identifiers are:

```
PXFDOPEN    = PXFILE(1).(0:8)#,   last DOPEN error code
PXFCOPEN    = PXFILE(1).(8:8)#,   last COPEN error code
PXFNOCB     = PXFILE(2).(0:1)#,   no CB's in PXFILE CBT?
PXFKOPEN    = PXFILE(5).(0:8)#,   last KOPEN error code
PXFFOPEN    = PXFILE(5).(8:8)#,   last FOPEN error code
```

Discueeion:

PXFAFTSIZE — This is the size (in words) of the Active File Table (AFT). The size ie in words to simplify calculating the size of the available block.

PXFCBT1-8 — These are the DST nunbere of the user (NDBUF) control block tables. A DST nunber of 0 indicates that no data eegnent is allocated.

PXFCOPEN — This contains the last CDPEN error nunber. Not used by the file systen.

PXFCTAINFO — This contains information pertinent to the CS trace file. Not used by the file systen.

PXFDDPEN — This contains the last DDPEN error nunber. Not used by the file systen.

PXFDSINFO — Reserved for DS. Not used by the File systen.

PXFFDPEN — This contains the last FDPEN error nunber. If it is zero then the last FOPEN successfully completed; otherwise the last FOPEN was unsuccessful and the nunber is the file systen error nunber.

PXFKDPEN — This contains the last KDPEN error nunber. XSAM is partly embedded in the file systen, and an FDPEN failure on a KSAM file can be caused by a failure to open either the key file or the data file. This error nunber is used in conjunction with PXFFDPEN to determine which file caused the XSAM open failure. This error nunber is not used by the file system.

PXFLEFTDFF — This is the AFT entry number of the last file/line that completed a nowait I/O; if zero then no nowait I/O has been completed. This cell is maintained solely by and for the IOWAIT intrinsic.

PXFNDCB — This bit signifies that control blocks are not to be created in the PXFILE control block table. This bit is set by the NDCB paraneter to the CREATE intrinsic or the :RUN connand. This feature permits the user to have as nuch stack space as possible; otherwise the file systen will take several hundred words of stack for the PXFILE control block table.

PXFSIZE — This is the size (in words) of the complete PXFILE area. It is the sum of the overhead block, the control block table, the active file table and the available block.

PXFILE Control Block Table (PXFCBT)

Addressing within a PXFILE control block table is somewhat nore conplicated than addressing an extra data segnent CBT since the table does not begin at DB+0. As a result all pointers within the table are table relative; the starting address of the table must be added to a pointer to generate a final DB-relative address. This addressing convention ie consistently applied to all control block tables.

When the control block table is expanded, space is taken from the AVAILABLE area. If no space is available then the PXFILE area is expanded and the acquired space is added to the AVAILABLE area.

Available Block

The part labeled Available is used to provide space when the Control Block Table or the Active File Table is expanded. These two tables grow towards each other, and when nore space is needed it is simply taken fron the Available Block.

When the Available area is exhausted, the PXFILE area is expanded, the AFT is relocated and the new space is added to the Available Block.

Currently the PXFILE area is only expanded; it is never contracted.

Active File Table (AFT)

The part labeled Active File Table contains inFormation used by the file systen (or CS, DS, etc.) to grossly characterize the file access and, most importantly, to give the location of the control blocks.

The overall structure of the AFT is:



where N = PXFAFTSIZE/6.

The length oF the AFT ie specified by PXFAFTSIZE. Unused entries are all zeros. When the table is full it is expanded by taking space from the Available block.

The AFT is negatively indexed by file number: the entry at DL-9 corresponds to file number 1, the entry at DL-15 corresponds to file nunber 2, etc.

The structure of the global AFT DST, described in Section 2 is as follows:



The etructure oF a file system AFT entry is:



The entry Format depends on the entry type; the File systen uses entry type 0.

The Following partial word Field identifiers are used:

```
AFTTYPE     = AFT.(0:4)N,    entry type
AFTNULL     = AFT.(4:1)#,    $NULL file
```

Discussion:

AFTIOQX — This is the IOQ index of the pending nowait I/O (if any). This is applicable if the file was opened with the NOWAIT option specified. Also, CS and DS have the sane capability and use this cell in a consistent manner. This is because the IOWAIT intrinsic services the file systen as well as CS and DS, and is the principal user of this cell. If the IOQX is negative, then one of two possibilities exist. If the file is a nessage File, then file IOQX is the accessor's reply port. If the file is a standard MPE file, then a read was done to a nonexistent extent and this is simply a stub inserted by the file systen.

AFTLACBDST — This is the DST that the Logical ACB (LACB) if it exists. This is applicable if the file was opened with the multi-access option specified.

AFTLACBENTRY — This is the word offset into the control block table of the LACB vector table entry, applicable if the file was opened with the multi-access option specified.

AFTNULL — This bit signifies that the file is $NULL and that there are no control blocks.

AFTPACBDST — This is the DST that contains the Physical ACB (PACB). A PACB exists for all files except $NULL.

AFTPACBENTRY — This is the word offset into the control block table of the PACB vector table entry. This will be nonzero for all files except $NULL.

AFTTYPE — This is the AFT entry type number. At present the following entry types are defined:

0 - file system
1 - remote file
2 - DS (nowait I/O disallowed)
3 - DS (nowait I/O allowed)
4 - CS
5 - CS
6 - KSAM
8 - Message File

Remote file AFT entry:



AFT 0
FSTYPE - This value will be 1 for remote files.
MR - Set if the file was opened multi-access.
AFT 1 - Local line number of remote file.
AFT 2 - File number of the remote file.
AFT 3 - Pending disposition of the file. Set when file was FOPEN'd and will possibly be used as the FCLOSE disposition.
AFT 5 - No wait I/O Queue Index.

DS AFT entry:



AFT 0
FSTYPE - This field will have the value 2 or 3.
C - On if DSOPEN called by CXDSLINE or REMOTE'HELLO.
M - On if Master PTOP AFT.
P - On if PTOP related.
R - On if remote main process.
AFT 1 - DS data segment table pointer.
AFT 2 - OSDSCB Index - DS data segment control block index.
AFT 3 - Logical device number.
AFT 4 - Preceding DS open AFT Pointer.
AFT 5 - IOQX - Same as described above.

CS Line entry:



AFT 0
FTYPE - This value will be 4 or 5. A 5 signifies that the line has an autodialer attached.
W - The line has been opened with no waiting on I/O requests.
ID - Line is a multipoint control or 3270 station.
B - Line was opened with buffering.
AFT 1 - Logical device number of the line.
AFT 2 - Vector to Multiple IOQ indices.
AFT 3
TR - Bit 0 on signifies tracing enabled. Bit 1 on signifies trace all.
I - On if line is currently connected.
R - Signifies that this CS device is an SCCP device.
DIAL - 0 = Dial on write, answer on read.
1 = Answer on write, dial on read.
2 = Always dial.
3 = Never dial.
AFT 4 - DST number of the line's misc data segment.
AFT 5 - If <> 0, then it is the system DB address of a single request IOQ entry. IOWAIT uses this word to pass the IOQ index of the completed request for this AFT to CSIOWAIT.

File Control Block Table (CBTAB)

A file control block table can be located in two places: (a) as a subpart of the PXFILE area, as discussed in Section 3.1.2; or (b) in a data segment. Although putting control block tables in PXFILE has the advantage of providing rapid access, it detracts from the space for the user's stack; so the larger control blocks (or optionally, all control blocks) are put into extra data segments. On the other hand, referencing extra data segment control block tables are of three kinds: expandable, nonexpandable, and shared FCB. Nonexpandable CBT's are used for a single PACB with buffers, i.e., where the control block is large or where the control block can't be local to a single process (for multi-access). Expandable (or NOBUF) CBT's are used for small control blocks ,as LACB's, PACB's with no buffers, and FCB's which are local to a single process. A list of the expandable CBT's associated with a process is kept in the overhead area of PXFILE (cf. Section 3.1.1). When a small control block is needed, these CBT's are checked in order to see if one of them has room. Shared FCB CBT's are similar to expandable CBT's except that they belong to the system rather than to a single process; the system keeps a list of DST's which it has assigned for this purpose.

The overall structure of a control block table is:



Overhead

The part labeled Overhead contains information pertaining to the entire table.



Other identifiers used:

```
CBTTYPE   = CBTAB(2).(0:2)    Control block table type
CBTVTSIZE = CBTAB(2).(2:14)   Vector table size
CBTLOCKBIT= CBTCONTRDL.(0:1)  Lock bit
```

Discussion:

CBTDSTX — This is the DST number of the data segment that contains the control block table. If the table is contained in a stack, i.e. in the PXFILE area, then this is the DST number of the stack and not 0.

CBTLOCKBIT — If the entire control block table is locked, then this bit is set. No locking count is kept since control blocks are locked only once from FCREATECB and FDELETECB when control blocks are added to and deleted from the table. The procedure LOCK'CB does not lock the control block because it runs PSEUDODISABLED during the critical times.

CBTQUEUE — This is the impeded queue for the table and has the same format as the impeded queue for a control block in the table. There is no second impeded queue because that facility is used exclusively for BREAK requests against the PACB for $STDIN/$STDLIST.

CBTPIN — This is the PIN number of the process that has the control block locked.

CBTSIZE — This is the size in words of the table. It is initialized when the table is created and changed when the table is expanded. At present a table is never contracted, even though this is possible.

CBTTYPE — This field is the type of the control block table. Possible values are:

0 - stack [PXFILE]
1 - NDBUF (expandable)
2 - System shared FCB
3 - Buffered (Contains a single PACB)

CBTVTSIZE — This is the size, in words, of the vector table area in the control block table. It does not reflect the number of entries used or unused.

NOTE: All PIN's are kept as the word offset into the PCB table and as the actual PIN number.

Vector Table

The part labeled Vector Table contains information used to locate and lock or unlock control blocks in the control block table.

The overall structure of the vector table is:



where N = (CBTVTSIZE/8)-1.

An unused vector table entry will have zeros in all the words of the entry. A used vector table entry will have a nonzero value in the first word of the entry (the control block address is necessarily nonzero).

The general structure of a vector table entry is:



The following partial word identifiers are used:

```
VT'LOCK'BIT  = VT'CONTADL.(0:1)
VT'BREAK'BIT = VT'CONTADL.(1:1)
VT'COUNT     = VT'CONTROL.(2:6)
```

Discussion:

VT'ADR — Control block address is the table relative address of the control block associated with the vector table entry. It is a word displacement from the beginning of the control block table.

VT'BREAK'BIT — This bit signifies that we are in the middle of break mode. This is used for the PACB of $STDIN/$STDLIST from a terminal session only.

VT'LOCK'BIT — This bit is set whenever the control block is locked.

VT'COUNT — This is the count of the number of times that the control block has been locked by the process identified in VT'PIN. If it is zero, then the control block is not locked.

VT'PIN — Contains the PIN of the process which has exclusive access to the control block. Other processes attempting to access the block will be impeded and queued.

VT'QUEUE — The high priority impeded queue is a double word of PINs that are the head and tail of the impeded queue of processes waiting for access to the control block. Processes are impeded and unimpeded by the file system using the normal mechanisms available under MPE.

VT'SAVEDQUEUE — The low priority impeded queue is a double word of PINs and has the same format as VTQUEUE. The only time this word is used is when the control block is in BREAK mode, which can only happen to an ACB corresponding to $STDIN/$STDLIST. It is used to save the current VT'QUEUE when the control block goes into BREAK mode and to restore VT'QUEUE when the control block goes back into non-BREAK mode.

NOTE: All PIN's are stored as offsets within the PCB table and not as actual PIN numbers.

Control Block Area

The part labeled CONTROL BLOCK AREA contains the control blocks used by the file system.

To facilitate storage management, all control blocks have the same overall structure:



where N = Size-1.

Partial word field identifiers are:

```
CBTYPE          = CB.(0:2)#,      control block type number.
CBSIZE          = CB.(2:14)#;     control block size
```

Discussion:

CBDESCRIP — This is the first word of a control block; the format is common for all control blocks.

CBSIZE — This is the size (in words) of the control block. The size includes the descriptor word.

CBTYPE — This is the type number of the control block. There are four types of control blocks:

0 - Garbage 1 - FCB 2 - PACB 3 - LACB

When a control block table is created the initial control block area is completely allocated to a single control block of type garbage. When space is requested for a new control block the control block area is scanned (using a first fit algorithm) for a garbage control block that is as large as the size requested. The space for the new control block is taken from this garbage control block and the space remaining becomes the new garbage control block size.

When space is returned it becomes a new garbage control block. To reduce fragmentation the new garbage control block is combined with either of the two neighboring control blocks if they are of type garbage.

If space is requested and no garbage control block is large enough to contain the new control block then the control block area and control block table are expanded by a sufficient amount. If expansion is not possible, some other control block table must be used.

Access Control Block (ACB)

Virtually every file system intrinsic constructs an ACB as its first action. When using the multi-access option, each accessor shares a single PACB. However each accessor is permitted to view the shared file in a slightly different manner than the other accessors. For example, one accessor may access the file in a read-only mode while the other accessors may access the file in a read-write mode. To do this, each accessor must, during his access, have a slightly different ACB.

The PACB holds information that is global to all accessors of the file. The LACB holds information that is local to each accessor of the file. At the beginning of a particular access, an ACB is constructed by calling LOC'ACB, which copies information from both the LACB and the PACB. At the end of the access, the ACB is released by calling UNLOC'ACB; this updates the PACB and LACB from the ACB since some of the fields may have been modified due to the access. This scheme nearly eliminates EXCHANGEDB's to access the various data segments.

Logical Access Control Block (LACB)

All LACBs have the same structure:



Partial word field identifiers are:

```
LACBSIZE        = LACB.(2:14)#,   size in words
LACBSTOPCHAR    = LACB(2).(0:8)#, terminal stop character
```

Discussion:

LACBAOPTIONS — See ACBAOPTIONS.

LACBBSIZE — See ACBBSIZE.

LACBCTL — See ACBCTL.

LACBERROR — See ACBERROR.

LACBFNUM — See ACBFNUM.

LACBFOPTIONS — See ACBFOPTIONS.

LACBMODE — See ACBMODE.

LACBNAME1-8 — See ACBNAME.

LACBPACB — This is the DST and vector table entry for the Physical ACB (PACB) for the file. file.

LACBRSIZE — See ACBRSIZE.

LACBSIZE — This is the size, in words, of the LACB. All LACBs are eighteen (decimal) words long.

LACBSTATE — See ACBLSTATE.

LACBSTOPCHAR — See ACBSTOPCHAR.

LACBTLOG — See ACBTLOG.

Physical Access Control Block (PACB)

The overall structure of the PACB is:



The buffering extension is optional; it is present if and only if the file is accessed with buffering. There are thus two possible formats for an ACB:

1. No buffers; the buffering extension is not present.

2. PACB buffers; the buffering extension is present and the buffers are in the buffering extension.

If multiple PACB buffers exist, there will be a buffering extension for each, immediately preceding the buffer. The basic PRCB (or NOBUF PRCB) is copied into the the RCB as words 0 through %63; an RCB "extension" is then generated in words %64 - %67. The resulting ACB thus has the following format:

	0 1 2 3 4 5 6 7 8 9 10 11 12 13 14 15	
0	2 | COMPLETE RCB SIZE	0
1	| FILE NUMBER	1
2	FILE NAME - 1ST CHRR. | FILE NRME - 2ND CHRR.	2
3	FILE NAME - 3RD CHRR. | FILE NAME - 4TH CHRR.	3
4	FILE HRME - 5TH CHRR. | FILE HAME - 6TH CNAR.	4
5	FILE NAME - 7TH CHRR. | FILE NAME - 8TH CHAR.	5
6	FOPTIONS	6
7	ROPTIONS	7
8	Record size in bytes	10
9	BLOCK SIZE IH WORDS	11
10	UNUSED	12
11	CARRIAGE CONTROL CODE	13
12	|EOF|PG |LN |ST |FK |TC |TB |BB |CAR|OB | EOF T | EDF M |	14
13	C| | TE| IC| Q | | TERMINAL STOP CHARRCTER	15
14	ERROR CODE	16
15	LAST I/O TRANSMISSIDN LOG	17
16	FILE POIHTER	20
17		21
18	CURRENT VARIABLE BLOCK NUMBER	22
19		23
20	RECORD TPANSFER COUNT	24
21		25
22	BLOCK TRANSFER COUNT	26
23		27
24	HIGHEST BLOCK HUMBER STARTED	30
25		31

26	FCB VECTOR	32
27		33
28	TOTAL HUMBER OF LACB'S	34
29	|BK | DEVICE TYPE | LAST LOGICRL I/O STATUS	35
30	LOGICAL OEVICE NUMBER	36
31	PF |HIT| | CURRENT BUFFER| TAPE DISPLACE | HO. BUFFERS	37
32	CURRENT RECORD WORD INDEN	40
33	BUFFER SIZE	41
34	VIRTUAL LOGICAL OEVICE ND.	42
35	FHAVT INDEN	43
36	NUMBER OF INPUT LACB'S	44
37	NAME TYPE | FILE DISPOSITIDH	45
38	ACCESS BIT MAP | BLOCKING FACTOR	46
39	S | M | Q | R | D | | AE| RW|ABR| NE| SEDFS| EDFS	47
40	SPDOLEO DEVICE TYPE | SPOOLED DEVICE AECORD SIZE	50
41	SPOOLED DEVICE FOPTIDNS	51
42	SPOOLEO DEVICE AOPTIDNS	52
43	IDD OR ODD INOEX	53
44	NO-WAIT DISK ADDRESS	54
45		55
46	UNUSED	56
47	NO-WPIT LOGICAL DEVICE	57
48	P1P2 USED BY FDEVICECONTROL	60
49		61
50	UNUSED	62
51	UNUSED	63

The above words, 0-%63, are physically located in the PACB of the file. Below, words %64-%67, are used by file system intrinsics- and are placed onto the stack by the procedure LOC'ACB when locking the ACB. Therefore, the buffering extension, if pres- ent, will immediately follow word %63 of the actual ACB in the Control Block Table of the file.

52	DST RELATIVE OFFSET TO PACB	64
53	DST RELATIVE OFFSET TO LRCB	65
54	DST RELATIVE OFFSET TO ACB IH THE STACK	66
55	STACK RELATIVE OFFSET TO DB	67

The following identifiers are used when referring to an RCB:

```
(RCBSIZE)      = RCB.(2:14)#,      size in words
RCBFNUM        = RCB(1).(8:8)#,    file number
RCBNAME        = RCB(2)#,          file name
RCBHRME1       = RCBDBL(1)#,       file name - first half
RCBNPME2       = RCBDBL(2)#,       file name - second half
RCBFOPTIONS    = RCB(6)#,          FOPTIONS
RCBROPTIONS    = RCB(7)#,          ROPTIONS
RCBRSIZE       = RCB(8)#,          record size (bytes)
RCBBSIZE       = RCB(9)#,          block size (words)
Spare          = RCB(10)#,         Unused
RCBCTL         = RCB(11)#,         carriage control word
RCBLSTATE      = RCB(12)#,         local state flags
RCBEOF         = RCBLSTRTE.(1:1)#, end of file sensed
PCBLPCTL       = RCBLSTATE.(2:2)#, page and line control
PCBPAGECTL     = RCBLSTATE.(2:1)#, page control
RCBLINECTL     = RCBLSTRTE.(3:1)#, line control
RCBSTREAM      = RCBLSTRTE.(4:1)#, stream I/O
RCBFKEYS       = RCBLSTPTE.(5:1)#, restore function keys
RCBXMITCRLF    = RCBLSTATE.(6:1)#, transmit CR,LF to user
RCBTBLOCK      = RCBLSTATE.(7:1)#, disable block mode
RCBBINARYIO    = RCBLSTPTE.(B:1)#, B-bit terminal transfers
PCBCARRIAGE    = RCBLSTATE.(9:1)#, carriage control flag
(RCBDEFBLOCK)  = PCBLSTATE.(10:1)#, default blocking
PCBREADCODE    = RCBLSTRTE.(11:4)#, input EOF check
PCBREADTYPE    = RCBLSTATE.(11:2)#, input EOF type
PCBREADMODE    = RCBLSTRTE.(13:2)#; input EOF mode
RCBMODW        = RCB(13)#,         mode word
PCBMODE        = RCBMODW.(0:8)#,   mode setting
PCBCIROVERFLOW= RCBMODW.(0:1)#,    Signifies CIR overflow
RCBSETMODE     = RCBMODW.(4:4)#,   FSETMODE bits
RCBTAPEERROR   = RCBMODW.(4:1)#,   report recovered tape error
RCBINHIBCRLF   = RCBMODW.(5:1)#,   inhibit terminal CR/LF
RCBQUIESCE     = RCBMODW.(6:1)#,   critical output verify
RCBSTOPCHAR    = RCBMODW.(B:8)#,   terminal stop character
```

```
ACBERROR     = ACB(14)#,          error code
ACBTLOG      = ACB(15)#,          last I/O transmission log
ACBFPTR      = ACB00BL(08)#,      current record number
ACBBLK       = ACB00BL(09)#,      current variable block
ACBRTFRCT    = ACB00BL(10)#,      logical record TFR count
ACBBTFRCT    = ACB00BL(11)#,      block transfer count
ACBHIBLK     = ACB00BL(12)#,      highest block started
ACBFCBV      = ACB00BL(13)#,      FCB Vector table entry
ACBSNCNT     = ACB(28)#,          # of LACBs
ACBSTATW     = ACB(29)#,          access class, status, etc.
ACBBREAK     = ACBSTATW.(1:1)#,   break ($STDIN/LIST only)
ACBDTYPE     = ACBSTATW.(2:6)#,   device type
ACBACCCL     = ACBSTATW.(2:3)#,   device access class
ACBSUBCL     = ACBSTATW.(5:3)#,   device sub-class
ACBSTATUS    = ACBSTATW.(8:8)#,   last logical I/O status
ACBQSTATUS   = ACBSTATW.(8:5)#,   qualifying status part
ACBGSTATUS   = ACBSTATW.(13:3)#,  general status part
ACBDADDR     = ACB(30)#,          Ldev number of file
ACBBUFX      = ACB(31)#,          buffer data & misc. flags
ACBPRIV      = ACBBUFX.(0:1)#,    privileged access only
ACBHIT       = ACBBUFX.(1:1)#,    buffer hit flag
ACBCURRABUF  = ACBBUFX.(4:4)#,    current buffer nor.
ACB#UMBUFS   = ACBBUFX.(12:4)#,   number of buffers less 1
ACBBUFUSED   = ACB(32)#,          used block word count
ACBBUFSIZE   = ACB(33)#,          buffer size (words)
ACBSPVDEV    = ACB(34)#,          spooled virtual device
ACBFMAVTK    = ACB(35)#,          FMAVT index
ACBSHCNTI#   = ACB(36)#,          #umber of input LACB's
ACBONTD      = ACB(37)#,          type & disposition
ACBO#TYPE    = ACBONTD.(0:8)#,    name type for dir. search
ACBDISP      = ACBONTD.(8:8)#,    file disposition
ACBAMLD      = ACB(38)#,          access mask & LDEV
ACBACCESS    = ACBAMLD.(0:8)#,    access mask
ACBBLKFACT   = ACBAMLD.(8:8)#,    Blocking factor of file
ACBGSTW      = ACB(39)#,          spool control flags
ACBSPOOLED   = ACBGSTW.(0:1)#,    spooled device flag
ACBSPOOLIO   = ACBGSTW.(0:2)#,    spooled I#/OUT
ACBSPSQ      = ACBGSTW.(2:2)#,    squeeze flags
ACBSPSQZ     = ACBGSTW.(2:1)#,    file squeezed
ACBSPRSQ     = ACBGSTW.(3:1)#,    request to squeeze
ACBSPOSQ     = ACBGSTW.(4:1)#,    squeeze just done
ACBNOWAITEOF = ACBGSTW.(8:1)#,    EOF advanced?
ACBNOWAITMODE= ACBGSTW.(9:1)#,    last I/O: 0=read, 1=write
ACBABORTREAD = ACBGSTW.(10:1)#,   abort broken re-read?
ACBNEWEOF    = ACBGSTW.(11:1)#,   EOF advanced - tape file
ACBSAVEEOFS  = ACBGSTW.(12:2)#,   for saving ACBEOFS
ACBEOFS      = ACBGSTW.(14:2)#,   EOF flags - :EOD/:
ACBSPTYRC    = ACB(40)#,          spooled dev type/recsize
ACBSPTYPE    = ACBSPTYRC.(0:6)#,  spooled dev type
ACBSPREC     = ACBSPTYRC.(6:10)#, spooled dev rec size
ACBSPFOPT    = ACB(41)#,          spooled dev FOPTIONS
ACBSPAOPT    = ACB(42)#,          spooled dev AOPTIONS
ACBSPKDOK    = ACB(43)#,          IDD/ODD index
ACBNOWAITDA  = ACB00BL(22)#,      Nowait disc address
```



```
Spare        = ACB(46)#,          Unused
ACBNOWAITLDEV= ACB(47)#,          #owait logical device
ACBP1P2      = ACB00BL(24)#,      Used by FDEVICECONTROL
ACBP1        = ACB(48)#,            "  "    "    "
ACBP2        = ACB(49)#;            "  "    "    "
```

Discussion:

ACBABORTAREAD — This flag is used to abort a broken terminal re-read. The flag is set via the ABORT parameter to FUNBREAK. If the flag is set then the READ PENDING message will be aborted along with the re-read. This feature is needed to handle the BREAK...:ABORT, etc. situation.

ACBACCCL — This is the access class part of the device type number. The following are legal values:

0 - direct (e.g. disc)
1 - serial input (e.g. card reader)
2 - parallel input/output (e.g. terminal)
3 - serial input/output (e.g. magnetic tape)
4 - serial output (e.g. line printer)

ACBACCESS — This is the access bit map for the file. The following are the bit definitions of this eight-bit field:

(0:1) - unused
(1:1) - unused
(2:1) - read
(3:1) - append
(4:1) - write
(5:1) - lock
(6:1) - execute
(7:1) - save

This access security is determined by the ACCCNECK intrinsic and enforced by the file systen.

ACBAOPTIONS — This is the AOPTION#S in effect for this file access.

ACBBINARYIO — This bit controls full eight bit transfers on the 2644 page mode terminal. It is adjusted by FCONTROL(26) and FCONTROL(27).

ACBBLK — This is the block number of the current variable record format block. Applicable if the record format is variable.

ACBBLKFACT — This is the blocking factor for the file. It is the number of records in a block. Legal values range from 1 to 255.

ACBBREAK — This is the break mode flag. It is applicable if the ACB is for $STDIN or $STDLIST. If set it means that the BREAK key has been hit and that the CI should have high priority access to the ACB. The flag will be cleared when a RESUME or ABORT is issued.

ACBBSIZE — This is the block size, in words, of the file.

ACBBTFACT — This is the total number of blocks transferred to and from the file. The initial value is 00.

ACBBUFUSED — This is the word index, relative to the base of the block, for the selected record within the block. This is applicable if the file access is buffered.

ACBCARRIAGE — This bit signifies that the file has carriage control. It is the same as the carriage control bit in ACBFOPTIONS if the file is spooled. If not spooled, the bit is zero, and IOMOVE will pass the FWRITE carriage control parameter directly to the driver rather than embedding it as the first character of the output record.

ACBCTL — This is the CONTROL parameter from the last FWRITE. This value is pertinent if the file was opened with carriage control.

ACBCURRABUF — This is the buffer number (0-relative) containing the most recently referenced record. Applicable if the file access is buffered.

ACBDADDR — This is the logical device number of the file. For a disc file this is the logical device number of the first extent.

ACBOEFBLOCK — This bit signifies that the file is to be accessed with default blocking. The bit is initialized from the FOPEN stateword STATE. It does not need to be in the ACB; it is mentioned here only to signify that the bit is effectively used due to the way ACBLSTATE is initialized from STATE.

ACBOISP — This is the file close disposition derived from the FOPEN# call. The only way this can be specified is via a file equation. The legal values are the same as those for FCLOSE. ACBONTYPE This is the file reference format type number and is derived from the FOPEN call. The following are legal values:

0 - full name
1 - account name absent
2 - group and account name absent
3 - null name

This information is needed by FRENAME.

ACBDTYPE — This is the device type number of the file. The following are legal values (octal):

0 - moving head disc
1 - fixed head disc
7 - foreign disc
10 - card reader
11 - paper tape reader
20 - terminal
24 - card reader/interpreter/punch
26 - SSLC
27 - programmable controller
30 - magnetic tape
31 - serial disc
40 - line printer
41 - card punch
42 - paper tape punch
43 - CALCOMP 500 plotter
44 - CALCOMP 600 plotter
45 - CALCOMP 700 plotter

ACBEOF — This bit is set when EOF has been sensed.

ACBEOFS — This is the type of EOF detected on $STDI#(X). This field consists of two bits:

(0:1) - super colon (i.e. EOF for $STDINX)
(1:1) - regular colon (i.e. EOF for $STDI#)

Applicable for multi-access to $STDI#(K) only.

ACBERROR — This is the error number for the file. It is used by all intrinsics except FOPEN. When an error is detected the error number is placed in this cell. The error number is cleared at the beginning of each callable intrinsic except FCHECK (which reads it).

ACBFCB — This is the FCB vector for the file. Applicable only to disc files.

ACBFKEYS — This bit controls the definition of the f1 and f2 function keys on the 2644 page mode terminal; it is adjusted by FCONTROL(32) and FCO#TROL(33). (Obsolete function)

ACBFNUM — File number, range from 1 to 255. Used mostly for calling routines that access things such as labels by file number.

ACBFOPTIONS — This is the FOPTIONS in effect for this file access.

ACBFPTR — This is the sequential access record pointer; it contains the next sequential record number. The initial value is 00. This value is used only by the FREAD, FWRITE and FUPDATE intrinsics. However the value is

maintained by all data transferring file system intrinsics.

ACBFMAVTX — This is the entry index into the file multi-access vector table (FMAVT). This is valid if the file access is multi-access.

ACBGSTATE — These are miscellaneous state flags. These are "global" in nature in that they are the same for all accessors in a multi-access environment. The constituent bits are described individually.

ACBGSTATUS — This is the general part of the last I/O status for the file. The following are the legal values:

0 - pending
1 - successful
2 - end of file
3 - unusual condition
4 - irrecoverable error

ACBHIBLK — This is the highest block number for which an anticipatory read has been issued, and is applicable if the file access is buffered. The initial value is -10.

ACBHIT — This is the buffer hit flag. If set it indicates that the last read or write request was serviced without any physical I/O required. This flag is used only for performance measurement. The code which manipulates it is optional to the file system, and is controlled by compiler toggle X3.

ACBINHIBCRLF — This bit controls the termination of lines written to the terminal. If not set then each line is terminated with a CR and LF; if set then no line termination characters are used. This bit is valid if the file is a terminal file; it is adjusted by FSETMODE.

ACBLINECTL — This is the line control bit. If not set then each line is post-spaced; if set then each line is prespaced. This bit is used by line printers and terminals only. It is adjusted by FCONTROL(1) and FWRITE with the appropriate carriage control.

ACBLPCTL — This are the line and page control bits, which are described separately.

ACBLSTATE — These are miscellaneous state flags. They are "local" in nature in that they may be different for each accessor in a multi-access environment. Bits (9:6) are initialized from the stateword local variable called STATE in FOPEN; the ten remaining bits are initialized individually. The constituent bits are described individually.

ACBMODE — These are miscellaneous mode flags. The constituent bits are described individually.

ACBNAME — This is the local file name. The name is eight bytes in length with trailing blanks added.

ACBNEWEOF — This flag when set indicates that a new tape mark should be written before the tape is rewound or backspaced. Applicable only to magnetic tape files.

ACBNOWAITEOF — This bit is used to save the value of the local EOF advanced flag NEWEOF in IOMOVE between the I/O initiation and I/O completion calls. This flag is applicable if the file is accessed in nowait I/O mode.

ACBNOWAITMODE — This cell is used to save the I/O mode between nowait I/O initiation and completion calls. If the bit is set then the last I/O request was a write; otherwise it was a read. This cell is pertinent if the file is accessed in nowait I/O mode.

ACBNUMBUFS — This is the number of buffers, less one, used for the file access. Applicable if the file access is buffered.

ACBPAGECTL — This is the page control bit. If not set then a page is assumed to consist of 60 lines (auto page eject); if set then a page is assumed to consist of 66 lines (no auto page eject). This is used primarily for line printers but is also valid for terminals; these are the only devices for which this is valid. This bit is adjusted by FCONTROL(1) and FWRITE with the appropriate carriage control.

ACBPRIV — This flag when set indicates that the file is privileged in that it has a negative file code; the user must be in privileged mode to access it.

ACBQSTATUS — This is the qualifying part of the last I/O status for the file. The values are unique for each general status part. See I/O System IMS for all legal values.

ACBQUIESCE — This bit controls critical output verification. If set, buffered output is guaranteed to have been written to the device when control is returned to the user. This bit is adjusted by FSETMODE.

ACBREADCODE — This field consists of the input EOF checking type and mode, and is used to generate the P1 parameter to ATTACHIO. These fields are described individually.

ACBREADMODE — This field controls the input EOF checking mode. It is 00 for reading $STDIN, 01 for reading $STDINX, and 10 for the command interpreter.

ACBREADTYPE — This field controls the input EOF checking type. It is 01 for JOBs, 10 for SESSIONs, and 00 for DATA.

ACBRSIZE — This is the file's record size in positive bytes.

ACBRTFACT — This is the total number of records transferred to and from the file. The initial value is 00.

ACBSAVEEOFS — This field is used to save the contents of ACBEOFS during BREAK mode processing.

ACBSHCNT — This is the total number of LACBs that exist for this PACB. Valid if the file access is multi-access.

ACBSHCNTIN — This is the total number of input-only LACBs that exist for this PACB. Valid if the file access is multi-access.

ACBSHCNTS — This is the total LACB and total input-only LACB counts, each of which is described separately.

ACBSIZE — This is the size, in words, of the ACB. The complete size (including buffers) may be calculated from the DST size containing the ABC. It does not include the buffering extension, if present.

ACBSPAOPT — This is the AOPTIONS for the spooled device. Applicable if the file access is to a spooled device.

ACBSPFOPT — This is the FOPTIONS for the spooled device. Applicable if the file access is to a spooled device.

ACBSPOOLED — This is the spooled device flag. If set then the file access is to a spooled device.

ACBSPOOLIO — This field is a combination of the spooled device flag and the input/output mode of the spooled device. Legal values are:

00 - not spooled
01 - illegal
10 - input spooling
11 - output spooling

ACBSPREC — This is the record size, in bytes, of the spooled device. Applicable if the file access is to a spooled device.

ACBSPTYPE — This is the device type (from the LDT) of the spooled device. Applicable if the file access is to a spooled device.

ACBSPTYRC — This cell contains the spooled device type and record size, which are described separately.

ACBSPVDEV — This is the logical device number of the spooled device. Applicable if the file access is to a spooled device.

ACBSPXOOX — This is the index into the IOO or ODD for a spoolfile. Applicable if the file access is to either a spooled device or a spoolfile.

ACBSTATUS — This is the last I/O status for the file. It comes from the I/O status part of the IOCB returned by ATTACHIO. Not all ATTACHIO calls update this cell.

ACBSTOPCHAR — This is the record termination character used for terminal reads. This character can be changed via FCONTROL(25).

ACBSTREAM — This bit signifies inter-block garbage for disc files. If set, the block size is a multiple of 128 words and therefore there is no garbage data between blocks. This fact is used to improve multirecord I/O by mapping the request into as few ATTACHIOs as possible.

ACBSUBCL — This is the sub-class part of the device type number. The sub-class is unique for each access class. The following are the legal sub-class values for each device class:

0 - direct
  0 - moving head disc
  1 - fixed head disc
  7 - foreign disc
1 - serial input
  0 - card reader
  1 - paper tape reader
2 - parallel input/output
  0 - terminal
  4 - card reader/punch
  6 - SSLC
  7 - programmable controller
3 - serial input/output
  0 - magnetic tape
  7 - serial disc
4 - serial output
  0 - line printer
  1 - card punch
  2 - paper tape punch
  3 - CALCOMP 500 plotter
  4 - CALCOMP 600 plotter
  5 - CALCOMP 700 plotter

RCBTRPEERROR — This bit controls the reporting of recovered magnetic errors. If not set the recovered errors are not reported to the user; if set then recovered errors are reported to the user by returning CCL and error number 39. Valid if the file is a magnetic tape file. This bit is adjusted by FSETMODE.

RCBTBLOCK — This bit controls block mode transfers on the 2644 page mode terminal. This bit is adjusted by FCONTROL(28) and FCONTROL(29).

RCBTLOG — This is the last I/O transmission log for the file. It comes from the I/O transmission log part of the IOCB returned by ATTACHIO. Not all ATTACHIO calls update this cell.

RCBVOADDR — This is the volume table index for the file. Applicable if the file is a disc file.

RCBKMITCRLF — This bit controls CR and LF insertion into the user buffer on the 2644 page mode terminal. This bit is adjusted by FCONTROL(30) and FCONTROL(31).

If present, the PRCB buffering extension contains from one to sixteen block buffers each having the following format:



Other identifiers used:

```
BLKFLAGW       = BLK(1)#,          Flag and LDEV word
BLKLDEV        = BLKFLAGW.(0:8)#, block logical device number
BLKFLAGS       = BLKFLAGW.(0:8)#, block I/O flags
BLKUNALLOCEKT  = BLKFLAGW.(10:1), Block from unalloc. extent
BLKREVERSE     = BLKFLAGW.(11:1), FREADBACKWARD (not used )
BLKODNTWAIT    = BLKFLAGW.(12:1), I/O status not checked
BLKIOOUT       = BLKFLAGW.(13:1)#,last I/O was write?
BLKDIRTY       = BLKFLRGW.(14:1)#,buffer modified?
BLKIOPEND      = BLKFLAGW.(15:1)#,I/O in progress?
BLKIOCOMP      = BLKFLAGW.(14:2)#,I/O complete - not dirty
BLKIOCB        = BLKDBL(1)#,       IOCB
```


Discussion:

BLKBLOCK — This is the block number of the data contained in the buffer. A value of -1D indicates that the buffer is empty.

BLKBUFFER — This is the actual file system buffer space. Each buffer is exactly one file block in size.

BLKDADDR — This is the block's logical device and sector number.

BLKDIRTY — This flag is set if the contents of the buffer has been modified. When the block buffer is re-used this flag is checked to see if the block needs to be written to the device.

BLKOONTWAIT — This bit will be on if the I/O was already completed via "DONT'WAIT" but the status has not been checked yet. Check the status before using the block in the buffer.

BLKEXTBASE — This is the sector address of the extent base in which the block resides. This is used for disc caching.

BLKEKTSIZE — The size, in sectors, of the extent in which the block resides. This is used for disc caching.

BLKFLAGS — These are the miscellaneous flags associated with the block, which are described separately.

BLKIOCB — This is the IOCB returned by the I/O system when the block I/O has completed. On a blocked I/O request this is obtained from the ATTACHIO call; on an unblocked I/O request this is obtained from WAITFORIO.

BLKIOCOMP — This is the buffer modified flag (BLKDIRTY) and the I/O in progress flag (BLKIOPEND), which are described separately. This field is usually interrogated to see if it contains the value 2, which means that the buffer has been modified but not yet written to the device.

BLKIOOUT — This is the mode of the I/O operation for the block. It is set by a write and cleared by a read.

BLKIOPEND — This is the I/O in progress flag. It is set if the I/O is pending; it is cleared when the I/O has completed.

BLKIOQX — This is the IOQ index of the unblocked I/O request for the block. It is used as the argument to WAITFORIO, which ensures the completion of the I/O request.

BLKLDEV — This is the logical device number of the block. (Valid only for disc files.)

BLKLSTAT — The I/O status part of the IOCB consists of the PCB number and the error code for the completed I/O request.

BLKTLOG — The transmission log part of the IOCB is the number of words or bytes transferred by the the I/O request.

BLKREVERSE — This bit would indicate that we are reading back- wards from a tape. However, currently FREADBACK- WARDS can only be performed unbuffered.

BLKUNALLOCEXT — This bit signifies that the block was "read" from an unallocated extent. Actually, the buffer was simply cleared with fill characters. Therefore, if a write is attempted to the block residing in this buffer, it must pass through FCONVBLK to allocate the extent first.

File Control Block (FCB)

The FCB coordinates access to a file on a sharable device. At present the only sharable device is a disc, so only disc files have FCBs.

The information contained in an FCB is derived from the file label. The FCB is used to hold this information, rather than the file label, since it can be accessed more quickly.

There are two strategies to choose from in deciding where to place the FCB. If the file has been opened exclusive and no other process could possible share this file, then the FCB is placed into the PXFILE area (or in a NOBUF expandable CBT if it won't fit in the PXFILE area or if the program is run with NOCB). If the file could possible be shared, then the FCB is always placed in a shared control block table. The number of a data segment containing a list of shared file systen data segments is kept in systen global location 1076 octal. The size of the FCB depends on the maximum number of extents specified at FOPEN; there are 44 (octal) words plus two per extent. There will be at least one extent, since the file label always exists in the first extent. The FCB extent map is in terms of logical device and sector number. The extent map in the file label is in terms of volume rather than logical device; the map is converted by VTABDLDEV when the label is read, and converted back by LDEVTOVTAB when the label is written to disc.

The FCB has the following format:







Other identifiers used:

```
FCBSIZE      = FCB.(2:14)#,     size in words
FCBLKST      = FCB(4).(0:2)#,   previous lock state
FCBDTYPE     = FCB(4).(2:6)#,   device type
FCBCRUNCH    = FCB(4).(8:1)#,   pending crunch disposition
FCBSUBTYPE   = FCB(4).(12:4)#,  device subtype
FCBOCNTOUT   = FCB(5).(0:8)#,   no. accessors - output
FCBOCNT      = FCB(5).(8:8)#,   no. accessors
FCBCLASSFLG  = FCB(9).(0:1)#,   PV class flag
FCBMVTABX    = FCB(9).(4:4)#,   Mounted volume table index
FCBVMASX     = FCB(9).(8:8)#,   Volume Mask
FCBLBLEOF    = FCB(16).(0:8)#,  no. labels written
FCBLBL       = FCB(16).(8:8)#,  no. labels available
FCBBLKFACT   = FCB(18).(0:8)#,  blocking factor
FCBSECTPBLK  = FCB(18).(8:8)#,  sectors per block
FCBSECTOFF   = FCB(19).(0:8)#,  sector offset to data
FCBOISP      = FCB(19).(8:3)#,  pending disposition
FCBNUMEKTS   = FCB(19).(11:5)#, no. extents less 1
FCBOCNTIN    = FCB(21).(8:8)#,  no. accessors - input
FCBLABEL     = FCBOBL(18)#,     label LDEV and sector
FCBLDEV      = FCB(36).(0:8)#,  label LDEV
```

Discussion:

FCBACBOST — This is the OST of the ACB that was created at the same time as the FCB. This is used in conjunction with FCBNEWFCBOST when relocating the FCB.

FCBACBV — This is the vector table entry of the ACB that was created at the same time as the FCB. This is used in conjunction with FCBNEWFCBV when relocating the FCB.

FCBAN — This is the account name of the file. It is eight bytes in length with trailing blanks added.

FCBBLKFACT — This is the blocking factor of the file. It is the number of logical records in a physical block. Legal values range from 1 to 255.

FCBDEVICE — This specifies the device on which the file resides. If it is positive then it represents a logical device number; if negative it represents a (negative) device class index.

FCBOISP — This is the pending FCLOSE disposition for the file. Legal values are:

0 - no change
1 - save permanent
2 - save temporary and rewind
3 - save temporary but do not rewind
4 - release
7 - invalid file (file label access error)

FCBCRUNCH — This bit governs if space will be returned beyond the EOF upon the last FCLOSE of the file.

0 - no change
1 - return space beyond EOF

FCBDTYPE — This is the device type number of the first extent of the file. See ACBDTYPE for a list of legal values.

FCBEND — Block number of the file's EOF, relative to FCBSTART.

FCBEOF — This is the end-of-file pointer for the file. It is a double integer representing the number of records in the file. It can also be viewed as the record number of the next record past EOF.

FCBEXCLSTAT — This is the exclusive status of the file access. If -1 then the file is being accessed exclusively; otherwise it is the number of semi-exclusive accessors.

FCBEXTMAP — This is the extent map of the file. The number of extents is specified by FCBNUMEKTS; a 0D extent descriptor indicates that the extent has not been allocated.

FCBEXTSIZE — This is the extent size, in sectors, of the file. All extents in the file except possibly the last have this size. This is a logical value, and legal values range from 1 to 65535 sectors. This restricts the maximum file size to 2097120 sectors (268,431,360 words).

FCBFLIM — This is the end-of-space pointer for the file. It is a double word integer representing the maximum number of records (fixed length record format) or blocks (undefined or variable length record format) in the file.

FCBFOPTIONS — This is the FOPTIONS in effect for the file.

FCBGN — This is the group name of the file. It is eight bytes long with trailing blanks added.

FCBLOBL — This is the logical device and sector number of the file label, which is the same as the first extent descriptor.

FCBLASTEXTSIZE This is the size, in sectors, of the last extent in the file. If the file has one extent then this is the same as FCBEXTSIZE; otherwise this value may be different from FCBEXTSIZE. This is the size of the last physical extent for the file; it is not the size of the last allocated extent.

FCBLBL This is the number of user labels allocated for the file. Since each label is a sector long, this is also the number of sectors allocated for user labels.

FCBLBLEOF This is the end-of-data pointer for the user labels. It is analogous to FCBEOF in that it represents the number of labels written. The initial value is 0.

FCBLDEV This is the logical device number of the first extent of the file.

FCBLKST This is the previous lock state of the file and is derived from the file label. Legal values are:

0 - no accessors
1 - read
2 - write
3 - read/write

FCBMVTABX If the file resides on a private volume, then this field represents the mounted volume table index of the volume set entry on which the file resides.

FCBNEWFCBDST This is the DST of the new FCB for the file. It is used in conjunction with FCBACBDST to move the FCB to a system (shared FCB) control block table when the second accessor is established. If this value is zero then there is no new FCB; if nonzero then a new FCB has been created.

FCBNEWFCBV This is the vector table entry of the new FCB for the file. It is used in conjunction with FCBACBV to move the FCB to a system (shared FCB) control block table when the second accessor is established. If this value is zero then there is no new FCB; if nonzero then a new FCB has been created.

FCBNUMEXTS This is the maximum number of extents, less one, allowed for the file. It is not the number of extents presently allocated, which is always determined by counting nonzero entries in the extent map.

FCBNUMOPENCLSREC Number of open and close records in the message file.

FCBOCNT This is the number of accessors for the file. Alternatively it can be viewed as the number of PACBs created for the file.

FCBOCNTIN This is the number of file accessors having input access.

FCBOCNTOUT This is the number of file accessors having output access.

FCBRIN This is the RIN number used to support dynamic locking (i.e. FLOCK and FUNLOCK) for the file. If there is no dynamic locking then this number is zero.

FCBSECTOFF This is the sector offset from the file label to the first block of the file. This is not necessarily equal to FCBLBL+1 since an integral number of blocks are allocated for the file and user labels.

FCBSECTPBLK This is the number of sectors in a block for the file.

FCBSIZE This is the size, in words, of the complete FCB. It includes the extent map.

FCBSTART Block number of the file's start, excluding the file label block.

FCBSUBTYPE This is the device subtype number of the first extent.

FCBUSERLBL This field describes the user labels for the file. It consists of FCBLBL and FCBLBLEOF, described separately.

FCBVMASK If the file resides on a private volume set, this bit mask signifies which volume of the set in which the file resides. Bit 15 is on it resides on the first volume, bit 14 if on the second, etc.

File Label (FLAB)

The file label has the following format:

0 1 2 3	7 8	12 13 14 15		
FILE NAME - 1ST CHAR.	FILE NAME - 2ND CHAR.		0	FLLOCNAME
FILE NAME - 3RD CHAR.	FILE NAME - 4TH CHAR.		1	
FILE NAME - 5TH CHAR.	FILE NAME - 6TH CHAR.		2	
FILE NAME - 7TH CHAR.	FILE NAME - 8TH CHAR.		3	
GROUP NAME - 1ST CHAR.	GROUP NAME - 2ND CHAR.		4	FLGRPNAME
GROUP NAME - 3RD CHAR.	GROUP NAME - 4TH CHAR.		5	
GROUP NAME - 5TH CHAR.	GROUP NAME - 6TH CHAR.		6	
GROUP NAME - 7TH CHAR.	GROUP NAME - 8TH CHAR.		7	
ACCT NAME - 1ST CHAR.	ACCT NAME - 2ND CHAR.		10	FLACCTNAME
ACCT NAME - 3RD CHAR.	ACCT NAME - 4TH CHAR.		11	
ACCT NAME - 5TH CHAR.	ACCT NAME - 6TH CHAR.		12	
ACCT NAME - 7TH CHAR.	ACCT NAME - 8TH CHAR.		13	
CREATOR NAME - 1ST CHAR.	CREATOR NAME - 2ND CHAR.		14	FLUSERID
CREATOR NAME - 3RD CHAR.	CREATOR NAME - 4TH CHAR.		15	
CREATOR NAME - 5TH CHAR.	CREATOR NAME - 6TH CHAR.		16	
CREATOR NAME - 7TH CHAR.	CREATOR NAME - 8TH CHAR.		17	
LOCKWORD - 1ST CHAR.	LOCKWORD - 2ND CHAR.		20	FLLOCKWORD
LOCKWORD - 3RD CHAR.	LOCKWORD - 4TH CHAR.		21	
LOCKWORD - 5TH CHAR.	LOCKWORD - 6TH CHAR.		22	
LOCKWORD - 7TH CHAR.	LOCKWORD - 8TH CHAR.		23	
SECURITY MATRIX			24	FLSECMX
			25	
FILE LANGUAGE ATTRIBUTE		SR S	26	

File Label (Cont.)

CREATION DATE	27	FLCREATE
LAST ACCESS DATE	30	FLLASTACC
LAST MODIFICATION DATE	31	FLLASTMOD
FILE CODE	32	FLFILECODE
C | MVTABX | VMASK	33	FLPVINFO
S | R | L | X | SUBTYPE | DISC TYPE | R/W	34	FLLOCK
NO. USER LABELS WRITTEN | NO. USER LABELS AVAIL.	35	FLUSERLBL
FILE LIMIT IN BLOCKS	36 37	FLFLIM
FCB VECTOR	40 41	FLFCBVECT
CHECKSUM	42	FLCHECKSUM
COLD LOAD ID	43	FLCLID
FOPTIONS	44	FLFOPTIONS
RECORD SIZE IN BYTES	45	FLRECSIZE
BLOCK SIZE IN WORDS	46	FLBLKSIZE
SECTOR OFFSET | | NO. EXTENTS -1	47	
LAST EXTENT SIZE IN SECTORS	50	FLLASTEXT-SIZE
EXTENT SIZE IN SECTORS	51	FLEXTSIZE
END OF DATA POINTER	52 53	FLEOF
VOLUME TABLE INDEX |	54	FLEXTMAP
1ST EXTENT SECTOR NUMBER	55	

File Label (Cont.)



Other identifiers used:

```
FLSECURE     = FLAB(22).(15:1)#,   file secure bit
(FLSRRELEASE)= FLAB(22).(14:1)#,   STORE/RESTORE released bit
FLCLASSFLG   = FLPVINFO.(0:1)N,    Class flag bit
FLMVTABX     = FLPVINFO.(4:4)#,    Mounted volume table index
FLVMASK      = FLPVINFO.(8:8)N,    Volume mask
(FLSTORE)    = FLAB(28).(0:1)N,    file being stored
```



```
FLRESTORE    = FLAB(28).(1:1)N,    file being restored
(FLLOAD)     = FLAB(28).(2:1)#,    File loaded
FLEXCL       = FLAB(28).(3:1)#,    exclusive access
FLSR         = FLAB(28).(0:2)#,    S & R bits
FLSRL        = FLAB(28).(0:3)#,    S, R, & L bits
(FLSALX)     = FLAB(28).(0:4)N,    S, R, L, & K bits
FLSUBTYPE    = FLAB(28).(4:4)N,    device subtype
FLDTYPE      = FLAB(28).(8:6)N,    device type
FLSTATUS     = FLAB(28).(14:2)#,   write/read status
(FLLBLEOF)   = FLAB(29).(0:8)#,    no. labels written
(FLLBL)      = FLAB(29).(8:8)#,    no. labels available
FLSECTOFF    = FLAB(39).(0:8)#,    sector offset to data
FLNUMEXTS    = FLAB(39).(11:5)#,   no. extents less 1
FLLABEL      = FLABDBL(22)#,       label VTAB and sector
FLVTAB       = FLAB(44).(0:8)#,    label VTAB index
```

Discussion:

FLACCTNAME — This is the account name of the file. It is eight bytes in length with trailing blanks added.

FLALLOCDATE — Date that the file was allocated on this system.

FLALLOCTIME — Doubleword containing the time that the file was allocated on this system.

FLBLKSIZE — This is the block size, in sectors, of the file.

FLCHECKSUM — This is the exclusive-OR checksum of the file label (excluding words 34, 42, and 43 octal) and is used for error detection. Each time the file label is read from disc the check sum is calculated and compared against the value recorded in the file label. Similarly, each time the file label is written to the disc the check sum is calculated and inserted into the file label.

FLCLID — This is the cold load number in effect the last time that the file was accessed. This should always be the current cold load number. If it is not, it means that the system crashed while the file was open and that the data in the File label should be "reset" (principally the FCB vector FLFCBVECT).

FLCREATE — This is the creation date of the file. It is in the format defined by the intrinsic CALENDAR.

FLDEVNAME — This is the FOPEN device specification that was used when the file was created. This information is needed when new extents are allocated.

FLDTYPE — This is the device type number of the first extent of the file; see ACBDTYPE for a list of legal values. This value is determined by configuration.

FLEND — Number of current data blocks (that is, the end of file block number relative to the start of file).

FLEOF — This is the end-of-file pointer for the file. It is a double word integer representing the number of records in the file. It can also be viewed as the record number of the next record past EOF.

FLEXCL — This is the exclusive access flag for the File. If set it means that the file has been opened exclusively by a single accessor. If not set then the file is potentially accessible by others.

FLEXTMAP — This is the extent map of the file. The number of extents is specified by FLNUMEXTS; a 0D extent descriptor indicates that the extent has not been allocated.

FLEXTSIZE — This is the extent size, in sectors, of the file. All extents in the file, except the last, have this extent size. This is a logical value, and legal values range from 1 to 65535 sectors. This limits the maximum file size to 2097120 sectors.

FLFCBVECT — If nonzero, this is the vector of the FCB for the file. If zero, the File is not being accessed.

FLFILECODE — This is the file code of the file. Known values are:

1024	User Subprogram Library
1025	Basic Data
1026	Basic Program
1027	Basic Fast Program
1028	Relocatable library
1029	Program File
1031	Segmented Library
1035	View Form File
1036	View Fast Forms File
1037	View Reformat File
1040	Cross Loader ASCII File (SAVE)
1041	Cross Loader Relocated Binary File
1042	Cross Loader ASCII File (DISPLAY)
1050	Edit Quick File
1051	Edit KEEPD File (COBOL)
1052	Edit TEXT File (COBOL)
1054	TDP Diary File
1055	TDP Proof Marked DMARKED
1056	TDP Proof Marked non-COBOL File
1057	TDP Proof Marked COBOL File
1058	TDP Workfile
1059	TDP Workfile (FORM)
1060	RJE Punch File
1070	QUERY Procedure File
1080	KSAM Key File

1083	GRAPH Specification File
1084	User Logging Log File
1090	Self-describing File
1100	HPWORD Document
1101	HPWORD Hyphenation dictionary
1102	HPWORD Configuration File
1103	HP 2601 Environment File
1110	IDS/3000 Character Cell File
1111	IDS/3000 Form File
1112	IFS/3000 Environment File
1114	Graphics Image in RASTR Format
1130	DPT/3000 Log File
1131	TEPE/3000 Script File
1132	TEPE/3000 Log File
1133	APS/3000 Log File
1139	MPEDCP/DRP Log File
1140	HPToolset Root File
1141	HPToolset Data File
1145	Drawing File for HPDRAW
1146	Figure File for HPDRAW
1147	Reserved
1148	Reserved
1149	Reserved
1152	Compressed SLATE File
1153	Expanded SLATE Workfile
1156	Store File for RAPID/3000 Utility DICTDBU
1157	Code File for Transact/3000 Compiler
1158	Code File for Report/3000 Compiler
1159	Code File for InForm/3000 Compiler
1166	HPDESK Distribution list
1167	HPDESK Text
1177	Term Type File
1178	Term Vertical Format Control File
1192	Network Configuration File
1193	Network Trace File
1194	Network Log File
1211	Reserved
1212	Reserved
1226	VC File
1227	DIF File
1228	Language Definition File
1229	Character Set Definition File
1230	Formatted Application Message Catalog
1235	Reserved
1236	Reserved
1258	Pathflow STATIC File
1259	Pathflow DYNAMIC File
8000 to 9099	Reserved for APL

FLFLIM — This is the end-of-space pointer for the file. It is a double integer representing the maximum number of

records (fixed length record format) or blocks (undefined or variable length record format) in the file.

FLFOPTIONS This is the FOPTIONS of the file.

FLGRPNAME This is the group name of the file. It is eight bytes long with trailing blanks added.

FLLABEL This is the volume table index and sector number of the file label, which is the same as the first extent descriptor. FLLASTACC This is the last access date of the file. It is in the format defined by the intrinsic CALENDAR.

FLLASTMOD This is the last modification date of the file. It is in the format defined by the intrinsic CALENDAR.

FLLASTEXTSIZE This is the size, in sectors, of the last extent in the file. If the file has one extent, then this is the same as FLEXTSIZE; if the file has more than one extent, then this value may be different from FLEXTSIZE. This is the size of the last physical extent for the file; it is not the size of the last allocated extent.

FLLBL This is the number of user labels allocated for the file. Since each label is a sector long, this is also the number of sectors allocated for user labels.

FLLBLEOF This is the end-of-data pointer for the user labels. It is analogous to FLEOF in that it represents the number of labels written.

FLLOAD This is the LOADED flag for the file. If set, it means that the file is a loaded program or SL file and cannot be modified except by a privileged accessor. This flag is set and cleared by the loader, not the file system.

FLLOCK This identifies the word containing the lock bits, which are described separately.

FLLOCKWORD This is the lock word of the file. It is eight bytes long with trailing blanks added. If it is all blanks, then the file does not have a lockword.

FLLOCNAME This is the local name of the file. It is eight bytes long with trailing blanks added.

FLNUMEXTS This is the number of extents, less one, allowed for the file. It is not the number of extents allocated. Legal values range from 0 to 31, i. e., 1 to 32 extents.

FLNUMOPENCLSREC Number of open and close records in the message file.

FLPVINFO File label private volume information. This is in the same format as the FCBPVINFO.

FLRECSIZE This is the record size of the file in negative bytes.

FLRESTORE This is the RESTORE flag for the file. If set, it means that the file is being RESTOREd and cannot be accessed. RESTORE also sets the STORE bit for the file (FLSTORE); see FLSR for a full description of the use of these bits. This flag is set and cleared by STORE/RESTORE, not the file system.

FLSECMX This is the security matrix of the file. The bits are organized into five groups of six bits each. (Bits 0:2 are not used.) The groups correspond to the access types: READ, APPEND, WRITE, LOCK, and EXECUTE. Within each group, each bit specifies who may have the access: ANY, ACCOUNT MGR, ACCOUNT LIB- RARIAN, GROUP, GROUP LIBRARIAN, CREATOR.

FLSECTOFF This is the sector offset from the file label to the first block of the file. This is not necessarily equal to FLLBL+1 since an integral number of blocks are allocated for the file and user labels.

FLSECURE This is the file security enforcement flag for the file. If not set, then the file has been RELEASEd and the security matrix FLSECMX should be ignored. If set, then secure as specified by the security matrix.

FLSR This is the STORE and RESTORE flags for the file, which are described separately. STORE and RESTORE decode the two-bit field to indicate their operation. Legal values are:

0 - file not in use by either STORE or RESTORE
1 - illegal value
2 - file being STOREd
3 - file being RESTOREd

The file system interprets the leftmost bit as indicating that the file is being accessed by either STORE or RESTORE. The rightmost bit is interpreted as indicating what access should be permitted: 0 (file being STOREd) allows read access; 1 (file being RESTOREd) allows no access. This field is set and reset by STORE/RESTORE, not the file system.

FLSRL This is the STORE, RESTORE and LOADED flags for the file, which are described separately.

FLSALX This is the STORE, RESTORE, LOADED and exclusive flags for the file, which are described separately.

FLSAVERELEASE This flag is used by STORE/RESTORE. If a file is STOREd with the ";RELEASE" keyword, STORE will set this flag

in the tape copy of the file label. RESTORE will allow any user to access such files, regardless of the file's normal security. If this bit is off in the tape copy of the file label, RESTORE applies normal security checks (as defined by the information in FLSECMX and FLSECURE). This bit is zero for files on disc.

FLSTART Block number of the file's start, excluding the file label block.

FLSTATUS This is the read/write status of the file. Legal values are:

0 - no accessors
1 - read
2 - write
3 - read/write

FLSTORE This is the STORE/RESTORE flag for the file. If set it means that the file is being either STOREd or RESTOREd. The RESTORE bit (FLRESTORE) must be interrogated to determine which operation is taking place; see FLSR for a full description of the use of these bits. This flag is set and cleared by STORE/RESTORE, not the file system.

FLSUBTYPE This is the device subtype number of the first extent of the file. This value is determined by configuration.

FLUSERID This is the creating user name of the file. It is eight bytes long with trailing blanks added.

FLUSERLBL This field describes the user labels of the file. It consists of FLLBL and FLLBLEOF, which are described separately.

FLVTAB This is the volume table index of the first extent of the file.

File Multi-Access Vector Table (FMAVT) DST(%54)

The FMAVT is used to locate shared PACB's for files opened multi-access. When an old disc file has been opened multi-access, the FMAVT is searched to determine if the file has previously been opened. The JITDST and the DADDR found in the FMAVT are compared to the JITDST of the job and the DADDR of the device or disc file being opened multi-access. If an entry exists for the file, then the PACB can be easily located for that file. If this is the first process opening the file, then an entry is created and inserted into the FMVAT for the file.

Spoolfiles are opened multi-access, therefore, they will have entries in the FMAVT. $STOIN and $STOLIST also have entries in the FMAVT since they too are opened multi-access.

Zero Entry Format

CURRENT TABLE SIZE	0 FM'CURR'SIZE
ENTRY SIZE = 6	1 FM'ENTRY'SIZE
MAXIMUM TABLE SIZE	2 FM'MAX'SIZE
0	3
0	4
0	5

Descriptions:

FM'CURR'SIZE The current size of the FMAVT in words. This value increases in increments of %200 words until FM'MAX'SIZE is reached.

FM'MAX'SIZE The maximum allowable size in words that the FM'CURR'SIZE can get. The current value of this is %4000. FM'MAX'SIZE can be changed only by changing the code in Initial. The open of the multi-access file is failed if this maximum is reached.

FM'ENTRY'SIZE Size in words of an FMAVT entry, 6 words at present.

Typical Entry Format




```
FM'DEVICE    = FMAVT(0).(2:1)N,    Device bit
FM'GLOBAL    = FMAVT(0).(1:1)N,    Global multi-access bit
FM'LDEV      = FM'DADDA(0).(0:8)N, Logical device number of file
```

Descriptions:

FM'DADDR — The disc address of the File label for disc files. For device files, the disc address is zero.

FM'DEVICE — This bit is 1 for device files and 0 for disc files.

FM'LDEV — Logical device number of device files or the LDEV of the disc containing the file label for disc files.

FM'JITDST — The DST number of the JIT for the job that has the file open. If this field is nonzero, then only processes in the family tree of this particular job can open the file. This field is zero if the file was open global multi-access.

FM'GLOBAL — This bit is 1 if the file was opened global multi-access, this allows multi-access to the file between jobs.

FM'PACBV — The PACB vector for this multi-access file. Used to easily find the Physical Access Control Block for files opened multi-access.

System Global Area (SYSGLOB)

The file system uses several words in the system global area for its own use.

```
SHFCBDST     = SYSDB+X76,     shared CBT DST no.
MONITOR      = SYSDB+X77,     monitoring flag word
MAXSSECT     = SYSDB+X100,    max N spoolfile sectors
NUMSSECT     = SYSDB+X102,    current N spoolfile sectors
EXTSSECT     = SYSDB+X104,    N sectors/spoolfile extent
SPOOLINDEX   = SYSDB+X132,    class spool index
CSIOWAIT     = SYSDB+X135,    CSIOWAIT PLABEL
CCLOSEPLABL  = SYSDB+X140,    CS CCLOSE PLABEL - FPRDCTERM
DSCHKPLABL   = SYSDB+X335,    DSCHECK PLABEL
DSOPENPLABL  = SYSDB+X336,    DSOPEN PLABEL
DSCLOSEPLABL = SYSDB+X337,    DSCLOSE PLABEL
SDSLDEVLABEL = SYSDB+X323,    PLABEL for SDSLDEV
MANWCPLABL   = SYSDB+X340;    MANAGEWRITECONV PLABEL
GLOBALAFTDST = SYSGLBEXT+X121 Global AFT DST number
```

SIRs, Locks, and Deadlocks

The file system uses two SIRs: the File SIR, which is intended to protect file label integrity, and the FMAVT SIR, which is to guarantee the integrity of the FMAVT. Since the File system locks these resources and also locks control blocks, deadlocks can occur if locking is done in the wrong order. Not only must the file system handle locking correctly, but the entire ensemble of the file system, its callers, and its callees must do so also. These include KSAM, which has a SIR of its own, SYSDUMP, and STORE, which lock the File SIR because they tweak bits in file labels. The presently accepted order is:

Get FMAVT SIR Lock ACB Get File SIR Lock FCB

It may not be necessary to do all of these things in any particular procedure. In modifying a procedure, you should be sure that any of these locks which you change are consistent not only within your own code, but also with its callers and callees.

Shared CBT DST

In sysglobal X76 (ABSOLUTE X1076) there exists the shared Control Block Table DST number. This DST holds a list of shared CBT's. Shared CBT's are used to keep any and all file system control blocks that have the potential to be shared between processes. Any disc file opened shared will have its FCB kept in one of these CBT's. Also, all terminal PACB's will be stored in a system shared CBT so that an extra data segment is not wasted. This is possible because all terminal access is performed NOBUF, which means that the PACB will be a minimal PACB and can be placed in these CBTs. Lastly, any file opened with global File access will have all its control blocks placed into these system CBT's.

The format of the system shared CBT DST is similar to a Control Block Table. It has the same words of overhead and the data (the list of DST's) starts in the next word after the overhead. The system CBT's are created one at a time as needed. Usually, there are only a few DST's in the list.

TABLE SIZE IN WORDS (X200)	0
DST NUMBER OF THIS TABLE	1
0	2
0	3
0	4
0	5
0	6
0	7
1ST. SHARED CBT DST NUMBER	10
2ND. SHARED CBT DST NUMBER	11
.	
.	
.	
118TH. SHARED CBT DST NUMBER	177

CHAPTER 7 PROCESS TABLES

The operating system maintains state, control, and accounting information on each process. The data structures for this purpose are the process control block table (PCB; core resident, 1 entry per process) and the process control block extension (PCBX; contained in the process' stack below OL). Process related information which must be accessible when the process' stack is not present in main memory is maintained in the process' PCB entry. ALL other process related information is maintained in the process' PCBX.

A process is identified in the system by its PCB entry number, referred to as its PIN (process identification number), or by its PCBPT=(PIN)*(PCB entry size).

The structure of the PCB table, PCB entry format, PCBX structure, and PCBX format are specified in this chapter.

Process Control Block Table Structure and Format

Fixed Cells Related to PCB

4 PCB relative index of current process' PCB entry
X1003 Absolute address of the PCB table base
The bank & address are represented as per the MPEV ERS.
X1271 PCB relative address of head of dispatching queue's PCB entry
X1272 PCB relative address of tail of dispatching queue's PCB entry

PCB Entry 0 Format

0	# OF CONFIGURED ENTRIES
1	ENTRY LENGTH (X25)
2	# OF UNASSIGNED ENTRIES
3	TABLE RELATIVE INDEX TO FIRST UNASSIGNED ENTRY
4	TABLE RELATIVE INDEX OF LAST FREE ENTRY
5	HIGH WATER MARK
6	NUMBER OF PRIMARY CONFIGURED ENTRIES (0)
7	HEAD OF IMPEDED QUEUE PCB RELATIVE INDEX
8	TAIL OF IMPEDED QUEUE PCB RELATIVE INDEX
9	NUMBER OF CURRENTLY IMPEDED PROCESSES
10	NUMBER OF MAXIMUM IMPEDED PROCESSES (CURRENT)
11	CUMULATIVE NUMBER OF IMPEDED PROCESSES(CURRENT)
12	0
13	0
14	0
15	0
16	0
17	0
18	0
19	0
20	0

Unassigned PCB Entry Format

0	0
1	TABLE RELATIVE INDEX TO NEXT UNASSIGNED ENTRY
2	0
3	0
4	0
5	0
6	0
7	0
8	0
9	0
10	0
11	0
12	0
13	0
14	0
15	0
16	0
17	0
18	0
19	0
20	X177777

Assigned PCB Entry Format



Assigned PCB Entry Format (Cont.)

PCB14	BLKINX	PBX
PCB15	CST MAPPING DST #	MAPDST
PCB16	PIMP PCB INDEX	PIMPPIN
PCB17	NIMP PCB INDEX	NIMPPIN
PCB18	BPTLINK	BPTLINK
PCB19	PCB INDEX OF NEXT PCB ENTRY IN QUEUE	NQPTR
PCB20	PCB INDEX OF PREVIOUS PCB ENTRY IN QUEUE	PQPTR

PCB00 .(0:1) SAR ==> scheduling attention required
.(1:1) Bounds Flag -- Privilege mode bounds check
.(2:1) CRIT ==> process is critical
.(3:1) HSIR ==> process has a sir
.(4:1) PIOVR ==> pending PI, process critical
.(5:1) NSPRI ==> hold sir priority
.(6:1) IPEXP ==> incore protect expired
.(7:1) PC ==> pre-empt capability
.(8:1) DSOFT ==> Delayed soft int processing. A pending soft int cannot be processed because of sir or critical state. PSEUDOINT will be invoked when these condition(s) go away.
.(9:1) LW ==> long wait
.(10:1) SW ==> short wait
.(11:1) TRW ==> terminal read wait
.(12:1) USEDQ ==> used a quantum since transaction began
.(13:1) HIPRI ==> hold impeded priority
.(14:1) STOVR ==> processing abort due to stack overflow.
.(15:1) RITBK==> Request Information Table Break

PCB01 .(0:16) SLLPTR, SLL relative index to process' segment locality list

PCB02 .(0:1) ADB, set if DB pointing to an absolute address
.(2:14) XDS, DST entry number of extra data segments to which DB is set; zero if none.

PCB03 .(0:1) STOVWRN, FLAG ==> stack overflow is already allocated
.(1:2) SC, set if executing system code
.(2:14) DST entry number of process' stack

PCB04 .(0:1) M, mourning wait.
.(1:1) RG, global RIN wait.
.(2:1) RL, local RIN wait.

.(3:1) MW, mail wait.
.(4:1) BIO, blocked I/O wait.
.(5:1) IO, I/O wait.
.(6:1) UCOP, UCOP wait and RIT wait.
.(7:1) JWAT, junk wait.
.(8:1) TIM, timer wait.
.(9:1) MSG, file system basic IPC message wait.
.(10:1) SON, son wait.
.(11:1) FA, father wait.
.(12:1) IMP, process waiting to be unimpeded.
.(13:1) SIR, process waiting for a sir.
.(14:1) TOT, process waiting for a time out.
.(15:1) MEM, process waiting for memory.

PCB05 .(0:16) FPIN, father's PCB relative index

PCB06 .(0:16) SAIN, son's PCB relative index

PCB07 .(0:16) BRIN, brother's PCB relative index

PCB08 .(0:3) PSIN, pseudo - interrupt mode
0: hard kill
1: soft kill
2: stop
3: hibernate
4: escape
5: break
6: normal
.(3:1) ADOFT, ON for soft interrupt to wake process even though it is waiting on another event.
.(4:2) DM:
0: other source
1: father
2: son
3: reply done on RIT wait
.(6:1) DEMQ, set during expiration.
.(7:1) FSC, if set, the father is to be activated on process termination.

PCB09 .(0:1) ALIVE, set if process is alive.
.(1:2) BMS, block mail, valid if MA set
0: sent to father
1: received from father
2: send to son
3: received son
.(3:2) PMC, process to process communication, set with respect to son.
0: null
1: son to father
2: father to son
3: blocked
.(5:1) STOV, stack overflow bit
.(6:3) PTYPE, process type
0: user

1: user, son of main
2: user, main
3: user, main, task
4: system
5:
6: system, UCOP
7:

.(9:1) SI, set when the Dispatcher (and PSEUDOINT) should be aware of a pending soft interrupt.
.(10:1) HK, hard kill pseudo interrupt
.(11:1) SK, soft kill pseudo interrupt
.(12:1) ST, stop pseudo interrupt
.(13:1) HB, hibernate pseudo interrupt
.(14:1) CY, control-y pseudo interrupt
.(15:1) BK, break pseudo interrupt

PCB10 .(0:15) EVENTFLAGS, one for each wait class in PCB04
.(15:1) WS, wake up waiting switch set if an awake is missing.

PCB11 .(0:32) LASTREFSWAPSEG, segment identifier of last referenced swappable code segment.

PCB13 (QUEUING INFO)
.(0:1) DISPQ ==> on dispatching queue
.(1:1) L scheduling class
.(2:1) C scheduling class
.(3:1) D scheduling class
.(4:1) E scheduling class
.(5:1) INTER ==> process is interactive
.(6:1) CORER ==> process is core resident
.(7:1) RSOFT, Allow soft interrupt. A value of 1 implies that user soft interrupts will be processed. A zero value inhibits user soft ints (they are queued). This bit is managed by FINTSTATE and FINTEXIT intrinsics.
.(8:8) Process' scheduling priority

PCB14 .(0:16) PBX, CSTX block map index of process' program.

PCB15 .(0:16) MAPDST, DST entry number of the CST mapping table.

PCB16 .(0:16) PIMPPIN, PCB relative index of previous impeded PCB.

PCB17 .(0:16) NIMPPIN, PCB relative index of next impeded PCB.

PCB18 .(0:16) BPTLINK, breakpoint link for process

PCB19 .(0:16) NQPTR, PCB relative index of next proc in diep queue

PCB20 .(0:16) PQPTR,PCB relative index of prev proc in diep queue queue

PCBX Structure and Format

PCBX General Structure



PXGLOB Format

The PXGLOB portion of the pcbx is for job information, and contains the same job related information for all processes belonging to the same job.



R = restart bit
I = job in/list interactive
D = job in/list duplicative
TY = job type
0 = undefined
1 = session
2 = job
3 = task
* = reserved:
SB= stun bit ;used for stack underflow simulation for ICF44 or ICF55.

Stack Dump Flags
Bit 10 = Armed
Bit 11 = Suppress traceback
Bit 12 = Suppress ASCII
Bit 13 = Q-63 to S
Bit 14 = QINIT to S
Bit 15 = OL to QINIT

PXFIXED Assignments

The PXFIXED portion of the pcbx contains specific information and control information.



PXFIXED Assignments (Cont.)



PXFIXED Assignments (Cont.)



NOTES: P = 1 if opened by priv user
S = 1 if data segment is sharable

PCLASSMASK = BIT MASK OF CLASSES THIS PROCESS HAS ENABLED
PROCQUESTOPWORD.(0:4) = PROCESS PRIORITY: 7 => L QUEUE
6 => C QUEUE
2 => D QUEUE
1 => E QUEUE

```
                    .(4:12)= REASON STOPPED: 1 => STOP SEG FAULT
                                             2 => STOP DISC WRIT
                                             3 => BLOCKED I/O, NON TERMINAL
                                             4 => TERMINAL READ
                                             5 => STOP IMPEDE
                                             6 => STOP ACTIVE
          PROCSTOPTIME = DBL WORD TIMESTAMP OF WHEN PROCESS STOPPED FOR
                         REASON GIVEN IN PROCQUESTOPWORD
```



```
        DCY          A DELAYED CONTROL Y IS PENDING (THIS BIT
                     IS CHECKED BY ININ ON BOUNDS VIOLATION TO
                     DETERMINE IF GOT:  1) TRUE BOUNDS VIOLATION
                     OR  2) AN INDUCED BOUNDS VIO THAT INDICATES
                     THAT THE CONTROL Y TRAP PROCEDURE MAY NOW
                     BE ENTERED).
        DSI          STATE OF THE "ASOFT" PCB BIT WHEN CONTROL Y
                     TRAP WAS ENTERED.  ASOFT = 1 ALLOWS USER SOFT
                     INTERRUPTS AGAINST THE PROCESS.  IT IS SET TO
                     ZERO WHEN THE CONTROL Y HANDLER IS ENTERED.
                     IT IS SET TO ITS PRIOR STATE WHEN THE USER
                     CALLS RESETCONTROL.
 * SET TO COMMAND RECORD LENGTH WHEN COMMAND PENDING
   (I.E. COMMAND ENTERED DURING BREAK OR ENCOUNTERED
   DURING FLUSHING).

** CONTINUE FLAG VALUES
     0 = NO CONTINUE IN EFFECT
     1 = CONTINUE JUST ENCOUNTERED
     2 = CONTINUE IN EFFECT FOR THIS COMMAND

CY FLAG

     PCBXFIXED(56).(1:1)    = SET BY PSEUDDINT WHEN THERE IS A PENDING
                              CONTROL Y WHICH CANNOT BE PROCESSED BECAUSE
                              OF SYSTEM CODE OR PRIVILEGED CODE.  ININ
                              CHECKS THIS BIT ON BOUNDS VIOLATION OR
                              TRACE TRAP.

SI FLAG

     PCBXFIXED(56).(3:1)    = SPECIFIES THE STATE OF THE USER INTERRUPT
                              FLAG WHEN THE CURRENT CONTROL Y WAS PROCESSED.
```

PXFIXED Expansion Bitmap

The PXFIXED bitmap and expansion area is for use in accounting of extra data segments acquired by the process.

PCBX For Core Resident System Process Stacks



NOTES: 1. There is no PXFILE area.
2. The PXFIXED area is much smaller than a normal PCBX.

Process To Process Communication Table

This table is used as the communication link by which father and son processes communicate with one another via the mailbox scheme. This table contains two words per entry and is indexed by PCB# (entry index 0 is meaningless). Each two word entry of index N essentially relates where, as well as how much, mail may be found for a process N with respect to communications between N and his father process.

ENTRY FORMAT



where word 0 = the # of mail words to be transferred.
word 1 = the only word of mail itself if word 0 = 1
otherwise
it contains the DST# of the extra data segment where "word count" words of mail exist.

NOTE: Assume process S is the son of process F. Then the process to process communication table index which will be used for mailbox communication between son S and father F will be that of the son (i.e. S).

Subsystem Reserved DL Rrea



FORTRRN Logical Unit Table (FLUT)

The segnenter is responsible for the preparation and initialization of a FORTRAN logical unit table. This is done when a program is prepared if that program contains at least one program unit that references a logical unit. The location of the FLUT is in the secondary DB area and the address of this location is contained in DB-1.

The FLUT is formatted as per the following example:



CHAPTER 8 JOB TABLES

Job Tables Overview

Job Master Table (JMAT): One entry per job/session. Contains information needed to get the job/session running. Entry is created at the introduction of job/session.

Job Information Table (JIT): One DST per job/session. Contains information needed by the job/session as it is executing.

Job Process Count Table (JPCNT): One entry per job/session. Entry number used to index into the JIR to lock job resources.

Job Directory Table (JDT): One DST per job/session. Contains the following sub-tables used by descendants of job/session. Must obtain JIA (by using JPCNT index) before accessing JDT. Sub-tables:
1. Data Segment Directory - Directory of DSTs used by job/session
2. Tenporary File Directory
3. File Equation Table
4. Line Equation Table
5. Job Control Word Table

Job Cut-off Table (JCUT): Stores total CPU time limit of job/session and accumulates the CPU time that job/session uses.

Ucop Request Queue: A queue of Process Identification Numbers that are terminating.

Job Master Table Structure (JMAT)



JMAT (Cont.)



Job Master Table Entry (JMAT)

JMAT (Cont.)

37	Reserved	31
40	Reserved	32
41	Reserved	33
42	Reserved	34
43	Reserved	35
44	Unused	36
45	Unused	37

```
0|1:2:3|4:5:6|7:8:9|0:1:2|3:4:5
                1 1 1 1 1 1
```

R = RESTART
N = SEQUENCED
S = ORIGJIN is spooled.

FT = funny terminal
00 - regular term.
01 - regular term., special logon
10 - RPL term.
11 - RPL term.

Job States

JOB STATES - JMAT ENTRY WORD 0.(0:6)

SNOWJOB - Displays job states by scanning JMAT DST (%31)

LOGON USES ALL STATES EXCEPT "SUSPEND"

STATE NO.	STATE NAME	PROCESS	SEGMENT	PROCEDURE(S)
1	INTRO	DEVREC JSMP SPOOLER	NURSERY	STARTDEVICE ->PUTJMAT ->ALLOCENTRY IN SEGMENT ALLOCUTIL
%70	SCNED	UCOP	JOBSCNED	CXSTSTREAM SCNEDULEDSCNED
%40	WAIT	DEVREC JSMP SPOOLER	NURSERY \ SPOOLING /	STARTDEVICE ->SCHEDULEJOB SPOOLSTUFFIN ->SCNEDULEJOB
%60	INIT-IALIZAT-ION	UCOP	UCOP	LAUNCHJOB
2	EXEC	JSMP	NURSERY	INITJSMP
3	TERMIN-ATING	JSMP	MORQUE	TERMINATE ->EXPIRE ->CLEANUPJOB
0	FREE ENTRY	JSMP	MORQUE	TERMINATE ->EXPIRE ->CLEANUPJOB ->DEALLOCENTRY IN ALLOCUTIL
4	SUSP	JSMP	OPLOW	CXBREAKJOB

For states INTRO and WAIT,

DEVREC => logon command originated on terminal or other unspooled device.
SPOOLER => logon command originated on spooled device.
JSMP => logon command is the result of the execution of a :STREAM command. (This also includes USER processes which have done programmatic :STREAMs.)

Job Process Count Table (JPCNT)

(1 Bit Entry/Running Job)

MEMORY RESIDENT

SYSGLOB BASE = DB+13(%15)
DST = 24(10)
SIA = 13(10)

```
  0 1 2 3 4 5 6 7 8 9 10 1 2 3 4 5
 |-------------------------------|
0| Total Configured number of Jobs |
 |        and Sessions           |
 |-------------------------------|
1|   Total number of free entries |
 |-------------------------------|
2| Bit Map relative index of word |
 |  containing next free entry   |
 |-------------------------------|
3|           unused              |
 |-------------------------------|
4|                               |   free entry = 1
 |                               |   allocated entry  = 0
 |          Bit Map              |
       64 words long
 |-------------------------------|
```

A JPCNT entry must be allocated before the main process can be procreated.

The job SIR (PXGJSIR) = zone base+JPCNT index.

NOTE: This table is completely bit oriented with each entry consisting of one bit. Entries are taken from available pool on a "first found" basis. A "1" found in the bit map indicates a free entry. A zero (0) found in the bit map indicates an allocated entry. Word 2 of this table is the index of the word in the Bit Map where the next free entry resides. At system start up, this word is set to zero (0). The Bit Map can be thought of as ranging from 0-63 (64 total words - 1024 entries).

Job Cutoff Table (JCUT)
1 Entry/ CPU-limited Job

MEMORY RESIDENT

SYSGLOB BASE = DB+11(%13)
DST = 36(10);SIR = 14(10)
SYSGLOB + %117 = default CPU time limit for jobs

```
  0  1  2  3  4  5  6  7  8  9 10 11 12 13 14 15
 |--|--|--|--|--|--|--|--|--|--|--|--|--|--|--|--|  ------------
 | # OF REAL ENTRIES                                |  0
 |--------------------------------------------------|
 | ENTRY SIZE (3)                                   |  1   HEADER
 |--------------------------------------------------|      ENTRIES
 | FREE HEAD                                        |  2
 |--------------------------------------------------|      (2)
 | POINTER TO LAST ENTRY (0)                        |  3
 |--------------------------------------------------|
 | UNUSED                                           |  4
 |--------------------------------------------------|
 | UNUSED                                           |  5
 |--------------------------------------------------|  ------------

                                                        TYPICAL ENTRY
 |--------------------------------------------------|  ------------
 |                  JCUTCPUL                        |   time limit
 |--------------------------------------------------|   (seconds)
 |                  JCUTCPUC                        |   time count
 |--------------------------------------------------|   (nsec)
 |                                                  |  ------------
 |--------------------------------------------------|  ------------
 | POINTER TO NEXT FREE ENTRY (END OF LIST = 0)     |
 |--------------------------------------------------|
 |                                                  |   FREE ENTRY
 |--------------------------------------------------|
 |                                                  |  ------------
 |                  LAST ENTRY                      |
 |--------------------------------------------------|
 |                                                  |
 |--------------------------------------------------|
 |                                                  |
 |--------------------------------------------------|
```

Job Information Table (JIT)
JIT OST ie word 11 (base 10) in PXGLOB



F - Job/Session-wide FPMAP option flag (JSFPMAP)
ty - 1 = Session
2 = Job

JITMAXP - MAXJOBPRI capability
JITMPN - Job main PIN.
JITEOF - used by FCLOSE to tell CI that a $STDIN(X) file was closed w/out encountering an EOF. (0:1)=$STDIN, (1:1)=$STDINX

JIT (Cont.)

48 Accounting Info
NIPRI - highest job priority
53 Account
54 Index Pointer
55 Group index pointer
56 Syetem volume set
57 Group index pointer
58 Mounted private volume set
MVTABX - Mounted Volume Table Index

Allow Mask Format

The Allow mask for MPE V ie expanded to eix words. There ie a mask in each user's JIT and in the SYSGLOB area. The Allow mask contains enough bits for a one-to-one correspondence to every present OPERATOR type command, or any future OPERATOR command. When a user is ALLOWed any OPERATOR command or ASSOCIATEd to a device (which will use OPERATOR type commands) then the corresponding bit(s) in the mask in that user's JIT for that command is set. If the ALLOW or ASSOCIATE was done on a global scale, then the bit(s) in the mask of the SYSGLOB area is/are updated.

The following EQUATEs define the mask bit for each operator command.

The first set of commands define the operator commands dealing with devices.

JIT (Cont.)



P - Group's home volume is a private volume
M - Private volume mounted (i.e. group bound to home volume set), JITGIP = 57

When adding a new command to this set of EQUATEs, be sure to add a corresponding move statement in LOGIMAGE, even if the command will not be logged.

	Word	Bit	#
ABORTIO	0	0	0
ACCEPT	0	1	1
DOWN	0	2	2
GIVE	0	3	3
HEADOFF	0	4	4
HEADON	0	5	5
REFUSE	0	6	6
REPLY	0	7	7
STARTSPOOL	0	8	8
TAKE	0	9	9
UP	0	10	10
MPLINE	0	11	11
DSCONTROL	0	12	12
UPPER LIMIT->DEVICE COMMANDS			
ABORTJOB	0	13	13
ALLOW	0	14	14
ALTFILE	0	15	15
ALTJOB	1	0	16
BREAKJOB	1	1	17
DELETE	1	2	18
DISALLOW	1	3	19
JOBFENCE	1	4	20
LIMIT	1	5	21
STOPSPOOL	1	6	22
SUSPENDSPOOL	1	7	23
OUTFENCE	1	8	24
RECALL	1	9	25
RESUMEJOB	1	10	26
RESUMESPOOL	1	11	27
STREAMS	1	12	28
CONSOLE	1	13	29
WARN	1	14	30
WELCOME	1	15	31
MON	2	0	32
MOFF	2	1	33
VMOUNT	2	2	34
LMOUNT	2	3	35
LDISMOUNT	2	4	36
MRJECONTROL	2	5	37
JOBSECURITY	2	6	38
DOWNLOAD	2	7	39
MIOENABLE	2	8	40
MIODISABLE	2	9	41
LOG	2	10	42

	Word	Bit	#
FOREIGN	2	11	43
INF	2	12	44
SHOWCOM	2	13	45
OPENQ	2	14	46
SHUTQ	2	15	47
OISCAPS	3	2	48

* THE FORMAT FOR UCAP (X46-47) IS AS FOLLOWS:

	0	1	2	3	4	5	6	7	8	9	10	11	12	13	14	15
WORD1	SN	AM	AL	IGL	OI	OP	CV	UV	LG	///	///	WA	WM	CS	ND	SF
WORD2									BA	IA	PM			AR		OS	PH

Job Directory Table (JDT)



Job Data Segment Directory Entry (In JDT)



NOTE: A return of X2004 in the INDEX value after using the GETDSEG intrinsic indicates that there is no more room in the Job Directory Table for another job sharable data segment.

Job Temporary File Entry (In JDT)



File Equation Table Entry (In JDT)



Job Line Equation Entry



JLEQ Entry (Cont.)



Job Control Word Table (JJCW)



MODIFIER = VALUE FROM 0 TO %377777

Aoptions and Foptions Word Breakdown



PMASK Word Breakdown



1->info present
0->info absent

UCOP Request Queue (QST89)



UCOP Entry Format

Each entry is 2 words long



CHAPTER 9 RELOCATABLE OBJECT CODE

USL Files Introduction

* USL record length 128 words always.
* Layout of doubleword disc addresses



* Hash links join all entries with the same hash key regardless of type.
* Linear lists terminate with a zero link
* Circular lists containing only the list head point directly to themselves.
* Single-word disc addresses



Uninitialized fields are reserved for future use and should be set to zero.

Record 0 and Overall USL File Format

0	LIO	0	LOADER IO
1	NE	1	NR. DIRECTORY ENTRIES
2	DL	2	DIR. LENGTH
3	SUMDG	3	TOTAL DIR. GARBAGE
4	NDG	4	NR. DIR. GARB. ENTRIES
5	SRBDL	5	S.A. BLOCK DATA LIST
6	SAIPL	6	S.A. INTERRUPT PROC. LIST
7	SASL	7	S.A. SEGMENT LIST
10	FL	8	FILE LENGTH
11		9	

NOTE:
S.A. = Starting Address

USL File Format (cont.)

12	SARD	10	S.R. AVRIL. DIR.
13	ADL	11	AVRIL. DIR. LENGTH
14	SAI	12	S.A. INFO BLOCK
15		13	
16	IL	14	INFO BLOCK LENGTH
17		15	
20	SARI	16	S.R. AVAIL. INFO
21		17	
22	AIL	18	AVRIL. INFO LENGTH
23		19	
24	TOTRL	20	TOTAL INFO GARBAGE
25	I.G.	21	
26	NIG	22	NR. INFO GARB. ENTRIES
27		23	
30		24	
31		25	
32		26	
33		27	
34		28	
35		29	
36		30	
37		31	
40		32	
41	HL 0	33	HASH LINKS
.	.		
.	.		
177	NL 94	127	

USL Files General Information (cont.)



*SRI MUST BE ON A RECORD BOUNDARY

NOTE: ALL ADDRESSES IN RECORD 0 ARE WORD ADDRESSES.

USL Files General Information (cont.)



R \
K >SEGMENT NAME ENTRIES
B /

PROC C \
PROC A >SUBPROGRAM
MAIN / ENTRIES

A \
3 |
R |
1 } SECONDARY ENTRY POINT ENTRIES
R |
5 /

Data Descriptors, Passed Parameters



TYPE	WORDS	CODE
NULL		0
LOGICAL	1	1
INTEGER	1	2
BYTE	1/2	3
REAL	2	4
DOUBLE	2	5
LONG	3	6
COMPLEX	4	7
LABEL (SPL)		10
CHARACTER (STRING)	N/2	11
LABEL (FORTRAN)		12
UNIVERSAL (MATCHES ANY TYPE)		13

STRUCTURE

SIMPLE VARIABLE	0
POINTER	1
ARRAY	2
PROCEDURE	3

MODE

NULL	0
VALUE	1
REFERENCE	2
NAME	3

NOTE: A descriptor of 0 results in an automatic match.

Pascal

Pascal sets the high order bit in the parameter type descriptor when it is generating hashed values. The remaining 15 bits are based on a hash of the types of the parameter. Only the Pascal compiler can compute the value, and the SEGMENTER must match the whole 16 bit value.

Entry Type 0

GARBAGE

NW - Number of words in this block

Entry Type 1

SEGMENT NAME



NW - Number of words in entry block

HL - Hash link - points to next entry having the same hash code

R - Activity bit
0 if active
1 if inactive
(initialize to 0)

Note: An inactive segment implies that all entry points are inactive

NC - Number of characters in name. Max is 16

CHAR. 1 - First character in variable field
CHAR. NC - Last character in variable field
SEGL - Segment link - points to next segment name entry
SUBL - Subprogram link - points to next entry having the same segment name
L - Last entry in list
0 if not last
1 if last

Clarification Notes on Entry Types 2 and 4
With Respect to SPL and FORTRAN

*ENTRY TYPE 2 SPL D.B.	**ENTRY TYPE 4 SPL PROC	*ENTRY TYPE 2 FORTRAN MAIN	**ENTRY TYPE 4 FORTRAN SUB.
TPDB	0	0	0
TSDB 1,5	TSDB 1	TSDB 1,2,3,4	TSDB 1,2,3,4
NWPUST	NWPUST	NWPUST	NWPUST
NWSDB 5	NWD	NWD	NWD

WHERE: TPDB = Total primary DB length in words
TSDB = Total secondary DB length in words
NWPUST = Number of words in "TRACE" array
NWSDB = Number of words in secondary DB array
NWD = Number of words in own array
NWD = Number of words in data array

Notes: 1. Does not include the length of the STLT
2. Does not include the length of the FLUT
3. Does not include the length of any common array
4. Includes the length of any DB-allocated format array
5. Are not necessarily equal

In general TPDB and TSDB are summations of storage allocated in the global area of the program's data segment. They are not, however, complete since the compilers are not aware of all storage actually allocated! The STLT and FLUT are examples of this since these tables are constructed by the segmenter. Common arrays also present a problem since their inclusion in TPDB and TSDB might cause their storage requirements to be counted more than once.

Entry Type 2

OUTER BLOCK



Entry Type 2 (cont.)



NW - Number of words in entry block.

HL - Hash link - points to next entry with same hash code.

A - Activity bit. 0 if active, 1 if inactive outer block.

C - Callability bit set if entry point is uncallable.

I - Privilege mode bit - set if program unit is to be executed in Privilege mode..

NC - Number of characters in name. Max is 16.

CHAR. 1 - First character in variable field.

CHAR. NC - Last character in variable field.

L - Last entry in list.
0 if not last
1 if last

Entry Type 2 (cont.)

SUBL - Subprogram link - points to next entry Entry having the same segment name.

SECL - Secondary entry point list link.

SSA - Program unit starting PB address.

SAC - Starting $FILE9 address of code module

F - Set if fatal error

W - Set if nonfatal error

NWC - Number of words in code module.

SE - Stack size estimate

TPDB - Total number of words of primary DB to be allocated

TSDB - Total number of words of secondary DB to be allocated.

NWPUST - Number of words in trace array (PUST)

NWD - Number of words in data array (FDRTRAN)

NWSDB - Number of words in secondary DB array (SPL)

T - Terminating bit - set if last set of headers in entry

NH - Number of headers

SAH - Starting address of header (relative to SAI)

HDW - Header (pointer)

Entry Type 3

OUTER BLOCK - SECONDARY ENTRY POINT



Entry Type 4

PROCEDURE



Entry Type 4 (cont.)



Entry Type 4 (cont.)

NW - Number of words in entry block
NL - Nash link - points to next entry with same hash code
A - Activity bit. 0 if active, 1 if inactive entry point
C - Callability bit set if entry point is uncallable
I - Privilege mode bit. Set if procedure is to be executed in privilege mode.
N - Hidden entry point. Set if entry point will not be in library directory.
NC - Number of characters in name. Max is 16.
CNAA1 - First character in variable field.
CNAA NC - Last character in variable field.
L - Last entry in list
0 if not last
1 if last
SUBL - Subprogram link. Points to next entry having the same segment Name
SECL - Secondary entry point list link.
SSA - Unit starting PB address
SAC - Starting (file) address of code module
F - Set if fatal error
W - Set if nonfatal error
NWC - Number of words in code module
SE - Stack size estimate
TPDB - Total number of words of primary DB to be allocated.
TSDB - Total number of words of secondary DB to be allocated.
NWPUST - Number of words in trace array (PUST)
NWD - Number of words in data array (FORTRAN)
NWO - Number of words in own array (SPL)
P - Parameter checker
00 no checking. (Inplies NP undefined, FN and PARM's absent)
01 check procedure type. (Implies NP is undefined and PARM's absent)
10 check procedure type and number of PARM's (implies PARM's absent)
11 check procedure type, number of PARM 's and type of each PARM.
NP - Number of PARM's
CN - Character count of PARM's
TN - Terminating bit. Set if last set of headers in entry.
NH - Number of headers
SAH - Starting address of header
NDW - Header (pointer)

Entry Type 5

PROCEDURE - SECONDARY ENTRY POINT



NW - Number of words in entry block

NL - Nash link - points to next entry with same hash code

A - Activity bit. 0 if active, 1 if inactive entry point

C - Callability bit set if entry point is uncallable.

H - Hidden entry point set if entry point will not be in library directory

NC - number of characters in name, max is 16

CNAA 1 - First character in variable field.

L - Last entry in list
0 if not last
1 if last

SECL - Secondary entry point list link

SSA - Unit starting PB' address

Entry Type 6

INTERRUPT PROCEDURE



Entry Type 6 (cont.)

NW - Number of words in entry block

NL - Nash link. Points to next entry with same hash code

A - Activity bit. 0 if active, 1 if inactive entry.

IT - Interrupt procedure type number

NC - Number of characters in name (maximum is 16)

CNAR 1 - First character in variable field.

CNAA NC- Last Character in variable field

IPL - Interrupt procedure link

OBS - Number of words of OB storage required.

SSA - Unit starting PB' address

SAC - Starting (file) address of code module.

F - Set if fatal error

W - Set if nonfatal error

NWC - Number of words in code module

T - Terminating bit. Set if last set of headers in entry.

NN - Number of headers

SAH - Starting address of header.

NDW - Header (pointer)

Entry Type 7

BLOCK DATR



Entry Type 7 (cont.)



NW Number of words in block

NL - Nash link. Points to next entry with same hash code.

R - Rctivity bit. 0 if active, 1 if inactive block.

F - Set if fatal error.

W - Set if nonfatal error.

CNAR 1- First character in variable field.

CNAR NC-Last character in variable field.

BDL - Block data link

CAL - Common array length

T - Terminating bit. Set if last set of headers in entry.

NH - Number of headers.

SAH - Starting address of headers.

HDW - Neader (pointer)

Entry Type 8

PROCEDURE - SECONDARY ENTRY POINT



NW - NUMBER OF WORDS IN ENTRY BLOCK

HL - HASH LINK - POINTS TO NEXT ENTRY WITH SAME NASH CODE

A - ACTIVITY BIT. 0 IF ACTIVE, 1 IF INACTIVE ENTRY

C - CRLLABILITY BIT SET IF ENTRY POINT IS UNCALLABLE

N - HIDDEN ENTRY POINT. SET IF ENTRY POINT WILL NOT BE IN LIBRRY DIRECTORY

NC - NUMBER OF CHRRCTERS IN NAME. MAX IS 16

Entry Type 8 (cont.)

CHAR 1 - FIRST CHRRCTER IN VARIBLE LIST

CHRR NC - LAST CHRRCTER IN VARIBLE LIST

L - LAST ENTRY IN LIST
0 IF NOT LAST
1 IF LAST

SECL - SECONDARY ENTRY POINT LIST LINK

SSA - UNIT STRRTING PB' RDDRESS

P - PARM CNECKER
00 NO CHECKING (IMPLIES NP UNDEFINED, TN AND PRRMS ABSENT)
01 CHECK PROCEDURE TYPE (IMPLIES NP IS UNDEFINED AND PARMS ABSENT)
10 CHECK PROCEDURE TYPE AND NUMBER OF PRRMS. (IMPLIES PARMS RBSENT)
11 CHECK PROCEDURE TYPE, NUMBER OF PRRMS RND TYPE OF PARM.

NP - NUMBER OF PRRMS

CN - CHARACTER COUNT OF PARMS

TN - PROCEDURE TYPE

Entry Header Format



EACH ENTRY (EXCEPT SECONDARY ENTRY POINT ENTRIES) MAY DESCRIBE N> 0 SETS OF HEADERS. THE HEADERS IN EACH SET MUST BE CONTINUOUS AND IN THE SAME ORDER AS THE HOW LIST DESCRIBING THE SET.

THE CODE MODULE MAY BE PLACED IN ANY POSITION IN A HEADER SET. NOTE THAT IF THE CODE MODULE IS AT THE BEGINNING OF A SET, SAC = SAH.

IF THE ENTRY HAS NO HEADER SET, THEN NH, SAH SEQUENCE IS ABSENT.

Header Type 0

GARBAGE

Header Type 1

PCALs

PBA - PB' ADDRESS OF LINKED LIST OF PCAL INSTRUCTIONS TO BE REPAIRED - LOWER 14 BITS USED AS NEGATIVE DISP. - BIT 0 SET MEANS THAT WORD IS NOT A PCAL INSTRUCTION BUT A POINTER TO A SST LABEL OF ''EXTERNAL'' FORMAT - A LINK OF 0 TERMINATES THE LIST - BIT 1 SET MEANS THAT THE WORD IS TO BE

INITIALIZED WITH THE PB ADDRESS OF THE PROCEDURE.

Header Type 2

PB ADDRESSES



PBA - PB' ADDRESS OF PB ADDRESS TO BE CORRECTED

Header Type 3

OWN/DATA VARIABLES



PBA - PB' ADDRESS OF OWN VARIABLE POINTER TO BE CORRECTED

Header Type 4

DSDB/OWN/DATA/VALUES

LD - LOGICAL WORD DISPLACEMENT IN OWN ARRAY FOR INITIAL VALUES
B - BYTE BIT-SET IMPLIES THAT LD IS TYPE BYTE AND THAT THE FIRST WORD OF THE INITIAL VALUE BLOCK IS A COUNT OF THE NUMBER OF BYTES IN THE INITIAL VALUE BLOCK
IN - INTEGRATION NUMBER - NUMBER OF TIMES THE BLOCK OF INITIAL VALUE IS TO APPEAR IN THE SECONDARY DB - 1->NO DUPLICATION, 2->DUPLICATION, ETC

Header Type 5

PUST

PBA - PB' ADDRESS OF LINKED LIST OF POINTERS TO BE INITIALIZED WITH DB ADDRESS OF PUST (SAME LIST FORMAT AS FOR FORMAT STRINGS) A PBA of -1 INDICATES NO FIX-UPS.

NOTE: ALL REFERENCES TO THE PUST INCLUDE THE FOUR-WORD HEADER THAT IS APPENDED BY THE SEGMENTER. THESE WORDS ARE NOT PRESENT IN THE HEADER; THEY ARE AUTOMATICALLY ALLOCATED AND INITIALIZED BY THE SEGMENTER.

Header Type 6

GLOBAL VARIABLES



Header Type 7

EXTERNAL VARIABLES



PBA-PB' address of linked lists of instructions to be repaired;lower 8 bits of inst. used as neg. displacement to next instruction;a link of 0 terminates the list.

M -Monitored variable bit;set if variable is being monitored by debug.

DA -Logical word disp. in PUST; lower 8 bits of word will be init. with prim.DB address of variable;DA is present if M=1.

NOTE:PBA of -1 implies null list

Header Type 8

PRIMARY DB



U - ADDRESS BITS
00 IF NO ADDRESS
01 IF NO ADDRESS
10 IF WORD ADDRESS IN SECONDARY DB
11 IF BYTE ADDRESS IN SECONDARY DB

N - NWPOB

NOTE: INITIAL ADDRESSES THAT ARE SECONDARY DB ADDRESSES ARE 0

RELATIVE (I.E., THEY ARE LOGICAL DISPLACEMENTS IN SECONDARY DB).

Header Type 9

COMMON VARIABLES



Header Type 9 (cont.)

NWC - NUMBER OF WORDS IN COMMON ARRAY

NC - NUMBER OF CHARACTERS IN COMMON NAME- IF BLANK COMMON 4 COM'

DA - LOGICAL WORD DISP. IN PUST - LOWER 8 BITS OF WORD WILL BE INIT. WITH PRIM. DB ADDRESS OF VARIABLE - NOTE DA IS PRESENT IF M = 1

B - BYTE BIT
0 IF THE PRIMARY DB POINTER TO BE ALLOCATED AND INITIALIZED AND LD ARE OF TYPE WORD
1 IF TYPE BYTE

M - MONITORED VARIABLE BIT - SET IF VARIABLE IS BEING MONITORED BY DEBUG

NL - NUMBER OF ADDRESS LISTS FOR VARIABLE

LD - LOGICAL DISPLACEMENT OF VARIABLE IN COMMON ARRAY

PBA - PB' ADDRESS OF LINKED LISTS OF INSTRUCTIONS TO BE REPAIRED LOWER 8 BITS USED AS NEGATIVE DISPLACEMENT TO NEXT INSTRUCTION A LINK OF 0 TERMINATES THE LIST

PBA = -1 INDICATES NO FIX-UPS

Header Type 10

LOGICAL UNITS



BIT MAP - BIT MAP OF LOGICAL UNITS
REFERENCED; BIT 0
CORRESPONDS TO LU 0, ETC.
(1 LESS THAN OR EQUAL TO LU
LESS THAN OR EQUAL TO 99)

Header Type 11

FORMAT STRING



PBA - PB' ADDRESS OF LINKED LIST OF
POINTERS TO BE INITIALIZED
LOWER 14 BITS OF WORD USED
AS NEGATIVE DISPLACEMENT TO
NEXT POINTER - BIT 0 SET
MEANS THAT THE POINTER IS TO
BE TYPE BYTE - A LINK OF 0
TERMINATES THE LIST.

RL File Format



NOTE: UNINITIALIZED FIELDS ARE
RESERVED FOR FUTURE USE AND
SHOULD BE ZERO.

Storage Management

FILE SPACE IS MANAGED IN TERMS OF 32 WORDS BLOCKS (4 BLOCKS PER 128 WORD RECORD).

FREE SPACE (BLOCKS) IS ACCOUNTED FOR IN A BIT MAP, WHICH IS PARTITIONED INTO RECORDS (2K BLOCKS PER SECTION). A 0 INDICATES THAT A BLOCK IS USED, A 1 INDICATES THAT IT IS FREE.

FILE SPACE IS ALSO PARTITIONED INTO 512 RECORD SECTIONS (64 MAX. SECTIONS, 2N BLOCKS PER SECTION, 1 MAP PER SECTION). THE NUMBER OF SECTIONS IN A FILE IS NS=(FL+511) & LSA(9). THE FIRST NS RECORDS FOLLOWING RECORD 0 (RECORDS 1 TO NS) ARE RESERVED FOR THE SECTION MAPS.

A COMPLETE FILE ADDRESS WOULD HAVE THE FOLLOWING CONFIGURATION:



FILE (WORD) ADDRESS
DOUBLE WORD

Entry Point Directory



THE DIRECTORY IS PARTITIONED INTO 95 HASH LISTS (SAME HASH FUNCTION AS USL); EACH HASH LIST IS A LINKED LIST OF RECORDS.

EACH RECORD CONTAINS A SUCCESSOR LINK (RECORD #) AND A USED SPACE COUNT. A LINK OF 0 TERMINATES A LIST. WHEN A RECORD IS VOID OF ENTRIES (USED=2), ITS SPACE IS RETURNED TO THE FREE STORAGE AREA.

Typical Directory Entry



S - SECONDARY ENTRY POINT BIT - SET IF THE ENTRY POINT WAS ORIGINALLY A SECONDARY ENTRY POINT.

U - UNCALLABLE BIT - SET IF ENTRY POINT IS UNCALLABLE.

I - PRIVILEGED MODE BIT - SET IF CODE MODULE IS TO BE RUN IN PRIVILEGE MODE.

LC is (0:2)...Level of Checking
0 = No checking
1 >= Check for procedure type
2 >= Check for # parameters
3 >= Check for parameter type
NP is (2:6) is # parameters

Procedure Information Block



ALL HEADERS FOR THE PROCEDURE ARE APPENDED TO THE INFO BLOCK. THE HEADER SETS (EXTERNAL LISTS) ARE LINKED BY INCREASING FILE ADDRESS; A LINK OF %17777777777D TERMINATES THE LIST.

Headers



F - SET IF FATAL ERROR
W - SET IF NON-FATAL ERROR
S - SATISFIED BIT - SET IF EXTERNAL IS SATISFIED WITHIN RL.
U - UNCALLABLE BIT
I - PRIVILEGED BIT

ALL HEADERS ARE THE SAME AS IN A USL EXCEPT FOR THE PCAL HEADER.

CHAPTER 10 PREPARED OBJECT CODE

Program File Format



Program File Format (Cont.)



P-PRIVILEGED MODE
S-Segment STT format: 0=> old format, 1=> new (extended) format
N=NS -1
K=2B + (NS +1) & LSA (1)
L=((2B + NS + (NS + 1)&LSR(1) + 127)/128)128 - 1

Flags



F - FATAL ERROR IN PROGRM
W - NON-FATAL ERROR IN PROGRAM
Z - ZERO UNIT OL AREP
P - SET IF ANY SEG IS PRIVILEGED MODE (IF NOT SET NORMAL= NONPRIV MODE)

CPPABILITIES



Flags2



T - PPTCH AREA EXISTED IN ALL CODE SEGMENTS
K - CHECKSUM VALID

CST Remapping Array

CONTAINS THE LAST CST NUMBERS ASSIGNED TO THE SEGMENTS; INDEXED BY SEGMENT NUMBER. WHEN A PROGRAM FILE IS PREPARED, THE ARRAY IS INITIALIZED TO 0, 1...,N. THIS ARRAY IS USED TO RE-ESTPBLISH INTRA-PROGRAM LINKAGE WHEN THE PROGRAM IS LOADED.

Segment Descriptor Prray

CONTPINS THE SEGMENT LENGTH AND A FLAG INDICATING IF THE SEGMENT IS TO BE LOADED IN PRIV. MODE. INDEXED BY SEGMENT NUMBER. ALL SEGMENTS BEGIN ON A RECORD BOUNDARY. THE NUMBER OF RECORDS FOR A GIVEN SEGMENT IS (SL + 127) & LSR(7). THE RECORD NUMBER, SAS, OF SEGMENT N IS

```
SAS:=0
FOR I=0 TO N-1
 BEGIN
 SPS:=SAS + (SL(I) + 127)&LSA(7)
 END
```

Global Area Format

P SET OF RECORDS CONTAINING THE INITIAL VALUES FOR THE GLOBAL AREA OF THE DATA SEGMENT. THIS SET BEGINS AT RECORD SAG (WORD 3) AND CONSISTS OF (GS + 127) & LSA(7) RECORDS.

External List



LC (0:2) = LEVEL OF CNECKING
0 = NO CNECKING
1 >= CNECK FOR PROCEDURE TYPE
2 >= CNECK FOR # PRRAMETERS
3 >= CNECK FOR PRRRMETER TYPE

NR = NUMBER OF REFERENCES

NP (2:6) = NUMBER OF PRRAMETERS

Entry Point List



NOTE THAT THE ENTRY POINT LIST MUST IMMEDIATELY FOLLOW THE EXTERNAL LIST.

Code Segment With Patch Area

Patch Rrea



PMRP Information



PMRP Type Table



NOTE : n = PTTL - 2

PMAP Records

Type 0 Segment PMAP Record



Type 1 Procedure PMAP Record



Type 2 Secondary Entry PMAP Record



N : HIDDEN ENTRY FLAG

SL File Format



SL File Format (Cont.)



Storage Management

FILE SPACE IS MANAGED IN TERMS OF 128 WORD BLOCKS (1 BLOCK PER 128 WORD RECORD).

FREE SPACE (BLOCKS) IS ACCOUNTED FOR IN A BIT MAP, WHICH IS PARTITIONED INTO RECORDS (2K BLOCKS PER SECTION). A 0 INDICATES THAT A BLOCK IS USED; A 1 INDICATES THAT IT IS FREE.

FILE SPACE IS ALSO PARTITIONED INTO 2048 RECORD SECTIONS (16 MAX. SECTIONS, 2K BLOCKS PER SECTION 1 MAP PER SECTION). THE NUMBER OF SECTIONS IN A FILE IS NS=(FL + 2047) & LSA(7). THE FIRST NS RECORDS FOLLOWING RECORDS 0, 1 (RECORDS 2 TO NS+1) ARE RESERVED FOR THE SECTION MAPS.

IF THE SECTION MAPS SPECIFY MORE SPACE THAN IS POTENTIALLY AVAILABLE, THOSE RECORDS BEYOND FLIMIT ARE MARKED AS "USED".

Entry Point Directory



THE DIRECTORY IS PARTITIONED INTO 95 HASH LISTS (SAME HASH FUNCTION AS USL); EACH HASH LIST IS A LINKED LIST OF RECORDS.

EACH RECORD CONTAINS A SUCCESSOR LINK (RECORD #) AND A USED SPACE COUNT. A LINK OF 0 TERMINATES A LIST. WHEN A RECORD IS VOID OF ENTRIES (USED=2), ITS SPACE IS RETURNED TO THE FREE STORAGE AREA.

THE HASH LIST HEAD POINTERS (HL IN THE DIAGRAM ABOVE) ARE IN RECORD 0 WORDS %41 TO %177.

Typical Directory Entry



LC is (0:2)...Level of Checking
0 = No checking
1 >= Check for procedure type
2 >= Check for # parameters
3 >= Check for parameter type
NR is (2:6) is # parameters

R - 0= Not permanently allocated
1= Permanently allocated

U - Uncallable bit - set if entry point is uncallable.

Code Segment Linkage Structure

EACH CODE SEGMENT OCCUPIES AN INTEGRAL NUMBER OF RECORDS. THIS BLOCK OF INFORMATION CAN BE SUBDIVIDED INTO THREE TABLES: THE CODE SEGMENT PROPER, AN STT SEGMENT MAP ARRAY, AND AN EXTERNAL LIST.

STT MAP ARRAY

A 1 BYTE X 256 BYTE ARRAY. IT IS INDEXED BY STT NUMBER AND RETURNS (IF THE STT CORRESPONDS TO AN EXTERNAL OF THE SEGMENT) THE SEGMENT NUMBER OF THE EXTERNAL AND 255 OTHERWISE. THIS ARRAY IS USED WHENEVER THE SEGMENT IS LOADED AND IS UPDATED WHENEVER THE SL IS BOUND BY THE SEGMENTER.

EXTERNAL LIST

A SYMBOLIC LIST OF THE EXTERNALS OF THE SEGMENT. EACH ENTRY CONTAINS INFORMATION ABOUT THE EXTERNAL: PARAMETER CHECKING LEVEL AND PARAMETER MATCHING INFORMATION, AND THE SEGMENT NUMBER AND STT NUMBER IF THE EXTERNAL IS SATISFIED WITHIN THE SL.

Code Segment Structure (Cont.)



S - SATISFIED BIT - SET IF EXTERNAL IS SATISFIED WITHIN SL

EXTERNAL LIST TERMINATOR

Reference Table Structure

FOR ERCH SEGMENT THERE IS R REFERENCE TRBLE ENTRY OF 32 WORDS. TNE REFERENCE TRBLE ENTRIES RRE PRCKED FOUR TO R RECORD. THE RECOROS CONTRINING TNE REFERENCE TRBLE ENTRIES ARE LISTEO IN RECORD 1. THE RECORD CONTRINING REFERENCE TRBLE ENTRY N IS REC 1 (N.(O : 14)); TNE FIRST WORO OF TNE ENTRY IS REFTRB (N.(14 : 2) & LSL (5)).

WHEN R SEGMENT IS OELETEO, THE REFERENCE TRBLE ENTRY CORRESPONDING TO THE SEGMENT IS RELERSEO. THESE FREE ENTRIES ARE LINKEO TOGETNER IN R LIST; THE SEGMENT # IS USEO RS R LINK RND IS PLACEO IN TNE FIRST WORO OF TNE ENTRY.

WNEN R SEGMENT IS RDDED IT IS ASSIGNED R SEGMENT NUMBER (O LESS TNRN/EQURL TO N LESS THRN/EQURL TO 254); TNE NUMBER IS TNRT OF THE FIRST FREE REFERENCE TRBLE ENTRY, OR, IF NONE RRE FREE, TNE NEXT AVRILABLE REFERENCE TABLE ENTRY (CRUSING SPRCE RLLOCRTION FOR TNE ENTRY).

Reference Table (256 Maximum Entries)

TYPICAL ENTRY



Code Segment With Patch Rrea

Patch Rrea (Cont.)



PMRP Information



PMRP Type Table



NOTE : n = PTTL - 2

PMAP Records

Type 0 Segment PMAP Record



Type 1 Procedure PMAP Record



Type 2 Secondary Entry PMAP Record



H : HIDDEN ENTRY FLAG

CHAPTER 11 LOADER

MPE Loader

The loader is a system process which will do loads sequentially. If a process needs code to be loaded, it will get the load process' SIR, fill loader communication table, and then awake the loader. Upon completion, the loader will return its status through the loader communication table, and then activate the waiting process.

Loader Segment Table Overview

Loader Segment Table consists of two DST's. The main one is DST X22 (LST). The other DST (XLST) has its DST number stored in SYSGLOB X226.

LST Overview



XLST Overview



The above DST's has exactly the same primary DB area so that directory entry handling procedures can be used on both DST'S. XLST is the LST extension and is used to store the extension entry only. When a extension entry is needed, it is copied into the LST to eliminate frequent EXCHANGEDB. Note that XLST is capable for any types of entries. It is used for extension entry only for now. Also, some of the primary DB's in the XLST are not used. They are there just for the consistency.

Loader Segment Table Primary DB



ENTPn : POINTERS POINT TO THE CURRENT ACCESSED ENTRY.
SBUF : UTILITY BUFFER. USUALLY CONTAINS PROGRAM FILE RECORD 0 INFORMATION.
SI ST : UTILITY DB RELATIVE VARIABLES.
HDFWLINKs : HEAD OF FORWARD LINK FOR EACH TYPE.
HOBKLINKs : HEAD OF BACKWARD LINK FOR EACH TYPE.

Directory Entries



Directory Entries (Cont.)



Directory Entries (Cont.)



Directory Entries (Cont.)



Directory Entries (Cont.)



Directory Entries (Cont.)



Loader Cache

SYSGLOB extension area + 272 contains DST number of cache
BUCKETSIZE = 252

Cache Data Segment Format



Bucket Format



All bucket words are initialized to BUCKETSIZE +1, indicating no entries.

Loader Communication Table (LCT)

Form Incoming to Loader (Load/Allocate Program)



LCT (Cont.)

Form Incoming to Loader (Load/Allocate Procedure)



LCT (Cont.)

Form Returned (No Error)



Form Returned (Error Occurred)



Logical Segment Transform Table (LSTT)

When a process references any user SL segments, these segments are assigned logical segment numbers if the new mapping ucode is running. The LSTT provides a map mapping these logical segments into their physical segment numbers and having true STT's for the mapped segments. The LSTT is created by LOADER during the load time. It occupies an OST and the DST number is stored in PCB(15). If no user SL segment is referenced, the LSTT will not be needed, hence it will not be created.

The new mapping microcode depends on the existence of the LSTT for getting the physical segment number for a mapped segment. So the LSTT has to be included in process' locality list if there is an LSTT. Dispatcher will then bring the LSTT in before the process can be run. Also the bank and address for the LSTT belonging to the current running process are stored in sysglob cells (%221 and %222) during the launch time by the dispatcher. These cells are used by microcode for fast accessing the LSTT.

Logical Segment Transform Table (LSTT) (Cont.)



CHAPTER 12 PRIVATE VOLUMES / SERIAL DISC

Mounted Volume Table (MVT AB) DCT =53 (Z65)



MVTAB (Cont.)



MVTAB (Cont.)



cycl - cyclical volume index (local VTABX) for disc space allocation

hvol - highest (ordinal) volume index (volume index being the volume set's local VTABX) of a mounted member of the volume set(class).

nvol - # of volumes mounted for the volume set(class).

ucnt - # of users having mounted the volume set.

dbms - directory bit map size (sectors).

vcnt - # of users having mounted the volume.

Private Volume User Table (PVUSER) DST =54 (66)



PVUSER (Cont.)

```
|-----------------------------|  |           |
|      bind names count       |  |           |
|-----------------------------|  |           |
|  DST # of bind names segment|  |           |
|-----------------------------| ----         |
~              .              ~              |
~              .              ~              |
|                             |              |
|-----------------------------| ----         |
|            vmask            |  |           |
|-----------------------------|  |           |
|             pin             |  |           |
|-----------------------------|  |           |
|       user bind count       |  |           |
|-----------------------------|  |           |
|       user mount count      |  |           |
|-----------------------------|  |- user entry n
|      system bind count      |  |           |
|-----------------------------|  |           |
|      system mount count     |  |           |
|-----------------------------|  |           |
|      bind names count       |  |           |
|-----------------------------|  |           |
| DST # of bind names segment |  |           |
|-----------------------------| -------------|
|                             |
~                             ~

~                             ~
|                             |
|-----------------------------| -------------|
|  op mask    :     MVTABX    |              |
|-----------------------------|              |
|                             |              |-- volume set
~                             ~              |   entry n
|                             |              |   (MVTABX = k)
|-----------------------------| -------------|
|              a              |
|              v              |
~              a              ~
               i
~              l              ~
|              a              |
|              b              |
|              l              |
|              e              |
|-----------------------------|
```


Bind Names Data Segment

(Created and managed via PVUSER Table)

```
                        1 1 1 1 1 1
   0|1:2:3|4:5:6|7:8:9|0:1:2|3:4:5
   |-----------------------------| ----------
 0 |     max segment length      | 0        |
   |-----------------------------|          |
 1 |   current segment length    | 1        |
   |-----------------------------|          |
 2 |              0              | 2        |
   |-----------------------------|          |
   |                             |          |
   ~                             ~          |-- entry 0
                                            |
   ~                             ~          |
   |                             |          |
   |-----------------------------|          |
 8 |              0              |10        |
   |-----------------------------| ---------|
 0 |         bind count          | 0        |
   |-----------------------------|          |
 1 |                             | 1        |
   |-         G R O U P         -|          |
 2 |                             | 2        |
   |-          N A M E          -|          |
 3 |                             | 3        |
   |-                           -|          |
 4 |                             | 4        |-- entry 1
   |-----------------------------|          |
 5 |                             | 5        |
   |-       A C C O U N T       -|          |
 6 |                             | 6        |
   |-          N A M E          -|          |
 7 |                             | 7        |
   |-                           -|          |
 8 |                             |10        |
   |-----------------------------| ---------
   |                             |
   |                             |
   ~                             ~
```


Bind Names Data Segment (Cont.)

```
   ~                             ~
   |                             |
   |-----------------------------| ---------
 0 |         bind count          | 0       |
   |-----------------------------|         |
 1 |                             | 1       |
   |-         G R O U P         -|         |
 2 |                             | 2       |
   |-          N A M E          -|         |
 3 |                             | 3       |
   |-                           -|         |
 4 |                             | 4       |-- entry n
   |-----------------------------|         |
 5 |                             | 5       |
   |-       A C C O U N T       -|         |
 6 |                             | 6       |
   |-          N A M E          -|         |
 7 |                             | 7       |
   |-                           -|         |
 8 |                             |10       |
   |-----------------------------| ---------
   |              a              |
   |              v              |
   ~              a              ~
                  i
                  l
   ~              a              ~
   |              b              |
   |              l              |
   |              e              |
   |-----------------------------|
```


Serial Disc Tables and Data Structures

Data Record Format

The primary purpose of the Serial Disc Interface (SDISC) is to adapt the undefined length transfers characteristic of magnetic tape to the fixed-length environment of a disc or integrated cartridge tape(ICT). To accomplish this, data is buffered within SDISC. The buffer is an integral number of sectors (blocks for the ICT) long. Files always start on a sector boundary, but data records within files may start anywhere and straddle sector boundaries. A record in the buffer is structured as follows:

```
+---------+---------------------------+---------+
| record  |                           | record  |
| length  |           data            | length  |
| (bytes) |                           | (bytes) |
+---------+---------------------------+---------+
```

The record length is always a one-word positive byte count which includes only the data portion of the record, not the length words themselves. Records within a file might be stored on the disc as follows:

```
+----+-----------------------------+---         -----
| RL |/////////////////////////////|              ^
+----+------+----+----+------------+              |
|///////////| RL | RL |////////////|              |
+-----------+----+-+--+-+----+-----|           Sector N-1
|//////////////////| RL | RL |/////|              |
+------------------+----+----+-----|              |
|//////////////////////////////////|              v
+---+----+----+--------------------+---         -----
|///| RL | RL |////////////////////|              ^
+---+----+----+-+--+--+------------+              |
|///////////| RL | RL |////////////|              |
+-----------+----+----++---+-------+           Sector N
|/////////////////////| RL | RL |                 |
+---------------------+----+----+--+              |
|//////////////////////////////////|              v
+-----+----+----+------------------+---         -----
|/////| RL | RL | .....            |
+-----+----+----+------------------+
```

The reason for the trailing byte count is to implement an easy way to backspace records.

End of File Format

Since files always start on a sector boundary, it follows that they also end on one. End of files consist of a 0 record length and 0-fill to the end the current sector as follows:



In addition, an End-of-File entry is made in the Gap Table, so that files may be skipped by scanning Gap Table entries instead of serially scanning the data area. The Gap Table is described a few pages from now.

Contiguous Block Format

A serial disc, if it can do everything a magnetic tape can do, must also be a cold-load device. This means that machine microcode must be able to read a bootstrap channel program and the resident segments of INITIAL from the disc into memory. The microcode and channel programs cannot deal with the record length words which surround standard data records, so for them we have a structure, called a CONTIGUOUS BLOCK, which has the data without the length words. Information as to the length of each contiguous block must therefore be kept elsewhere, so there are Gap Table entries which hold the beginning and ending sector addresses of each contiguous block. This implies that each block must begin and end on a sector boundary. In this way they are similar to data files. To set contiguous blocks off from normal data, and to reach a sector boundary, a record length and fill character = %177777 is used, as follows:



Hole Format

Holes on the serial disc have the same format as contiguous blocks (that is, they start and end on sector boundaries with -1 fill characters as required). Starting with MPE version G.00.00, holes are obsolete and SDISC will not generate them. However, code has been left in SDISC to process any holes found on serial discs written with earlier versions of SDISC. Further details may be found in the Serial Disc IMS.

Gap Table Format

The Gap Table is a four-word header followed by a series of two-word device address entries. A permanent copy lives on the device, starting in sector 4, while a working copy lives in main memory. The copy in memory is posted to the disc only when a backspace or rewind operation occurs after writing (in other words, when the copy in main memory has changed). The length of the Gap Table is device-dependent according to the table below:

Device	Number of sectors (or ICT blocks)
HP7920	44
HP7925	106
HP7933/35	219
HP7902/9895	26
ICT	4 blocks ("S" cartridge) or 15 blocks ("L" cartridge)

The Gap Table looks like this:



The type field is bits 0, 1 and 2 of the first word. The eight possible types are:

0. End of File. The associated sector address contains one or more end of file fill characters (0) to fill out that sector. In the worst case (the previous record ended exactly at the end of the previous sector), the end of file sector contains all zeros.
1. End of data. The associated sector address is the last address of valid data plus 1, in other words, the next available address. In practice, such an entry is usually preceded by an end-of-file entry, since the EOD entry is written when you stop writing, and the file system will not let you backspace or rewind after writing without sending a Write End of File. An EOD entry is also written at the beginning of the Gap Table when new (unwritten) media is inserted. This prevents erroneous reading of blank media.

2. Beginning of Hole. The starting address of a "defective" area of the disc. Usually on a track boundary, but may be in mid-track if a contiguous block was being written when the "defect" was encountered. Obsolete, starting with MPE version G.00.00.
3. End of Hole. The corresponding ending address of the "defective" area. Always at a track boundary. Obsolete, starting with MPE version G.00.00.
4. Beginning of (contiguous) Block. The starting address of a contiguous block, exclusive of the -1 fill characters which may have been required to get us to a sector boundary. Unlike the End of File fill characters, there need not be any -1 characters if the previous record or contiguous block (with or without the trailing length word) ended exactly on a sector boundary.
5. End of (contiguous) Block. The address of the last sector containing contiguous block data. The sector may also contain -1 fill characters to get us to a sector boundary, but as with the beginning of block they are not required if the contiguous block ends exactly on a sector boundary.
6. End of Tape mark. The sector address of the simulated End of Tape reflector. This type is now written only to floppy discs for use by INITIAL's serial disc interface. When read by MPE's SDISC, it will be skipped no matter what device it is found on. This ensures compatibility with older serial discs.
7. End of Gap Table. No associated sector address. If you hit this while scanning the Gap Table, you've gone too far. In practice, this type is created whenever the Gap Table is cleared, by the simple device of initializing the table to -1.

SDISC Extra Data Segments

With insignificant exceptions, SDISC operates entirely in split-stack mode, that is, using an extra data segment for its working storage. Starting with MPE version G.00.00, there are two additional data segments used as no-wait data buffers. For the most part, our discussion here is restricted to the original data segment, now used only for variables, the Gap Table, and data buffer management.

The working storage extra data segment (XDS) is usually acquired by the external procedure ALLOCATE when the serial disc device is first assigned to a user as part of an FOPEN. The external procedure DEALLOCATE makes the XDS go away as part of its processing of the final FCLOSE against the device. The system program PVPROC may also acquire and release an XDS so that the tape label routines in LABSEG may also use SDISC for their work when DEVREC processes a device on-line interrupt. SDISC allocates the two data buffer segments as they are needed, then deallocates them as part of the Device Close processing.

In addition to the Gap Table already described, the XDS contains SDISC's global storage area, including the data buffer management areas (BUFFER'INFO), and a small buffer (called WORKTABLE). WORKTABLE holds the contents of the Serial Disc label sector when SDISC reads it in as part of its self-configuration. It also hold the Defective Tracks Table (MAC family discs) or Defective Sector Table (CS80 discs) while reassigning suspect or deleted tracks.

The three arrays in the XDS (WORKTABLE, BUFFER'INFO and GPT (Gap Table)) are all dynamically configured by SDISC as vanilla indirect arrays, such as might have been constructed by SPL. This is done by declaring the array names as pointers, then inserting appropriately computed element-0 addresses in them.

The extra data segment is organized as follows:

0	WORDSPERSECTR	These twelve words are reserved for use by ALLOCATE when the data segment is created. However, ALLOCATE only stuffs the last five of them. We fill the first seven ourselves with information we get from the label sector.
1	SECTORSPERTRAK	
2	STARTADDRESS (BOT)	
3	EOTSECTR (disc address of simulated end of tape)	
4		
5	EODSECTR (last sector of disc)	
6		Simulates tape runoff.
7	JUSTALLOCATED	Tells us to initialize SDISC parameters to BOT if true.
8	WRITE RING	Simulation of tape write ring.
9	FATALERROR	Disables SDISC when true.

10	No longer used.	
11	MAX'DSEG'SIZE	Max size of our XDS, so we can check that it's big enough.
	SDISC global variables, including array pointers.	
	WORKBUFFER	Length is 512 words.
	BUFFER'INFO	Length is calculated as MAX'NUM'BUFFERS (currently 2) * INFO'ENTRY'SIZE (currently 8).
	GPT	Length varies with device, and is calculated by SDISC as part of its self-configuration.

Serial Disc Organization

The disc is organized as follows:

Label sector	0 See expanded view in Chapter 3.
DTT/DSCT	1 DTT (MAC family) or DSCT (CS80).
Cold load	2 HP-IB cold load channel prog.
Soft dump	3 SDFTDUMP channel program.
Gap Table	4 to STARTADDRESS - 1.
Data	STARTADDRESS . . to . EOTSECTR . to . EODSECTR
Last data sector	

CHAPTER 13 I/O
I/O Table Linkage



Device Reference Table (DRT)



SIDP - absolute address of SID program
PI - interrupt handler plabel
DBI - this is the absolute address of the ILT

Driver Linkage Table (DLT)



There is one DLT for each type of driver. A pointer in the OIT allows different devices on a controller to have different drivers and interrupt handlers.

DPROC.QNUMB - This field contains the I/O process request queue number for type 2 drivers. Zero for all other types.
.(8:1).DRVRFRZN (DF) - Driver code frozen. Set by MAM when then the driver code segment has been made present and frozen from a request from SIDDM.
.(9:1).MAMERRDRC (MC) - MAM Error on Code Makepresent
.(10:1).CORERES (CR) - If set both initiator and completor code are core resident.
.(14:2).DRVRTYPE (MTVP) - DRIVER/MONITOR TYPE
0 - not used
1 - driver can be executed on any stack
2 - driver can be executed in the user process or in the I/O process identified by IONUMB
3 - run only in process whose PCB number is in IONUMB

OMNTR - I/O Monitor Plabel.
OINIT - Driver Initiator Procedure Plabel.

OCOMP - Driver Completor Procedure Plabel.
OINTP - Special interrupt handler Plabel. This procedure is called by GIP if ISPEC is set DFLAG. No other action is taken by GIP except to set the Interrupt Status in DSTRT.
DTYPE.DITSIZE - The length of the DIT in words for this driver.

Logical-To-Physical Device Table (LPDT)

DST = 13 (= %15)
SIR = 9 (= %11)

The LPDT has several fields which describe the state of a device. Some of these fields have the same meaning for all devices. Others are device dependent. All are described below.

There are two types of devices represented in the LPDT: real devices and virtual devices. A real device is one which has been configured into the system and is capable of performing input and/or output. A virtual device simulates some of the properties of a real device (for example a spooled line printer or an INP), but there is no physical I/O involved. The two main uses for virtual devices are for OPEN spooled devicefiles and certain communication devices (such as INP's).
A given virtual device entry is in use only while the devicefile it represents is open. When the file is FCLOSEd, the entry becomes available for another virtual device. This is the reason for the SYSDUMP/INITIAL configurator question MAX # OF OPEN SPOOLFILES--it needs to know how many virtual device entries to allocate to the LPDT (and to the LOT).
Entries in the LPDT are ordered by logical device number. The first word address of a real device entry is obtained by multiplying the LDN by the entry size. Except for the 0th entry, entries for which no logical device is configured on a given system are used for virtual device entries. Any remaining virtual device entries follow the last real device entry.

Entry 0



Discussion:
Word 2 is incremented by a device driver whenever it sets the Device Ownership State field (below) to 2 (Service Requested). DEVREC decrements the count for each interrupt it services until the count reaches 0, at which time DEVREC hibernates.

-- CAUTION --
Device drivers must lock this table by DISABLE/ENABLEing, -NOT- by trying to acquire the LPDT SIR.

Typical Entry (Virtual Devices)



ID -- 0 for input, 1 for output.

Word 0, bit 0 is 1 for a virtual device, 0 for a real device. The fields in word 1 are the same, as applicable, as for the real device represented by a given virtual device. See below.

Typical Entry (All Real Devices)



Discussion:
Word 1.(0:2) -- Device Ownership State:
0 -- Not owned by any process.
1 -- Owned by a process.
2 -- Service requested. Set by driver for unexpected interrupt, then wakes DEVREC.
3 -- Service granted. Set by DEVREC. Logon sequence is 0-2-3-1.
3 -- Device reserved (alternate use). Set during STARTSPOOL, spooler process sets to 1 when it gets started.
Word 1.(2:1) -- Device is Job/Session Accepting if true.
Word 1.(3:1) -- Device is Data Accepting if true.
Word 1.(5:1) -- Device is Duplicative if true (all devices except discs).
Word 1.(6:1) -- Device is Interactive if true (all devices except discs).
Word 1.(7:3) -- End of File condition:
0 -- No EOF detected.
1 -- Hardware EOF (e.g., tape mark).
2 -- :DATA record read.
3 -- :EOD record read.
4 -- :HELLO record read.
5 -- :BYE record read.
6 -- :JOB record read.
7 -- :EOJ record read.
Word 1.(12:4) -- Device subtype. See discussion for tape entry (below) for a description of the Ruto bit (12:1).
The remaining bits in Word 1 are device-dependent and are described with their corresponding entry diagram.

Entry for Terminal-Like Devices



Discussion (unique fields only):
Word 1.(4:1) -- CONTRDL-Y is allowed and has been detected.

Word 1.(10:1) -- BREAK has been detected -OR- ignore BREAK if the C.I. is running.

Word 1.(11:1) -- The terminal is logging on. This bit is set by PRDGEN and DEVREC when the logon sequence etarts. If the bit is off when polled by INITJSMP, the terminal has disconnected. For now, only IDTERMO and HIDTERM support the use of this bit. Multipoint and DS pseudo-terminals do not.

Entry for Tape Drives



Discussion (unique fields only):

Word 1.(4:1) -- BOT. Tape is at Load Point -OR- no tape mounted. Recording density may only be switched when this bit is true (for multiple density tape drives).

Word 1.(11:1) -- If true, DEVREC is performing Automatic Volume Recognition (AVR) on a tape (or PVFROC is doing the same on a serial disc), -OR- AVR is to be suppressed on job or data accepting devices.

Word 1.(12:1) -- Part of Device Subtype field. If true, device is allocated automatically when opened. If false, operator must allocate.

Entry for Disc Drives



Discussion (unique fields only):
Word 1.(0:2) -- Device Ownership State. May not be 1 (owned) for shared device (system volume or private volume). Serial and foreign discs are non-sharable and may be owned. See the full discussion of this field under Typical Entry, above.

Word 1.(4:1) -- If true, the disc is a nonsystem domain (private volume, serial disc or foreign disc) disc drive.

Word 1.(5:1) -- If true, disc is a mounted private volume.

Word 1.(6:1) -- If true, the disc is a reserved volume used to satisfy the requirements of a multiple volume private volume set.

Word 1.(10:1) -- If true, the disc is a physically and logically mounted serial or foreign disc. Bits 5 and 6 must be false.

Word 1.(11:1) -- If bit 10 is true, then 1 ==> foreign disc, 0 ==> serial disc.

Word 3.(1:1) -- If true, the device is currently being used as a serial disc (that is, it is allocated to a user as a serial disc). This bit duplicates a bit in the LDTX entry so that this information can be found in a system (memory-resident) table.

Logical Device Table (LDT)

Overview of Data Segment



Logical Device Table

Zero Entry Format



Typical Entry Format

Discussion:

Word 2.(8:1) -- Communication system device if set.
Word 2.(9:1) -- If set, there are special forms mounted on the device.
Word 3.(0:2) -- Spooled state of the device:
0 -- Not spooled.
1 -- Owned by an input spooler.
2 -- Owned by an output spooler.
Word 3.(2:1) -- Device is available to system (not down).
Word 3.(3:1) -- Device is available to diagnostics (obs).
Word 3.(4:1) -- :DOWN requested, honored when use count = 0.
Word 3.(5:1) -- If set, trailers are disabled.
Word 3.(6:1) -- If set, headers are disabled. These two bits are managed such that header/trailers are generated in pairs or not at all.
Word 3.(7:1) -- If I/O, word 6 is the Device Class Table index/LDEV# of the default output class/device associated with this device.
Word 3.(8:1) -- Spooling has been enabled (spool queues are open) for this device.
Word 3.(9:7) -- Device dependent information:
1. For terminal-like devices, the default terminal type to be used if not specified in the :HELLO command.
2. For variable density tape drives:
Word 3.(10:3) -- actual tape density.
Word 3.(13:3) -- density requested in FOPEN for writes to unlabelled tapes only.
For either:
0 = unknown density/no FOPEN w/ write.
1 = 1600 BPI
2 = 6250 BPI
3 = 800 BPI

Logical Device Table Extension (LDTX)

Overview of Data Segment



Zero Entry



Typical entry



Where:

S.....Seek ahead enable/disable flag (system or PV disc only).
SD....This logical device is a Serial Disc or a Foreign Disc.
CP....This logical device uses the CIPER protocol.
FS....This is a system or PV disc with Oisc Free Space management.
DS....This LDEV is a DS or data communications device.

Terminal Entry



TBRC..Terminal's baud rate code (CPS = characters per second).

Speed (CPS)	ADCC/ATP (NPIB) TBRC
Not known	0
1920	16 (ATP only)
960	8
480	9
240	7
120	11
60	6
30	13
15	14
14	---
10	15

WS....This terminal is connected to a Workstation Configurator port.

TDT offset...Offset from the base of the Terminal Descriptor Table (TDT) to the TDT entry for this terminal. A -1 indicates no TDT entry exists for this terminal.

Serial or Foreign Disc Entry



CIPER Entry



DB.....If set to 1, then debugging is in effect.
DN.....If 1, the CIPER facility has been de-activated for this device because of error.
CTMI...Control Table Map Index (an index into the Control Table Map (CTM), which is located in the CDCDS.

Systen or Private Volume Disc Entry



S.....Seek ahead enable/disable flag.

Device Class Table (DCT)

Overview of Data Segment



Device Class Table

Header Entry Format



Typical Entry Format



Discussion:

The Device Class Table (DCT) contains a varying number of variable length entries. This is because you may configure an arbitrary number of device classes on a systen, and each device class may be comprised of an arbitrary number of logical devices. There is one DCT entry per device class, and each DCT entry contains a list of logical devices in the class. There is no established order of entries in the DCT, nor is there an order of LDEVs within an entry.

Due to the haphazard nature of the DCT, its overall properties are kept in the header entry. These include the segment-relative starting address of the DCT (in case the header entry should be expanded later) and the number of entries in the table A segment-relative pointer to the Terminal Descriptor Table (which follows the DCT) may also be used to calculate the size of the DCT. Also note the "Entry size" word. It is meaningless for this table, but is included for compatibility with other fixed-length entry MPE tables.
Since the DCT entries are of variable length, when you want a particular entry you must always start at the beginning of the DCT and link through each entry until you find the one you're interested in.

A few of the fields in the DCT require further description:

Word 4.(1:7) -- Cyclical pointer. Currently used only for system and private volume disc devices. The pointer varies from 1 to N (number of en-

tries in the class) and indicates the LDEVN in the class list on which the last extent was allocated. The disc space allocation routines will try to satisfy the next re- quest on the next disc drive indicated by the cyclical pointer (with wraparound to 1 if the pointer > N). If that fails, the pointer is incremented until space is found or all devices in the class have been tried.

Word 4.(8:1) -- If set, spooling has been enabled (spool queues opened) for this device class.

Word 4.(9:1) -- If set, the class is a terminal type class.

Word 4.(10:6) -- Usually the same as the device type represented sented by the class (0 for24 for tape, 32 for printer, etc.). Serial disc classes are disc devices accessed as tape drives, so their true device types are kept in the LDT, while this field holds a special cial type (31, or %37), indicating a serial I/O (non-concurrent) device. Similarly, a foreign disc is a nonsharable disc drive, so that fact is reflected by a special type 7 in this field, even though the true hard- ware type is kept in the LDT, as for serial discs.

Interrupt Linkage Table (ILT) for HP-IB Systems



ILT (Cont.)

IPCVA - These four words comprise the channel program variable area where information is stored concerning a channel program Interrupt instruction or abort. CPVA0 should be used only for channel program aborts.
ICPVA4 - Words 4 and 5 contain DMA address, when channel program aborts during DMA transfer.
ISRQL - Serial poll request queue length. HP-IB Systems do not support any serial poll devices. This should always be zero.
ICPGM - This is the SYSDB relative address of the channel program to be started for this device after receiving a HIDP interrupt in GIP. GIP will call STRRTID when the flags word indicates "ignore halt interrupt" and "start channel program" bits are set.
ICNTRL - Contains controller information.
.M If set, the controller is sharing a software channel resource in order to limit bandwidth.
.CHNQ The software channel resource number.
.DRTN The DRT number for a Series 33 device is equivalent to:
.CHAN - channel number (4 most significant bits of DRTN)
.DEV - device number (3 least significant bits of DRTN)
IFLAG - Used for controller flags.
.RW Runwait flag. An idle channel program should be started when there are no active requests to process.
.WP Waitprog flag. An idle channel program has been started for this controller. This bit is reset by an interrupt.
.IG Ignorehi flag. An HIDP instruction has been issued against this controller, but the channel program was not in a wait statement. Therefore, ignore the interrupt generated by the channel code when this program halts.
.SC Start channel program flag. When set along with the IG flag, GIP will start a previously attempted SIDP on this device.
.SQ Start channel program "queued" flag. When bit SC is set, this bit will determine if the call to START'MPIB will have logical parameter QUEUED true or false.
.HCUNIT Highest configured unit number for this controller.

Device Information Table (DIT)

There is one DIT per physical device. If a physical device represents represents more than one logical device, the logical device number is obtained from the I/O queue element. Although details of DIT's vary with device, the following structure is common to all:

DIT for HP-IB Systems



DTRQX Used by some device drivers, it denotes timer request index.

DIT Terminology for HP-IB Systems

```
DFLAG - DEVICE RELATIVE FLAGS
  T     SET IF DEVICE IS A TERMINAL.
  D     SET IF DEVICE IS A DISC.
  AC    ACTIVE BIT. 1 IMPLIES A MONITOR CURRENTLY SERVICING
        THIS DEVICE.
  RQ    REQUEST BIT. 1 IMPLIES SERVICE REQUESTED WHILE
        MONITOR IS ACTIVE.
  MU    IF SET, MULTIPLE UNIT CONTROLLER.
  ID    IF SET, THEN A CHANNEL PROGRAM IS CURRENTLY EXECUTING.
  IR    IF SET, AN INTERRUPT OR RESPONSE HAS OCCURRED.
  ND    IF SET, DEVICE IS IN A NOT READY OR OPERATOR WAIT.
  ST    IF SET, AN IDLE CHANNEL PROGRAM SHOULD BE STARTED FOR
        THIS DEVICE.
  SI    SPECIAL INTERRUPT HANDLER
  NS    DO NOT SHORT WAIT THIS DISC
  STATE CURRENT DRIVER STATE AS DEFINED BY THE MONITOR.
        ALLOWABLE STATES ARE:
          0 - START REQUEST
          1 - NOT USED (BUT RESERVED)
          2 - CALL DRIVER INITIATOR
          3 - CALL DRIVER COMPLETOR
          4 - NOT USED (BUT RESERVED)
          5 - COMPLETE REQUEST
          6 - UNEXPECTED INTERRUPT OCCURRED
          7 - START OPERATOR INTERVENTION WAIT
        %10 - WAITING (ON OPERATOR). RESTART AT 0
        %11 - WAITING (DATA MAKEPRESENT/FREEZING)
        %12 - WAITING (INITIATOR CODE MAKEPRESENT/FREEZE)
        %13 - WAITING (FOR COMPLETION INTERRUPT)
        %14 - WAITING (FOR DEVICE CONTROLLER AVAILABILITY)
        %15 - NOT USED (BUT RESERVED)
        %16 - WAITING (INITIATOR CODE MAKEPRESENT)
        %17 - WAITING (COMPLETOR CODE MAKEPRESENT)
IDT - I/O System type  0-Series II/III I/O System
                       1-HP-IB Systems
                       2-unused
                       3-unused
```

Device Information Table (DIT) for CIPER

There is one DIT per physical device. If a physical device represents more than one logical device, the logical device number is obtained from the IOQ element (however, this driver only supports one device per controller.) The following diagram shows the DIT used for the HP-IB CIPER physical driver.


```
    0  1  2  3  4  5  6  7  8  9 10 11 12 13 14 15   MNEMONIC
  +--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+
0 | D| D|AC|RD| D| D| D|ID|IA|ND|ST| D|   STATE   |   DFLAG
  +--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+
1 | SYSDB relative pointer to the DIT for the next  |   DLINK
  | device requesting this resource or service      |
  +-------------------------------------------------+
2 | IOQ table index to the first IOQ in             |   DIOQP
  | request list for this device                    |
  +-----+-------------------+-----------------------+
3 | IDT |    Phys. unit #   | Logical device number |   DLDEV
  +-----+-------------------+-----------------------+
4 | SYSDB relative pointer to Device Linkage Table  |   DDLTP
  +-------------------------------------------------+
5 | SYSDB relative pointer to Intrp Linkage Table   |   DILTP
  +--+--+--+--+--+--+--------+----------------------+
6 |VS|AB|RE|TP|NR| NR CNT |      DEVICE STATUS     |   DSAVE
  +--+--+--+--+--+--+--------+----------------------+
7 | Hardware error status.  Set when the driver     |   DSERR
  | detects an error.  Whenever <>0, the driver     |
  | monitor logs an I/O error and clears this word  |
  +-------------------------------------------------+
%10| Bit 0 is set at completion of timer            |   DTIME
  +-------------------------------------------------+
%11| Holds the time out request entry index while   |   DADST
  | a timer is active.                              |
  +--+--+--+--+--------+--------+--------+--------+
%12|RF|UE|DE|TD|UNIT CNT|DATA CNT| TO CNT |PATY CNT|   DCOUNTS
  +--+--+--+--+--------+--------+--------+--------+
%13|          Error logging location #1             |  DLOGERROR
  +-------------------------------------------------+
%14|          Error logging location #2             |  DLOGCOUNT
  +-------------------------------------------------+
```

```
DFLAG - Flags and request state
  AC  ACTIVE  - A monitor is currently servicing this device.
  RQ  REQUEST - A service request is pending while the monitor is
                active.
  ID  IOPROG  - An I/O Channel Program is running for this device.
  IR  IAK     - An interrupt or response has occurred for this device.
  ND  NOTRDY  - Go to state %10 after Idle Channel Program is started.
  ST  STWRIT  - The device monitor is starting an Idle Channel Program
                for this device.  There is no IOQ associated with this
                type of request.
  STATE       - State of the device monitor.  Specifies the next action
                to be taken in SIODM in servicing the request:
                  0 - start new request
                  1 - not used
                  2 - call driver initiator procedure
                  3 - call driver completor procedure
                  4 - not used
                  5 - process request completed
                  6 - initiate device recognition sequence
                  7 - start operator intervention wait
```



```
                %10 - wait for interrupt (operator intervention)
                      restart at state 0
                %11 - wait for data segment freeze, then state 2
                %12 - wait for driver initiator to be frozen, then
                      allocate controller (state 2)
                %13 - wait for I/O completion interrupt, then state 3
                %14 - wait for controller, then call driver initiator
                %15 - not used
                %16 - wait for initiator make present, then state 2
                %17 - wait for completor make present, then state 3

DLDEV - I/O system type, unit and logical device number
    0 - HP3000 Series II/III
    1 - HP 3000 HP-IB
    2 - Unused
    3 - Unused

DSAVE - Device processing flags
  VS - VALID STATUS - Set to indicate Device Status has been updated.
  AB - DVRABFLAG    - Sequence Abort in progress due to ABORT request.
  RE - RETRYFLAG    - Sequence Abort in progress due to an error.
  TP - TIMERPOPPED  - Current error is due to software timer popping.
  NR - NOTADYFLAG   - Not Ready Wait in progress.
  NR CNT            - Number of Not Ready Waits during this request.
  DEVICE STATUS     - Device status returned during a Sequence Abort.
       BIT  8       -   CAC available and enabled.
       "  9         -   Reserved.
       " 10         -   Reserved.
       " 11         -   Reserved.
       " 12         -   Power fail or reset has occurred.
       " 13         -   A protocol error has been detected.
       " 14         -   A parity error has been detected.
       " 15         -   The peripheral has data to send.

DSERR - Pointer to status to be logged.
        Bits(0:8)   - Number of words to be logged.
        Bits(8:8)   - Offset relative to DITP(0).

DCOUNTS             - Error flags and error counts (4).
   RF - RED FAILED  - An error has forced this request to be aborted.
   UE - UNIT ERROR  - The current error is a Unit Error.
   DE - DATA ERROR  - The current error is a Data Error.
   TO - TIME OUT    - The current error is a GIC Time Out Error.
   UNIT CNT         - Number of Unit Errors during this request.
   DATA CNT         - Number of Data Errors during this request.
   TO CNT           - Number of GIC Time Outs during this request.
   PRTY CNT         - Number of HP-IB Parity Errors during this request.
```


DIT for Channel Devices

```
   0   1   2   3   4   5   6   7   8   9 10 11 12 13 14 15
 +---+---+---+---+---+---+---+---+---+---+---+---+---+---+
0|TERM|DISC|RCT|RED|   | M |SID|IO |IAK|M |NT|   |  STATE  |DFLAG
 |   |   |   |   |   |UNIT|PREMP|PROG|  |HEAD|RY|   |       |
 +---+---+---+---+---+---+---+---+---+---+---+---+---+---+
1|                          NEXT DITP                      |DLINK
 +---------------------------------------------------------+
2|                           IOQP                          |DIOQP
 +---------------------------------------------------------+
3|                     LOGICAL DEVICE NUMBER               |DLDEV
 +---------------------------------------------------------+
4|                           DLTP                          |DLTP
 +---------------------------------------------------------+
5|                           ILTP                          |DILTP
 +---------------------------------------------------------+
6|                  Controller Hardware Status             |DSTAT
 +---------------------------------------------------------+
7|                    Hardware Error Status                |DSERR
 +---------------------------------------------------------+
8|                                                         |DTIME
 +---------------------------------------------------------+
9|                                                         |DTRQX
 +---------------------------------------------------------+
10|  IDT  |                       |      PHYS. UNIT #       |DUNIT
 +-------+-----------------------+-------------------------+
 |
 |                  DRIVER DEPENDENT DIT AREA              |
 |                                                         |
 |                                                         |
 |                                                         |
 ----------------------------------------------------------
```

```
DFLAG.TERMINAL - Device is a terminal
     .DISC     - Device is a Disc (Bit 0 = 0)
     .ACTIVE   - A monitor is currently servicing this device
     .REQUEST  - Service requested while monitor was active

     .MUNIT    - device controller servicing multiple units
     .SIDPREMPT- If set then a              request has been queued for
                 this device.  Preempt code is set in IOQ.
     .IOPROG   - I/O program in progress.  Decrement SIOCOUNT and
                 check for multi-channel when complete
     .IAK      - Interrupt or Response has occurred.
     .M HEAD   -Moving head disc
     .NT RDY   -Not ready for SID. SIODM holds off next SID until
                ALLOWPOLL is done.

DTRQX        - Used by some device drivers, it denotes timer
               request index.
```

DIT for Channel Devices (Cont.)

DFLAG.STATE - this quantity specifies the next action to be taken in servicing the request.

0-new - start request.
1-not used.
2-call Driver Initiator Procedure
3-call Driver Completor Procedure
5-complete request
6-device recognition
7-start operator intervention wait (%10)
%10-restart request on interrupt
%11-wait for data to be frozen then state 2
%12-wait for driver code to be frozen then state 2
%13-call completor on interrupt
%14-wait for device controller
%15-not used
%16-wait for initiator make present then state 2
%17-wait for completor make present then state 3

DLINK - SYSDB relative pointer to the DIT for the next device requesting this resource or service.
DIDQP - SYSDB relative pointer to the first IDQ in the request list for this device
DLDEV.LDEVN - Logical Device Number
.UNIT - unit number of the physical device.
.IDT - IO type 0=> Series III I/D, 1=> NPIB I/O
DDLTP - SYSDB relative pointer to the DLT.
DILTP - SYSDB relative pointer to the ILT.
DSTAT - interrupt status for this device. Set each time the device interrupts.
DSERR - Hardware Device Controller Status. Set when the driver detects an error. Whenever not zero, SIODB logs an I/D error and clears this word.
DTIME - time out completed flags. If a timeout occurs in response to a timer request type %20 (I/O request), the sign bit is set in this word. The IA bit im DFLAG is also set, and the monitor for this device is awakened. (Only used if timer services are requested. Must be word #8 if timer services are requested.)

DIT For 7905/7906/7920/7925



DIT for 7905/7906/7920/7925 (Cont.)



DMISC
(15:1) L'STAT'ERR - 1 Last transfer ended in error.

IDT - I/D Devices
0 - non-HP-IB
1 - NP-IB Systems
2 - unused
3 - unused

Error and Retry Information



D - retry determination
S - request syndrome
E - request error information
M - update track map
W - writing track map
C - issued a recalibration
CL- driver issuing channel clear
T - timeout wait

NOTE: Integrated Cartridge Tape's DIT has the same format.

CS 80 Disc Device Information Table (OIT)

There is one DIT per physical device. If a physical device represents more than one logical device, the logical device number is obtained from the IOQ element. for the CS'80 disc controller, there will only be one device. The following diagram shows the DIT used by the CS'80 disc driver.





DFLAG - Flags and request state

TM TERM - Set if device is a terminal. DS DISC - If TM = 0 and this bit is set then the device is a disc, otherwise device dependent. RC RCTIVE - R monitor is currently servicing this device. RQ REQUEST - R service request is pending while the monitor is active. IO IOPROG - Rn I/O Channel Program is running for this device. IR IRK - Rn interrupt or response has occurred for this device. HO HOTROY - Go to state %10 after Idle Channel Program is started. ST STWRIT - The device monitor is starting an Idle Channel Program for this device. There is no IOQ associated with this type of request. STRTE - State of the device monitor. Specifies the next action to be taken in SIODM in servicing the request:

0 - start new request 1 - not used 2 - call driver initiator procedure 3 - call driver completor procedure 4 - not used 5 - process request completed 6 - initiate device recognition sequence 7 - start operator intervention wait %10 - wait for interrupt (operator intervention) restart at state 0 %11 - wait for data segment freeze, then state 2 %12 - wait for driver initiator to be frozen, then allocate controller (state 2) %13 - wait for I/O completion interrupt, then state 3 %14 - wait for controller, then call driver initiator %15 - not used %16 - wait for initiator make present, then state 2 %17 - wait for completor make present, then state 3

DLINK - R SYSDB relative pointer to the next OIT requesting this resource or service.

DCURREQP - R current request sysbase index.

OUNIT.(0:2) - I/O system type

0 - non-HP-IB 1 - MP3000 HP-IB Systems 2 - Unused 3 - Unused

DLDEV - Logical device number of this device.

DSTRT - Set to a -1 when a system powerfail has occurred.

DSERR - Pointer to status to be logged.

Bits(0:7) - Number of words to be logged. Bits(8:15) - Offset relative to DITP(0).

DMISC - Device dependent processing flags

LOCK'FLG - Lock flag denoting unload status of the disc volume.

0 - Allow operator unload to the volume. 1 - Deny operator unload to the volume.

IGNORE'INT'FLG - Ignore unexpected interrupt flag.

SUBSTRTE - Indicates state of the idle channel program:

0 - Normal idle channel program wait 1 - Idle request being serviced wait

DSBUFRDDR - SYSDB relative pointer to the system buffer element used to read the DSCT. Zero, if no element gotten.

DBRDBLK1 - High order logical sector address of the bad block for the Defective Sector Table (DSCT) entry.

DBRDBLK2 - Low order logical sector address of the bad block for the DSCT entry.

DBRDXFER - Byte transfer left when bad block occurred.

DLOGERROR - CPVR(0) logged on hardware error status.

DSIOPSTOP - Stopped channel program relative offset location due to an error in CPVR(0).

DSTRTUS - 20 bytes disc status logged on status error. (See CS'80 Disc Drive Status).

RPSWORD1 - Flags and local state

RE - Read revision code done. Set if read revision code level is done. DC - RPS revision code. Set if controller is "PEP"ed. DR - RPS desirable. Set if RPS is desirable. EN - RPS enabled. Set if default value for RPS is enabled. MR - Driver is processing a marginal data error from the drive. Do not return hard error. Local State - State of the local request made by driver

0 - No local request is being processed 1 - Reading rev code 2 - Setting default RPS

RPSWORD2 - Default value for RPS

T1 - Time to target in hundreds of microseconds T2 - Window size in hundreds of microseconds

OIT For 7970 Magnetic Tape



IOT - I/O Devices
0 - non-HP-IB
1 - HP-IB Systems
3 - unused
4 - unused

DSRVE - Device processing flags
RW RWBIT - Indicates tape has been rewound.
RU RWUNLD - Indicates that a rewind/unload was performed to allow a write-ring mount.
SH SHORT - R short read is in progress. After completion of read, EOF is checked for and if not present, the requested bytes are transferred from the short-read buffer to the user's buffer.
CE CESTAT - Channel parity error processing is in progress.
DC DSFLAG - Transfer used data chaining - used for computing the transmission log.
RW - (ODFLAGS, bit 15) if set, tape is rewound
RB4 - (bit 14) if set, need to rewind tape before next write

OMISC

```
 0  1  2  3  4  5  6  7  8  9 10 11 12 13 14 15

|--|--|--|--|--|--|--|--|--|--|--|--|--|--|--|--|
|  |  |  |  |  |  |  | FORWARD|  BRCK  |        |
| R| B| F| G| E| S| U| SPRCE  | SPRCE  | RETRY  |
|  |  |  |  |  |  |  |COUNTER |COUNTER |COUNTER |
|--|--|--|--|--|--|--|--------|--------|--------|
```

Where
- R - retry in progress
- B - backspace in progress
- F - forward space in progress
- G - gap in progress
- E - backspace on data end-of-file
- S - short read in progress
- U - unload tape for write ring installation

DIT for 7976 Magnetic Tape

There is one DIT per physical device. If a physical device represents more than one logical device, the logical device number is obtained from the IOQ element. The following diagram shows the DIT used for the mag tape driver.

```
    0  1  2  3  4  5  6  7  8  9 10 11 12 13 14 15   MNEMONIC
  +--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+
 0| 0| 0|RC|RQ| 0|MU| 0|IO|IA| 0| 0| 0|   STRTE   |  DFLAG
  +--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+
 1| SYSOB relative pointer to the DIT for the next|  DLINK
  | device requesting this resource or service    |
  +-----------------------------------------------+
 2| SYSOB relative pointer to the first IOQ in    |  OIOQP
  | request list for this device                  |
  +-----------------------------------------------+
 3|              Logical device number            |  OLDEV
  +-----------------------------------------------+
 4| SYSOB relative pointer to Device Linkage Table|  ODLTP
  +-----------------------------------------------+
 5| SYSOB relative pntr to Interrupt Linkage Table|  OILTP
  +-----------------------------------------------+
 6|RW|RU|SH|  |DC|PF|                              |  DSAVE
  +-----------------------------------------------+
 7| Hardware error status.  Set when the driver   |  DSERR
  | detects an error.  Whenever <>0, the driver   |
  | monitor logs an I/O error and clears this word|
  +--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+
%10| Bit 0 is set at completion of timer           |  DTIME
  +--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+
%11| Interrupt status for this unit.  Set by the   |  DSTRT
  | driver each time it processes an interrupt.   |
  +-----------------------------------------------+
%12| IOT \//////////////////|   Physical unit #    |
  |-----------------------------------------------|
%13| Holds the time out request entry index while  |  ORQST
  | a timer is active.                            |
  +-----------------------------------------------+
%14| Error log. Contains 5 valid bytes of status   |  OLOGERROR
  +-----------------------------------------------+
```

DFLAG - Flags and request state
- RC ACTIVE - A monitor is currently servicing this device.
- RQ REQUEST - A service request is pending while the monitor is active.
- MU MUNIT - This device is on a multi-unit controller.
- IO IOPROG - An I/O Channel Program is running for this device.
- IR IRK - An interrupt or response has occurred for this device.
- NO NOTRDY - Go to state %10 after Idle Channel Program is started.
- ST STWAIT - The device monitor is starting an Idle Channel Program for this device. There is no IOQ associated with this type of request.

STATE - State of the device monitor. Specifies the next action to be taken in SIODM in servicing the request:
- 0 - start new request
- 1 - not used
- 2 - call driver initiator procedure
- 3 - call driver completor procedure
- 4 - not used
- 5 - process request completed
- 6 - initiate device recognition sequence
- 7 - start operator intervention wait
- %10 - wait for interrupt (operator intervention) restart at state 0
- %11 - wait for data segment freeze, then state 2
- %12 - wait for driver initiator to be frozen, then allocate controller (state 2)
- %13 - wait for I/O completion interrupt, then state 3
- %14 - wait for controller, then call driver initiator
- %15 - not used
- %16 - wait for initiator make present, then state 2
- %17 - wait for completor make present, then state 3

OSAVE - Device processing flags
- RW RWBIT - Indicates tape has been rewound.
- RU RWUNLD - Indicates that a rewind/unload was performed to allow a write-ring mount.
- SH SHORT - A short read is in progress. After completion of read, EOF is checked for and if not present, the requested bytes are transferred from the short-read buffer to the user's buffer.
- DC DSFLAG - Transfer used data chaining - used for computing the transmission log.
- PF POWER - Device power up indication.

OSTRT - Mag tape controller status

BITS	USE
0	END OF FILE (EOF)
1	BEGINNING OF TAPE (BOT) / LOAD POINT (LP)
2	END OF TAPE (EOT)
3	SINGLE TRACK ERROR (NOT LOGGED FOR REROS)
4	COMMAND REJECT (REJECT)
5	FILE PROTECT (NOT WRITE ENABLED; NO WRITE RING)
6	MULTIPLE TRACK ERROR (MTE)
7	UNIT ONLINE
8	GCR (6250 BPI DENSITY)
9	UNIT NUMBER (MSB)
10	UNIT NUMBER (LSB)
11	TIMING ERROR
12	TAPE RUNAWAY
13	REWINDING *
14	UNIT BUSY ** (REPORTED AS UNIT NOT READY)
15	INTERFACE BUSY *

Card Reader DIT



DSTAT bits:

BIT0=SID OK
BIT1=0
BIT2=INT PENDING
BIT3=TIMING ERROR
BIT4=LIGHT DARK CHECK
BITS 5-6 = 00 COLUMN BINARY MODE
01 UNUSED
10 PACKED BINARY MODE
11 HOLLERITH-TO-ASCII MODE
BIT7=COMPARE ERROR
BIT8=EOF DETECTED
BITS 9-10 = 00 NORMAL
01 HOPPER EMPTY
10 UNUSED
11 STACKER FULL
BIT11=INVALID HOLLERITH
BIT12=PICK FAIL OR MOTOR CHECK
BIT13=TEST
BIT14=TROUBLE
BIT15=NOT READY

Card Reader DIT Field Definitions

DFLAG - Flags and device state

ACTIVE Monitor is currently active servicing this device.

REQUEST Service for this device was requested while the monitor was active.

IOPROG SIO program in progress.

IAK Interrupt occurred or request aborted or preempted.

READDONE Previous read resulted in an EOF with a backup save requested. The data has been saved in an auxiliary buffer and will be passed back on the next read request.

NRMESSAGE Set when a not ready message has been issued, and cleared when the reader is found ready. Used to prevent multiple Not Ready messages when power is turned on.

MSTATE Monitor State. See SIODM specifications for details.

DLINK - SYSDB relative pointer to the DIT for the next device requesting service for this resource.

DIODP - SYSDB relative pointer to the first IDD element in the request list for this device.

DLDEV - Logical device number and unit number.

UNIT Unit number of device.

LDEVN Logical device number.

DDLTP - SYSDB relative pointer to driver linkage table (DLT).

DSTAT - Device interrupt status. Contains the device interrupt status at the last interrupt. See hardware ERS for details.
DSERR - Device interrupt error status. If not zero, then holds the device interrupt status from an operation with an erroneous completion status. Causes SIODM to log an error.

DWCNT - Holds the requested transfer count in words.

Device Information Table for HP-IB Card Reader

There is one DIT per physical device. If a physical device represents more than one logical device, the logical device number is obtained from the IDD element. The following diagram shows the DIT used for the card reader driver.



DFLAG - Flags and request state
AC ACTIVE - A monitor is currently servicing this device.
RD REQUEST - A service request is pending while the monitor is active.
MU MUNIT - This device is on a multi-unit controller.
ID IDPROG - An I/O Channel Program is running for this device.
IA IAK - An interrupt or response has occurred for this device.
ND NOTRDY - Go to state X10 after Idle Channel Program is started.
ST STWAIT - The device monitor is starting an Idle Channel Program for this device. There is no IDD associated with this type of request.

STATE - State of the device monitor. Specifies the next action to be taken in SIODM in servicing the request:
0 - start new request
1 - not used
2 - call driver initiator procedure
3 - call driver completor procedure
4 - not used
5 - process request completed
6 - initiate device recognition sequence
7 - start operator intervention wait
X10 - wait for interrupt (operator intervention) restart at state 0
X11 - wait for data segment freeze, then state 2
X12 - wait for driver initiator to be frozen, then allocate controller (state 2)
X13 - wait for I/O completion interrupt, then state 3
X14 - wait for controller, then call driver initiator
X15 - not used
X16 - wait for initiator make present, then state 2
X17 - wait for completor make present, then state 3

DLDEV - Device logical device number
IDT I/O TYPE - I/O System type
0 = Series II / III I/O system
1 = HP-IB Systems
2 = unused
3 = unused

DSAVE - Device processing flags
RD READDONE - A card has already been read.
AF ABORTFLAG - A device clear has already been sent for this series of aborted IDDs.

2608 Line Printer DIT (NP-IB Systems)

There is one DIT per physical device. If a physical device represents more than one logical device, the logical device number is obtained from the IOQ element (however, there is only one device per 2608 controller.) The following diagram shows the DIT used for the 2608 line printer driver.

```
    0  1  2  3  4  5  6  7  8  9 10 11 12 13 14 15   MNEMONIC
  +--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+
 0| 0| 0|RC|RQ| 0| 0| 0|ID|IR|ND|ST| 0|   STATE   |   DFLAG
  +--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+
 1| SYSDB relative pointer to the DIT for the next|   DLINK
  | device requesting this resource or service    |
  +-----------------------------------------------+
 2| IOQ table relative index to the first IOQ in  |   DIOQP
  | request list for this device                  |
  +--------+--------------+-----------------------+
 3|                Logical device number           |   DLDEV
  +--------+--------------+-----------------------+
 4| SYSDB relative pointer to Device Linkage Table|   DDLTP
  +-----------------------------------------------+
 5| SYSDB relative pntr to Interrupt Linkage Table|   DILTP
  +-----------------------------------------------+
 6|VM|     |    TRB    |                  |PS|FL|TP|   DSAVE
  +-----------------------------------------------+
 7| Hardware error pointer. Set when the driver   |   DSERR
  | detects an error.  Whenever <>0, the driver   |
  | monitor logs an I/O error and clears this word|
  +------+----------+----------------+--+--+--+--+
%10| Bit 0 is set at completion of timer           |   DTIME
  +------+----------+----------------+--+--+--+--+
%11| Holds the time out request entry index while  |   DRQST
  | a timer is active.                            |
  +-----------------------------------------------+
%12| IOT |//////////////////\     Physical Unit #   |   DUNIT
  +-----------------------------------------------+
%13|          Hardware logged error status         | DLOGERRDR
  +-----------------------------------------------+
```

DFLAG - Flags and request state
- RC ACTIVE - R monitor is currently servicing this device.
- RQ REQUEST - R service request is pending while the monitor is active.
- ID IOPROG - Rn I/O Channel Program is running for this device.
- IR IRK - Rn interrupt or response has occurred for this device.
- ND NOTRDY - Go to state %10 after Idle Channel Program is started.
- ST STWRIT - The device monitor is starting an Idle Channel Program for this device. There is no IOQ associated with this type of request.

STATE - State of the device monitor. Specifies the next action to be taken in SIODM in servicing the request:
- 0 - start new request
- 1 - not used
- 2 - call driver initiator procedure
- 3 - call driver completor procedure
- 4 - not used
- 5 - process request completed
- 6 - initiate device recognition sequence
- 7 - start operator intervention wait
- %10 - wait for interrupt (operator intervention) restart at state 0
- %11 - wait for data segment freeze, then state 2
- %12 - wait for driver initiator to be frozen, then allocate controller (state 2)
- %13 - wait for I/O completion interrupt, then state 3
- %14 - wait for controller, then call driver initiator
- %15 - not used
- %16 - wait for initiator make present, then state 2
- %17 - wait for completor make present, then state 3

DLDEV - I/O system type, unit and logical device number
IDT I/O TYPE- Type of I/O system
- 0 - HP3000 Series II/III
- 1 - NP3000 NP-IB Systems
- 2 - unused
- 3 - unused

DSAVE - Device processing flags
- VM VFCMOD - VFC has been modified.
- TRB TABDFRULT - System tab default.
- PS PRESPRCE - Last request used prespacing.
- FL FULL - Line printer buffer is full.
- TP TOP - Printer is at top of form

2608 Line Printer Status

BYTE 1 & BYTE 2:

BITS	USE
0	ON LINE
1	NOT READY
2	VFC CHANNEL 9 (BOTTOM OF FORM)
3	VFC CHANNEL 12 (TOP OF FORM)
4	VFC INITIRLIZED
5	6/8 LINES PER INCH
6	(NOT USED)
7	POWER RESTORED/UNIT RESET
8	ON LINE
9	PRINT MECH ERROR
10	SELF TEST FRILURE
11	PAPER ERROR
12	SELF TEST MODE
13	6/8 LPI
14	PLATEN/RIBBON ERROR
15	(NOT USED)

BYTE 3: PRINT MODE
BITS 0-7 MODE NUMBER
BYTE 4: PRIMARY/SECONDRRY
BITS 0-3 SECONDARY CHRRRCTER SET CODE
BITS 4-7 PRIMRRY CHRRRCTER SET CODE
BYTE 5: SELF TEST
BITS 0 PRSS FAIL
BITS 1-7 SUBTEST NUMBER
BYTE 6: 6 LPI DOT ROW COUNT
BYTE 7: 6 LPI FORM LINE NUMBER
BYTE 8: 6 LPI FORM LENGTH IN LINES
BYTE 9: 8 LPI DOT ROW COUNT
BYTE 10: 8 LPI FORM LINE NUMBER
BYTE 11: 8 LPI FORM LENGTH IN LINES
BYTE 12: FIRMWARE IDENTIFICRTION CODE
BYTE 20: POWER-UP LRNGUAGE
BITS 0-3 SECONDORRY CHRRRCTER SET CODE
BITS 4-7 PRIMARY CHRRRCTER SET CODE

HP 2619R or 2613 Line Printer DIT (NP-IB Systems)

There is one DIT per physical device. If a physical device represents more than one logical device, the logical device number is obtained from the IOQ element (however, there is only one device per 2631 controller.) The following diagram shows the DIT used for the 2631 line printer driver.

```
    0  1  2  3  4  5  6  7  8  9 10 11 12 13 14 15   MNEMONIC
  +--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+
 0| 0| 0|RC|RQ| 0| 0| 0|IO|IR|NO|ST| 0|   STATE   |   DFLAG
  +--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+
 1| SYSDB relative pointer to the DIT for the next|   DLINK
  | device requesting this resource or service    |
  +-----------------------------------------------+
 2| IOQ table relative index to the first IOQ in  |   DIOQP
  | request list for this device                  |
  +-----+----------------+-----------------------+
 3|           Logical device number                |   DLDEV
  +-----+----------------+-----------------------+
 4| SYSDB relative pointer to Device Linkage Table|   DDLTP
  +-----------------------------------------------+
 5| SYSDB relative pntr to Interrupt Linkage Table|   DILTP
  +-----------------------------------------------+
 6|                                |BJ|AB|PS|FL|TP|   DSAVE
  +-----------------------------------------------+
 7| Hardware error status.  Set when the driver   |   DSERR
  | detects an error.  Whenever <>0, the driver   |
  | monitor logs an I/O error and clears this word|
  +-----------------------------------------------+
%10| Bit 0 is set at completion of timer           |   DTIME
  +-----------------------------------------------+
%11| Holds the time out request entry index while  |   DRQST
  | a timer is active.                            |
  +-----------------------------------------------+
%12| IOT |//////////////////|     Physical unit #   |   DUNIT
  +-----------------------------------------------+
%13|          Hardware logged error status         | DLOGERRDR
  +-----------------------------------------------+
```

DFLAG - Flags and request state
- RC ACTIVE - R monitor is currently servicing this device.
- RQ REQUEST - R service request is pending while the monitor is active.
- IO IOPROG - Rn I/O Channel Program is running for this device.
- IR IRK - Rn interrupt or response has occurred for this device.
- NO NOTRDY - Go to state %10 after Idle Channel Program is started.
- ST STWRIT - The device monitor is starting an Idle Channel Program for this device. There is no IOQ associated with this type of request.

```
STRTE       - State of the device monitor.  Specifies the next action
              to be taken in SIODM in servicing the request:
                0 - start new request
                1 - not used
                2 - call driver initiator procedure
                3 - call driver completor procedure
                4 - not used
                5 - process request completed
                6 - initiate device recognition sequence
                7 - start operator intervention wait
              %10 - wait for interrupt (operator intervention)
                    restart at state 0
              %11 - wait for data segment freeze, then state 2
              %12 - wait for driver initiator to be frozen, then
                    allocate controller (state 2)
              %13 - wait for I/O completion interrupt, then state 3
              %14 - wait for controller, then call driver initiator
              %15 - not used
              %16 - wait for initiator make present, then state 2
              %17 - wait for completor make present, then state 3

OLDEV - I/O system type, unit and logical device number
  IOT I/O TYPE - Type of I/O system
            0 - HP3000 Series 2/3
            1 - HP3000 HP-IB Systems
            2 - Unused
            3 - Unused

DSRVE - Device processing flags
  BJ   BETJOB     - Between jobs flag. If set, suppress
                    Powerfail message.
  RB   ABORT      - Rbort (caused by Powerfail or Operator)
                    has occurred.
  PS   PRESPACE   - Last request used prespacing.
  FL   FULL       - Line printer buffer is full.
  TP   TOP        - Printer is at top of form
```


HP 2680R/2688R DIT




```
DFLAG - DEVICE RELATIVE FLAGS.
        AC          ACTIVE BIT. 1 IMPLIES A MONITOR CURRENTLY
                    SERVICING THIS DEVICE.
        RQ          REQUEST BIT. 1 IMPLIES SERVICE REQUESTED
                    WHILE MONITOR IS ACTIVE.
        SP          SID PREEMPTION. IF SET THEN A PREEMPTIVE
                    REQUEST HAS BEEN QUEUED FOR THIS DEVICE.
                    PREEMPT CODE IS SET IN IOQ ELEMENT.
        CP          CHANNEL PROGRAM IN PROGRESS. IF SET, THEN
                    A CHANNEL PROGRAM IS CURRENTLY EXECUTING.
        IR          IF SET, AN INTERRUPT OR RESPONSE HAS OCCURRED.
```



```
        NR          IF SET, DEVICE IS IN A NOT READY OR OPERATOR WAIT.
        SW          IF SET, AN IOLE CHANNEL PROGRAM SHOULD BE STARTED
                    FOR THIS DEVICE.
        MSTRTE      CURRENT DRIVER STATE AS DEFINED BY THE MONITOR.
                    ALLOWABLE STATES ARE:
                    0  - START REQUEST
                    1  - NOT USED(BUT RESERVED)
                    2  - CALL DRIVER INITIATOR
                    3  - CALL DRIVER COMPLETOR
                    4  - UNUSED(BUT RESERVED)
                    5  - COMPLETE REQUEST..PERHAPS RETURN TO USER.
                    6  - UNEXPECTED INTERRUPT OCCURRED.
                    7  - START OPERATOR INTERVENTION WAIT.
                   %10 - WAITING (ON OPERATOR). RESTART AT 0.
                    11 - WAITING (DATA MAKEPRESENT/FREEZING)
                    12 - WAITING (INITIATOR CODE MAKEPRESENT/FREEZE)
                    13 - WAITING (FOR COMPLETION INTERRUPT)
                    14 - WAITING (FOR DEVICE CONTROLLER AVAILABILITY)
                    15 - UNUSED(BUT RESERVED)
                    16 - WAITING (INITIATOR CODE MAKEPRESENT)
                    17 - WAITING (COMPLETOR CODE MAKEPRESENT)

DLDEV - I/O SYSTEM TYPE, UNIT AND LOGICAL DEVICE NUMBER.
      IOT       I/O SYSTEM TYPE.
                0 - HP3000 SERIES II/III (SIO/OIO)
                1 - HP-IB Systems
                2 - RESERVED
                3 - RESERVED

DCBCNT - CURRENT BYTE COUNT TO BE TRANSFERRED.

DCWCNT - CURRENT WORD COUNT TO BE TRANSFERRED.

DRCNT  - REMAINING WORD COUNT TO TRANSFER.

DOFFSET - OFFSET IN BUFFER OF NEXT N WORDS TO TRANSFER.

DDEBUG  - IF BIT 15=1 THEN DEBUGGING INFO WILL BE SENT TO CONSOLE

DLOGBUFFER - STATUS WORDS 1 & 3 ARE MOVED HERE TO BE LOGGED
             IF THEY WERE LOGGED FROM THE I/O STATUS BLOCK
             THEIR CONTENTS MIGHT BE CHANGED BEFORE THEY
             WERE LOGGED.

DIOSTRT - I/O STATUS AREA 16 WORDS, SEE I/O STATUS BLOCK DEFINITION.
```


I/O Status Block




```
WORD 0 - EACH BIT IS THE 'OR' OF ONE WORD IN THE TABLE (EXCEPT
         BIT 0 WHICH IS NOT USED).  THEREFORE, BIT .(1:1) IS SET
         IF WORD 1 IN THE TABLE IS NON-ZERO.

WORD 1 - BIT= 0 - (OF)  OFFLINE/OFFLINE BIT.
              1 - (MS)  MESSAGE BEING DISPLAYED ON THE 2680R/2688R CONSOLE.
              2 - (PW)  POWER UP COMPLETED SINCE LAST I/O STATUS READ.
              3 - (PE)  PARITY ERROR DETECTED ON PNI COMMAND.
              4 - (TE)  TRANSMISSION ERROR DETECTED IN THE PRINTER.
            5/15 -      RESERVED.  UNUSED.

WORD 2 - NOT USED. RESERVED.

WORD 3 - MCS FAULT NUMBER.  CONTAINS AN INTEGER DESCRIBING THE LAST
         FAULT TO OCCUR SINCE THE LAST TIME THE I/O STATUS WAS READ
         OR THE HP 2680R/2688R WAS POWERED DOWN.  IF THE WORD IS ZERO THERE
```

IS HO MCS FAULT. SEE OCS ERS FOR A DESCRIPTION OF THE MCS FAULT HUMBERS.

WORO 4 - BIT= D - (CL) HO ROOM FOR ATTEMPTEO CHARACTER SET LOAO.
1 - (FL) NO ROOM FOR ATTEMPTEO FORM LOAO.
2 - (VL) HO ROOM FOR ATTEMPTEO VFC LOAO.
3 - (CU) ATTEMPT TO PRINT OATA AHO THERE IS NO CURREHTLY SELECTED CHARACTER SET.
4 - (FU) ATTEMPT TO SELECT AN UNOEFINED FORM SET.
5 - (VU) ATTEMPT TO PRINT OATA ANO THERE IS NO CURREHTLY SELECTED VFC SET.
6 - (IL) ATTEMPT TO PRINT OATA AHO TWERE IS NO CURRENTLY SELECTEO LOGICRL PAGE TABLE (LPT) ENTAY.
7 - (IP) ATTEMPT TO MOVE PEH OFF THE LOGICAL PAGE.
8 - (ST) THE 2680R/2683A COULO NOT PROCESS ALL OF THE OATR BEFORE IT WAS SUPPOSEO TO BE TRANSFERRED TO THE ORUM/PAPER. ORTA WAS LOST!
9 - (SB) SPOOLER BLOCK CONTAINS FORMAT ERROR.
10 - (IR) INVALID RECOVERY BLOCK RECEIVED FROM SPOOLER.
11 - (MP) MRXIMUM NUMBER OF COPIES PER PHYSICRL PAGE HAS BEEN EXCEEOED. THIS IS A RESULT OF THE SPOOLER PROCESS SETTING THE MAXIMUM COPIES PER PAGE WITH FUNCTION CODE 132.
12 - (NJ) A COMMAND OR FUHCTIOH CODE WAS RECEIVED WHEN NO "JOB" WAS IN PROGRESS. THE COMMAND OR FUNCTION WAS IGNORED BY THE OCS.
13 - (NM) NO MEMORY. 2680A/2683R OYNRMIC MEMORY ALLOCATION HAS OETECTEO TNAT MAIN MEMORY IS COMPLETELY OCCUPIEO WITH CHARACTER SETS, VFC'S, FORMS AND OATA SUCH TNAT THE 2680A/2688A CAHHOT PROCESS THE CURRENT INPUT OATA. OATA WILL BE LOST!
14 - (TL) ATTEMPT TO PRINT OATA AND THERE ARE MORE THAN THE MAXIMUM RLLOWRBLE LOGICAL PRGE TRBLE (LPT) EHTRIES SELECTED.
15 - (NC) A NON-EXISTEHT VFC CHANNEL WRS SKIPPED TO.

WORO 5 - BIT= D - (LP) LOGICAL PAGE TRUNCATED TO FIT PHYSICAL PAGE.
1 - (PF) PRGE SIZE REQUIRED BY PROGRMMER OID NOT MATCH PRGE SIZE SET BY OPERRTOR. OPERRTOR PRGE SIZE PREVAILS.
2 - (NC) NO CHRRACTER SET SELECTEO.

WORDS 6/11 NOT USEO BUT RESERVEO FOR FUTURE USE.

WORDS 12/13 - THE RECORO NUMBER WHICH COHTAIHS THE OFFENOIHG ERROR AS OEFIHED BY WORO FOUR. IF A POWER FAIL OCCURS OURING A "JOB", THE POWER FAIL BIT IS SET AHO A SHEET HUMBER IS MADE AVRILABLE IN WORDS FOURTEEN AND FIFTEEN. HOWEVER, THE RECORO HUMBER IS LOST AHO CANNOT BE REPORTEO. THESE WORDS OCCUR IH A "JOB" ONLY.

WORDS 14/15 - THE SHEET HUMBER OH WHICH THE ERROR OCCURRED AS OEFINEO BY WORO FOUR. IF AN ERROR OCCURS IN THE ENVIRONMENT FILE AT THE STRRT OF A "JOB", TNEN TNIS NUMBER WILL BE ZERO.

IH AOOITIOH, WHEH A POWER FRIL OCCURS OURIHG R "JOB", THE POWER ON BIT IS SET IN WORO ONE AND THE SHEET HUMBER OF THE LAST SUCCESSFULLY TRANSFERRED PRGE IS PLACEO HERE. TNIS INFORMATION IS FOR USE BY THE SPOOLER SHOULO A RECOVERY OF A "JOB" BE OETERMINED. THESE WORDS OCCUR IH "JOB" ONLY.

ALL WORDS OF THE I/O STATUS ARE CLEARED WHENEVER THE STATUS BLOCK IS RETURHEO TO THE HOST. IT IS UP TO THE HOST CPU TO RETAIN ANY ONGOING STATUS BITS REQUIRED.

QMISC -

	0	1	2	3	4	5	6	7	8	9	10	11	12	13	14	15
IOO3	!MB	!RB	!AB	!IO	!TO	!		XFER		!	PARITY		!	!		OMISC

WHERE:

.(0:1) - MB USER REQUESTED TRANSFER IN EXCESS OF 4096 WORDS. THE DRIVER CAN WRITE UP TO 4096 WORDS TO THE 2680A/2688A. IN ORDER TO HANDLE UP TO 32K WORDS, MULTIPLE WRITES ARE USED WITHOUT R RETURN TO THE USER WHO CRLLEO THE ORIVER. THIS BIT IHOICATES THAT MULTIPLE WRITES ARE BEING DONE TO THE 2680A/2688A.

.(1:1) - RB THE CURRENT WRITE BLOCK MUST BE RETRIED.

.(2:1) - AB USER REQUESTED RBORT IN PROGRESS FLAG.

.(3:1) - IO I/O STATUS HRS BEEN READ AHO IS AVAILABLE.

.(4:1) - TO GENERAL I/O CONTROLLER TIMED OUT.

.(5:4) - RESERVED NOT CURRENTLY USEO.

.(9:3) - XFER 2680A/268BR TRRNSFER ERROR COUNTER.

.(12:3)- PARITY CHANNEL PROGRAM COMMAHO PARITY ERROR COUNTER.

.(15:1)- RESERVEO HOT CURREHTLY USEO.

NOTE IN THE ABOVE, SINGLE BIT FIELOS ARE AS OEFINEO WHEN THE BIT IS A LOGIC "1".

Disc Request Table and Disc Requests

Requests for disc transfers are effected by acquiring an entry from the Disc Request Table (OISCREQTAB), filling the proper information, and calling the OISCOMANRGER to link the request into the device's doubly linked request qu queue.
The head and tail of a device's request queue are contained in the devices' OIT.

DISCREQTAB



Disc Request Table

DISCREQTAB OST ENTRY# = 56 (X70)
DISCREQTAB PRT = X1017

Disc Request Table Entry O Format

	O 1 2 3 4 5 6 7 8 9 10 11 12 13 14 15	
DISCREQTAB00	TOTAL ENTRIES	
DISCREQTAB01	ENTRY SIZE (X21)	
DISCREOTAB02	PRIMARY ENTRIES	
DISCREQTAB03	IMPEDEO PROCESS PCB	
DISCREQTAB04	TABLE INOEX OF HEAD OF AVAILABLE ENTRY LIST	
DISCREQTAB05	TABLE IHDEX OF TAIL OF AVAILABLE EHTRY LIST	
DISCREQTAB06	MAX ENTRIES IN USE	
DISCREQTAB07	CURREHT ENTRIES IN USE	
DISCREQTAB08	OVERFLOWS	
DISCREQTAB09	TOTAL REOUESTS	
DISCREQTAB10		
DISCREOTAB11	SYSBASE INDEX OF HEAO OF DISABLED REO O	DISCQHEAD
DISCREOTAB12	SYSBASE INDEX OF TAIL OF DISABLED REO Q	DISCQTAIL
DISCREQTAB13	SERIAL WRITE OUEUE HEAD	SERWQHEAD
DISCREOTAB14	A |//////////////////|MAX. SERIAL WRITE OUEUE	A = Active
DISCREOTAB15	//	
DISCREQTAB16	//	

Disc Request Element Format



Note: Upon return to free list, word (N1) becomes index of next EE free entry.

Word 0 - QFLAG - Request dependent flags

Bit 0	.ABORT	Requeet has been aborted externally.
Bit 1	.MMREQ	Request is for a eegment tranefer.
Bit 2	.DIRG	Oiagnostic request (not used).
Bit 3	.SBUf	Systen Buffer. Target is a eystem buffer whose index is relative to the etart of the SBUF table.
Bit 4	.IOWRKE	Wake caller on completion of requeet.
Bit 5	.BLOCKED	Blocked I/O. Caller ie waited in RTTACNIO until requeet ie completed.
Bit 6	.COMPLETEO	Requeet hae been completed and caller woken if he had epecified.
Bit 7	.DATAFRZH	Data eegnent hae been nade preeent and ie frozen.
Bit 8	.MAMERRORO	MAM error on data eegnent nake preeent.
Bit 9	.PREOQUEUED	Requeet ie queued into diec'e req queue
Bit 10	.SfRIL	Start SIO failure in GIP.
Bit 11	.PFRIL	The I/O has been aborted because of a powerfail.
Bit 12	.CURREO	Requeet ie device'e current request.
Bit 13	.DISABLED	Requeet ie dieabled.
Bit 14	.LDR	Requeet in local ORQ.
Bit 15	.INLOCRL	Buffer OST ie in procese locality.

Word 2 - QLDEV.OLDEVN - Logical Device Nunber
Word 3 - QMISC - Device dependent.

Word 4
QDSTN - If SYSBUFRs ie clear then thie ie the DST nunber of the target data eegnent. If bit 0 ie eet then buffer addreee ie a DB offeet value inetead of eegnent relative offeet (inplenented for NOWAIT IO and NOBUff).
Word 5
QRDDR - Offeet in data eegnent or sys buff table to target data buffer.
Word 6
OFUNC.FUNC - Function code and quallfiers ae epecified by driver.

Word 7
QXFERCNT-On initiation epecifiee the word count if poeitive or byte count if negative. Rt completion of the requeet thie location containe the actual transnieeion count in the eame unite ae the call. Certain control requeste return data through thie location.
Word 8
QPRR1 - Paraneter one, defined by driver
Word 9
QPAR2 - Paraneter two, defined by driver
QMISC - Miecellaneoue requeet dependent etorage available to driver.
Word 10
QSTRT.PCBN - PCB Number of proceee which nade thie request. Zero if not aseociated with any proceee and IOO ie to be returned by the eyeten.
.QURLIFIER - R code which further defiee or qualifiee the general etatus. Defined by driver.
.STRTUS - General Status. Indicates current and reeult etate of the requeet according to the following codes.
0 - not etarted or awaiting completion.
1 - succeseful completion.
2 - end of file detected.
3 - unusual condition.
4 - irrecoverable error.

NOTE: See I/O Syeten Status Returne.

Word 11 - bit 0=1 Q elenent ie on free liet.

IOQ Table Layout



IOQ (Cont.)



I/O Queue Element (IOQ)



QFLAG - Request dependent flags

Bit 0	.ABORT	Request has been aborted externally.
Bit 1	.SPECIAL	Special handling is to be applied to this request. For disc, indicates a memory management request.
Bit 2	.DIAG	Diagnostic request (not used).
Bit 3	.SBUF	System Buffer. Target is a system buffer whose index is relative to the start of the SBUF table.
Bit 4	.IOWAKE	Wake caller on completion of request.
Bit 5	.BLOCKED	Blocked I/O. Caller is waited in ATTACHIO until request is completed.
Bit 6	.COMPLETED	Request has been completed and caller woken if he had specified.

I/O Queue Element (Cont.)

Bit 7	.DATAFAZN	Data segment has been made present and is frozen.
Bit 8	.MAMERAORD	MAM error on data segment make present.
Bit 9	.PREQ	This request has been started but was preempted by a MAM request.
Bit 10	.SFAIL	Start SIO failure in GIP.
Bit 11	.PFAIL	The I/O has been aborted because of a powerfail.
Bits12-13	.PREEMPT	Preemptive type code: 1-soft, 2-hard.
Bit 15	.MSGDONE	A message request reply has completed.

QLINK - Table relative index of next IOQ element. Points to first word of element.
QLDEV - Logical Device Number
QMISC - Device dependent.

QDSTN - If SYSBUFAs is clear then this is the OST number of the target data segment. If bit 0 is set then buffer address is a DB offset value instead of segment relative offset (implemented for NOWAIT IO and NOBUFF).
QADDR - Offset in data segment or sys buff table to target data buffer.
QFUNC.FUNC - Function code and qualifiers as specified by driver.
QWBCT - On initiation specifies the word count if positive or byte count if negative. At completion of the request this location contains the actual transmission count in the same units as the call. Certain control requests return data through this location.
QPAR1 - Parameter one, defined by driver
QPAR2 - Parameter two, defined by driver
QMISC - Miscellaneous request dependent storage available to driver.
QPCBN - PCB Number of process which made this request. Zero if not associated with any process and IOQ is to be returned by the system.
.QUALIFIER - A code which further defies or qualifies the general status. Defined by driver.
.STATUS - General Status. Indicates current and result state of the request according to the following codes.
0 - not started or awaiting completion.
1 - successful completion.
2 - end of file detected.
3 - unusual condition.
4 - irrecoverable error.

Word 11 bit 0- Queue element is on free list.

I/O System Status Returns

	STATUS %
0 - PENDING	
1 - WAITING FOR COMPLETION	10
2 - DOING ERROR RECOVERY	20
3 - NOT READY WAIT	30
4 - NO WRITE RING WAIT	40
5 - NEW PAPER TAPE WAIT	50
1 - SUCCESSFUL	
0 - NORMAL	1
1 - READ TERMINATED WITH SPECIAL CHARACTER	11
2 - TAPE RETRY FOR SUCCESS REQUIRED	21
3 - LOW TAPE OR END OF TAPE AFTER WRITE	31
2 - END OF FILE	
1 - PHYSICAL END OF FILE	12
2 - DATA	22
3 - END OF DATA	32
4 - HELLO	42
5 - BYE	52
6 - JOB	62
7 - END OF JOB	72
3 - UNUSUAL CONDITION	
1 - TERMINAL PARITY ERROR	13
2 - TERMINAL READ TIMED OUT	23
3 - I/O ABORTED EXTERNALLY	33
4 - DATA LOST	43
5 - DATA SET NOT READY OR DISCONNECT OR UNIT NOT ON LINE	53
6 - ABORTED BECAUSE OF POWER FAIL	63
7 - BOT AND BSR, BSF REQUEST	73
10 - TAPE RUNAWAY	103
11 - EOT AND WAITE REQUEST	113
12 - NO WRITE RING AFTER REQUEST TO OPERATOR	123
13 - END OF TAPE (PAPER TAPE LOW)	133
14 - PLOTTER LIMIT SWITCH REACHED	143
15 - ENABLE SUBSYSTEM BREAK AND NO CONTROL Y PIN	153
16 - READ TIME RETURNED OVERFLOW	163
17 - BREAK STOPPED READ	173
20 - WAITE AND NO CARD IN WAIT STATION	203
21 - DEVICE POWERED ON - OPERATING ENVIRONMENT LOST	213
27 - VFC HAS BEEN RESET	273

I/O System Status Returns (Cont.)

4 - IRRECOVERABLE ERROR

0 -	INVALID REQUEST	4
1 -	TRANSMISSION ERROR	14
2 -	I/O TIME OUT	24
3 -	TIMING ERROR	34
4 -	SIO FAILURE	44
5 -	UNIT FRILURE	54
6 -	INVALID OISC ADDRESS	64
7 -	TAPE PARITY ERROR	74
11 -	PAPER TAPE TAPE ERROR	114
12 -	SYSTEM ERROR	124
13 -	INVALIQ SBUF INDEX	134
14 -	CHANNEL FAILURE, TIMEOUT OR NO RESPONSE FROM CONTROLLER	144
15 -	UNINITIALIZED MEDIA (LINUS)	154
16 -	NO SPARE BLOCKS AVAILABLE	164
17 -	DELETED RECORD DETECTED ON IBM FLOPPY OISC	174
20 -	LABELED DEVICE UNAVAILABLE AFTER REELSWITCH	204
21 -	PARITY ERRQR DETECTED ON PNI COMMAND (EPOC)	214

5 - ERROR IN DATA CONTROL INFORMATION

		XLOG	
0 -	INVALID ITEM NUMBER	5	
1 -	INVALID ACCESS FOR ITEM	15	VALID RCCESS
2 -	FAILURE IN FOPEN OR FREAD	25	FS ERROR NUMBER
3 -	PARITY CHANGE IN 8 BIT MODE	35	
4 -	INVALID INFO. FILE FORMAT	45	
5 -	CHECKSUM ERROR IN INFO FILE	55	
6 -	PASSED VALUE LESS THAN MIN.	65	MIN.VALUE ALLOWED
7 -	PASSED VALUE GREATER THAN MAX.	75	MAX.VALUE ALLOWED
10 -	PASSED VALUE IS UNSUPPORTED	105	
11 -	COUNT LESS THAN REQUIRED TO RETURN ALL INFO.	115	MIN.SPACE NEEDED
12 -	COUNT GREATER THAN AVAILABLE TO STORE INFO.	125	MAX.SPACE AVAIL
13 -	PASSED VALUES NOT IN ASCENDING QRDER	135	OFFSET OF ELEMENT
14 -	PASSED CHARACTER WAS OTHER DEFINED FUNCTION	145	OTHER FUNCTION

I/O Queue Element for 7976A Magnetic Tape



QFLAG - Request dependent flags

Bit 0 ABORT - Rbort this request and return an error indication to the caller.

Bit 1 SPECIAL - Apply special handling to this request. (Not used)
Bit 2 OIAG - This is a request from the diagnostic subsysten. (Not used)
Bit 3 SYSBUFF - Target is an index relative to the SBUF Table of the data buffer.
Bit 4 IOWAKE - Wake caller on completion of request.
Bit 5 BLOCKED - Blocked I/O. The caller is waited in ATTACHIO

until the request is completed. Implies IOWAKE.
Bit 6 COMPLETED - The request has been completed and the caller awakened if he had requested (with IOWRKE).
Bit 7 DATAFRZN - Set by the nenory nanagenent routines (MAN) when a MAKEPRESENT request is successfully completed and indicates the data segnent is frozen in nenory.
Bit 8 MAMERRORD - An error has occurred while MAM was trying to nake the target data segnent present and freeze it in nenory.
Bit 9 PREQ - (Not used)
Bit 10 SFAIL - Delayed failure of SIO instruction. If a call to START'NPIB resulted in the request being added to the channel queue, this bit indicates that the SIO instruction failed when the request was selected for execution.
Bit 11 PFAIL - The request was aborted because of a systen power failure.

QMISC - Driver request dependent flags and counters. Used nostly for error retries.

RETRY - Indicates an error retry is in progress.
BACK - Backspace record processing for an error retry is in progress.
FORWARD - Forward space record processing for an error retry is in progress.
GRP - Gap processing for an error retry is in progress.
BODEOF - Backspace record due to a data EOF processing is in progress.
TQUTCNTR - GIC tined-out counter.
FSCNTR - Forward space record counter.
BSCNTR - Backspace record counter.
RTCNTR - Error retry counter.

QSTAT - PCB nunber and request conpletion status.

PCBN - The Process Control Block (PCB) nunber of the process which nade this request. If zero, the request is not associated with any process and the IOQ elenent is to be returned by the systen when the request has completed.
STATUS - General status indicating the final state of the request. The following codes are used:
0 - Not started or awaiting completion.
1 - Successful completion.
2 - End-of-file detected.
3 - Unusual, but recoverable, condition detected.
4 - Irrecoverable error has occurred.
QUALIFIER - A code which further defines or qualifies the general status. (See the section Driver Return Status Codes.)

I/O Queue Element (IOQ) for CIPER



QFLAG - Request dependent flags

Bit 0 ABORT - Abort this request and return an error indication to the caller.
Bit 1 SPECIAL - Apply special handling to this request. (Not used)
Bit 2 DIAG - This is a request fron the diagnostic subsystem.
Bit 3 SYSBUFF - Target is an index relative to the SBUF Table of the data buffer.
Bit 4 IOWAKE - Wake caller on completion of request.
Bit 5 BLOCKED - Blocked I/O. The caller is waited in ATTACHIO until the request is completed. Implies IOWAKE.
Bit 6 COMPLETED - The request has been completed and the caller awakened if he had requested (with IOWAKE).
Bit 7 DATAFRZN - Set by the Memory Management routines (MAM) when a

MAKEPRESENT request is successfully completed and indicates the data segment is frozen in memory.
Bit 8 MAMERRORD - An error has occurred while MAM was trying to make the target data segment present and freeze it in memory.
Bit 9 PREQ - (Not used)
Bit 10 SFAIL - Delayed failure of SIO instruction. If a call to STARTIO resulted in the request being added to the channel queue, this bit indicates that the SIO instruction failed when the request was selected for execution.
Bit 11 PFAIL - The request was aborted because of a system power failure.

QSTAT - PCB number and request completion status.

PCBN - The Process Control Block (PCB) number of the process which made this request. If zero, the request is not associated with any process and the IOQ element is to be returned by the system when the request has completed.
RSTATUS - General status indicating the final state of the request. The following codes are used:

0 - Not started or awaiting completion.
1 - Successful completion.
2 - End-of-file detected.
3 - Unusual, but recoverable, condition detected.
4 - Irrecoverable error has occurred.

QUALIFIER - A code which further defines or qualifies the general status. (See the section Driver Return Status Codes.)

HP-IB CIPER Physical Driver Request Codes

OPERATION	FUNCTION	PARAMETERS
READ	0	None
WRITE	1	None
FILE OPEN	2	None
FILE CLOSE	3	None
DEVICE CLOSE	4	None
CIPER INIT	184	None

CIPER Driver Return Status Codes

General Status (13:3)	Qualifying Status (8:5)	Overall (8:8)
0 - Pending	1 - Waiting For Completion	%10
	3 - Not Ready Wait	%30
1 - Successful	0 - No Errors	%1
2 - End of File	(Not Used)	
3 - Unusual Condition	3 - Request Aborted	%33
	6 - Powerfail Abort	%63
	%21 - Device Powered Up	%213
4 - Irrecoverable Error	0 - Invalid Request	%4
	1 - Transfer Error	%14
	2 - I/O Timed Out Before Complete	%24
	4 - SIO Failure	%44
	5 - Unit Failure	%54
	%12 - System Error	%124
	%14 - Channel Failure	%144
	%21 - Parity Error	%214

2608 Line Printer I/O Queue Element (HP-IB Systems)





QFLAG - Request dependent flags

Bit 0 ABORT - Abort this request and return an error indication to the caller.
Bit 1 SPECIAL - Apply special handling to this request. (Not used)
Bit 2 OIAG - This is a request from the diagnostic subsystem. (Not used)
Bit 3 SYSBUFF - Target is an index relative to the SBUF Table of the data buffer.
Bit 4 IOWAKE - Wake caller on completion of request.
Bit 5 BLOCKED - Blocked I/O. The caller is waited in ATTACHIO until the request is completed. Implies IOWAKE.
Bit 6 COMPLETED - The request has been completed and the caller awakened if he had requested (with IOWAKE).

Bit 7 DATAFRZN - Set by the memory management routines (MAM) when a MAKEPRESENT request is successfully completed and indicates the data segment is frozen in memory.
Bit 8 MAMERRORD - An error has occurred while MAM was trying to make the target data segment present and freeze it in memory.
Bit 9 PREQ - (Not used)
Bit 10 SFAIL - Delayed failure of SIO instruction. If a call to STARTIO resulted in the request being added to the channel queue, this bit indicates that the SIO instruction failed when the request was selected for execution.
Bit 11 PFAIL - The request was aborted because of a system power failure.

QMISC - Driver request dependent flags and counters.

PRE'TO'POST - Pre to post spacing change flag.
PEJECT - Last operation was a page eject.
MASTERCLR - Master clear done to clear powerfail bit in status. Master clear needs to be done from not ready condition.
TOUTCNTR - Channel time-out retry counter.
WAITCODE - Indicates type of wait:
0 - new request
1 - completion wait
2 - not ready wait

QSTAT - PCB number and request completion status.

PCBN - The Process Control Block (PCB) number of the process which made this request. If zero, the request is not associated with any process and the IOQ element is to be returned by the system when the request has completed.
STATUS - General status indicating the final state of the request. The following codes are used:
0 - Not started or awaiting completion.
1 - Successful completion.
2 - End-of-file detected.
3 - Unusual, but recoverable, condition detected.
4 - Irrecoverable error has occurred.
QUALIFIER - A code which further defines or qualifies the general status. (See the section Driver Return Status Codes.)

2608 Line Printer Request Codes

Operation	Function	Parameters
WRITE	1	P1 - Vertical Format Specification 1 - use 1st data char as format spec %53 - "+", print and suppress spacing %55 - "-", print and triple space %60 - "0", print and double space %61 - "1", print and top of form %200-%277, print and space N-%200 lines %300-%377, print with channel N-%277 All others, print and single space. P2 - Space Mode Flags (15:1) - Prespace flag if set, print then fill buffer if clear, fill buffer then print (14:1) - No page stepover flag if set, single and double space without stepover (66 lines/page) if clear, single and double space with stepover (60 lines/page)
FILE OPEN	2	Page eject if not at top of form
FILE CLOSE	3	Page eject if not at top of form
DEVICE CLOSE	4	Page eject if not at top of form
READ STATUS	%17	Read I/O status Count - buffer must be at least 2 bytes
VFC SET	%100	Load VFC RAM Count - form length in words (0 loads RAM form internal ROM) P1 - 6 for 6 LPI or 8 for 8 LPI any other value defaults to 6 LPI
TRB SET	%101	Sets logical column definition P1 - 0 to 15, any other value defaults to 15

2619A & 2631 Line Printer IOQ Element (NP-IB Systems)



QFLAG - Request dependent flags

Bit 0	ABORT	- Abort this request and return an error indication to the caller.
Bit 1	SPECIRL	- Apply special handling to this request. (Not used)
Bit 2	DIRG	- This is a request from the diagnostic subsystem. (Not used)
Bit 3	SYSBUFF	- Target is an index relative to the SBUF Table of the data buffer.
Bit 4	IOWAKE	- Wake caller on completion of request.
Bit 5	BLOCKED	- Blocked I/O. The caller is waited in RTTRCHID

until the request is completed. Implies IOWAKE.

Bit 6	COMPLETED	- The request has been completed and the caller awakened if he had requested (with IOWAKE).
Bit 7	DATAFAZN	- Set by the memory management routines (MAM) when a MAKEPRESENT request is successfully completed and indicates the data segment is frozen in memory.
Bit 8	MAMERROR	- An error has occurred while MAM was trying to make the target data segment present and freeze it in memory.
Bit 9	PREQ	- (Not used)
Bit 10	SFRIL	- Delayed failure of SIO instruction. If a call to STARTIO resulted in the request being added to the channel queue, this bit indicates that the SIO instruction failed when the request was selected for execution.
Bit 11	PFRIL	- The request was aborted because of a system power failure.

QMISC - Driver request dependent flags and counters for 2631.

PRE'TO'POST	- Pre to post spacing change flag.
PEJECT	- Last operation was a page eject.
TOUTCNTR	- Channel time-out retry counter.
POWERFAIL	- Power fail flag indicates power fail occurred.
WAITCODE	- Indicates type of wait: 0 - new request 1 - completion wait 2 - not ready wait

Format for 2619A



TOUT	- Channel timed out flag
BUF'FILL	- Buffer fill operation in progress

QSTAT - PCB number and request completion status.

PCBN	- The Process Control Block (PCB) number of the process which made this request. If zero, the request is not associated with any process and the IOQ element is to be returned by the system when the request has completed.
STATUS	- General status indicating the final state of the request. The following codes are used: 0 - Not started or awaiting completion. 1 - Successful completion. 2 - End-of-file detected. 3 - Unusual, but recoverable, condition detected. 4 - Irrecoverable error has occurred.
QUALIFIER	- A code which further defines or qualifies the general status. (See the section Driver Return Status Codes.)

2619 Line Printer Request Codes

Operation	Function	Parameters
WRITE	1	P1 - Vertical Format Specification 1 - Use 1st data char as format specification. %53 - "+", print and suppress spacing %55 - "-", print and triple space %60 - "0", print and double space %61 - "1", print and top of form %200-%277, print and space N-%200 lines %300-%312, print with channel N-%277 %320 - Fill Line Printer Buffer Only All others, print and single space. P2 - Space Mode Flags (15:1) - Prespace flag if set, print then fill buffer if clear, fill buffer then print (14:1) - No page stepover flag if set, single and double space without stepover (66 lines/page) if clear, single and double space with stepover (60 lines/page)
FILE OPEN	2	Page eject if not at top of form
FILE CLOSE	3	Page eject if not at top of form
DEVICE CLOSE	4	Page eject if not at top of form
REQ STATUS	%17	Read I/O status Count - buffer size
*IDENTIFY	%110	Return ID value in Bank & Buffaddr
*SELF TEST:		
INITIATE	%111	Subtest number to execute in Bank and Buffaddr (subtest number ranges from 0 to 7)
STATUS	%112	Subtest result returned in Bank & Buffaddr
*LOOPBACK TEST:		
WRT DATA	%113	Data to LP in Bank & Buffaddr [PING]
READ DATA	%114	Data from LP read into Bank & Buffaddr [PONG] Count - Buffer Size (256 bytes max)

2631 Line Printer Request Codes (HP-IB)

Operation	Function	Parameters
WRITE	1	P1 - Vertical Format Specification 1 - Use 1st data char as format specification. %53 - "+", print and suppress spacing %55 - "-", print and triple space %60 - "0", print and double space %61 - "1", print and top of form %200-%277, print and space N-%200 lines %300-%307, print with channel N-%277 %320 - Fill Line Printer Buffer Only All others, print and single space. P2 - Space Mode Flags (15:1) - Prespace flag if set, print then fill buffer if clear, fill buffer then print (14:1) - No page stepover flag if set, single and double space without stepover (66 lines/page) if clear, single and double space with stepover (60 lines/page)
FILE OPEN	2	Page eject if not at top of form
FILE CLOSE	3	Page eject if not at top of form
DEVICE CLOSE	4	Page eject if not at top of form
READ STATUS	%17	Read I/O status Count - 1 byte minimum required
VFC SET	%100	LOROS VFC ARM P1 - 1 - 1 LPI (lines per inch) 2 - 2 LPI 3 - 3 LPI 4 - 4 LPI 5 - 5 LPI 6 - 6 LPI 8 - 8 LPI 12 - 12 LPI Any other value defaults to 6 LPI.

I/O Queue Element For HP-IB Card Reader



QFLPG - Request dependent flags

Bit 0	ABORT	- Abort this request and return an error indication to the caller.
Bit 1	SPECIAL	- Apply special handling to this request. (Not used)
Bit 2	DIAG	- This is a request from the diagnostic subsystem.
Bit 3	SYSBUFF	- Target is an index relative to the SBUF Table of the data buffer.
Bit 4	IOWRKE	- Wake caller on completion of request.
Bit 5	BLOCKED	- Blocked I/O. The caller is waited in ATTACHIO until the request is completed. Implies IOWAKE.

Bit 6	COMPLETED	- The request has been completed and the caller awakened if he had requested (with IOWAKE).
Bit 7	QRTAFRZN	- Set by the memory management routines (MAM) when a MRKEPRESENT request is successfully completed and indicates the data segment is frozen in memory.
Bit 8	MRMERRORQ	- An error has occurred while MRM was trying to make the target data segment present and freeze it in memory.
Bit 9	PAEQ	- (Not used)
Bit 10	SFAIL	- Delayed failure of SIO instruction. If a call to STARTIO resulted in the request being added to the channel queue, this bit indicates that the SIO instruction failed when the request was selected for execution.
Bit 11	PFAIL	- The request was aborted because of a system power failure.

QMISC - Auxiliary buffer flag used to indicated a read into the driver's buffer and not the user's buffer.

QSTRT - PCB number and request completion status.

PCBN	- The Process Control Block (PCB) number of the process which made this request. If zero, the request is not associated with any process and the IOQ element is to be returned by the system when the request has completed.
STRTUS	- General status indicating the final state of the request. The following codes are used: 0 - Not started or awaiting completion. 1 - Successful completion. 2 - End-of-file detected. 3 - Unusual, but recoverable, condition detected. 4 - Irrecoverable error has occurred.
QUALIFIER	- A code which further defines or qualifies the general status. (See the section Driver Return Status Codes.)

CS 80 Disc Request Queue Element (IOQ)



QFLAG - Request dependent flags

Bit 0 ABORT - Request has been aborted externally.
Bit 1 MAREQ - Requast ie for a segment transfer.
Bit 2 OIAG - Thie is a requeet from the diagnostic subsyeten.
Bit 3 SBUF - Target ie an index relative to tha SBUF Table of the data buffer.
Bit 4 IOWAKE - Wake caller on completion of request.
Bit 5 BLOCKED - Blocked I/O. The caller is waited in ATTACNIO until the request is completed. Inplies IOWAKE.
Bit 6 COMPLETED - The request has been completed and the caller awakened if he had requeeted (uith IOWAKE).
Bit 7 DATAFAZN - Data sagment hae baen present and is frozen.
Bit 8 MAMERROR - An error hae occurred while MAM was trying to make the target data eegnent present and freeze it in nemory.
Bit 9 PREQUEUED - Request is queued into disc'a request queue
Bit 10 SFAIL - Delayed failure of SIO instruction. If a call to STARTIO resulted in tha request being added to the channel queue, thie bit indicates that the SIO inetruction failed uhen tha request was selected for execution.
Bit 11 PFAIL - The requeet was aborted because of a aystan power failure.
Bit 12 CURREQ - Request is device'e current requeet.
Bit 13 DISABLEQ - Requeet ie diaabled.
Bit 14 DISATMPT - Attenpt to dieable thie request.
Bit 15 MSGDONE - A naaaage request reply hae completed.

QLDEV.QLDEVN - Logical Devica Nunbar

QMISC - Drivar requast dependent flaga and countere.

CNAN'ERR'FLG - Channel error retry flag.
RSTAT'FAIL'FLG - Requeet etatue failed flag.
OPER'REQ'FLG - Operator requested releaas flag.
IM'FAULT'FLG - Internal naintenanca fault flag.
STAT'RTRY'FLG - Statue error eingle retry flag.
RTAANS'FLG - Retransnit required flag.
LOAD'FLG - Media load flag.
SYS'PFAIL'FLG - Syetem pouarfail flag.

WAITCODE - Indicatee type of wait:

0 - new request
1 - conplation uait
2 - not ready wait
3 - releaee/relaaaa dany wait
4 - IOQ defer wait
5 - OSCT read wait
6 - OSCT urite uait
7 - eynchronization uait

QDSTN - If eyetem buffer ie clear than thie ia the QST number of the target data eegnent. If bit 0 ie aet then buffer addraae ie a OB offaat value inetead of eegnent relative offeet (inplanentad for NOWAIT I/O and NOBUFF).

QADQR - Offaat in data eegnent or eyeten buffer table to target data buffer.

QFUNC - Function coda and qualifiers ae specified by drivar.

QSTAT - PCB nunber and requeat conplation etatua.

PCBN - The Procasa ControI Block (PCB) nunber of tha proceaa which nada thie requeet. If zaro, tha request ie not aeeociated with any proceas and the IOQ elenent is to be returned by the eyeten uhen tha requaat haa completad.

STATUS - General etatue indicating the final etate of tha requaat.

0 - Not started or auaiting completion.
1 - Succeseful completion.
2 - End-of-file detected.
3 - Unusual, but recoverable, condition detected.
4 - Irrecoverable error has occurred.

QUALIFIER - A coda uhich further defineas or qualifies the general statue. (See the eection Driver Return Status Codes.)

CS 80 Integrated Cartridge Tape Request



QFLAG - Request dependent flags

Bit 0 ABORT - Request has been aborted externally.
Bit 1 MMREQ - Request is for a segment transfer.
Bit 2 DIAG - This is a request from the diagnostic subsysten.
Bit 3 SBUF - Target is an index relative to the SBUF Table of the data buffer.
Bit 4 IOWAKE - Wake caller on completion of request.
Bit 5 BLOCKED - Blocked I/O. The caller is waited in ATTRCHIO until the request is completed. Implies IOWRKE.
Bit 6 COMPLETED - The request has been completed and the caller awakened if he had requested (with IOWAKE).
Bit 7 DATAFRZN - Data segment has been present and is frozen.
Bit 8 MMMERRORD - An error has occurred while MMM was trying to make the target data segment present and freeze it in nenory.
Bit 9 PREQUEUED - Request is queued into disc's request queue
Bit 10 SFAIL - Delayed failure of SIO instruction. If a call to STARTIO resulted in the request being added to the channel queue, this bit indicates that the SIO instruction failed when the request was selected for execution.
Bit 11 PFAIL - The request was aborted because of a system power failure.
Bit 12 CURREQ - Request is device's current request.
Bit 13 DISABLED - Request is disabled.
Bit 14 DISATMPT - Attempt to disable this request.
Bit 15 MSGDONE - A message request reply has completed.

QLDEV.QLDEVN - Logical Device Number

QMISC - Driver request dependent flags and counters.

CHRN'ERR'FLG - Channel error retry flag.
RSTAT'FAIL'FLG - Request status failed flag.
OPER'REQ'FLG - Operator requested release flag.
IM'FAULT'FLG - Internal maintenance fault flag.
RETRY'COUNT - Retry count area.
LOAD'FLG - Media load flag.
SYS'PFAIL'FLG - System powerfail flag.

WAITCODE - Indicates type of wait:

0 - new request
1 - completion wait
2 - not ready wait
3 - release/release deny wait
4 - IOQ defer wait
5 - DSCT read wait
6 - DSCT write wait
7 - synchronization wait

QDSTN - If system buffer is clear then this is the DST number of the target data segnent. If bit 0 is set then buffer address is a DB offset value

instead of segment relative offset (inplenented for NOWRIT I/O and NOBUFF).

QRADR - Offset in data segnent or system buffer table to target data buffer.

QFUNC - Function code and qualifiers as specified by driver.

QSTAT - PCB number and request completion status.

PCBN - The Process Control Block (PCB) number of the process which made this request. If zero, the request is not associated with any process and the IOQ element is to be returned by the system when the request has completed.

STATUS - General status indicating the final state of the request.

0 - Not started or awaiting completion.
1 - Successful completion.
2 - End-of-file detected.
3 - Unusual, but recoverable, condition detected.
4 - Irrecoverable error has occurred.

QUALIFIER - A code which further defines or qualifies the general status. (See the section Driver Return Status Codes.)

SBUF Table Layout



3 - 1 - 5 - 4 - 2

Table Element Allocation (SBUF)

The allocation of the elements in the IOQ terminal buffer (TBUF) and system buffer (SBUF) tables is of concern to the I/O system.

FREE LIST OF TABLE ELEMENTS

These tables are in the form of a free-linked list of the free elements. For the SBUF's the -1 word of entry is the link to the next element. For the TBUF's, word zero is the link and word 1 is the link for the IOQ elements.

Each word has an 11-word header beginning at the base of the table . The first six words of the header are for managing the table and the second five are for monitoring table activity.

The entries follow the header at word eleven.

ELEMENT RLLOCATION

Elements are obtained from the beginning of the free list, pointed to by the head and returned to the end of the free list pointed by the tail.

When the free list is empty, the head index is zero and the tail index is set to point at the head index.

The tables are divided into two areas: a primary and a secondary area. Most requests are obtained from the primary area. The secondary area is used only for critical requirements when the primary area is exhausted. These areas are logical areas determined by parameters in the header.

The utility of the core resident tables is seriously reduced if their use is not restricted to dynamic situations.

One of three responses must be specified to the routines which allocate elements from the I/O system tables.

1. Inpede caller if primary is empty.

2. Get from primary area only.

3. Get from secondary area if primary area is empty.

Table Element Allocation (Cont.)

Request types 2 and 3 return an indication to the caller if the request could not be satisfied. The following table specifies the types of calls for element allocation and the action if an element is not activated.

BUFFER USER	CALL TYPE	FINAL ACTION
SBUF's		
file system	Impede	---
Ptape	Impede	---
Bad track	Primary	forget request
IOQ's		
RTTACNIO (not impedable)	Primary	Return IOQX-0
RTTRCHID (impedable)	Impede	---
SIODM (memory management)	Secondary	Sudden death
IOMESSAGE	Secondary	I/O error

NERDER DEFINITION

Primary #	- Number of elements in the primary area.
Total #	- Total number of elements in the table.
Size	- Size in words of each element.
Impeded PCB	- If not zero then contains the PCB number of the first process waiting for an elenent in this table.
Head index	- Index of first free element.
Tail index	- Index of last free element.
In use	- Current number not in free list.
Overflows	- Number of requests made for an element.
Total requests	- Total number of elements requested.

ICS Global

QI -

63.	
.	RESERVED
50.	
49	CANOPIN
48	LAST WEIGHT
47	PRUSETIME
46	
45	LISTSTRTE
44	CUREFILTER
43	CURDFILTER
42	CWTNUM
41	CWTDENOM
40	CURCFILTER
39	MAXCFILTER
38	MINCFILTER
37	ESCHEDBASE
36	DSCHEDBASE
35	CSCHEDBASE
34	WORSTEPRI
33	WORSTOPRI
32	WORSTCPRI
31	MISC. BOUNDS FLAGS
30	SYSTEM MEM BOUND
29	XDS UPPER BOUND
28	DL INITIAL

27		
26	XDS SEGMENT BANK	Series 64 only
25	XDS SEGMENT BASE	Series 64 only
24	XDS SEGMENT LIMIT	Series 64 only
23	PRIV BNDS STRT WD	Series 64 only
22		
.	RESERVED	
19		
18	OISAP	PSEN, PSOB counter
17	Reserved	
16	SDST	process' stack DST#
15	PSTA	pseudo-interrupt status
14	PADDR	pseudo-interrupt address
13	TAACE FLAG	flag set non-zero on IXIT away from ICS
12	PFRIL	PTR to powerfail PCB
11	JCUT	absolute JCUT address
10	XP	pointer to executing process PCB
9	PCBX	absolute stack address
8	Z	stack DB relative Z
7	DL	stack DB relative DL
6	S	stack DB relative S
5	SBANK	stack bank
4	STDB	absolute stack DB
3	0	
2	P	> DISPATCH stack marker
1	STATUS	
QI 0	P | 0	

+1	DB BANK RETURN	
	DB RETURN	> FDR DISPRTCN
D	PARM	

P=PSEUDO-DISABLED AND DISP INSTRUCTION EXECUTED.
D=DISPATCHER INTERRUPTED.

ICS Global Cells With Initial Values

STDB - absolute address of the currently running process's stack.
SBANK - bank address for process' stack.
S - stack DB relativeS
DL - stack DB relative DL
Z - stack DB relative Z
PCBX - absolute stack address
XP - PCB table relative pointer to word 0 of the running process' PCB.

The above cells are to be initialized for the PROGENITOR.

CPCB - absolute 4, is an absolute version of XP. If CPCB is zero, then the above cells are invalid. This will never be the case in a process. CPCB should also be set by INITIAL.
SDST - DST# for running process' stack.
JCUT - the bank zero absolute address of the JCUT table.
PADDR - PB relative address for the procedure PSEUDDINT.
PSTA - status value for PSEUDOIHT, %140000+CST#.
DISAP - PSDB counter, initially 0.

INITIAL sets the above as described.

CS 80 Disc Interrupt Linkage Table (ILT)

There is one ILT for each device controller configured on the system. A controller may support more than one unit, however the CS'80 disc driver will only concern itself with the single unit controller.



ICPVA0 - Channel Program Variable Area

The first word is used by the channel program processor to store status information after I/D channel aborts. The next word is used by the driver to indicate if status should be examined for special conditions or errors. The other two words are not used.

ICPVA4 - DMA abort address

If a DMA abort occurs, the absolute address where the abort occurred is stored in this area.

ICNTRL - Contains controller information

LIM -If this bit is set, the controller is sharing a software channel resource in order to limit bandwidth.

CHANQUE -The software channel resource number.

CHAN -Channel number (four most significant bits of DRTH).

DEV -Device number (three least significant bits of DRTH).

IQUEUE - The channel program contains:

SIDPSIZE - (number of words + 1)/2 in the channel program area.

CQUEN - or a multi-unit controller this field contains the software controller resource number.

IFLAG - Controller and Channel Program state flags

RUNWAIT - An Idle Channel Program should be started when there are no active requests to process.

WAITPRDG - An Idle Channel Program has been started for this controller. This bit is reset by an interrupt.

IGNOREHI - An HIDP instruction has been issued against this controller but the channel program was not in a wait statement. Therefore ignore the interrupt generated by

HCUNIT the channel code when this program halts. - Highest configured unit number for this controller.

ISTAT - 20 bytes of status from the idle channel program.

CHAPTER 14 SPOOLING

Input Device Directory/Output Device Directory

IDD/ODD (Common attributes referred to as XDD)

IDD: DST = 45 (= X55) SIR = 3 ODD: DST = 46 (= X56) SIR = 4

Overview of Table Structure



Entry 0 (Overall Table Definitions)



DD: 0 ==> This is the IDD,
1 ==> This is the ODD.

Fence: For spooled output devices (ODD), the system-wide outfence. For spooled input devices (IDD), the jobfence.

Typical Head Entry (4 words)



There are two types of head entry, a class entry and a logical device entry. There is only one class entry, if it exists at all, and it is the first head entry in the XDD. All spoolfiles opened by class (e.g., LP, SLOWLP, EPOC, PP, etc.) are linked to this entry. There is one logical device entry for each real (physical, as opposed to virtual) device on the system. Output devices appear in the ODD, input devices in the IDD. AC/DC devices such as terminals appear in both directories.
Each head entry is linked to 0 or more subentries (a typical subentry is shown in the next table). A null chain (0 subentries) consists of head pointer = 0 and tail pointer = segment-relative address of the associated head pointer. If one or more subentries exists, the pointers are segment-relative addresses of the first word of the first and last subentries of the chain. Any intermediate subentries are linked through the subentries. The tail subentry always contains a 0-link.
The Device Outfence and LDEV# fields are meaningless for the class entry. For logical device entries (non-0 Logical Device Field), a non-0 Device Outfence means that this outfence overrides the system-wide outfence in word 4 of entry 0, but only for this device.

Typical Subentry (X40 words)



Note: Words 0-X24 are used in all subentries. Words X25-X37, although present in all subentries, are zero unless the subentry is for a spooled file (spoolfile).

Word 0: State -- State of subentry:
0 ==> Active
1 ==> Ready
2 ==> Open
3 ==> Locked
CL -- 1 ==> Word X24 is a class index into the Device Class Table.
0 ==> Word X24 is the LDEV associated with this subentry.

Word 1: Type -- Describes which environment created the subentry:
0 ==> Session' (SPOOK)
1 ==> Session
2 ==> Job
3 ==> Job' (SPOOK)

Word X22: ID -- 1 ==> Output DFID
0 ==> Input DFID

Word X23: FS -- There are one or more forms message requests in the spoolfile.
DR -- The spoolfile was created via a :DATA record (input spooling only).
Head index -- The (segment-relative address)/4 of the head entry with which this subentry is linked. Since head entries are four words long, this can be thought of as an index into the head entry portion of the XDD--if you disallow values of 0 and 1.

Word X24: -- See description of Word 0.

Word X25 VDEV -- LPDT index of virtual device LDEV. Simulates the properties of a real LDEV to the process which FOPENs a new (previously non-existing) file (State field (XDD(0).(1:2)) = 2 (Open)).

Word X26: VTINX -- The volume table index of the logical device in class SPOOL where the file label (first extent) of the spoolfile lives.

Word X32: SQ -- 1 ==> Squeeze (purge) spoolfile extents as the final copy is printed. Obsolete starting with C.00.20.
0 ==> Purge only when final copy printed.
RS -- 1 ==> Restart job when warmstarting (input spooling only).
FD -- 1 ==> There are non-standard forms on the device.
SD -- Spaced Out bit. File System could not acquire a new extent when creating spoofile.
AB -- This is the $STDLIST of an aborted job.

Words X36-37: -- Time stamp when spoofile was made READY, or DD if not closed properly. Julian day is 9 bits starting with Word X36, bit 8.

SPOOK Tape Format

The overall format of output tapes produced by the SPOOK "OUTPUT" command is shown below. The various components of the tape are then described in detail. The format described here is subject to change as MPE evolves. Also, there may be errors in SPOOK which would cause the actual tape format to differ from the one described here in some cases. All numeric information is in integer format unless otherwise specified.

EOF

EDF

Label Record

EDF

File Directory Records

Device and Class Directory Record

EDF

Spoolfile

EDF

Spoolfile

EDF

.....

Mechanisms for End-of-tape and tape switching are the same as for STORE/RESTORE tapes.

Label Record

Words 0-13: "SPOOLFILETAPE LABEL-HP3000."

Word 23: reel number (first reel is number 1)

Word 24: date (from CALENDAR intrinsic)

Words 25&26: time (from CLOCK intrinsic)

Words 30&31: "MPE V" if an MPE V SPOOK tape

All other words are zero.

File Directory

The File Directory has one entry for each spoolfile on the tape. Each entry is 12 words, and entries are packed into as many 1020word records as needed. The last record will be padded with zeros if necessary. The entry format is:

Word 0: Device file id number (bit 0 is on to indicate that the file is an output spoolfile)

Words 1-3: zero

Words 4-7: User name

Words 8-11: Account Name

Device and Class Directory

The Device and Class Directory is contained in one 1024-word record. There is no EOF separating this record from the File Directory. This directory contains one entry for each logical device or device class linked to the spoolfiles on the tape. Also, there is an entry for each logical device in each class in the directory, whether or not that logical device was directly referenced by a spoolfile. The entries are packed into the tape record one after another in no particular order. The entry formats are shown below.

Logical Device Entry

Word 0: logical device number

Word 1: Bits 0:8 : device subtype
Bits 8:8 : 3 (=length of this entry in words)

Word 2: device type

Device Class Entry

Word 0: Device class number (negated). This is the number of the entry of this device class in the system's Device Class Table.

Word 1: Total number of words in this entry.

Words 2 on: The entire contents of the Device Class Table entry for this device class.

Spoolfile Format

DDD entry (32-word tape record)

Spoolfile block ---> Two spoolfile blocks packed into one
Spoolfile block 1024-word tape record.

Two spoolfile blocks

Two spoolfile blocks

.....

The first few spoolfile blocks have been modified to contain user label information from the spoolfile. This is explained later.

Spoolfile Block Format

A spoolfile block is a 512-word block that contains variable length records in spooler format. Spoolfile records start at the first word of the block. The last record is followed by a -1 to indicate that no more records follow. The last two words of the block contain a doubleword which is the record number of the first record in the block.

Spoolfile Record Format

Word 0: Byte count of record - 2

Word 1: Byte count of data portion of record. Note that this count includes trailing blanks. However, trailing blanks are truncated in

the actual record, so this count may be more than the number of bytes actually present in the data portion.

Word 2: Function Code: 1=Furite
2=Fcontrol
3=Fopen
4=Fclose
%100 and beyond=FDEVICECONTROL

Word 3: P1 -- ATTACNIO parameter

Word 4: P2 -- ATTACNIO paraneter

Words 5 on: Data Portion of Record

User Labels Information

Spoolfiles have a number of user labels with several kinds of information. These are:

1. Master: user label 0.
2. FOPEN entry catalog: user labels 1-10.
3. Circular queue for restart checkpointing: user labels 11-27.

Since older versions of MPE did not use user labels, a way was needed to incorporate them into the SPOOK tape format without losing forward and backward compatibility. The method used is to add several special spoolfile blocks to the beginning of the spoolfile on tape. Each of these blocks has exactly one FOPEN record at its beginning. This record is followed by a -1. Thus old versions of MPE will assume that the rest of the block is garbage. However, the rest of the block is actually used to contain user label information. The first two spoolfile blocks (i.e. the first tape record of the spoolfile proper) contain only the FOPEN records. The next 5 tape records actually contain user labels in addition to the FOPEN records. The user labels are packed 3 to a spoolfile block, 6 to a tape record. Each spoolfile block of 512 words has the following format:

Words 0-4: FOPEN record

Word 5: -1 (to "terminate" the block)

Words %200-%377: user label

Words %400-%577: user label

Words %600-%777: user label

Following this special group of blocks, the spoolfile resumes a normal format. The special FOPEN records all have the number of user labels in P2.

It is often the case that some of the 27 user labels have not been initialized before the tape is written. In that case, their places will be filled with garbage. There is no easy way of detecting this except by careful inspection.

CHAPTER 15 UNIFIED COMMAND LANGUAGE (UNCL)

Reply Information Table (RIT)
DST X34; SIR X25



NOTE: Process Number = 0 means entry is empty
Reply Type = 0 for number (num)
= 1 for yes or no (y/n)
= 2 for string (sxx)
= 3 for yes, no, or STRING

.flag=2
= 4 for string
TABLE SIZE = 2046 words
.flag=2
MAX # OF ACTIVE ENTRIES = 39
MAX # OF QUEUED ENTRIES = 52

Message System General Description

The message system consists of the following parts:
- Callable intrinsic GENMESSAGE.
- Uncallable procedure GENMSG which is used by MPE.
- System message catalog (CATALOG.PUB.SYS) and any number of user catalogs.
- Program MAKECAT which builds message catalogs.
- MESSAGE SIR X24
- MESSAGE SYSGLOB CELLS X371-373
- MESSAGE DATA SEGMENT

The message system is used by calling GENMESSAGE (or GENMSG) with a message number. The message system fetches the message from a message catalog, inserts parameters, then routes the message to a file or returns the message in a buffer to the caller.

A message catalog is a numbered editor-type file containing sets of messages. The sets serve to break a catalog into manageable portions. A message system user may call GENMESSAGE using either his own message catalog or using MPE's catalog (CATALOG.PUB.SYS).

After creating a message file, run the program MAKECAT in order to build a catalog that is readable by the message system. This file is still readable by the editor (it can be "texted") but it contains a directory (written as a userlabel).

In order to use the message catalog, the program must first open the message catalog, then call GENMESSAGE with the file number, set number and message number. (MPE users don't need to open the catalog, GENMSG automatically uses CATALOG.PUB.SYS.) The file must be opened with the options "NOBUF" and "MULTI" -record access.

Message Catalog

Messages in the catalog can be of any length and can contain up to five parameters. Continuation of a message is indicated by "%" or "&" at the end of a line. The "%" symbol indicates that the message is continued and that a carriage return, line feed be issued the terminal. The "&" symbol indicates that the message is continued on the same line with no carriage return, line feed.

Parameters may be inserted into the message fetched from the catalog. The parameters are passed in the GENMESSAGE (or GENMSG) call and inserted wherever a "!" is found. For the system message catalog, the back slash (\) is also a parameter, reflecting a logical device number. The message is routed to the user associated with that logical device through the :RSSOCIATE command. Message sets are indicated by "$SET n" starting in column 1 (the rest of the line is treated as a comment). Maximum value for n is 63. Comments can be inserted in the catalog by placing "$" in column 1. Message numbers are positive integers, need not be contiguous, but must be in ascending order. After processing by the program MAKECAT, the catalog file contains records of 80 bytes, blocked 16, in 32 extents. (The system message catalog is only one extent, however). The format of the message catalog is as follows:

```
$SET 1    SYSTEM MESSAGES
1 LDEV #! IN USE BY FILE SYSTEM
2 LDEV #! IN USE BY DIAGNOSTICS
3 LDEV IN USE, DOWN PENDING
5 IS "!" ON LDEV#! (Y/N)?
   .
   .
   .
$ MESSAGE 35 IS TWO LINES LONG, A PARAMETER STARTS THE
$ FIRST LINE AND THE SECOND LINE IS "HP32002"
35 !%
HP32002B.00.!
   .
   .
   .
276 LDEV # FOR "!" ON ! (NUM)!
$
$SET 2 CIERROR MESSAGES
82 STREAM FACILITY NOT ENABLED:  SEE OPERATOR.  (CIERR 82)
200 MORE THAN 30 PARAMETERS TO BUILD COMMAND.  (CIERR 200)
   .
   .
   .
204 FILE COMMAND REQUIRES AT LEAST TWO PARAMETERS, INCLUDING
```



```
THE
 FORMAL NAME OF THE FILE  (CIERR 204)
   .
   .
```

MAKECAT Program

The program MAKECAT.PUB.SYS is used to build message catalogs (and also HELP catalogs). The program's input file has the formaldesignator INPUT, which must be used for all entry points. The program has the following entry points:

(no entry point) - Reads from input file and builds a temporary file (formaldesignator CATALOG). Also renames any old temporary CATALOG, CATnn, using an archival numbering scheme (i.e., CAT1, CAT2, etc.).

BUILD - (Must log on under MANAGER.SYS.) Reads from input file, build the system message catalog (formaldesignator CATALOG), and installs the message system. Existing catalog is renamed CATnnnn according to the same scheme as for no entry point (above). Installation of the message system means moving the directory contained in the userlabel of the catalog into a data segment. The DST number and the disc address of CATALOG are placed in system global area. The message system may be installed while the system is running.

OIR - (Must have PM or OP capability.) Installs the system message catalog (does not build a new one). Opens input file, moves the directory in the CATALOG into a data segment, and places the DST number and disc address of CATALOG in system global area. This may be done when the message system seems to be "broken", but the catalog is intact. (MPE is issuing "MISSING MSG. SET=nn. MSG=nn" at terminals and at the console.) This may be done while the system is running.

HELP - Used to build the HELP catalog. Reads input file and builds a HELP catalog (formaldesignator HELPCAT).

Message System CATRLOG.PUB.SYS

$SET 1 - System messages.
$SET 2 - CI errors and warnings messages.
$SET 3 - Miscellaneous ABORT messages.
$SET 4 - Program error abort messages.
$SET 5 - Intrinsics abort messages.
$SET 6 - Run-time abort messages.
$SET 7 - CI general messages.
$SET 8 - File System error messages.
$SET 9 - Loader error messages.
$SET 10 - CREATE error messages.
$SET 11 - ACTIVATE error messages.
$SET 12 - SUSPEND error messages.
$SET 13 - MYCOMMAND error messages.
$SET 14 - LOCKGLORIN error messages.
$SET 15 - Private Volumes error messages.
$SET 16 - OS/3000 messages.
$SET 17 - HELP Facility error messages.
$SET 18 - Graphic devices messages.
$SET 19 - Serial Disc error messages.
$SET 20 - User Logging error messages.
$SET 21 - Rssociation Utility (RSOCTABL) messages.
$SET 22 - 2680R Page Printer messages.
$SET 25 - 2680A Page Printer error file messages.
$SET 26 - Disc Free Space messages.
$SET 27 - System Internal Error messages.

Message Set Directory

DST # IN SYSGLOB X373

CAT DISC ADDR IN SYSGLOB X371-372

CREATED BY RUNNING MAKECAT.PUB.SYS.
KEPT IN A DATA SEGMENT AND IN A USER LABEL.



EMPTY ENTRY:

HELP Subsystem

KEPT AS USER LABEL
READ ONTO USER'S STACK
USES SEARCH INTRINSIC FORMAT
VARIABLE ENTRY SIZE



UDC Directory

*EXTRA DATA SEGMENT - DST # IN DB+X255 OF UMRIN STACK

*BUILT BY INITUDC



UDC's COMMAND.PUB.SYS

*RECORD SIZE = 20(10) WORDS, 6 RECORDS/BLOCK

*KEEPS TRACK OF WHO IS USING WHAT UDC CATALOG

*CAN BE PURGED TO DISABLE UDC'S

*CAN BE REBUILT TO RE-ENABLE UDC'S

%	RECORD 0	#
0	1st FREE ENTRY #	0
1	not used	1
2	MAX IN USE	2
3	# IN USE	3
4	not used	4
23		19

%	FREE ENTRY	#
0	NEXT FREE ENTRY #	0
1	ENTRY TYPE=0	1
2	not used	2
23		19

COMMAND.PUB.SYS (Cont.)

%	USER ENTRY	#
0	CATALOG ENTRY #	0
1	ENTRY TYPE=1	1
2	USER*	2
3		3
4		4
5		5
6		6
7	ACCOUNT*	7
10		8
11		9
12		10
13	not used	11
14		12
15		13
16		14
17		15
20		16
21		17
22		18
23		19

%	FILE ENTRY	#
0	NEXT CAT. ENTRY #	0
1	ENTRY TYPE = 2	1
2	FILE NAME	2
3	FOPEN FORMAT:	3
4		4
5		5
6	FILE	6
7	[/LOCKWORD]	7
10	GROUP	8
11	ACCOUNT	9
12	0	10
13		11
14		12
15	(UP TO 36 BYTES)	13
16		14
17		15
20		16
21		17
22		18
23		19

* IF THE USER FIELD AND THE ACCOUNT FIELD CONTAIN "@_____", THIS INDICATES SYSTEM LEVEL UDC'S.

IF ONLY THE USER FIELD CONTAINS @ AND 7 SPACES, THIS INDICATES ACCOUNT LEVEL UDC'S.

CI Stack Definition

DB+X0	BCOMIMAGE (Byte Ptr. To Command)
DB+X1	COMMAND IMAGE (280 bytes)
DB+X215	LINELENSTACK (30 words)
DB+X253	NEXTMSG (Not currently used)
DB+X254	THIS IS SPARE
DB+X255	UDC0
DB+X256	UDC1
DB+X257	UDC2
DB+X260	UDC3
DB+X261	UDC4
DB+X262	IFNESTING
DB+X263	IFSKIP
DB+X264	ELSESEEN
DB+X265	CIFLAGS
DB+X266	CONTINUE STATE STACK (2 words)
DB+X270	PENDINGCOMLEN
DB+X271	BLASTCOMIMAGE (Byte Ptr.)
DB+X272	LAST COMMAND IMAGE (280 bytes)

Field Definitions

BCOMIMAGE: Byte pointer to COMIMAGE (sometimes called WCOMIMAGE) in the CI stack.

COMMAND IMAGE: Command character string currently being executed.

LINELENSTACK: A CI command can span up to 30 input lines. This stack holds the length of each input line.

NEXTMSG: Used to be used to link messages together. No longer being used.

THIS IS SPARE: Not used.

UDC0: Holds the DST number of the UDC definitions.

UDC1: Holds the old S register value for UDC's.

UDC2: (0:1)--FLUSHUDC, used by :SETCATALOG

UDC3: UDC options for current UDC.

UDC4: (0:1)--UDC Fatal CI Error
(1:1)--UDC EXITBREAK
(2:1)--UDC BREAKDETECTED
(3:1)--UDC NOPRINT
(4:1)--UDC IMAGEADJUST
(10:6)--UDC NESTLEVEL

IFNESTING: Level of nesting of :IF commands.

IFSKIP: Whether the current commands are being skipped as the false part of a :IF command.

ELSESEEN: Level of the :ELSE commands.

CIFLAGS: (13:1)--Sequenced: line numbers at rear.
(15:1)--Not REDOable (last command).

CONTINUE STATE STACK: History of the :CONTINUE commands.
= 0--no :CONTINUE
= 1--just seen
= 2--in effect.

PENDINGCOMLEN: If <> 0, command is already in stack and this word is the command string length.

BLASTCOMIMAGE: Byte pointer to last command image.

LAST COMMAND IMAGE: When a command completes execution, the command string is copied here for use by the :REDO command.

Association DST Layout



CHAPTER 16 SYSDUMP/INITIRL

CONFDATA File

Record 0 of CONFDRTR File (CTRB0)

0	CHECKSUM OF CTRB	0
1	CURRENT VERSION OF CTRB	1
2	STRNDARD STACK SIZE	2
3	CORESIZE IN K WORDS	3
4	TERMINRL BOUND PRIORITY	4
5	NORMRL PRIORITY	5
6	CPU BOUND PRIORITY	6
7	# OF SECONDS TO LOG-ON	7
10	LOG FILE RECORD SIZE (SECTORS)	8
11	LOG FILE SIZE (RECORDS)	9
12	//	10
13	LOG BITS (ONLY 11 USED)	11
14		12
15	<<DEFINES WHRT IS BEING LOGGED>>	13
16		14
17		15
20	DEFRULT JOB/SESSION CPU TIME LIMIT	16
.	// .	
.	// .	
.	// .	
34	MRXIMUM OPEN SPOOL FILES	28
35	//	29
36	MAXIMUM # OF SPOOL FILES (KILO SECTORS)	30
37		31
40	//	32
41	# SECTORS PER SPOOL EXTENT	33

Record 1 of CONFDATA File (CTRB)

0	# OF CST ENTRIES	0
1	# OF DST ENTRIES	1
2	# OF PCB ENTRIES	2
3	# OF IOQ ENTRIES	3
4	# OF TERMINRL BUFFERS	4
5	# OF CST EXTENSION ENTRIES	5
6	INTERRUPT CONTROL STRCK SIZE (Q1 to Z1)	6
7	# UCOP REQUEST QUEUE ENTRIES	7
10	# BREAKPOINT ENTRIES	8
11	# TRL ENTRIES	9
12	# LOCAL RINS	10
13	# GLOBAL RINS	11
14	# OF SYSTEM BUFFERS	12
15	# OF CONCURRENT PROGS	13
16	LORDER SEGMENT SIZE	14
.	// .	
.	// .	
.	// .	
24	SIZE OF VIRTUAL MEMORY	20
25	DIRECTORY SIZE (SECTORS)	21
.	// .	
.	// .	
.	// .	

CONDRTA (Cont.)

36	MRXIMUM CODE SEGMENT SIZE	30
37	MRXIMUM # OF CODE SEGMENTS/PROCESS	31
40	MAXIMUM STRCK SIZE (MRXDATR)	32
41	MAXIMUM EXTRA DATA SEGMENT SIZE	33
42	MRXIMUM # OF EXTRR DATA SEGMENTS/PROCESS	34
.	// .	
.	// .	
.	// .	
50	MRXIMUM # RUNNING SESSIONS	40
51	MRXIMUM # OF RUNNING JOBS	41
52	# LOG PROCS	42
53	LOG IO's	43
54	# OISC REQUEST TRBLE ENTRIES	44
55	# SPECIRL REQUEST TABLE ENTRIES	45
56	# PRIMRRY MESSRGE TRBLE ENTRIES	46
57	# SWRP TABLE ENTRIES	47
58	# SECONDARY MESSRGE TRBLE ENTRIES	48

DEVDRTR.PUB.SYS

Overview



Parameter Record

0	CHECKSUM
1	VERSION
2	NEXT RECORD
3	HIGHEST LDEV
4	HIGHEST DRT
5	NR. ROD'L DRIVERS

64	REC #	DVR TABLE
	LENGTH	
66	REC #	LPOT
	LENGTH	
68	REC #	LDT
	LENGTH	
70	REC #	LDTX
	LENGTH	
72	REC #	OCTN
	LENGTH	
74	REC #	CLASS
	LENGTH	
76	REC #	TERM DEF
	LENGTH	
78	REC #	ADD'L DVR
	LENGTH	
80	REC #	CS DEF
	LENGTH	
82	REC #	CS TABLE
	LENGTH	

Driver Table

The Driver Table consists of 7 word entries, in correspondence to the LDEV entries, up to the highest LDEV used, entry zero is a dummy entry.

0	1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	
ORT #																
CR	CHAN #							DS	UNIT #							
MASTER LDEV																TYPICAL ENTRY FORMAT
D								R								
I								V								
N								A								
M								E								

OS — OS DEVICE (if set ORT is zero)
CR — CORE RESIDENT
CHAN # — CHANNEL #
MASTER LDEV — LDEV of device which this DS device is linked to.

Words 3-7 contain the driver name.

SYSDUMP Format

CHECKSUM	<---ENTRY POINT #1 (ROM BASED
AMIGO CHANNEL PROGRAM	0 MACHINES)
WCS TABLE PRT	95
AMIGO	127
WCS TABLE	
WCS #1	
WCS #2	Only for the 64/68. Refer to the
WCS #n	WCS Table for the 64/68 below.
CHECKSUM AMIGO	<---ENTRY POINT #2 (WCS BASED 0 MACHINES)
	127
AMIGO	
ICS	
LOW CORE	
Initial CST	
CS TABLE	
DEVICE CLASS TABLE HEADER	
DEVICE CLASS TABLE	
TERMINAL DESCRIPTOR TABLE	
VTAB	
OLDVTRB	*
OISC COLD LOAD INFORMATION TABLE	*
CTAB	
CTABO	
COMMUNICATION RECORD	
CSDVR	
CSOEF	
INITIAL'S DB AREA	

STACK MARKER	
DRIVER TABLE	
LPOT	
LDT	
LDTX	
INITIRL'S SEGMENTS	
RIN TABLE	*
LOGGING IDENTIFIER TABLE	*
DIRECTORY HEADER	*
DIRECTORY	*
XXXXXXXXXXXXXXXXXX EOF XXXXXXXXXXXXXXXX	
SYSTEM PROGRAMS, SL, NON-STD. DRIVERS	
XXXXXXXXXXXXXXXXXX EOF XXXXXXXXXXXXXXXX	
STORE/RESTORE HEADER	
XXXXXXXXXXXXXXXXXX EOF XXXXXXXXXXXXXXXX	
STORE/RESTORE DIRECTORY	*
XXXXXXXXXXXXXXXXXX EOF XXXXXXXXXXXXXXXX	
USER FILES (SEPARATED BY "EOF's"	*
STORE/RESTORE TRAILER	
XXXXXXXXXXXXXXXXXX EOF XXXXXXXXXXXXXXXX	
XXXXXXXXXXXXXXXXXX EOF XXXXXXXXXXXXXXXX	
XXXXXXXXXXXXXXXXXX EOF XXXXXXXXXXXXXXXX	

* NOT DUMPED IF DATE = CARRIAGE RETURN

NOTE: ON OISC, READ-SIO-PROGRAM KEPT IN OISC LABEL.

WSC Table Format



Note: Currently only one entry used (Entry 4, by Series 64).

Series 64/68 WCS TABLE FORMAT



Store Tape Format

First Volume



First Volume (Cont.)



Subsequent Volumes



End of Volume



CHAPTER 17 MISCELLANEOUS

Labeled Tape Subsystem

The MPE labeled tape subsystem permits convenient access to tapes labeled to either ANSI or IBM standards. It operates as a set of subprocedures to the file system. A labeled tape consists of one or more logical files. Each logical file consists of three physical files, i. e. tape areas delimited by tapemarks. The first physical file contains header labels, the second contains the data, and the third contains trailer labels which are (except for minor differences) copies of the header labels. The tape mark following trailer labels will be followed either by header labels for the next file, or by another tapemark if there is no next file. Labels are 80 bytes long, and conventionally are identified by their first four characters (three letters and a digit) and contain information as follows (CP := character position; L:= length):

VOL1: Present only on the first file of a volume, the volume label contains the volume identifier, which is usually the number on the tape strap, and is thus not expected to be changed.

CP	Field Name	L	Content
1/3	Label identifier	3	"VOL"
4	Label Number	1	"1"
5/10	Volume Identifier	6	Vol ID
11	Accessibility	1	"0" if IBM, else " "
12/79	Not used	62	Blanks
80	Label-Standard Version	1	"1" if HP ANSI else " "

UVLn: User volume labels. May be present on tapes from foreign shops, but are not written by MPE. If encountered, they are ignored.

HDR1: First header label. Required for each file. Specifies:

CP	Field Name	L	Content
1/3	Label identifier	3	"HDR"
4	Label Number	1	"1"
5/21	File Identifier	17	File name, if tape was not written by MPE, only the first eight are significant.
22/27	Volume Set Identifier	6	Names the volume on which the set of files begins
28/31	Reel Number	4	Counts the reels that contain this file (1 starts)
32/35	File sequence number	4	Counts the files in the set of files (1 starts)
36/41	Not Used	6	MPE writes blanks
42/47	Creation Date	6	Year and day within year when the file was written.
48/53	Expiration Date	6	Year and day within year when the file may be over-written without permission.
54	Accessibility	1	X230 if Lockword, "0" if IBM
55/60	Block count	6	Number of blocks if IBM.
61/73	System Code	13	"HP MPE 3000 "
74/80	Not Used	7	Blanks

HDR2: Second header label. Although defined by the standard, may be missing on foreign tapes. Contains:

CP	Field Name	L	Content
1/3	Label identifier	3	"HDR"
4	Label Number	1	"2"
5	Record Format	1	"F" = Fixed "V" = Variable "U" = Undefined Others treated as Undefined
6/10	Block Length	5	Block length (in character

			format).
11/15	Record Length	5	Record length (adhering to to MPE rules) in characters.
16/23	Lockword	8	MPE File Lockword.
24/36	Not Used	13	MPE writes blanks
37	Record Type	1	"A" = ASCII "B" = Binary.
38	Carriage Control	1	"C" = control " " = no control.
39/80	Not Used	42	Blanks

IBM has a slightly different format. It is:

CP	Field Name	L	Content
1/3	Label identifier	3	"HDR"
4	Label Number	1	"2"
5	Record format	1	"F" = Fixed "V" = Variable "U" = Undefined Others treated as Undefined
6/10	Block Length	5	Block length (in character format).
11/15	Record Length	5	Record length (adhering to to MPE rules) in characters.
16	Not Used	1	Blank.
17	IBM Position	1	"0" = no volume switch "1" = a switch has occurred.
18/38	Not Used	11	Blanks.
39	IBM Block Attribute.	1	"B" = Blocked records. "S" = Spanned records. "R" = Blocked and Spanned. " " = No blocked or spanned.
40/80	Not Used	41	Blanks

User header labels: optional. Standard prescribes UHLn in the first four characters, but MPE doesn't care.

EOV1: End of Volume; used as first trailer label. Required if the logical file is continued onto another reel. Identical to HDR1, except contains the number of physical blocks of data in the data area.

CP	Field Name	L	Content
1/3	Label identifier	3	"EOV"
4	Label Number	1	"1"
5/54	Same as HDR1	50	
55/60	Block Count	6	Number of data blocks since last beginning of file section label group.
61/80	Same as HDR1	20	

EOV2: Defined by the standard, but may be missing on foreign tapes. Follows EOV1; format same as HDR2.

EOF1: End of File; used as first trailer label. Required if this is the end of the logical file. Format same as EOV1.

EOF2: Same as EOV2 except used after EOF1.

User trailer labels: optional. Standard prescribes UTLn in the first four characters, but MPE again doesn't care.

Tape Label Table

The tape label table is the private playground of the tape label subsystem. It consists of two parts: LDEV Control Blocks (LCBs) and Volume Control Blocks (VCBs). The LDEV area is set up at system initialization and contains one entry for each magnetic tape LDEV and serial disc device in the system. As is common in MPE, the first entry is a dummy which tells where the other things in the table are. The volume area contains one entry for each labeled tape volume requested or active on the system.

Although table entries are stored in an extra data segment, they are generally manipulated via local copies on the stack. The procedures GETLDEV and GETFNUM look for LDEV and volume entries as specified; they copy them to stack buffers and return the DST address for use in copying them back. POSTVTENT copies the entries back, and in the case of a new volume entry, allocates space for it in the volume section of the tape label table.

Initial will build the "uninitialized" TLT as follows:



T: 1 if Tape drive 0 if not Tape drive (i.e. serial disc)

During PROGEN, SETUP'TAPES is called to initialize the table. The overall structure of the initialized TLT is:



The LCB entries have the following structure:



Type: 00 = no tape mounted
01 = unlabelled
10 = ANSI
11 = IBM
L: 1 if file has lockword.
T: 1 if device is a tape drive.
B: 1 if tape is from Burroughs, which has incorrect block/record size in the HDR2 label. Code can be patched to correct the size.
HP: 1 if tape is Hewlett-Packard ANSI format.

VCB address: Pointer to VCB entry describing volume mounted on tape drive, only if linked. Otherwise, 0.
The VCB format is:



VCB (Cont.)

```
|                                                          | 26
|----------------------------------------------------------|
|                                                          | 27
|                                                          |
|                       Volume name                        | 30
|                                                          |
|                                                          | 31
|----------------------------------------------------------|
```

R: ASCII FOPTION
F: Flush bit - operator did REPLY <pin>,0.
D: DEVREC Wait (used with reelswitching).
Position: Gives head position within logical file.
0 = at load point (LDPNT)
1 = HDR1 label next (N1NX)
3 = after HDR2 label (AN2)
4 = after user header labels (RNU)
6 = data next (DNX)
7 = after data (AD)
8 = EOF1/EOV1 label next (T1NX)
10 = after EOF2/EOV2 label (RT2)
11 = after user trailer labels (ATU)
W: Write access specified.
SeqTyp: File open sequencing type.
0 = match filename
1 = NEXT
2 = RODF
3 = use file sequence number
LblTyp: Re in LCB entry.
L: Linkwait - mark left by CREATETLTENT for LINKLABEL.
M: Mount wait - waiting for operator to mount tape on FOPEN.
R: Reelswitch wait - waiting for next reel.
B: Busy bit - this entry is in use.

LDEV #: Logical device number of tape drive with this volume, only if linked. Otherwise, 0.

S: STORE tape.
R: REELSWITCH has been done. Used by STORE/RESTORE to handle STORE label and directory file.
D: Next file is directory. Used by STORE.
C: VOL1 label is to be created (written).
Density: volume set density. During a volume set open, contains the density requested by the user in FOPEN. Once the volume set is open, contains the actual density of the volume set. Only valid for tapes on variable density tape drives.
0 = default density for volume set open
1 = 1600 BPI
2 = 6250 BPI
V: 1 if volume set is being opened. Reset after completion of FOPEN.

Volume Recognition

Volume recognition is the responsibility of DEVREC, which reads the first record of a newly-mounted tape on an unowned drive and passes the record to AVREC. AVREC may see: VOL1 in the first 4 bytes, in ASCII, in which case the tape is ANSI; VOL1 in the first 4 bytes, in EBCDIC, in which case the tape is IBM; Anything else, in which case the tape is considered unlabelled.

If the tape is unlabelled, AVREC reports to DEVREC that no further action is required. If the tape is labelled, AVREC wants to see the first HDR1 label, so asks DEVREC to read another record. (Unfortunately, DEVREC cannot be stopped long enough for AVREC to do its own read.) When the HDR1 record is found, the volume entries can be searched to see if there is a pending request for this volume. If so, the waiting process is restarted.

If the system has been restarted with tapes mounted, there will not be interrupts to alert DEVREC. The procedure RECOGNIZE is called when needed to see if any such tapes exist.

Opening a File

FOPEN gets into the tape label code in three different places. The first is to call CRERTETLTENT, which parses the string passed in the FORMSMSG parameter to identify the labeled tape file required. If there is no existing corresponding entry in the volume area, this is a volume set open, and a new volume entry is created. There may be an existing entry (if the tape was FOPENed and FCLOSEd with disposition 2 or 3), in which case there is an associated LDEV entry for the drive on which the tape was left mounted by the prior operation; in this case, the new information is stuffed into the existing volume entry. R bit (LINKWAIT) is left set to mark the entry for LINKLABEL.

The second entry is through LINKLABEL, which is called from ALLOCRTE. At this time, it is necessary to identify the LDEV to be used for the tape. If no LDEV is associated, the LDEV entries are searched to see if the operator has already mounted the required tape; if so, the volume and LDEV entries are cross-tied and LINKLABEL is done. If the search turns up nothing suitable, the operator is requested to mount the appropriate tape, and the procedure waits for either a REPLY or for AVREC to discover the appearance of a suitable tape and restart the process. If the operator enters a reply, it is validated.

The third entry is through POSITION, which is responsible for positioning the tape to the requested file. At the file, the HDR1 and HDR2 label are examined as required to determine the file characteristics.

Reading and Writing Files

All procedures which move tape go through the catchall procedure CHECKUL, which takes care of necessary labeled tape doings. The code insures that the sequence: header labels (including user labels), data, trailer labels

(including user labels) is maintained. There is a separate CASE leg for each such procedure.

If an EOT reflective mark or an EOF in data is found, REELSWITCH is called (principally from the file system procedure IOMOVE) to call for the next reel, if any. If another reel is needed, the tape drive is set Unowned so that AVREC will be called to recognize the new tape when it is mounted. REELSWITCH returns to its caller when it is satisfied that an appropriate tape is mounted.

Closing Files

FCLOSE calls CHECKUL to handle writing EOF1 and EOF2 if needed and resolving the tape position. If the disposition is 3, the tape is left positioned at the next file. If the disposition is 2, the tape is supposed to be left at the beginning of the current file, but the code does not presently provide for reelswitching if the present file began on a prior reel.

At present, ensuing volumes of a multi-volume set must be mounted on the same drive as the first, mostly because neither the file system nor STORE-RESTORE was capable of dealing with LDEV changes in the middle of a file. REELSWITCH reports the LDEV being used, however, so that the capability of using a different LDEV can be added in the future.

Store-Restore

Complications ensue on labeled STORE-RESTORE tapes because there needs to be a file directory at or near the beginning of each tape of a multi-volume set; RESTORE uses this directory to determine whether the specified file(s) can exist on this tape. Because the reel switching process would otherwise be invisible to STORE-RESTORE, special bits (VCB'RSWDONE and VCB'WRITOIR) are kept to enable special intrinsics callable by STORE-RESTORE to report whether a directory needs to be written or is about to be encountered.

The special procedure NEXTTAPEFILE is used by STORE-RESTORE in lieu of doing a FCLOSE(,3) followed by an FOPEN to get to the next file. This permits cleaner handling of both REPLY 0 and Forward Space (logical) File over a Reelswitch, as well as saving the time needed to tear down and reconstruct all the control blocks.

Miscellaneous

FVOLID is used by the SHOWDEV command processor (in SPOOLCOMS) to obtain the name of the volume on the specified drive without having to know the structure of the tape label table. For the same reason, TGETINFO is used by the FFILEINFO intrinsic (in FILEID) to get labeled tape information.

System failure 86 in MPE is defined as a major problem in LABSEG. Generally speaking it is a problem with the TLT setup, for example if LABSEG cannot find an LDEV in the table.

Breakpoint Table

DST = 30(10) = %36

The break point table is divided into 2 sections:

1) PCB BREAKPOINT EXTENSION TABLE (PCB'BKPT'EXT)
This table contains the heads of the breakpoint chains

2) BREAKPOINT ENTRY TABLE (BKPT'ENTRY'TRB)
This table contains the actual entries

General Layout



PCB Breakpoint Extension Table



Breakpoint Entry Table



The breakpoint entry table consists of variable length entries
The minimum entry size is 7.

Active Entry



Breakpoint Entry Table (Cont.)

```
ENTRY(0).(0:1) = FR:    FREE ENTRY
                          1 = FREE
                          0 = USED
ENTRY(0).(1:1) = P:     PRIVILEGED MODE BREAKPOINT
                          1 = PRIV.
                          0 = NON-PRIV
ENTRY(0).(2:1) = L:     PROCESS-LOCAL BREAKPOINT
                          1 = PROCESS-LOCAL
                          0 = SYSTEM
ENTRY(0).(3:1) = V:     VARIORTION BIT
                          1 = INSTRUCTION IN ENTRY(3)
                          0 = INSTRUCTIDN NOT IN TAB.
ENTRY(0).(4:1) = D:     DOUBLE TRAP
                          1 = BREAKPOINT OSCILLATES BETWEEN
                              P/P+1
                          0 = NOT DOUBLE TRAP
ENTRY(0).(5:1) = F:     FAKE 'DUMMY' TRAP
                          1 = BREAKPOINT AT P+1
                          0 = BRERKPOINT AT P (ORIG. LOC)
ENTRY(0).(6:1) = T:     TWO WORD INSTRUCTION
                          1 = TWO WORD INSTRUCTIDN
                          0 = NOT TWO WORD INSTRUCTION
ENTRY(0).(7:1) = U:     USER LABEL PRESENT
                          1 = TRAP TO USER SUPPLIED LABEL
                          0 = TRAP TO DEBUG
ENTRY(0).(8:1) = PM:    PERMANENT BREAKPOINT
                          1 = PERM
                          0 = TEMPORARY
ENTRY(0).(9:1) = C:     CONDITIDN/COUNT
                          1 = CONDITION/COUNT SPECIFIED
                          0 = NO COND/COUNT
ENTRY(0).(10:1) = UP:   UPDATING
                          1 = ENTRY IN PROCESS OF BEING
                              UPDATED/REMOVED
                          0 = NOT BEING UPDATED/REMOVED
ENTRY(1).(0:1) = M      USER PLABEL MODE
ENTRY(6) = LINK:        LINK
                          0 = END OF CHAIN
                          >0= INDEX NEXT ENTRY
```


Breakpoint Entry Table (Cont.)




```
RELOP -> (8:8) RELOP NUMBER:
                 3 = LT      9 = LTE
                 4 = GT     10 = GTE
                 5 = EQ     11 = NEQ
OPT1  -> (0:2) OPERAND1'S TYPE
OPT2  -> (2:2) OPERAND2'S TYPE

OPERAND TYPES:
   0 -> CONSTANT (SINGLE WORD)
   1 -> ADDRESS (DOUBLE WORD)
   3 -> INDIRECT ADDRESS (TRIPLE WORD)

OPERAND FORMS:
   CONSTANT ->  ------------
                | CONST     |
                ------------

   ADDRESS  ->  ------------
                | REG | BASE|
                ------------
                |  OFFSET   |
                ------------
                |IND. OFFSET|   (TYPE 3 ONLY)
                ------------

   REG      ->  (0:6) CORRESPONDING INDEX INTO 'REGY':
                        3 = A     10 = DL
                        4 = SY    11 = Q
                        7 = DR    12 = S
                        8 = DK    17 = EA
                        9 = DB
   BASE     ->  (6:10) SEG M/BANK M
```

Timer Request List (TRL)

The system clock interrupts every 100 ms, with the CR being automatically cleared. An exception is the Shared Clock Interface measurement service which allows rates as fast as 5 ms. The interrupt handler is the procedure TICK. On entry, DB is pointing to the base of timer request list. Besides timeout requests, the clock also controls time slicing.



TRL (Cont.)

CODE & REQ indicate the type of request.

CODE:	REQ:	TYPE:
0	DITP	Hangup
1	DITP	Carrier failure
2	DITP	202 turnaround
3	DITP	Read
4	DITP	Logon
5	PCBB index to process	Delay
6	DITP	LP not ready
7	DITP	2640
%10	Port mask	Msg port timeout
%11	DITP	Block mode read timeout (30 secs)
%12	PCBB index to process	Watchdog timer for process

The list of pending requests is kept ordered by time with later entries at the tail.

%20-%37	DITP	SIO device timeout: DIT8. (code_1 on expiration, cleared on Tinereq.
%5/%6	*DTIME	For Series 30/33, DTIME is # of TICS (0.091457 ms) since last midnight.

MPE User Logging

MPE USER LOGGING enables users and subsystems to log changes to data sets on disc or serial files. This "change" file can later be used to recover data lost due to a system or program failure. The log file can itself be used for auditing purposes.

General Design Overview

Hardware Environment

No special hardware is required to operate the system. However, if logging to a tape file is desired, the hardware configuration must include a tape drive. If there is no tape drive, then may log to a serial disc class device.

Software Environment

MPE User Logging is an integral part of MPE. No other special software is required.

Design Narrative

User Logging enables users and subsystems to journalise additions and modifications to MPE and subsystem files. The journal can reside on either disc or serial logfiles.

User Logging consists of a logging process, a memory buffer, a disc resident logging buffer (for serial logging) and a user defined destination log file on disc or serial media.

The logging process has two functions depending on whether the destination file resides on disc or serial media. If the destination file is serial, the logging process performs all output to the destination file. If the destination file is on disc, the logging process allocates additional space (extents) as it is required by the user.

The logging buffer is divided into communication and buffer areas. The communication area is used to pass information among the users and the logging process. This information includes status of the logging process and logging file, space remaining in the logging file and error information important to users or the logging process. The buffer portion of the logging data segment blocks inputs into the logging file before the data is actually posted. The buffer is flushed any time a user requests to close a log file or when a logging process is terminated. (The buffer is also flushed by the begin/end transaction or buffer flush requests).

Error Recovery Description

The error recovery mechanisms provided by User Logging are: power fail recovery and recovery from system failure.

Power failure recovery applies only to tape log files since MPE provides adequate recovery for disc files during power fail. When a power failure is detected, a message will be printed on the console asking the operator to place the tape drive back on-line. (If the operator places the tape on-line before the message valid data may be overwritten). (To reset the tape drive the operator must hit the load button until the tension returns to the drive. Then hit the reset button followed by placing the tape drive back on-line). At this time the log process will recover the file by rewinding to the load point and then forward spacing to the point where the power fail occurred. Writing to the log file will continue at that point.

In the event of a system failure, the warm start load option initiates recovery of User Logging files. In the case of a serial file, the file is read and compared to the disc logging buffer. All records found in the disc buffer that are not on the serial log file are posted and a proper end of file written. If the destination file is a disc file, all records are read and verified and an end of file posted to the file. In order to continue logging to a User Logging file that has been recovered in this manner, the logging process for the file must be restarted using the console command :LOG.

NOTE:

Any records in the buffer area of the logging buffer will be lost.

User logging has been enhanced to work with labeled serial discs. Internally the log process handles serial disc (or cartridge tape) log files the same as for tape files.

Design Structures

User Logging Table

ENTRY SIZE = N38 words
DST X33

Table containing an entry for each activated user logging process. Each entry is created when the process is started, and deleted when the process terminates. (Via :LOG command). The information is extracted from the Logging Identifier Table (LIDTAB).

ENTRY 0

N		X
0	NUMBER OF ENTRIES	0
1	FREE ENTRY HEAD PT.	1
2	INUSE ENTRY HEAD PT.	2
3	NEXT BUFFER NUMBER	3
4	MAX N PROCESSES	4
5	MAX N USERS/PROCESS	5
6		6
7	ENTRY SIZE	7
	.	
	.	
37	.	45

WORD ENTRIES

```
NUMENTRIES      =   LOGTAB
FREE            =   LOGTAB(1)
INUSE           =   LOGTAB(2)
BUFNUM          =   LOGTAB(3)
MAXLOGPROC      =   LOGTAB(4)
MAX'USR'PROC    =   LOGTAB(5)
LOGTAB'ESIZE    =   LOGTAB(7)
```


NUMENTRIES
The number of entries in the logging table.

FREE
A table relative pointer to the first free entry in the logging table. (-1 = table full).

INUSE
A table relative pointer to the first entry in the logging table that is being used (-1 = no entries in use).

BUFNUM
The number of the buffer associated with this logging process. Used to create the name of buffer file if serial logfile. (i.e. ULDGxxxx.PUB.SYS).

MAXLOGPROC
The maximum number of user logging processes allowed.

MAX'USR'PROC
The maximum number of users per logging process.

LOGTAB'ESIZE
The size (in words) of each entry in the table.

Typical Entry

#		X
0	LOGGING IDENTIFIER	0
4	BUFFER NAME	4
8	FILE NAME	10
12	LOCK WORD	14
16	GROUP	20
20	ACCT	24
24	NUMBER OF USERS	30
25	BUFFER DST NO	31
26	LOG STATUS	32

27	CURR AUTO | CURR TYPE	33
28	LOG DEV	34
29	LOG PCB N	35
30	SWITCH FLAG	36
31	NEW AUTO | NEW TYPE	37
32	ADDRESS OF LOGGING BUFFER	40
34	SIZE OF LOGGING BUFFER	42
36	FWRD ENTRY PT	44
37	BWRD ENTRY PT	45

```
TABINDEX        =       WORD INDEX TO CURRENT ENTRY
BTABINDEX       =       BYTE INDEX TO CURRENT ENTRY
DTABINDEX       =       DOUBLE INDEX TO CURRENT ENTRY

LGNAME          =       BTABINDEX
BNAME           =       BTABINDEX+8
LFNAME          =       BTABINDEX+16
LFLOCKW         =       BTABINDEX+24
LFGROUP         =       BTABINDEX+32
LFACCT          =       BTABINDEX+40

NUMUSERS        =       TABINDEX+24
DST             =       TABINDEX+25
STATUS          =       TABINDEX+26
LGAUTO          =       TABINDEX+27.(0:8)
LGTYPE          =       TABINDEX+27.(8:8)
LGDEV           =       TABINDEX+28
PIN             =       TABINDEX+29
LGSWITCH        =       TABINDEX+30
LGNEWAUTO       =       TABINDEX+31.(0:8)
LGNEWTYPE       =       TABINDEX+31.(8:8)
LGADDR          =       DTABINDEX+16
BSIZE           =       DTABINDEX+17
NEXT            =       TABINDEX+36
PREV            =       TABINDEX+37
```

LGNAME
The name of the logging process (logging identifier).

BNAME
The name of the disc buffer used if the logging process destination file is a serial file. This is a file that resides in PUB.SYS. The format of the name is ULOGxxxx where xxxx is the buffer number padded on the left with zeros.

If the switch flag is true, the following will be the fully qualified file name of the new log file.

LFNAME
The name of the logging file.

LFLOCKW
The lockword of the disc logging file.

LFGROUP
The group that the destination logging file resides in if the file is a disc file.

LFACCT
The account that the destination logging file resides in if the file is a disc file.

NUMUSERS
The number of users currently accessing the logging file.

DST
The dst number of the logging data segment (LOGBUFF). (-1 = LOGBUFF not created yet)

STATUS
The status of the logging process.
INITIALIZING = -1
INACT = 0
ACT = 1
RECOVERING = 2

LGAUTO
True if the automatic changelog facility was enabled. (Not used - for future use).

LGTYPE
The type of destination file of the logging process.
DISC = 0
TAPE = 1
SDISC = 2
CTAPE = 3

LGDEV
The logical device number of the disc logging file or the disc logging buffer.

PIN

The PCB number for the logging process (PIN * PCBSIZE).

LGSWITCH
Flag indicating a CHANGELOG is pending (if true). (Not used - for future use).

LGNEWAUTO
True if the automatic changelog facility was requested for the new log file. (Not used - for future use).

LGNEWTYPE
If a switch is pending, this will be the type of the new log process. (-1 = no switch pending). (Not used - for future use).

LGADDA
Sector number of the current extent in the disc logging file or the disc buffer file. (Disc buffer file has only 1 extent)

BSIZE
The number of records in the current extent (for disc logging) or the number available in the disc logging buffer.

NEXT
A table relative pointer to the next entry in the logging table. (-1 = this is last entry)

PREV
A table relative pointer to the previous entry in the logging table. (-1 = this is first entry)

User Logging Buffer

There will be one of these tables around for the life of any active user logging process. The table consists of three parts:

COMMUNICATIONS AREA - Information about status of the process, etc. that is common to all users of the process. Also the cells for messages to/from the process.

USER ENTRIES - Information for a specific user of the process. One of these for every user of a process (Setup by OPENLOG, released by CLOSELOG).

BUFFER AREA - Buffer used to hold logging records from all users before writing to the log file.



COMMUNICATIONS AREA

#		Z
0	LOGGING IDENTIFIER	0
4	SWITCH FLAG	4
5	NEW AUTO | NEW TYPE	5
6	AUTO | TYPE	6
7	BUFFER DST	7
8	LOG PIN	10
9	NUMBER OF USERS	11
10	MAX NUMBER OF USERS	12
11	NEXT USER NUMBER	13
12	SLEEP COUNT	14
13	STATE	15
14	MSG	16
15	LOG MSG	17
16	USER MSG	20
17	LOG ERROR	21
18	LOG DEVICE	22
19	BUFFER SPACE	23
20	USED SPACE IN BUFFER	24
21	FILE SET NUMBER	25
22	LOG ADDRESS	26
24	INPUT RECORD	30
26	FILE	32




```
LOGID       =   BLOGBUFF(0)

SWITCH'     =   LOGBUFF(4)
NEWAUTO     =   LOGBUFF(5).(0:8)
NEWTYPE     =   LOGBUFF(5).(8:8)
AUTO        =   LOGBUFF(6).(0:8)
LOGTYPE     =   LOGBUFF(6).(8:8)
BOST        =   LOGBUFF(7)
LOGPIN      =   LOGBUFF(8)
NUMUSER     =   LOGBUFF(9)
MAXUSER'    =   LOGBUFF(10)
USERNO      =   LOGBUFF(11)
SLPCT       =   LOGBUFF(12)
STATE       =   LOGBUFF(13)
MSG         =   LOGBUFF(14)
LOGMSG      =   LOGBUFF(15)
USERMSG     =   LOGBUFF(16)
LOGERR      =   LOGBUFF(17)
LOGDEV      =   LOGBUFF(18)
BSPACE      =   LOGBUFF(19)
BUFUSED     =   LOGBUFF(20)
VSETNO      =   LOGBUFF(21)

LOGADDR     =   DLOGBUFF(11)
INBUFREC    =   DLOGBUFF(12)
FSIZE       =   DLOGBUFF(13)
FSPACE'     =   DLOGBUFF(14)
TRECS       =   DLOGBUFF(15)
MAXFSPACE   =   DLOGBUFF(16)

LASTEXT'    =   LOGBUFF(34)
EXTENT      =   LOGBUFF(35)

RESOURCE    =   DLOGBUFF(18)

UHEAD       =   LOGBUFF(48)
FHEAD       =   LOGBUFF(49)
```


LOGID
The name of the logging process.

SWITCH'
True if log file switch is pending. (Not used - for future use).

NEWAUTO
True if the automatic changelog option has been specified for the new log file. (Not used - for future use).

NEWTYPE
If a switch was requested, this will be the type of the new logging file. (-1 = no switch pending) (Not used - for future use).

AUTO
True if the automatic changelog option was specified for the current log file. (Not used - for future use).

LOGTYPE
The type of destination file for the logging processe.
DISC = 0
TAPE = 1
SDISC = 2
CTAPE = 3

BOST
The data segment number of this table.

LOGPIN
This is the PCB number for the logging process (PIN*PCBSIZE).

NUMUSER
The number of users currently accessing the logging file.

MAXUSER'
The maximum number of users allowed to access the logging file.

USERNO
The next sequential number to be assigned users accessing the system. It will get incremented for every unique OPENLOG - used as the log # in the logging record format.

SLPCT
The number of users currently waiting for activation by the logging process.

STATE
The state of the user logging process.
INACTIVE = 0
ACTIVE = 1

MSG
An internal message word used to indicate an error or operator request.
0 - Continue processing, all is fine.
2 - Suspend - error reading buffer file or writing to serial file
3 - Stop - set when issue :LOG logid,STOP or when an EOF condition is found on the disc log file.

LOGMSG
messages from the logging process.
0 - Continue processing, all is fine.
15 - EOF - if there are no more extents available to be allocated.
12 - Disc space - could not allocate the new extent because no space left in the group.
9 - Write error - error occurred while writing to log file

USERMSG
messages from the user process.
0 - Continue processing, all is fine.
12 - Disc space - user process needs another extent allocated for disc logging.

LOGERR
Last error found. After changelog:
+N - File System error number encountered
0 - No error
-1 - New disc log file was not empty
-2 - New disc log file did not have file code LOG
-3 - New disc file is too small
(Not used - for future use).

LOGDEV
The logical device number of the current extent of the disc log file or the disc buffer file (buffer file has only 1 extent).

BSPACE
The amount of space, in records, that are currently available to the users. On the last block of the last extent, one record will be saved by the logging process so that the proper close information can be posted to the file - either the trailer record (if the log logging process is stopped) or the change'to'new record because of an EOF condition (and the AUTO option had been specified).

BUFUSED
The number of records currently in the buffer. On all extents, except the last extent BUFSPACE+BUFUSED = 32 (number of records in a complete block). However, on the last block of the last extent this will NOT be true since one record is always held in reserve by the logging process.

VSETNO
This shows the order in the log file "set" of the currently opened log file. (Not used - for future use).

LOGADDR
The disc address of the current extent of the disc log file. If it's a serial file, this is the disc address of the disc buffer for the file.

INBUFREC
The record number of the next block to be written to the logging destination file or the disc logging buffer for serial files. (Used as an offset into the current extent for the writes - since each record is one sector in length).

FSIZE
The current extent size of the logging destination file or disc logging buffer file for serial destination files. (on the last extent this will be the last extent size minus 1).

FSPACE'
The space in records that remains in the current extent of the disc logging destination file or disc buffer for tape destination files. (On the last extent of the disc log file, this is the amount of space minus 1).

TRECS
The total number of records written to the logging destination file (including those records currently in the buffer).

MAXFSPACE
The total file size, in records, minus 1. (Need that last record to post close information).

LASTEXT'
The extent number of the final extent in the disc logging file or disc buffer file.

EXTENT
The current extent number of the disc logging file or disc logging buffer.

RESOURCE
Used for resource management (i.e. locking the LOGBUFF). Format is:
RESOURCE + 0 = Owner PCB number
RESOURCE + 1 = Head of inpeded queue PCB number
RESOURCE + 2 = Tail of inpeded queue PCB number
RESOURCE + 3 = Queue length

WHEAD
A table relative pointer to the first entry into the logging data segment. (-1 = no entries currently in use)

FHEAD
A table relative pointer to the first free entry in the logging data segment. (-1 = no free entries)

TYPICAL LOGBUFF ENTRY




```
BINDEX    =   BYTE INDEX TO CURRENT ENTRY
INDEX     =   WORD INDEX TO CURRENT ENTRY
DINDEX    =   DOUBLE INDEX TO CURRENT ENTRY

USER      =   BINDEX
GROUP     =   BINDEX+8
ACCT      =   BINDEX+16

UPIN      =   INDEX+12
OPENCNT   =   INDEX+13
WSTATE    =   INDEX+14
ERROR     =   INDEX+15
LGNUM     =   INDEX+16
SCODE     =   INDEX+17

RECS      =   DINDEX+9

NENTRY    =   INDEX+23
PENTRY    =   INDEX+24
```

USER
The name of the user who opened the logging file through this entry.

GROUP
The group of the user who opened the logging file.

ACCT
The account of the user who opened the logging file.

UPIN
The PCB number of the user process (PIN * PCBSIZE).

OPENCNT
Counter of how many times this user called OPENLOG. (Incremented for every OPENLOG, decremented for every CLOSELOG). (Not used - for future use).

WSTATE
The wait status of the users process.
INACTIVE = 0
ACTIVE = 1

ERROR
Used to hold error information for this user.
-1 = No room in disc (or disc buffer) and NOWAIT.
0 = O.K.

LGNUM
The logging number assigned to the user. (From USERNO in global area to be used as log # in the log record).

SCODE
The subsystem code for the caller. This applies only to privileged callers.

RECS
The number of records written by this user.

NENTRY
A table relative pointer to the next entry in the logging data segment. (-1 = this is the last entry)

PENTRY
A table relative pointer to the previous entry in the logging data segment. (-1 = this is the first entry)

User Logging Identifier Table

ENTRY SIZE = #33 words
DST %41

Table containing an entry for each potential logging process. Entries are added via :GETLOG and released via :RELLOG.

Entry #0



ENTRIES

MENTRIES = LIDTAB(1)
ENTRYSIZE = LIDTAB(4)

MENTRIES
The maximum number of entries in the table. (i.e. maximum number of user logging processes. 1 entry for every process - activated or not).

ENTRYSIZE
The size of each entry in the table.

Typical Entry



Typical Entry (Cont.)



BYTE ENTRIES

LIO = BLIOTAB
PW = BLIOTAB(8)
FNAME' = BLIOTAB(16)
LW = BLIOTAB(24)
FGROUP = BLIOTAB(32)
FACCT = BLIOTAB(40)
UNAME = BLIOTAB(48)
UACCT = BLIOTAB(56)

WORD ENTRIES

TYP = LIDTAB(32)

LIO
The logging identifier name. This is a maximum of eight characters long.

PW
The pass word for the logging identifier. This is a maximum of eight characters long.

The following is the fully qualified file name of the current log file.

FNAME'
The name of the destination file.

LW
The lock word on the destination file if the file is on disc.

FGROUP

The group that the file resides in.

FACCT
The account that the destination file resides in.

UNAME
The name of the user who created the logging identifier.

UACCT
The account of the user who created the logging identifier.

TYP
The status of the entry. -1 = null entry
0 = disc logging file
1 = tape logging file
2 = serial disc logging file
3 = cartridge tape logging file

Logging Record Format

RECORD SIZE = 128 words
USER AREA = 119 words

LOG RECORD AT OPENLOG



USER OR SUBSYSTEM/CONTINUATION LOG RECORD (from WRITELOG)



LOG RECORD AT CLOSELOG



CRASH MARKER



HEADER RECORD (START/RESTART)



TRAILER RECORD (STOP)



NULL RECORD



BEGIN TRANSACTION MARKER



END TRANSACTION MARKER



CODE DEFINITION

```
CODE.(8:8) =
      1   Open log record
      2   User/subsystem record (writelog)
      3   Close log record
      4   Header record
      5   Trailer record
      6   Restart record
      7   Continuation of a user or subsystem record
      9   Crash marker
     10   End transaction record
     11   Begin transaction record
  SPACE   NULL record
```


DATA FIELDS OF LOG RECORDS

```
REC#      =     DOUBLE INTEGER
CKSUM     =     INTEGER
CODE      =     INTEGER
TIME      =     DOUBLE  (from intrinsic CLOCK)
DATE      =     INTEGER (from intrinsic CALENDAR)
LOGID     =     ASCII
LOG#      =     INTEGER
LEN       =     INTEGER
USERAREA  =     ASCII
CREATOR   =     ASCII
PCB       =     INTEGER
```

NOTE:

1. The checksum algorithm uses the exclusive or (XOR) function against a base of negative one.

2. Null record is used for filler.

3. The code word of the logging record can contain a subsystem code defined by the user in the first half of the word (0:8). User logging allows privileged users to pass this code in the index parameter of the Openlog intrinsic.

4. The "len" field will contain the entire length of the data in the transaction (i.e. the length passed to WRITELOG, BEGINLOG, ENDLOG). If a continuation record is part of the transaction, it will also contain the entire length of the data. For example, a length of 140 was passed to the intrinsic. The "len" field of the first record will be 140, the "len" field of its continuation record will also be 140 - even though the actual amount of data found in the first record will be 119 and the data found in the continuation record will be 21.
(Positive length = # words, negative length = # bytes)

MEASINFOTAB DST = 59 (% 73)

	0 LOEV # OF MEASIO	MEASLOEV
	1 MEASIO PLABEL	MEASPLAB
	2 MEASID DST #	MEASDSTN
Reserved for MEASIO control	3	
	4	
	5	
	6	
	7	
	10	
	11	
	12	
Reserved for performance tuning parameters	13	
	14	
	15	
	16	
	17	
	20 GLOBAL STATISTICS XDS NUMBER	MEASSTATX-DSNUM
	21 PROCESS STATISTICS XDS BANK	MEASPROC-XDSBANX
	22 PROCESS STATISTICS XDS BASE	MEASPROC-XDSBASE
	23 PROCESS STATISTICS XDS NUMBER	MEASPROC-XDSNUM
	24 CLASS 14 STATISTICS XDS BANK	
	25 CLASS 14 STATISTICS XDS BASE	

	26	CLASS 14 STATISTICS XOS NUM.
	27	CLASS 13 STATISTICS XOS BANK
	30	CLASS 13 STATISTICS XDS BASE
	31	CLASS 13 STATISTICS XOS NUM.
	32	CLASS 12 STATISTICS XDS BANK
	33	CLASS 12 STATISTICS XOS BASE
	34	CLASS 12 STATISTICS XOS NUM.
	35	CLASS 11 STATISTICS XOS BANK
	36	CLASS 11 STATISTICS XDS BASE
	37	CLASS 11 STATISTICS XOS NUM.
	40	CLASS 10 STATISTICS XOS BANK
	41	CLASS 10 STATISTICS XOS BASE
	42	CLASS 10 STATISTICS XDS NUM.
	43	CLASS 09 STATISTICS XDS BANK
	44	CLASS 09 STATISTICS XDS BASE
	45	CLASS 09 STATISTICS XDS NUM.

reserved for measurement interface	.		
	.		
	50	CLASS 0 ENABLED COUNT	CLASS 1 ENABLED COUNT
	51	CLASS 2 EN.CNT.	CLASS 3 EN.CNT.
	52	CLASS 4 EN.CNT.	CLASS 5 EN.CNT.
	53	CLASS 6 EN.CNT.	CLASS 7 EN.CNT.
	54	CLASS 8 EN.CNT.	CLASS 9 EN.CNT.
	55	CLASS 10 EN.CNT.	CLASS 11 EN.CNT.
	56	CLASS 12 EN.CNT.	CLASS 13 EN.CNT.
	57	CLASS 14 EN.CNT.	CLASS 15 EN.CNT.
	60		
	61		
reserved for shared clock interface user	62		
	63		
	64		
	65		
	66		
	67		

	70	M	FLAG	A
shared	71		XOSI	
clock	72		XOS2	
interface	73		OCOUNT	
cells	74		DLIMIT	
	75		TCOUNT	
	76		TLIMIT	
	77		DLABEL	
	100		MONITOR BUFFER INDEX	SMONIDX
	101		MERS BUFFER	MERSBUFO
	102		MERS BUFFER INDEX	MERSIOX
reserved for event logging	103		MERS ENABLED FLAGS	MERSMSKO
	104		MERS ENABLED FLAGS	MERSMSK1
	105		MERS BUFFER BANK	MERSBUFBANK
	106			
	.			
	.			
	116			
	117			

M: Interrupt has missed due to last interrupt handling.

A: Current interrupt handling active.

CHAPTER 18 MESSAGE FILES

Message File Data Structures

This chapter contains the data structures necessary to support message files. The first section details the message file's version of the familiar file system data structure; ie, the file label, file control block, access control block, etc..

The second section shows the tables used by the basic IPC mechanism which is a set of internal, MPE procedures designed to support the "boundary conditions" of IPC files. For example, signaling a no wait reader that its record has arrived. See the section's introduction for a detailed description.

File Structure

File Label/FCB Extent Map



The EOF and SDF are examples only, meant to show:

1) The start of file moves into the extent map as records are read
2) The file can wrap around and, hence, cause the SDF to be greater than the EOF.

When a file becomes empty the SOF and EOF are reset to the first block of extent zero.

Each extent is composed of a number of blocks. Extents all have the same number of blocks. Extent zero also contains space for the file label and user labels in the exact same format as standard files. Starting with block zero, sufficient blocks are allocated to the file label/user labels to satisfy their space requirements.

Extents outside of the SDF/EOF range may not exist. They are deleted at close time when there are no more writers accessing the file.

Block Structure



Separating the data portion of the records from their header enables the standard file system access procedures to read the records with no knowledge that they are msg file records.

Record Format



Length word's value does not include itself.

Header Format



C (0:1) - Set on if this was the last record written before the system crashed. This bit is set on by the first open on the file after the crash.

LC (1:1)- Valid only for close headers. Set to one if this is the last writer to close the file.

Type(8:8)- 0 data
1 open
2 close

Message Access Control Block

Notes:
1. Words/fields that do not pertain to message files are left blank.

2. This diagram shows the "combined" ACB as it appears to the message access procedures (the procedures in IPC). Thus it is a combination of the LACB and the PACB.











* Value is private to a particular accessor.

Word	Field	Description
66		Accessor's local flags.
	(0:1)	0 1 - have not yet issued an FREAD/FWRITE against the file.
	(1:1)	ex 1 - extended wait mode.
	(2:1)	nd 1 - do not destroy the next record read.
	(3:1)	vr 1 - writer has not yet written his first record (ie., he is a virgin).
	(4:1)	bt 0 - transmission log should be expressed in words. 1 - " " " " " " bytes.
	(5:1)	cls - Not currently used (reserved for group IPC standard).
	(6:1)	C - No wait completion message is in LACB area.
	(8:8)	car ctl- carriage control character to be used for the writer's record (a value of one indicates no carriage control character).

Word	Field	Description
40		File's global flags.
	(1:4)	- number of read buffers
	(5:4)	- number of write buffers
	(9:1)	er 1 - extended read
	(10:1)	qu 1 - one or more writers has been queued on the wait queue.
	(11:1)	n 1 - wait msg is located in the RCB
	(12:1)	c 1 - completion msg is located in the RCB
	(13:1)	d 1 - the current write buffer has dirty bit set
	(14:1)	s 1 - the start of file is block zero
	(15:1)	f 0 - the RCB buffers have not been filled

MMSTAT Definitions

Octal Value	Event Type	Parameter 1	Parameter 2
72/0	Read init	# free rec	
72/1	Read compl	(0:8) error, (8:8) ID	Number of records
72/2	Write init	(0:8) # rec, (8:8) ID	Number of free records
72/3	Write compl	(0:8) error, (8:8) ID	Number of free records
72/4	Control	(0:8) error, (8:8) ID	(0:4) func, (4:12) parm
72/5	EOF	(0:8) error, (8:8) ID	Number of records
72/6	Open	(0:8) error, (8:8) ID	Number of records
72/7	Close	(8:8) #free, (8:8) ID	Number of records
72/10	Initiation	0	(0:8) fix, (8:8) update
73/0	Put record	(0:8) error, (8:8) ID	(0:3) rec type, (3:13) number of records
73/1	Delete rec	(0:8) error, (8:8) ID	(0:3) rec type (3:13) number of records
73/2	Delete blk	Start of file block #	End of file block #

Notes:

1. The aa/bb notation in the "octal value" column denotes type/subtype. Type is the actual MMSTAT event number. Subtype is (0|4) of parameter 0.

2. Several items can possibly exceed their fields, in that case the bits beyond the field are lost. These items are number of records, number of free records, start of file, and end of file.

3. Parameter word zero has a common format for all the MMSTAT events.

Field	Description
(0:4)	Event's subtype.
(4:2)	File's state 0 - empty 1 - partially full 2 - only a fraction of a free record is left 3 - completely full
(6:1)	Nonzero indicates that there is one or more waiting readers.
(7:1)	Nonzero indicates that there is one or more waiting writers.
(11:1)	Nonzero indicates that the write has a carriage control character.
(12:4)	Flags local to the accessor. (12:1) - the accessor has done no FREADs/FWRITEs (13:1) - extended wait (14:1) - nondestructive read (15:1) - writer has not written any records

File System Basic IPC Definitions

The objective of this set of uncallable procedures is to provide a simple ipc mechanism to support the ipc file access procedures. It enables one process to send short, control messages to another process.

General Behavior

FCPORTOPEN Procedure

The heart of this mechanism is the port. A process desiring to receive messages would first open (create) a port. This process is termed the "port manager." When the port is created, a port number is returned to the opener. Since the port number value cannot be known in advance, potential senders need some method of obtaining the port number from the port manager.

Both the ports and the messages are contained in a single disc resident data segment. There can be a total of over thirty-five hundred open ports and outstanding messages Thus neither ports nor message blocks are scarce resources.

FCPORTSEND Procedure

This procedure sends a 0 to 5 word message to a port. Optionally a timeout value may be specified which will limit the duration the message will remain attached to the port. Expiration of the timeout causes the message to be deleted from the target port's queue and placed on the sender's reply port (specified by the sender in the FCPORTSEND procedure call).

{FCPORTRECEIVE}

Reads and deletes the head message from a port. The sender's return port number is also given to the receiver, enabling him to send a reply message.

{FCPORTCLOSE}

Demolishes the port.

{IPC file's use of this mechanism}

All open message files have two ports open for the file (read wait queue and write wait queue), plus one port per accessor (reply port). Their use is described in the following.

Reader and writer wait queues} R When an empty message file is accessed by more than one reader (share), then there must be a way of having the readers' FREADs satisfied in the same order that they were issued. That is, there must be queue of waiting readers. The ipc access procedures accomplish this by dedicating a basic ipc port as a "read wait queue." Whenever a reader's request is stalled because the file is empty, a message is sent to the read wait queue. Subsequent FREADs by other processes will queue up behind the first reader in a FIFO manner. An FWRITE will take the first entry from the wait queue and send a "read may be done" message to the reader's reply port.

In a like manner multiple writers will queue on the write wait queue when the file is full.

{Completion notification for nowait I/O}

The IOWAIT intrinsic waits for a message to be sent to the reply port (s) of the specified user files.

{Timeouts}

When an accessor encounters a boundary condition (ex, a reader accesses an empty file), it may specify that the condition must be satisfied in x seconds (FCONTROL 4). To this end the ipc access procedures merely issue the FCPORTSEND to the wait queue with the user's timeout value specified. The timeout will tear the message from the wait queue and place it on the accessor's reply port.

Port Data Structures

Port Data Segment



The chunks are a combination of free entries, ports, message queue entries, and timer list entries.

Port With Two Outstanding Messages

Port Number

0	1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16
Port index								Port data segment relative addr/8								

Port index Index into the port DST number array

Port DST Number Array

Located in System DB Extension Area.

64	Port data segment number	64
65	Reserved for a second port segment	65

Port Data Segment Global Area

0	Data segment number of this port data segment	0
1	Block size in words	1
2	Total number of blocks	2
3	Maximum number of blocks	3
4	Current number of free blocks	4
5	Number of open ports	5
6	Head of free list	6
7	Tail of free list	7
10	Head of impeded process list	8
11	Tail of impeded process list	9
12	Head of timeout thread (TQE address)	10
13	TRLX of timeout	11
14	Value returned by TIMER intrinsic when	12
15	Timeout was initiated.	13
16	Head of port list (in units of port numbers).	14
17	Not used.	15

Port

	0	1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	
D	Head MQE address																D
1	Tail MQE address																1
2	E		W		Next port number in port list thread												2
3	I	Subtype			Port Pin number												3
4	Soft interrupt parameter one																4
5	Number of MQEs in the port's queue																5
6	Number of sends to this port																6
7	Soft interrupt plabel																7
8	PIN of port's owner																10
	0	1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	

E Enable wake up bit
0 - Do not awaken the process
1 - Awaken the process

W type Action to be taken on an enabled port when a message is received.

0 - Awaken the process on a message wait bit.

1 - Generate user software interrupt

2 - Generate system software interrupt

I Interrupt mode.

Subtype Soft interrupt subtype

Message Queue Entry (MQE)



Timer entry definitions - 0 - no timeout
1 - timeout expired
2 - TLE address for a pending timeout

File System Message Files

Wait Message

parm#
0 - WRITER ID
1 - LOCAL FLAGS (differ with each accessor)
(0:1) - accessor just opened file
(1:1) - will wait on boundary condition if no symbiotic process
(3:1) - writer has not written a record
(4:1) - transmission log in bytes
(8:1) - carriage control code
2 - DST# of data buffer
3 - Address of data buffer (DST relative)
4 - Length of data buffer in bytes

Completion Message

0 - Resultant error code
1 - Resultant transmission log in bytes

Timer List Entry (TLE)



MMSTAT Definitions

Octal Value	Event Type	Parameter 0	Parameter 1	Parameter 2
62	Open	Port number	Port DST num	Flags parameter
63	Receive completion	Port number	MQE address 15:1 Waitspc	Return port
64	Send	Port number	MQE address 15:1 Q type	Return port
65	Change status	Port number	0 = enable 1 = disable	Head MQE address
66	Abort	Port number	Parameter zero	Return port
67	Close	Port number	Port DST	# open ports left
70	Expand	Port DST num	# expand blks	Total # blocks
71	Timeout expired	Port num	MQE address	Return port

CHAPTER 19 MPE MEMORY RESIDENT MESSAGE FACILITY

Overview of Facility

The memory resident message facility of MPE V addresses the need for an efficient, simple, and uniform method for system code to send short status-type messages to processes.

Each process is created with a "port" in the message harbor table (DST %71) which supports a set of message subqueues which are private to that process. There is a maximum of four subqueues per port in the initial implementation. This limit can be easily extended when new subqueues are required.

Any system code, even code running on the ICS, can send a message to any subqueue of any process. The destination process' PIN must be known, any a priori conventions on subqueue number and message formats must be established. The caller of SENDMSG may optionally specify that the destination process be awakended from a message wait.

Message can be any length up to the configured maximun. Message length is specified in the call to SENDMSG and RECEIVEMSG. In the initial implementation, messages are limited to 4 words in length. This maximun can easily be increased if the need arises.

By calling PORTSTRTUS, a process may at any time determine whether a specified subqueue is non-empty or obtain the subqueue number of the most urgent non-empty subqueue (lowest numbered one).

By calling RECEIVEMSG, a process may receive the message at the head of the specified subqueue. This receive is optionally non-destructive.

A process can wait on a message wait, or on a combination of message wait and other wait types.

Message Intrinsics

SENDMSG

```
Procedure SENDMSG(Destpin, Subqueue, MsgLength, Flags);
Value             Destpin, Subqueue, MsgLength, Flags;
Integer           Destpin, Subqueue, MsgLength;
Logical                                          Flags;
Option Privileged, Uncallable;
```

Destpin, Subqueue, and MsgLength have to be within range or a System Failure 622 will occur.

The caller of SENDMSG stacks the message contents before calling the procedure. SENDMSG expects the first msg word to be at Q-7-MsgLength, and the last msg word at Q-8. The message contents at Q-8 to Q-7-MsgLength are deleted from the top of stack by the exit from SENDMSG to the caller.

Flags.(1:1) = 1 ==> Wake-up destination process from a message wait.

Return CC = CCG if process was already awake else CC = CCE.

PORTSTRTUS

```
Logical Procedure PORTSTATUS(Subqueue);
Value                        Subqueue;
Integer                      Subqueue;
Option Privileged, Uncallable;
```

When supplied a valid subqueue number, PORTSTATUS returns a true value if the subqueue is non-empty and a false value if the subqueue is empty.

When passed a -1 a subqueue parameter, PORTSTATUS returns the subqueue number of the process' most urgent non-empty subqueue (the smaller the number, the more urgent the subqueue).

If all subqueues are empty, PORTSTRTUS returns CC = CCE. If at least one subqueue is non-empty, PORTSTRTUS returns CC = CCG.

RECEIVEMSG

```
Procedure RECEIVEMSG(Subqueue, MsgLength, Flags);
Value                Subqueue, MsgLength, Flags;
Integer              Subqueue, MsgLength;
Logical                                   Flags;
Option Privileged, Uncallable;
```

Subqueue and MsgLength has better be within range or a Systen Failure 622 will occur.

The caller of RECEIVEMSG does an RSSEMBLE(ADDS MsgLength) to make space for the message contents. RECEIVEMSG stores the message contents into Q-8, Q-9,...,Q-7-MsgLength. Q-7-MsgLength contains the first word of the message.

Flags.(0:1) ==> do not release message from head of subqueue (non destructive read).

Return CC = CCG if all subqueues were empty, else CC = CCE.

Supporting Data Structures

Message Harbor Table [DST #57 (%71)]

0	DST Index Number (%71)
1	Data Segment Size
2	Reserved
3	Maximun number of PINS + 1
4	Maximum Msg Size (6)
5	Reserved
6	Message Pool Head Pointer
7	Message Pool Tail Pointer
8	Available Msg Frames Count
9	Head of impeded queue
10	Tail of impeded queue
11	Reserved
13	Ports (16 words each) (8 for header + 2 link words for each of 4 subqueues)
	Messages (6 words each) (2 for header + 4 for data)

CHAPTER 20 MMSTRTS EVENTS

MMSTATS Catalog Index

MMSTRT CRTRLOG INDEX

MMSTRT Event Group 0 (Memory Management Events)

Event 0

EVENT NAME: QONSEG
DESCRIPTION: ABSENCE TRAP ON CODE/DATA SEGMENT

CALLING MODULE: KERNELC
CALLING PROCEDURE(S): QUEUEDNSEGMENT

PARAMETER DESCRIPTION

P1,P2 = Segment Identifier

P1.(0:4) = Segment type field
- 0 => Data Segment
- 1 => SL Segment
- 2 => Program Segment
- 3 => Cache Domain

P1.(4:12) = Program index into CSTBLK (type 2 only)

P2 = Segment Number

P3 = SLL Pointer (SLL table relative)

P4 = STATUS (in stack marker) of calling (trapping) segment

P5,P6 - Unused.

Event 1

EVENT NAME: MAKEOC
DESCRIPTION: MAKE SEGMENT AN OVERLAY CANDIDATE - RELEASE SEGMENT TO THE POOL OF AVAILABLE SPACE

CALLING MODULE: KERNELC
CALLING PROCEDURE: MAKEOC

PARAMETER DESCRIPTION

P1,P2 = Segment Identifier

P1.(0:4) = Segment type field
0 => Data Segment
1 => SL Segment
2 => Program Segment
3 => Cache Domain

P1.(4:12) = Program index into CSTBLK (type 2 only)

P2 = Segment Number

P3 = Bank of region
P4 = Address of region

P5,P6 - Unused.

Event 2

EVENT NAME: SPECIALRQ
DESCRIPTION: REQUEST OF SEGMENT EXPANSION/CONTRACTION, UNLOCK, UNFREEZE, IOUNFREEZE, LOCK, IOFREEZE, FREEZE

CALLING MODULE: KERNELC, KERNELD, ININ
CALLING PROCEDURES: UNLOCKSEG', IOFREEZE', FETCHSEGMENT-(KERNELC)
DLSIZE, ZSIZE, GETPXSEG, ALTDSEGSIZE,
RLTPXFILESIZE -(KERNELO)
STACKOVERFLOW -(ININ)

PARAMETER DESCRIPTION

P1,P2 = Segment Identifier

P1.(0:4) = Segment type Field
0 => Data Segment
1 => SL Segment
2 => Program Segment
3 => Cache Domain

P1.(4:12) = Program index into CSTBLK (type 2 only)

P2 = Segment Number

P3 = .(0:1) =1 => Request is through FETCHSEGMENT (types 0,1,2)
.(12:4) Type of request
= 0=> IOFREEZE
= 1=> FREEZE
= 2=> LOCK
= 3=> IOUNFREEZE
= 4=> UNFREEZE
= 5=> UNLOCK
= 6=> DLSIZE EXPANSION
= 7=> DLSIZE CONTRACTION
= 8=> PXFIXED EXPANSION
= 9=> PXFILE EXPANSION
= 10=> PXFILE CONTRACTION
= 11=> XDS EXPANSION
= 12=> XDS CONTRACTION
= 13=> ZSIZE EXPANSION
= 14=> ZSIZE CONTRACTION
= 15=> STACKOVERFLOW

P4 = For types (P3.(12:4))
= 0,2,3,5 => P4.(8:8) = LOCK OR IOFREEZE COUNT
= 1,4 => P4.(0:8) = FREEZE COUNT
= 6-15 => REQUESTED SIZE OF ARER IN WORDS

P5,P6 - Unused.

Event 4

EVENT NAME: FETCHSEG
DESCRIPTION: SEGMENT REQUEST (FOR I/D SYSTEM OR PROCESS)

CALLING MODULE: KERNELC
CALLING PROCEDURE: FETCHSEGMENT

PARAMETER DESCRIPTION

P1,P2 = Segment Identifier

P1.(0:4) = Segment type field
0 => Data Segment
1 => SL Segment
2 => Program Segment
3 => Cache Domain

P1.(4:12) = Program index into CSTBLK (type 2 only)

P2 = Segment Number

P3 = Requester ID
.(0:1) = 1 => I/D System request
.(1:15) = Ldev #
.(0:1) = 0 => Process request
.(1:15) = Pin # of requesting process

.(1:1) = 1 => IOFREEZE REQUEST
.(2:1) = 1 => BLOCKED LOCK REQUEST
.(3:1) = 1 => LOCK REQUEST
.(4:1) = 1 => FREEZE REQUEST

P4= .(13:3)= 0 => Segment already present
= 1 => Segment is Recover Overlay Candidate
= 2 => Segment already on its way in for someone (Segment In Motion In)
= 3 => Segment not present -- must fetch (Full fetch)

P5,P6 - Unused.

Event 5

EVENT NAME: SEGID
DESCRIPTION: MEMORY MANAGEMENT READ/WRITE OF SEGMENT FROM/TO DISC QUEUED

CALLING MODULE: KERNELC
CALLING PROCEDURES: PROCESSINITMSG, STARTSEGWRITE

PARAMETER DESCRIPTION

P1,P2 = Segment Identifier

P1.(0:4) = Segment type field
0 => Data Segment
1 => SL Segment
2 => Program Segment
3 => Cache Domain

P1.(4:12) = Program index into CSTBLK (type 2 only)

P2 = Segment Number

P3 = Disc Request Index - (DRQ Table relative)

P4 = .(0:1) = 1 => WRITE START
= 0 => READ START
.(1:15)= Ldev #

P5,P6 - Unused.

Event 6

EVENT NAME: SIODONE
DESCRIPTION: MEMORY MNRGEMENT SEGMENT READ/WRITE FRDM/TO DISC COMPLETE

CALLING MODULE: KERNELC
CALLING PRDCEDURES: SEGREADCDMPLETOR, SEGWRITECOMPLETOR

PARAMETER DESCRIPTION

P1,P2 = Segment Identifier

P1.(0:4) = Segment type field
0 => Data Segment
1 => SL Segment
2 => Program Segment
3 => Cache Domain

P1.(4:12) = Program index into CSTBLK (type 2 only)

P2 = Segment Number

P3 = Disc Request Index (ORQ Table relative)
P4 = .(0:1) = 1 => Write complete
= 0 => Read complete

P5,P6 - Unused.

Event 7 (%7)

EVENT NAME: CGARBAGE
EVENT DESCRIPTION: GARBAGE CDLLECTIDN NRS JUST TAKEN PLACE

CALLING MODULE: KERNELC
CALLING PROCEDURE: COLLECTGARBAGE

PARRMETER DESCRIPTION

P1 = BRNK OF SOURCE JUST MOVED FRDM
P2 = RDDR OF SOURCE JUST MOVED FRDM
P3 = MOVEPAGECNT, NUMBER DF PAGES JUST MOVED FRDM
P4,P5,P6 - Unused.

Event 8 (%10)

EVENT NRME: SWAPIN
DESCRIPTION: SWAP IN A PROCESS

CRLLING MODULE: KERNELC
CALLING PROCEDURE: SWAPIN

PARAMETER DESCRIPTION

P1 = PIN OF PRDCESS BEING SWAPPED IN
P2 = .(0:1) = 0 => BEING SWRP
= 1 => END SWAP
.(1:1) = 0 => NORMRL (PRRTIRL SWAP DK)
= 1 => SWRP REQUIRED
.(12:4)= 0 => PROCESS SWRPIN COMPLETE
2 => ND ROOM, NARD REQ MAY SUCCEED
3 => ND ROOM, NARD REQ FAILED
4 => SWRPIN STOPPED - MORE URGENT ACTIVITY
8 => NO LOCK SPACE
P3 = HRRDREQUEST = TRUE => NRRO REQUEST ON SWRPIN
FALSE=> NORMRL

P4,P5,P6 - Unused.

MMSTAT Event Group 1 (Memory Manager)

Event 12 (%14)

EVENT NRME: RLLOCMEM
DESCRIPTION: FOUND A NOLE FOR A SEGMENT REPLACEMENT REQUEST

CRLLING MDDULE: KERNELC
CALLING PRDCEDURE: RESERVEREGION

PARAMETER DESCRIPTION

P1 = REQUESTED SIZE IN PAGES
P2 = BANK DF SELECTED REGION
P3 = ADDRESS OF SELECTED REGIDN
P4,P5,P6 - Unused.

Event 13 (%15)

EVENT NAME: DEALLDCM
DESCRIPTION: RELEASE REGION OF MEMORY TO AVAILABLE STATUS

CRLLING MDDULE: KERNELC
CALLING PRDCEDURE: RELEASEREGIDN

PARAMETER DESCRIPTION

P1 = SIZE RELERSED IN PAGES
P2 = BANK DF RELEASED REGION BRSE
P3 = RDDRESS OF RELEASED REGION BASE
P4,P5,P6 - Unused.

Event 14 (%16)

Event Name: CRCHEMOV
Description: R cache move (i.e. logical disc request) has just completed.
Calling Module: CACHESEG
Calling Procedure: ProcessCDTLogReqQue

Parameter Description

P1,P2 = Segment identifier of target DST (LDR'BUFOST)
P2.(0:1) = 1 then this is a stack.
P3 = Mapped Domain CDT entry number
P4 = Transfer count
P5,P6 = Unused

Event 15 (%17)

Event Name: GET_CDT
Description: Called when an entry in the CDT table is obtained or released.
Calling Module: CRCHESEG
Calling Procedures: Get'CDT'Entry, CDT'Free'Entry, CDT'Get'MD'Entry, CDT'Rel'MD'Entry

Parameter Description

P1 = CDT entry number
P2 = Type of call
0 = Free entry
1 = Get entry
2 = Get Mapped Domain entry
3 = Release Mapped Domain entry
P3 = If P2=3 then Ldev Entry number
P4,P5,P6 Not used.

Event 16 (X20)

Event Name: QUE_LDR
Description: Called when an LDR is queued onto the CDT
Calling Module: CACHESEG
Calling Procedure: CDT'Queue'LDR

Parameter Description

P1 = Mapped Domain CDT entry number
P2 = LDR entry index to be Queued
P3 = Queue type
X12 - CDT impeded queue
X13 - CDT active queue
P4,P5,P6 Not used.

Event 17 (X21)

Event Name: DQUE_LDR
Description: Called when an LDR is removed from the CDT queue.
Calling Module: CACHESEG
Calling Procedure: CDT'Dequeue'LDR

Parameter Description

P1 = Mapped Domain CDT entry number
P2 = LDR entry index being removed from the queue
P3 = Queue type
X12 - CDT impeded queue
X13 - CDT active queue
P4,P5,P6 Not used.

Event 18 (X22)

Event Name: FIND_DE
Description: Called when need to find an assigned CDT
Device entry.
Calling Module: CACHESEG
Calling Procedure: CDT'Find'DE

Parameter Description

P1 = Ldev number of the CDT Device entry to be found.
P2 = CDT Device entry
P3,P4,P5,P6 Not used.

MMSTAT Event Group 2

Event -20 (-X24)

EVENT NAME: ALCSTBLK
DESCRIPTION: REQUEST TO RESERVE A BLOCK OF ENTRIES IN THE CSTX

CALLING MODULE: KERNELD
CALLING PROCEDURE: ALCSTBLOCK

PARAMETER DESCRIPTION

P1=EIX CST BLOCK INDEX ASSIGNED
P2=CSTX DST RELATIVE INDEX OF WORD 0
OF THE FIRST RESERVED CSTX ENTRY
P3=N NUMBER OF CSTX ENTRIES RESERVED
P4,P5,P6 - Unused.

Event -21 (X25)

EVENT NAME: DEALCSTBLK
DESCRIPTION: INDICATES THAT A CST EXTENSION BLOCK HAS BEEN
DEALLOCATED

CALLING MODULE: KERNELD
CALLING PROCEDURE: DEALCSTBLOCK

PARAMETERS PARAMETER DESCRIPTION

P1=EIX CST BLOCK INDEX ASSIGNED
TO THE BLOCK OF CST ENTRIES
P2=CSTX DST RELATIVE INDEX OF WORD 0
OF THE FIRST CST ENTRY TO BE
RELEASED
P3=NCHT =(#ALLOCATED CSTX ENTRIES-
#ENTRIES BEING RELEASED)*4
P4,P5,P6 - Unused.

Event -23 (-X27)

EVENT NAME:RELRESOURCES
DESCRIPTION: RESOURCES (VDS,MAIN MEMDAV, ST ENTRY) RESERVED FOR THE
FOR THE SEGMENT HAVE BEEN RELEASED

CALLING MODULE: KERNELD

CALLING PROCEDURE: RELDRTASEG

PARAMETERS PARAMETER DESCRIPTION

P1=NEW OB DST NUMBER
P2=DELTA P AT EXCHANGEDB CALL

P3=STATUS AT EXCHANGEDB CALL
P4,P5,P6 - Unused.

MMSTAT Event Group 3

(NOT CURRENTLY ASSIGNED)

MMSTAT Event Group 4 (Scheduling)

Event 40 (X50)

EVENT NAME: QUIESCE
DESCRIPTION: PROCESS SWITCH - STATE OF PROCESS SAVED

CALLING MODULE: KERNELC
CALLING PROCEDURE: DSP

PARAMETER DESCRIPTION

P1 = PCB00(CPCB)
.(0:1) = 1 => SRR - SCHEDULING ATTENTION REQUIRED
.(2:1) = 1 => CRIT - PROCESS IS CRITICAL
.(3:1) = 1 => NSIR - PROCESS HAS SIR
.(4:1) = 1 => PIOVR - PENDING PI, PROCESS CRITICAL
.(5:1) = 1 => NSPRI - HOLD SIR PRIORITY
.(6:1) = 1 => IPEXP - INCORE PROTECT EXPIRED
.(7:1) = 1 => PC - PREEMPT CAPABILITY
.(8:1) = 1 => MP - MUST PREEMPT
.(9:1) = 1 => LW - LONG WAIT
.(10:1)= 1 => SW - SHORT WAIT
.(11:1)= 1 => TRW - TERMINAL READ WAIT
.(12:1) =1 => USEDD - USED A QUANTUM SINCE TRANSACTION
BEGAN
.(13:1)= 1 => NIPRI - HOLD IMPEDED PRIORITY
.(14:1)= 1 => ALLOW SOFT INTERRUPTS EVEN THOUGH IN
SYSTEM CODE
.(15:1)= 1 => RITBK - PROCESS IN RIT BREAK

P2 = PCB04(CPCB)
.(0:1) = 1 => M - MOUNING WAIT
.(1:1) = 1 => RG - GLOBAL RIN WAIT
.(2:1) = 1 => RL - LOCAL RIN WAIT
.(3:1) = 1 => MA - MAIL WAIT
.(4:1) = 1 => BID - BLOCKED IO WAIT
.(5:1) = 1 => IO - IO WAIT
.(6:1) = 1 => UCP - UCOP WAIT, RIT WAIT
.(7:1) = 1 => JNK - JUNK WAIT
.(8:1) = 1 => TIM - TIMER WAIT
.(9:1) = 1 => INT - INTERRUPT WAIT
.(10:1)= 1 => SON - SON WAIT
.(11:1)= 1 => FA - FATHER WAIT
.(12:1)= 1 => IMP - PROCESS WAITING TO UNIMPEDED
.(13:1)= 1 => SIR - PROCESS WAITING FOR SIR
.(14:1)= 1 => TIM - PROCESS WAITING FOR TIME OUT
.(15:1)= 1 => MEM - PROCESS WAITING FOR MEMORY

P3 = PCB13(CPCB)
.(0:1) = 1 => DISPQ - PROCESS ON DISPATCHING QUEUE

.(1:1) = 1 => L SCHEDULING CLASS
.(2:1) = 1 => C SCHEDULING CLASS
.(3:1) = 1 => D SCHEDULING CLASS
.(4:1) = 1 => E SCHEDULING CLASS
.(5:1) = 1 => INTER- PROCESS IS INTERRCTIVE
.(6:1) = 1 => CORER- PROCESS IS CORE-RESIDENT
.(8:8) = PROCESS' SCHEDULING PRIORITY

P4,P5,P6 - Unused.

MMMSTAT Event Group 5

(SEE CHAPTER 18 FOR THESE EVENTS)

MMSTAT Event Group 6 (FILESYS)

THESE EVENTS ARE FOR DEVELOPMENT USE ONLY AND ARE NOT NORMALLY ENABLED

Event -60(X74)

EVENT NAME: FOPEN
DESCRIPTION: OLD FILE OPEN

CALLING MODULE: FILEACC

CALLING PROCEDURE: FOPENDA

PARAMETERS PARAMETER DESCRIPTION

P1= FILE # (0:2)=2 -> NON-SPOOLER ACCESS
(0:2).NE.2 ->

P2= AOPTIONS SEE INTRINSICS MANUAL
P3= FILE LABEL FOPTIONS SEE INTRINSICS MANUAL
P4= RECORD SIZE
P5= FILE LABEL BLOCK SIZE
P6= # OF BUFFERS

Event -61(X75)

EVENT NAME: FOPEN'
DESCRIPTION: OLD FILE OPEN (CONTINUATION OF EVENT -60)

CALLING MODULE: FILEACC

CALLING PROCEDURE: FOPENDA

PARAMETERS PARAMETER DESCRIPTION

P1= FILE LABEL FILE LIMIT MSW

P2= FILE LABEL FILE LIMIT LSW

P3= FILE LABEL # OF EXTENTS

P4-P6 unused

Event -60(X74)

EVENT NAME: FOPEN
DESCRIPTION: NEW DISC FILE OPEN

CALLING MODULE: FILEACC

CALLING PROCEDURE: FOPEN

PARAMETERS PARAMETER DESCRIPTION

P1= FILE # (0:2)=2 -> NON-SPOOLER ACCESS
(0:2).NE.2 ->
P2= AOPTIONS SEE INTRINSICS MANUAL

P3= FOPTIONS SEE INTRINSICS MANUAL

P4= RECORD SIZE

P5= BLOCK SIZE

P6= # OF BUFFERS

Event -61(X75)

EVENT NAME: FOPEN'
DESCRIPTION: NEW DISC FILE OPEN (CONTINUATION OF EVENT -60)

CALLING MODULE: FILEACC

CALLING PROCEDURE: FOPEN

PARAMETERS PARAMETER DESCRIPTION

P1= FCB FILE LIMIT

P2= FCB MAX # EXTENTS

P3= (0:8)= INITIAL ALLOCATION EXTENTS

P4-P6 unused

Event -62(X76)

EVENT NAME: FREAD
DESCRIPTION:

CALLING MODULE: FILEIO

CALLING PROCEDURE: FREAD

PARAMETERS	PARAMETER DESCRIPTION
P1= FILE #	
P2= ACBTLOG	TRANSFER COUNT
P3= FLAGS	(15:1) Buffer hit flag

Event -63(X77)

EVENT NAME: FWRITE
DESCRIPTION:

CALLING MODULE: FILEIO

CALLING PROCEDURE: FWRITE

PARAMETERS	PARAMETER DESCRIPTION
P1= FILE #	
P2= TCOUNT	SEE INTRINSIC MANUAL
P3= FLAGS	(15:1) Buffer hit flag

Event -64(X100)

EVENT NAME: FREADDIR
DESCRIPTION:

CALLING MODULE: FILEIO

CALLING PROCEDURE: FREADDIR

PARAMETERS	PARAMETER DESCRIPTION
P1= FILE #	
P2= ACBTLOG	TRANSFER COUNT
P3= FLAGS	(15:1) Buffer hit flag
P4= REC #	MSW
P5= REC #	LSW
P6= NOT USED	

Event -65(X101)

EVENT NAME: FWRITEDIR
DESCRIPTION:

CALLING MODULE: FILEIO

CALLING MODULE: FWRITEDIR

PARAMETERS	PARAMETER DESCRIPTION
P1= FILENUM	
P2= TCOUNT	See Intrinsic manual
P3= FLAGS	(15:1) Buffer hit flag
P4= REC #	MSW
P5= REC #	LSW
P6= NOT USED	

Event -66(X102)

EVENT NAME: FUPDATE
DESCRIPTION:

CALLING MODULE: FILEIO

CALLING PROCEDURE: FUPDATE

PARAMETERS	PARAMETER DESCRIPTION
P1= FILE #	
P2= TCOUNT	See Intrinsic manual
P3= FLAGS	(15:1) Buffer hit flag
P4-P6 not used	

Event -67(X103)

EVENT NAME: IOWAIT
DESCRIPTION:

CALLING MODULE: FILEIO

CALLING PROCEDURE: IOWAIT

PARAMETERS	PARAMETER DESCRIPTION
P1= FILE #	
P2= ACBTLOG	TRANSFER COUNT
P3= FLAGS	(15:1) buffer hit flag

Event -68(Z104)

EVENT NAME: FREADSEEK
DESCRIPTION:

CALLING MODULE: FILEIO

CALLING PROCEDURE: FREADSEEK

PARAMETERS	PARAMETER DESCRIPTION
P1= FILE #	
P2= FLAGS	(15:1) buffer hit flag
P3= REC #	MSW
P4= REC #	LSW
P5-P6 not used	

Event -69 (Z105)

EVENT NAME: FSPACE
DESCRIPTION:

CALLING MODULE: FILEIO

CALLING PROCEDURE: FSPACE

PARAMETERS	PARAMETER DESCRIPTION
P1= FILE #	
P2= DISPLACEMENT	SEE INTRINSIC MANUAL
P3-P6	not used

MMSTAT Event Group 7 (FILESYS)

THESE EVENTS ARE FOR DEVELOPMENT USE ONLY AND ARE NOT NORMALLY ENABLED

Event -70 (Z106)

EVENT NAME: FPOINT
DESCRIPTION:

CALLING MODULE: FILEIO

CALLING PROCEDURE: FPOINT

PARAMETERS	PARAMETER DESCRIPTION
P1= FILE #	
P2= REC #	MSW
P3= LSW	LSW
P4-P6	not used

Event -71 (Z107)

EVENT NAME: FCONTROL
DESCRIPTION:

CALLING MODULE: FILEIO

CALLING PROCEDURE: FCONTROL

PARAMETERS	PARAMETER DESCRIPTION
P1= FILE #	
P2= CODE	See Intrinsics manual
P3-P6	not used

Event -72 (Z110)

EVENT NAME: FSETMODE
DESCRIPTION:

CALLING MODULE: FILEIO

CALLING PROCEDURE: FSETMODE

PARAMETERS	PARAMETER DESCRIPTION
P1= FILE #	
P2= MODEFLAGS	SEE INTRINSIC MANUAL
P3-P6	not used

Event -74 (Z112)

EVENT NAME: FCHECK
DESCRIPTION:

CALLING MODULE: FILEIO

CALLING PROCEDURE: FCHECK

PARAMETERS	PARAMETER DESCRIPTION
P1= FILE #	
P2= ERRORCODE	SEE INTRINSIC MANUAL
P3-P6	not used

Event -75 (Z113)

EVENT NAME: FGETINFO
DESCRIPTION:

CALLING MODULE: FILEIO

CALLING PROCEDURE: FGETINFO

PARAMETERS	PARAMETER DESCRIPTION
P1= FILE #	
P2= FOPTIONS	SEE INTRINSIC MANUAL
P3= AOPTIONS	SEE INTRINSIC MANUAL
P4-P6	not used

Event -76 (Z114)

EVENT NAME: FREADLABEL
DESCRIPTION:

CALLING MODULE: FILEIO

CALLING PROCEDURE:

PARAMETERS	PARAMETER DESCRIPTION
P1= FILE #	
P2= TCOUNT	SEE INTRINSIC MANUAL
P3-P6	unused

Event -77 (X115)

EVENT NAME: FWRITELABEL
DESCRIPTION:

CALLING MODULE: FILEIO

CALLING PROCEDURE: FWRITELABEL

PARAMETERS	PARAMETER DESCRIPTION
P1= FILE #	
P2= TCOUNT	SEE INTRINSIC MANUAL
P3-P6	unused

Event -78 (X116)

EVENT NAME: FLOCK
DESCRIPTION:

CALLING MODULE: FILEID

CALLING PROCEDURE: FLOCK

PARAMETERS	PARAMETER DESCRIPTION
P1= FILE #	
P2= LOCKCOND	See Intrinsics manual
P3= COND CODE	" " " "

Event -79 (X117)

EVENT NAME: FUNLOCK
DESCRIPTION:

CALLING MODULE: FILEIO

CALLING PROCEDURE: FUNLOCK

PARAMETERS	PARAMETER DESCRIPTION
P1= FILE #	
P2-P6	unused

MMSTAT Event Group 8

Event -80 (X120)

EVENT NAME: FRENAME
DESCRIPTION:

CALLING MODULE: FILEACC

CALLING PROCEDURE: FRENAME

PARAMETERS	PARAMETER DESCRIPTION
P1= FILE #	
P2-P6	unused

Event -81 (X121)

EVENT NAME: FCLOSE
DESCRIPTION:

CALLING MODULE: FILEACC

CALLING PROCEDURE: FCLOSE

PARAMETERS	PARAMETER DESCRIPTION
P1= FILE #	
P2= DISP	See Intrinsic manual
P3= SECCODE	
P4-P6	unused

Event 83 (X123)

Event Name: STRRTEGY
Description: Called to determine the type of strategy used
based on who the caller of CDT'ATTACHIO is.
Calling Module: CACHESEG
Calling Procedure: CDT'STRATEGY

Parameter Description

P1 = CDT Mapped Domain entry
P2 = LDR entry index
P3 = Strategy
- 0 - Unknown caller
- 1 - Unknown from File System
- 2 - Spooler
- 3 - Directory
- 4-7 - Unknown
- 8 - Cenmessage
- 9 - File System, Quiesce I/O
- 10 - File System, sequential, NOBUF
- 11 - File System, direct, NOBUF
- 12 - File System, sequential, BUF
- 13 - File System, direct, BUF
- 14 - File System, KSRM
- 15 - File System, INRGE

P4,P5,P6 Not used.

Event 84 (X124)

Event Name: INITIATE
Description: Called when starting/completing logical disc request.
Calling Module: CACHESEG
Calling Procedures: CDT'Initiator, CDT'Completor

Parameter Description

P1 = CDT Mapped Domain entry number
P2 = LDR entry index
P3 = type
0 = Initiator
1 = Completor
P4,P5,P6 Not used.

Event 86 (X126)

Event Name: CDT_RTT
Description: Called from CDT'ATTACHIO.
Calling Module: CACHESEG
Calling Procedure: CDT'Attachio

Parameter Description

P1 = Ldev
P2 = Function
P3 = Flags
P4,P5 = Parm1, Parm2
P6 = Count

Event 87 (X127)

Event Name: MAP_DOM
Description: Called when need to "map" a disc domain.
Calling Module: CACHESEG
Calling Procedure: CDT'MAP'CACHED'DOMAIN

Parameter Description

P1 = New CDT entry number
P2 = Returned CDT entry
P3,P4,P5,P6 Not used.

Event 88 (X130)

Event Name: UN_MAP_RG
Deecription: Called when disc domain no longer napped. (i.e. both the logical and physical I/O ie complete).
Calling Module: CACHESEG
Calling Procedure: CDT'MAP'CACHED'REGION

Parameter Description

P1 = CDT Ldev entry number
P2 = Region CDT entry number
P3,P4,P5,P6 Not used.

Event 89 (X131)

Event Name: LINK_REG
Description: Called when a disc domain gets linked into the linked list of domains for an ldev.
Calling Module: CACHESEG
Calling Procedure: LINK'CACHED'REGION,UNLINK'CACHED'REGION

Parameter Description

P1 = Type
0 = Link
1 = Unlink
P2,P3 = Address of region base
P4 = CDT entry number found in the header
P5 = # of pages
P6 Not used.

MMSTAT Event Group 9 (Disc I/O Requests)

Event 90 (X132)

Event Name: REQCRCHE
Description: Called to see if caching will accept this I/O request.
Calling Module: CACHESEG
Calling Procedure: REQUEST'CRCHE

Parameter Description

P1 = LDR entry index
P2,P3,P4,P5,P6 Not used.

Event -98 (X142)

EVENT NAME: DISK TRAFFIC
DESCRIPTION: DISC I/O REQUEST HAS BEEN QUEUED

CALLING MODULE: HARDRES

CALLING PROCEDURE: RTTACHIO

PARAMETERS	PARAMETER DESCRIPTION
P1=CNT	DATA TRANSFER COUNT:WORDS IF >0; BYTES IF <0
P2=FLAGS.(0:4)	
P3=FNCT	=0 ==>READ =1 ==>WRITE =2 ==>OPEN FILE =3 ==>CLOSE FILE =4 ==>CLOSE DEVICE

MMSTAT Event Group 10

Event 100 (X144)

EVENT NAME: DISK ERROR
DESCRIPTION: RECORD DISC ERROR

CALLING MODULE: IOFDISC1

CALLING PROCEDURE: FHDDVR

PARAMETERS	PARAMETER DESCRIPTION
P1=DIPT(DSTAT)	HARDWARE STATUS
P2=SO	QMISC
P3=IOQP(QLDEV).QLDEVN LOR STDCOUNT&LSL(8))	=LDEV/SIO PROGRAM COUNTER

Event 101 (X145)

EVENT NAME: DISK ERROR
DESCRIPTION: RECGRD DISC ERROR

CALLING MODULE: IOMDISCD

CALLING PROCEDURE: MHDDVR

PARAMETERS	PARAMETER DESCRIPTION
P1=DIPT(DSTAT)	HARDWARE STATUS
P2=SO	QMISC
P3=IOQP(QLDEV).QLDEVN LOR STDCOUNT&LSL(8))	=LDEV/SIO PROGRAM COUNTER

MMSTAT Event Group 11

Event -110 (X156)

EVENT NAME: START I/O
DESCRIPTION:DRIVER INITIATOR FOR SIO DEVICE HAS BEEN CALLED

CALLING MODULE: HARDRES

CALLING PROCEDURE: SIODM

PARAMETERS PARAMETER DESCRIPTION

P1=IOQPL(QSTAT) LOR IOQPL(QLDEV).LDEVN
=(0:8) PCB ENTRY # OF PROCESS MAKING REQUEST
(8:8) LOGICAL DEVICE NUMBER OF DEVICE FOR I/O
P2=IOQP(QWBCT)=WORD COUNT IF>0;BYTE COUNT IF<0
P3=(0:2) = FUNCTION CODE SPECIFIED BY DRIVER

= 0 => READ
= 1 => WRITE
= 2 => CONTROL

=(6:10)= DSTN OF TARGET DATA SEG

Event -111 (X157)

EVENT NAME: I/O COMPLETION
DESCRIPTION: SIO COMPLETION

CALLING MODULE: HARDRES

CALLING PROCEDURE: SIODM

PARAMETERS PARAMETER DESCRIPTION

P1=IOQP(QLDEV).LDEVN=LOGICAL DEVICE NUMBER OF
DISC INVOLVED IN TRANSFER
P2=IOQP(QPAR1) (DEFINED BY DRIVER)
P3=IOQP(QPAR2) (DEFINED BY DRIVER)

MMSTAT Event Group 12

Event 120 (X170)

EVENT NAME: SOFT'DEATH
DESCRIPTION: BUG CATCHER

CALLING MODULE: HARDRES

CALLING PROCEDURE: SOFT'DEATH

PARAMETERS	PARAMETER DESCRIPTION
P1	SOFT'DEATH I.D. NUMBER
P2	CALLERS STATUS REGISTER
P3	CALLERS DELTA P

Event 125 (X175)

EVENT NAME: IOBUFTAP
EVENT DESCRIPTION: IOSYSTEM BUFFER TRAP

CALLING MODULE: HARDRES
CALLING PROCEDURE: SIODM

PARAMETER DESCRIPTION

P1 = IOQP
P2 = IOQP(QDSTN).DSTN = DST NUMBER OF BUFFER
P3 = 0

MMSTAT Event Group 13

Event 139 (X213)

Event Name: C_ABSENT
Description: Either the mapped disc domain or the target
DST was absent when a cache move was attempted.
Calling Module: CACHESEG
Calling Procedure: PROCESSCDTLOGREQQUEUE

Parameter Description

P1 = 0 Mapped Domain absent
P2 = Pin
P3,P4 = Segment identifier of Mapped Domain
P5,P6 Not used.

P1 = LDR entry index (DST not present)
P2 = Pin
P3,P4 = Segment identifier of DST (P4.(0:1) = 1 stack)
P5,P6 Not used.

MMSTAT Event Group 14 (CS/3000)

Event 140 (X214)

EVENT NAME: COPEN
DESCRIPTION:

CALLING MODULE: COMSYS2

CALLING PROCEDURE: COPEN

PARAMETERS PARAMETER DESCRIPTION

P1 (0:8) = CS ERROR CODE
(8:8) = LOGICAL DEVICE NUMBER

P2 PMAP1

P3 PMAP2

Event 142 (X216)

EVENT NAME: CABORTIO
DESCRIPTION:

CALLING MODULE: COMSYS1

CALLING PROCEDURE: CABORTIO

PARAMETERS PARAMETER DESCRIPTION

P1 LOGICAL DEVICE

A2 IOQINDEX

P3 0

Event 144 (X220)

EVENT NAME: CSIOWAIT
DESCRIPTION:

CALLING MODULE: COMSYS1

CALLING PROCEDURE: CSIOWAIT

PARAMETERS PARAMETER DESCRIPTION

P1 (0:8) = CS ERROR CODE
(8:8) = LOGICAL DEVICE NUMBER

P2 TRANSMISSION LOG

P3

Event 146 (X222)

EVENT NAME: CCLOSE
DESCRIPTION:

CALLING MODULE: COMSYS3

CALLING PROCEDURE: CCLOSE

PARAMETERS PARAMETER DESCRIPTION

P1 (0:8) = CS ERROR CODE
(8:8) = LOGICAL DEVICE NUMBER

P2 LINE NUMBER

P3 0

Event 147 (X223)

EVENT NAME: CREAD
DESCRIPTION:

CALLING MODULE: COMSYS4

CALLING PROCEDURE: CREAD

PARAMETERS PARAMETER DESCRIPTION

A1 (0:8) = CS ERROR CODE
(8:8) = LOGICAL DEVICE NUMBER

A2 INCOUNT

P3 STATION

Event 149 (X225)

EVENT NAME: CWRITE
DESCRIPTION:

CALLING MODULE: COMSYS4

CALLING PROCEDURE: CWRITE

PARAMETERS AARRMETER DESCRIPTION

P1 (0:8) = CS ERROR CODE
(8:8) = LOGICAL DEVICE NUMBER

P2 OUTCOUNT

P3 INCOUNT

MMSTAT Event Group 15 (CS/3000)

Event 150 (X226)

EVENT NAME: CSDRIVER
DESCRIPTION:

CALLING MODULE: BSCLCM

CALLING PROCEDURE: CSDRIVER

PARAMETERS PARAMETER DESCRIPTION

P1 TIMER LSW

P2 CURRENTSTATE WHERE THE DRIVER IS IN THE STATE TRANSITION TABLE

P3 CURRENTEVENT (0:8) = CURRENT EVENT
(8:8) = LOGICAL DEVICE
WHAT CAUSED THE DRIVER TO BECOME ACTIVE

Event 152 (X230)

EVENT NAME: CCONTROL
DESCRIPTION

CALLING MODULE: COMSYS5

CALLING PROCEDURE: CCONTROL

AARAMETERS PARAMETER DESCRIPTION

A1 (0:8) = CS EPROR CODE
(8:8) = LOGICAL DEVICE NUMBER

A2 CONTROL CODE

P3 PARAMETER

Event 153 (X231)

EVENT NAME: COPENTRACEFILE
DESCRIPTION:

CALLING MODULE:

CALLING PROCEDURE: COPENTRACEFILE

PARAMETERS	PARAMETER DESCRIPTION
P1	(0:8) = CS ERROR CODE (8:8) = LOGICAL DEVICE NUMBER
P2	CTRACEINFO
P3	0

Event 154 (X232)

EVENT NAME: CCLOSETRACEFILE
DESCRIPTION:

CALLING MODULE:

CALLING PROCEDURE: CCLOSETRACEFILE

PARAMETERS	PARAMETER DESCRIPTION
P1	(0:8) = CS ERROR CODE (8:8) = LOGICAL DEVICE NUMBER
P2	0
P3	0

Event 155 (X233)

EVENT NAME: CPOLLIST
DESCRIPTION:

CALLING MODULE:

CALLING PROCEDURE: CPOLLIST

PARAMETERS	PARAMETER DESCRIPTION
P1	LOGICAL DEVICE
P2	CS ERROR CODE
R3	PMAP

MMSTAT Event Group 16

Event 160 (X240)

EVENT NAME: CREAD
DESCRIPTION:

CALLING MODULE: OSMON

CALLING PROCEDURE:

PARAMETERS	PARAMETER DESCRIPTION
P1=	TIME STAMP
P2=	(0:4) NOT USED (4:1) BLOCK (5:2) STATE (7:3) MENT (10:1) :=0 INITIALIZATION EVENT :=1 COMPLETION EVENT (11:5) SUB EVENT NUMBER
P3=	DEPENDS ON THE SUB EVENT NUMBER AND IF IT IS AN INITIALIZATION OR COMPLETION EVENT. MSG: (0:4) STRATYPN (4:6) MSG CLS (10:16) STRNTYP

SUB EVENT NO.	SUB EVENT NAME	INIT PRAM	COMP PRAM
0	CREAD	0	LEN
1	CWRITE	N MSG	LEN
2	IOWAIT	0	LEN
3	CCHECK	0	ERRCOD
4	OSRTTN	0	0
5	OSWC	N MSG	R MSG
6	CHNGEWRIT	PRAM	0
7	MONREQ	REQ	0
10	CABORT	0	T/F
11	CRESET	0	0
12	CSDATR	R MSG	
13	CSREREAD		

MMSTAT Event Group 19

Event 191 (X277)

EVENT NAME: DISKINTRPT
DESCRIPTION: A 7905/7920 CONTROLLER IS PROCESSING AN ATTENTION INTERRUPT
(ONLINE/OFFLINE)
CALLING MODULE: MAADRES

CALLING PROCEDURE: SIODM

PARAMETERS	PARAMETER DESCRIPTION
P1= @DITP	(US)--i.e. WHO GOT THE INTERRUPT
P2= @DITP	(THEM)--i.e. WHO RAN THE POLL PROGRAM
P3= DITP	"OUR" DIT FLAGS WORD

THERE SHOULD BE AT LERST AN X300 AND AN X303 FOR EACH SIO PRGM.
A SINGLE ISOLATED (IN TIME) REQUEST WILL GENERATE AT LEAST A
X303, X300, X303. IF THE QUEUE OF IOQ'S ON A DIT NEVER EMPTIES,
THERE WOULD BE ONE X300 AND ONE X303 PER SIO PRGM.

Event 192 (X300)

EVENT NAME: GIPINTERRUPT
DESCRIPTION: INTERRUPT JUST PROCESSED

CALLING MODULE: HARDRES

CALLING PROCEDURE: GIP

PARAMETERS		PARAMETER DESCRIPTION
P1	=	LDEV
P2	=	QUEUE ELEMENT WORD ENTRY INDEX
P3	=	CONTENTS OF DIT WORD 0: THE FLAGS WORD
P4	=	CHANNEL PROGRAM INSTRUCTION POINTER
P5	=	CONTROLLER STATUS
P6	=	LSW of a Return from TIMER

Event 193 (X301)

EVENT NAME: STARTIO
DESCRIPTION: Issuing SIOP machine instruction.

CALLING MODULE: MARDRES

CALLING PROCEDURE: START'MPIB, STARTIO

PARAMETERS		PARAMETER DESCRIPTION
P1	=	Absolute address of SIO program to start.
P2	=	LDEV number
P3	=	CRT number
P4	=	Q'ENTRY'INDEX FROM DITP(DIOQP)
P5	=	DIT WORD 0: THE DIT FLAGS WORD
P6	=	LSW of A RETURN FROM A CALL TO TIMER

Event 194 (X302)

EVENT NAME: SIODM-ENTRY
DESCRIPTION: Entering SIODM

CALLING MODULE: HARDRES

CALLING PROCEDURE: SIODM

PARAMETERS		PARAMETER DESCRIPTION
P1	=	LDEV
P2	=	IOQ OR DRQ table relative index
P3	=	DIT WORD 0 (DIT FLAGS)
P4	=	CURRENT STATE OF THE VARIABLE STATE IN SIODM
P5	=	UNUSED AT THIS TIME
P6	=	LSW RETURNED BY CALL TO TIMER

Event 195 (X303)

EVENT NAME: SIODM-EXIT
DESCRIPTION: Leaving SIODM main loop.

CALLING MODULE: HARDRES

CALLING PROCEDURE: SIODM

PARAMETERS	PARAMETER DESCRIPTION

SAME AS EVENT 194 (X302)
EXCEPT THAT EVENT IS 195 (X303)

MMSTAT Event Group 20

THESE EVENTS ARE FOR DEVELOPMENT USE ONLY AND ARE NOT NORMALLY ENABLED

Event 200 (X310)

EVENT NAME: DISKBUGCATCHER
DESCRIPTION: A MOUNTED VOLUME TABLE CHANGE IS BEING MADE.

CALLING MODULE: PVSYS

CALLING PROCEDURE: MVTABLE

PARAMETERS	PARAMETER DESCRIPTION
P1= FUNCT	0 = DELETE ENTRY 1 = ADD ENTRY 2 = PRESERVE ENTRY
P2= MVTABX	(MOUNTED VOLUME TABLE INDEX)
P3= DELTAP	(VALUE OF Q-2)

Event 201 (X311)

EVENT NAME: DISKBUGCATCHER
DESCRIPTION: A PRIVATE VOLUME USER TABLE CHANGE IS BEING MADE.

CALLING MODULE: PVSYS

CALLING PROCEDURE: USERTABLE

PARAMETERS	PARAMETER DESCRIPTION
P1= FUNCT	0 = CREATE USER ENTRY 1 = RENAME USER ENTRY 2 = RETURN ALL MVTABX INDICES USED BY A SPECIFIC PCB 3 = RETURN ALL PCB POINTERS USING A SPECIFIC MVTABX 4 = GET USER ENTRY
P2= MVTABX	(MOUNTED VOLUME TABLE INDEX)
P3= DELTAP	(VALUE OF Q-2)

MMSTRT Event Group 21 Process Creations and

Terminations Logical Process Table

Event -211 (X323)

EVENT NAME: PROCESS COMPLETION
DESCRIPTION: PROCESS HAS TERMINATED

CALLING MODULE: MORGUE

CALLING PROCEDURE: TERMINATE

PARAMETERS PARAMETER DESCRIPTION

P1=0
P2=0
P3=0

MMSTAT Event Group 22

Time Stamp of Event Trace Enable and Disable

Event 221 (X335)

EVENT NAME: CONFIGURATION INFORMATION
DESCRIPTION: EVENT GROUP MASK

CALLING MODULE: CAIO

CALLING PROCEDURE: CONSMON

PARAMETERS PARAMETER DESCRIPTION

P1= MEASMSK0

P2= MEASMSK1

P3=Reserved

Event 222 (X336)

EVENT NAME: CONFIGURATION INFORMATION
DESCRIPTION: MPE VERSION FIX UPDATE

CALLING MODULE: OPCOMMAND

CALLING PROCEDURE: CXMON

PARAMETERS PARAMETER DESCRIPTION

P1= VERSION

P2= FIXL

P3= UPDATEL

Event -223 (-X337)

EVENT NAME: CONFIGURATION INFORMATION
DESCRIPTION: SYSTEM TABLE LOCATIONS AND AVAILABLE LINKED MEMORY
INFORMATION
CALLING MODULE: OPCOMMAND

CALLING PROCEDURE: CXMON

PARAMETERS PRRAMETER DESCRIPTION

P1=F (X1032)=@CST(0)-@OST(0)
=DISPLACEMENT TO CODE
P2=F(X1033)=@CST(LAST)-@OST(0)
=DISPLACEMENT TO SHRRABLE
P3=LOGICAL(TOTAL&DLSK(4))=LINKED MEMORY SIZE

Event -224 -(X340)

EVENT NAME: SYSPINS
DESCRIPTION: LOGICAL PROCESS TABLE

CALLING MODULE: OPCOMMAND

CALLING PROCEDURE: CXMON

PARAMETERS PARAMETER DESCRIPTION

P1=ABSOLUTE(X1141)=PROGEN'S PCBENTRY NUMBER
P2=ABSOLUTE(X1142)=MAM'S PCB ENTRY NUMBER
P3=ABSOLUTE(X1143)=UCOP'S PCB ENTRY NUMBER

Event -225 (-X341)

EVENT NAME: SYSPINS(CNTD.)
DESCRIPTION: LOGICAL PROCESS TABLE

CALLING MODULE: OPCOMMAND

CALLING PROCEDURE: CXMON

PARAMETERS PPARAMETER DESCRIPTION

P1=ABSOLUTE(X1144)=PFAIL'S PCB ENTRY NUMBER
P2=ABSOLUTE(X1145)=DEVREC'S PCB ENTRY #
P3=ABSOLUTE(X1146)=PRMSG'S PCB ENTRY #

Event -226 (-X342)

EVENT NAME: SYSPINS(CNTD.)
DESCRIPTION: LOGICAL PROCESS TABLE

CALLING MODULE: OPCOMMAND

CALLING PROCEDURE: CXMON

PARAMETERS PARAMETER DESCRIPTION

P1=ABSOLUTE(X1147)=STMSG'S PCB ENTRY #
P2=ABSOLUTE(X1150)=LOG'S PCB ENTRY #
P3=ABSOLUTE(X1151)=LOAD'S PCB ENTRY #

Event -227 (-%343)

EVENT NAME: SYSPINS(CNTO.)
DESCRIPTION: LOGICAL PROCESS TABLE

CALLING MODULE: OPCOMMAND

CALLING PROCEDURE: CXMON

PARAMETERS DESCRIPTION

P1=ABSOLUTE(%1152)=IOMESSPROC'S PCB ENTRY #
P2=ABSOLUTE(%1153)=SYSIOPROC'S PCB ENTRY #
P3=RBSOLUTE(%1154)=MEMLOGP'S PCB ENTRY #

Event -228 (%344)

EVENT NAME: TIMESTAMP
DESCRIPTION: TIMESTAMP

CALLING MODULE: DPCOMMAND

CALLING PROCEDURE: CXMON

PARAMETERS DESCRIPTION

P1=CALENDAR (0:7)=YEAR OF CENTURY
(7:9)=DAY OF YEAR
P2=CLOCK(WORD1).(0:7)=HOUR OF DAY
(8:8)=MINUTE OF HOUR
P3=CLOCK(WORD2).(0:7)=SECONDS INTO MINUTE
.(8:8)=TENTHS OF SECONDS

Event -229 (-%345)

EVENT NAME: MONOFF
DESCRIPTION: END EVENT TRACING

CALLING MODULE: DPCOMMAND

CALLING PROCEDURE: CXMON

PARAMETERS DESCRIPTION

P1=0
P2=0
P3=0

MMSTAT Event Group 23 (Terminal I/O)

Event 230 (%346)

EVENT NAME: TERMREAD
DESCRIPTION: TERMINAL READ COMPLETION

CALLING MODULE: HARDRES
CALLING PROCEDURE: TIP

PARAMETERS PARAMETER DESCRIPTION

P1 = LDEV
P2 = READ DURATION
P3 = BYTES READ

Event 231 (%347)

EVENT NAME: DC1DC2RCK
DESCRIPTION: DC1/DC2 HAS BEEN SATISFIED

CALLING MODULE: HARDRES
CALLING PROCEDURE: TIP

PARAMETERS PARAMETER DESCRIPTION

P1 = LDEV
P2 = DURATION (BETWEEN START AND DC2)
P3 = BYTES READ (EXCLUDING DC2)

Event 232 (%350)

EVENT NAME: TERMWRITE
DESCRIPTION: WRITE COMPLETION

CALLING MODULE: IOTERMO
CALLING PROCEDURE: TERMIOM

PARAMETERS PARAMETER DESCRIPTION

P1 = LDEV
P2 = 0
P3 = BYTE COUNT OF TRANSFER

Event 233 (%351)

EVENT NAME: BINREAD
DESCRIPTION: BINARY READ COMPLETED

CALLING MODULE: HARDRES
CALLING PROCEDURE: TIP

PARAMETERS PARAMETER DESCRIPTION
P1 = LDEV
P2 = DURATION
P3 = BYTES READ

Event 234 (%352)

EVENT NAME: TERMLOGON
DESCRIPTION: TERMINAL JUST LOGGING ON

CALLING MODULE: IOTERMO
CALLING PROCEDURE: TERMIOM

PARAMETERS PARAMETER DESCRIPTION
P1 = LDEV
P2 = 0
P3 = 0

Event 235 (%353)

EVENT NAME: TERMLOGOFF
DESCRIPTION: TERMINAL JUST LOGGED OFF

CALLING MODULE: IOTERMO
CALLING PROCEDURE: TERMIOM

PARAMETERS PARAMETER DESCRIPTION
P1 = LDEV
P2 = 0
P3 = 0

Event 236 (%354)

EVENT NAME: SPECCHAR
DESCRIPTION: PROCESSED SPECIAL CHARACTER

CALLING MODULE: MARORES
CALLING PROCEDURE: TIP

PARAMETERS PARAMETER DESCRIPTION
P1 = LDEV
P2 = SPECIAL CHARACTER PROCESSED
P3 = 0

Event 237 (%355)

EVENT NAME: BREAK
DESCRIPTION: PROCESSED BREAK

CALLING MODULE: MARORES
CALLING PROCEDURE: TIP

PARAMETERS PARAMETER DESCRIPTION
P1 = LDEV
P2 = DSTATE
P3 = 0

Event 238 (%356)

EVENT NAME: SPECREAD
DESCRIPTION: SPECIAL READ TERMINATION CHARACTER DETECTED

CALLING MODULE: MARORES
CALLING PROCEDURE: TIP

PARAMETERS PARAMETER DESCRIPTION

P1 = LDEV
P2 = DURATION
P3 = BCNT

MMSTAT Event Group 24 (Power Fail)

Event 240 (%360)

Event Name: PFAIL
Description: Power fail detected.
Calling Module: ININ, PFAIL
Calling Procedures: Powerup (ININ), Powerup (PFAIL)

Parameter Description

P1 = 0 Called from Powerup in ININ
1 Called from entry in Powerup in PFAIL
2 Called from end of Powerup in PFAIL

P2 = For P1=0 this is 0
For P1=1,2:
TRUE = Multiple powerfail
FALSE= First powerfail

P3 = PF
0 = No powerfail or PFAIL processing complete
1 = Set by the power down trap in ININ
2 = Set by the power up trap in ININ
3 = Set when awake the PFAIL process
4 = Set by PFAIL after message appears on console

P4 = SYSUP
0 = System not back up after powerfail
1 = System back up after powerfail

P5,P6 not used.

CHAPTER 21 ROOTFILE LAYOUT

General Rootfile Layout



The data base ROOT FILE is an MPE file with filecode equal to -400. The record size is 128 words, fixed, binary format with a blocking factor of 1. The size of the file depends on the number of data items and data sets defined in the data base.

Root File Label 0

			%
WORD 0	AL'CONDITION	(rootfile condition)	0
1	RL'DATE	(creation date)	1
2	RL'TIME	(creation time)	2
3			3
4	RL'EVEROPEN		4
5	RL'COLDLOADID	(cold load id)	5
6	RL'USERCOUNT		6
7	RL'DBCBDSTNUM	(DST number of DBCB)	7
8	RL'LOGID	(log id for transaction logging)	10
.			.
.			.
11			13
12	AL'LOGPASS	(log id password)	14
.			.
.			.
15			17
16	AL'FLAGS	(database flags)	20
17	RL'STORDATE	(DBSTORE date)	21
18	AL'STORTIME	(DBSTORE time)	22
19			23
20	AL'BUFSPECCOUNT	(buffer spec count)	24
21	RL'ILRCREATEDATE	(date ILR log created)	25
22	RL'ILRCREATETIME	(time ILR log created)	26
23			27
24	RL'ILRLASTDATE	(last log access date)	30
25	RL'ILRLASTTIME	(last log access time)	31
26			32
27	RESERVED FOR FUTURE USE		33
. .			. .
63			77
64	RL'MAINTWORD	(database maintenance word)	100
.			.
.			.
67			103
68	RL'BUFFERSPECS	(buffer specifications)	104
to			.
127			177

AL'CONDITION (IN ASCII):
- JB - Virgin. The database has not been created yet.
- FW - OK. The database is OK.
- AM - Modified deferred. The database is being modified.
- MC - Maintenance create. The database is being created.
- ME - Maintenance erase. The database is being erased.
- IL - ILR recovery in progress.

Root File Label 0 (cont.)

RL'DATE: Root file creation date*. Its format is:

0:1	2:3	4:5	6:7	8:9:10:11:12:13:14:15
year			day_of_year	

AL'TIME: Root file creation time*. Its format is:

0:1	2:3	4:5	6:7	8:9:10:11:12:13:14:15
hour			minutes	
seconds			tenth_of_seconds	

AL'EVEROPEN: This field is no longer used under IMAGE B

AL'FLAGS:
- (0:1) - RECOVERY Default is NO (0)
- (1:1) - LOGGING Default is NO (0)
- (2:1) - ACCESS Default is YES (1)
- (3:1) - DUMPING Default is NO (0)
- (4:1) - RESERVED-FOR-FUTURE-USE
- (5:2) - SUBSYSTEM ACCESS Default is R/W (00)
- (7:1) - ILR Default is NO (0)
- (8:2) - RESERVED-FOR-FUTURE-USE
- (10:1)- DIRTY FLAG Default is YES (1). This indicates the database has been modified but not DBSTOREd.
- (11:5)- RESERVED-FOR-FUTURE-USE

AL'STORDATE: Same format as RL'DATE*.

AL'STORTIME: Same format as RL'TIME*.

AL'BUFSPECCOUNT: Maximum number of buffer specifications allowed.

RL'ILRCREATEDATE: Same format as AL'DATE*.

RL'ILRCREATETIME: Same format as AL'TIME*.

AL'ILRLASTDATE: Same format as RL'DATE*.

RL'ILRLASTTIME: Same format as RL'TIME*.

RL'MAINTWORD: For data bases with no maintenance word this field has 2 semicolons (';;') and trailing blanks.

RL'BUFFSPECS:

BIT/	0:1	2:3	4:5	6:7	8:9:10:11:12:13:14:15	%
WD 68	buffers_for_1 user		buffers_for_2 users			104
69	buffers_for_3 users		buffers_for_4 users			105
.	etc...					.
.						.
127	buffers_for_119 users		buffers_for_120 users			177

* The DATE and TIME fields can be formatted (for display purposes) individually by calling the FMTCALENDAR and FMTCLOCK Intrinsics respectively. Or both fields can be formatted at once with FMTDATE Intrinsic.

Root File Labels 1 & 2



The PASSWORD TABLE occupies user labels number 1 and 2.
There are four words (8 characters) reserved for each password. The relative position of a password corresponds to the user class number defined in the schema. For user class numbers not defined in the SCHEMA, the four word field is filled with blanks.

Root File Label 3



The ITEM READ/WRITE TABLE starts in user label #3
There are eight words for each ITEM READ/WRITE bit map.
For databases with more than 16 items, the read/write table continues in the next user labels. The specific format of this table is explained after the SET READ/WRITE TABLE since it is defined the same way.
The number of user labels occupied by the ITEM READ/WRITE TABLE depends on the number of data items defined in the schema and can be obtained by rounding upwards (ceiling)the result of:

Num-of-labels = [(Num-of-items)*8]/128

Since there can only be a maximum of 255 data items in the schema, the maximum size for this table in user labels would be:

Max-size = [(255)*8]/128 = 15.93 => 16 labels.

Root File- Next Label



The SET READ/WRITE TABLE starts on a user label boundary after the ITEM READ/WRITE TABLE.
There are eight words for each SET READ/WRITE bit map.
For databases with more than 16 data sets, the read/write table continues in the next user labels.
The specific format of this table is shown in the next page.

The number of user labels occupied by the SET READ/WRITE TABLE depends in the number of data sets defined in the schema, and is obtained by rounding upwards (ceiling) the result of:

Num-of-labels = [(Num-of-sets)*8]/128

Since there can only be a maximum of 99 data sets defined in the schema the maximum size for this table in user labels is:

Max-size = [(99)*8]/128 = 6.18 => 7 labels

Item/Set Read/Write Table Format

There are eight words per item/set read/write table definition and up to 16 items/sets per record (user label). Within each 8 words, the first 4 words are the flags for the user classes which have read access to the item/set. The second 4 words are the flags for the user classes which have write access to the item/set. The detail format for an eight word field is shown below.

A. Four words for read access:

4 words represent 64 bits. Bit n represents read access for user class n to the item/set. If bit n is set to 1 then user class n has read access to the item/set.
For example, if the word settings are:

word 1	word 2	word 3	word 4
%000016	%020000	%000410	%001300

This means that user classes 12, 13, 14, 18, 39, 44, 54, 56 and 57 have read access to the item/set.
If no read/write security is defined at all for the item/set, then all of the read security bits are set to 1.

B. Four words for write access:



Write access flags have the same format as the read access flags. Bit n represents write access for user class n to the item/set. If bit n is set to 1, then user class n has write access to the item/set
For example, if the word settings are:

word 1	word 2	word 3	word 4
%000010	%020000	%000000	%001100

This means that the user classes 12, 18, 54 and 57 have write access to the item/set.
If no read/write security is defined at all for the item/set, then all of the write security bits are set to 0.

Root File Record 0



RDOT'DBSTATUS
(0:8) - IMAGE version ('B' in ASCII)
(8:8) - Binary 1 (filler)

RDOT'DBNAME - DATABASE name left justified (last 2 chars are blank).

NOWDPEN - Number of data sets opened. This field is not used in IMAGE B

MAXDPEN - Maximun number of data sets that can be opened. This field is not used in IMAGE B.

NOTE:
RDOT'ITEMPTR and RDOT'DSETPTR is a word offset from record 0 (beginning of the file, not including the space taken by the user labels) and can span several records.
These pointers point to the 0th entry of the table and since the 0th entry in the item table or the set table does not really exist, they actually point to 11 words before the beginning of the table. To get to the first entry in the table, this pointer should be incremented by the length of the entry (which is currently 11 words).

Root File Record 1

The ITEM TABLE starts in record #1.
Each entry is 11 words long and the length of the table depends on the number of data items defined in the schema. The relative position of an item definition depends on its relative position in the schema.

Item-name: is a data item name, left-justified and with trailing blanks

Item-number-of-synonym: is the number of the item whose name has the same hashed result as this one (this is utilized for quick item name searches).

Item-type: is one of the following: I, J, K, R, X, U, Z, or P



The maximun size for this table is 11*255 = 2805wds

NOTES:
The reserved-1 and reserved-2 fields are the 'old' level numbers for read and write security. Now, the values are always zero.

Root File- Next Record

Set table follows the Iten table.

Each entry is 11 words long. The length of the table depends on the number of data sets defined in the schema. The relative position of a set definition depends on its relative position in the schema.

Set-name: is a data set name, left-justified and with trailing blanks.

Set-number-of-synonym: is the number of a data set whose name has the same hashed result as this one (this is utilized for quick set name searches).

Data-set-type is one of the following: A, M or D.

DSCB-pointer: is a pointer to the Data Set Control Block. This pointer is word offset fron record #0. The DSCB is described ahead.

The maximun size for this table is 11*99 = 1089wds.

NOTES: The reserved-1 and reserved-2 fields are the 'old' level numbers for the read and write access respectively. Since this concept no longer applies, the values are set to zero.

Data Set Control Blocks (DSCB)- General Layout



The DSCBs follow the SET TABLE in the Root file.
There is one DSCB for each data set defined. The function of the DSCB is to define each data set within the data base.

Data Set Control Block (Global Area)



DSCAP - data set capacity as reported by the SCHEMA processor.

DSBLOCKLGTH - data set block length including the bit map overhead.

DSMEDIALGTH - data set media record length (remember that this length includes the pointer overhead)

DSENTRYLGTH - data set entry length.

DSBLOCKFAC - data set blocking factor.

DSFIELDCT - data set field count. This is the number of fields specified for the data set.

DSPATHCT - data set path count. This is the number of paths that are specified for the data set.

X-DSKEYTYPE - data set key type. If DSKEYTYPE = TRUE then the key is hashed.

DSPRIMKEY - data set primary path or key.
For master data sets, this is the field number of the search item.
For detail data sets, this is the field number of the primary path.

DSPRTHPTR - data set path table pointer. Word offset to the data set path table which contains an entry for each path defined. It points to path 0th entry in the table, so to get to the first entry the pointer should be incremented by the length of the entry (which is currently 2 words).

Data Set Control Block (Item Numbers)

The Item Numbers Table follows the Global Area of the DSCB. The size of this table (in words) is equal to the number of items in the given data set plus 1. The first n bytes are used to carry the item numbers of the fields within the data set. The remaining n+2 bytes are set to binary zeros.

Data Set Control Block (Record Definition Item Displacement)

This table immediately follows the Item Numbers Table.

The word offset points to the starting location of the field within the media record. Remember that the media record includes the pointer overhead so this offset varies for master and detail data sets: if a master data set has only one path, the word offset for the first field is 10, since there are 10 words of overhead--5 words for the synonym chain pointers and 5 words for the data set chain head that it would be pointing to. On a detail data set with one path, the overhead is only 4 words.

The 'length-of-entry' field is the same as the media record length.

Data Set Control Block (Path Table)

There are 2 words (4 bytes) for each path definition.
The PATH TABLE for master data sets has a different layout from the PATH TABLE for detail data sets.

Master sets:
Byte Description
1 - item number of the search item in the related detail set.
2 - item number of the sort item in the related detail set.
3 - set number of the related detail data set
4 - path number of the corresponding path in the related detail data set.

Detail sets:
Byte Description
1 - field number of the search item.
2 - field number of the sort item.
3 - set number of the related master data set
4 - path number of the corresponding path in the related master data set.

General Data Set Layout

Data Set User Label 0

Word 0-1: Record name of the highest readable record. For Masters, this is the highest record in the set (i.e. Capacity). For Details, this is the greatest number of records that have been written to the set thus far. For example, if there is room in the Detail data set for 100 records and 75 were written last week when the data set was loaded with DBLOAD, and yesterday 15 records were deleted from the data set, the "High Water Mark" is equal to a value of '75'.

Word 2-3: Number of unused records in the data set. This field is incremented when a record is deleted and decremented when a record is added. To determine the current number of entries used in the set subtract Word 1-2 (unused count) from Word 0-1 (capacity).

Word 4-5: The delete chain head for Details. This points to the record most recently deleted or contains a value of zero if no records have been deleted. This field is not used in Master data sets.

Data Set Records

The data in the data set records is arranged according to the Media records. These are formatted by the Schema Processor (DBSCHEMA).

CHAPTER 22 DISC FREE SPACE MAP

Disc Resident Data Structures

There are two disc resident free space data structures, the bit map and the descriptor table, for each disc volume that has a free space map, i.e. system discs and private volumes. The addresses of these data structures are kept in the disc label. The symbols that define the descriptor table and bit map are in the include file INCLDFS2.

Bit Map

The bit map is divided up into pages, which is the physical block of the map that is read or written. At the moment, a page is defined to be one sector (128 words) long, this may be changed by changing a compile time constant. The last word of the page is a checksum for that page, all other words are data. There is a one to one correspondence between bits in the map and sectors of the disc. A one bit represents a free sector and a zero bit represents an allocated sector. The bit map is a contiguous set of pages, enough to represent the entire disc, excluding spare tracks and spare sectors.

Descriptor Table (DT)

The descriptor table is an array of three word entries, one entry for each page of the bit map. Each entry looks like this:

```
                =====================
                =                   =
word 0    =  largest space    =
                =                   =
                =====================
                =                   =
word 1    =  starting space   =
                =                   =
                =====================
                =                   =
word 2    =  ending space     =
                =                   =
                =====================
```

Thus the descriptor table looks like this.

```
      ------------
=         = entry for page 0
      ------------
```



```
=         = entry for page 1
      ------------
=         = entry for page 2
      ------------
=         = entry for page 3
      ------------
          .
          .
          .
      ------------
=         = entry for last page
      ------------
```

Each entry describes the free space on the corresponding page of the bit map. The largest space word is the size of the largest contiguous block of free space on the page, which is not at the very beginning or very end of the page. That is, the first bit physically representing the space is not the first bit of data on the page or the last bit representing the space is not the last bit of data on the page. Starting space is the number sectors of contiguous space represented by the set of bits whose first bit is the first bit of data on the page. Ending space is the number of sectors of contiguous space represented by the set of bits whose last bit is the last bit of data on the page. The starting space and ending space fields allow looking across page boundaries, thus preventing fragmentation on page boundaries. Thus, if all sectors represented on a page are free, then starting and ending space will be the same and have the total number of free sectors represented on the page. Largest space will be zero, as there is no block of space that is not at the beginning or end of the page. A value of - 1 for all the fields in an entry indicates the corresponding page is bad, either from a checksum or I/D error.

Virtual Memory Resident Data Structures

For each system disc or physically mounted private volume there is a data segment which has information about the disc free space map, the current copy of the descriptor table, some work space for the procedures while in split stack mode and buffers for pages of the bitmap. The DST number of the data segment for a given disc is found in the LDTX entry for that disc.

Disc Free Space Data Segment

For each system disc or physically mounted private volume in the up and running system there is a DST which contains information about the disc free space map for that disc, some work area, a copy of the descriptor table and buffers for the pages of the bit map. All symbols that define these data segments are in the include file INCLDFS1, and they are prefixed with "ds'". The structure of the data segment is as follows:

```
                ==================================
0 (%0) =              ds'ldev               =
```



```
                =----------------------------------=
 1 (%1) =              ds'dst                =
                =----------------------------------=
 2 (%2) =                                    =
                =--------- ds'disc'size ----------=
 3 (%3) =                                    =
                =----------------------------------=
 4 (%4) =         ds'last'page'of'map        =
                =----------------------------------=
 5 (%5) =        ds'last'buffer'index        =
                =----------------------------------=
 6 (%6) =                                    =
                =-------- ds'map'address ---------=
 7 (%7) =                                    =
                =----------------------------------=
 8 (%10) =             ds'lock               =
                =----------------------------------=
 9 (%11) =           ds'lock'count           =
                =----------------------------------=
10 (%12) =           ds'queue'head           =
                =----------------------------------=
11 (%13) =           ds'queue'tail           =
                =----------------------------------=
12 (%14) =        ds'descriptor'table        =
                =----------------------------------=
13 (%15) =       ds'buffer'page'number       =
                =----------------------------------=
14 (%16) =           ds'buffer'dirty         =
                =----------------------------------=
15 (%17) =           ds'buffer'area          =
                =----------------------------------=
16 (%18) =      ds'first'threshold'page      =
                =----------------------------------=
17 (%21) =                                  =
                =-- ds'size'of'last'allocation --=
18 (%22) =                                  =
                =----------------------------------=
```



```
                =----------------------------------=
19 (%23) =   ds'last'page'allocated'from   =
                =----------------------------------=
20 (%24) =       ds'next'buffer'index       =
                =----------------------------------=
21 (%25) =          ds'page'number          =
                =----------------------------------=
22 (%26) =          ds'word'number          =
                =----------------------------------=
23 (%27) =           ds'bit'number          =
                =----------------------------------=
24 (%30) =          ds'page'pointer         =
                =----------------------------------=
25 (%31) =     ds'starting'word'number      =
                =----------------------------------=
26 (%32) =     ds'starting'bit'number       =
                =----------------------------------=
27 (%33) =                                  =
                =----- ds'number'of'sectors  -----=
28 (%34) =                                  =
                =----------------------------------=
29 (%35) =           ds'bit'count           =
                =----------------------------------=
30 (%36) =          ds'entry'type           =
                =----------------------------------=
31 (%37) =          ds'buffer'index         =
                =----------------------------------=
32 (%40) =                                  =
                =-------- ds'disc'address --------=
33 (%41) =                                  =
                =----------------------------------=
34 (%42) =          ds'error'status         =
                =----------------------------------=
```

The rest of the data segment contains tables whose size and location is dependent on the size of the disc and or the number of buffers in the data segment. They are shown below just to demonstrate there relation to one another, for there actual location, the pointers should be examined. The symbol "ds'array'area" defines the start of the area. The first table is the descriptor table, it is in the same format as the disc copy, but a dummy entry of all zeros is added before and after the table, these are needed by procedures "Find'Page" and "Build'Descriptor'Entry". The pointer to this table is "ds'descriptor'table", it points to the entry for page zero, not the dunny entry.



The next table is ds'buffer'page'number table, it has a one word entry for each buffer in the data segment. Each entry contains the page number of the page currently in the corresponding buffer or -1 if the buffer is empty. This is pointed to by "ds'buffer'page'number".





The next table is the ds'buffer'dirty table, which has a one word entry for each buffer. A TRUE indicates the page in the corresponding buffer is dirty, i.e. the disc copy is not up-to-date. A FALSE indicates that the buffer is clean. If DFS was compiled with dirty buffer management turned off, this table is not present and the ds'buffer'dirty pointer is zero.



The remainder of the data segment contains the buffers, each buffer is the size of one page of the bit map, which is currently one sector(128 words). The beginning of the buffer area is pointed to by "ds'buffer'area" and the number of buffers is the value in "ds'last'buffer'index" plus one.





Each of the fields of the data segment is described in the include file INCLDFS1, where they are defined. It should be noted that the following fields are just workspace, used to pass information between procedures while in split stack mode and have no meaning between calls to the disc free space management subsystem:

ds'page'number	ds'word'number
ds'bit'number	ds'page'ptr
ds'starting'word'number	ds'starting'bit'number
ds'number'of'sectors	ds'entry'type
ds'bit'count	ds'buffer'index
ds'disc'address	

The field ds'error'status normally has no meaning between calls unless the error'type field has a value greater than "fatal'dfs'error", in which case it means that disc space may no longer be allocated on this disc.

CHAPTER 23 MPE DISC CACHING

Disc Caching Overview

Disc Caching is an optional feature of MPE that utilizes excess main memory and excess CPU horsepower to keep portions of frequently referenced disc "domains" in memory. (A disc "domain" is a copy of a portion of disc residing in main memory. These disc domains are considered "cached" when they are in memory and are considered "mapped" when there is I/O pending against them.) Disc Caching manages the bi-directional transfer of these disc domains between main memory and disc storage. No main memory is permanently dedicated to cached disc domains. Cached disc domains share main memory with all other types of MPE segments and are not treated differently by the memory manager. By keeping cached disc domains in memory, a significant portion of the references to disc storage can be resolved without actually having to physically access the disc. Disc Caching policies are integrated into the MPE Kernel, File System, and I/O System which allows the system performance to be tuned based on the current workload and resource availability.

Disc Caching uses the MPE kernel resource management mechanisms and strategies. These mechanisms are extended to handle cached disc domains in the same manner as segments. Thus, cached disc domains can be of variable size, fetched in parallel with other segments or cached domains, garbage collected, and replaced in the same manner as stacks, data and code segments. The relative use of main memory between stacks, data and code segments, and cached disc domains is dynamic. This partitioning is based on the workload's current requirements and current memory availability.

Disc Caching can be enabled/disabled on a disc by disc basis. When caching is enabled for the first disc, the code segment containing the Disc Caching code will be locked into memory. Also at this time the Cache Directory Table (CDT) will be built and locked into memory. When caching is disabled for the last disc, the code segment will be unlocked from memory and the CDT will be released. Thus if caching is not enabled no memory will be wasted.

The CDT is used to keep track of the following information:

1) The disc ldevs currently enabled for caching. There will be a Device Entry in the table for each cached disc.

2) A linked list of cached domains for each disc with caching enabled. The head and tail of this linked list will be contained in the Device Entry. (I.e. there is a separate linked list of cached domains for each cached disc ldev.)

3) The cached domains that currently have user I/O pending (i.e. FREADS/FWRITES) or have memory management I/O pending (i.e. fetching the disc domain into memory, or posting the disc domain back out to disc). There will be a Mapped Domain Entry in the table for each disc domain has that I/O pending and is thus "mapped".

4) A linked list of all user I/O pending against the mapped disc domains. There will be a Logical Disc Request (LDR) queued to the Mapped Domain entries that will describe the user I/O to take place. This is analogous to a Disc Request queued to a specific DIT waiting for service.

When a request is made to access disc information, Disc Caching must first determine if the requested disc domain is present in memory. Disc Caching will first determine if the requested area of disc is already mapped into memory by scanning through the Mapped Domain entries of the CDT. If the requested transfer can be satisfied with a currently mapped disc domain, then the I/O request will be queued (FIFO) behind the other I/Os pending against that mapped domain. If the requested area is not already mapped, then a search is made through the linked list of cached disc domains for the specified disc ldev. (The region header contains the disc address and size that a disc domain represents.) If the requested domain is found in this list (i.e. present in memory), then this region will be mapped. A domain is then considered mapped when there is an entry for it in the Mapped Domain portion of the CDT. Mapping the domain allows Disc Caching to manage the I/O pending and/or currently active for a particular disc domain. Once the disc domain is mapped and present, the data can be moved between the process' data area and the mapped disc domain. The process can then continue executing without interruption or a process switch. The user/subsystem process for which the move is done will be charged with the CPU overhead.

When a request is made to read data that is not currently cached in memory (i.e. a read "miss"), the fetch strategy uses the File System's knowledge of the type of access (sequential or random), the extent size of the file, along with the current memory load to select the optimal size of the disc domain to be fetched and mapped into memory. The fetch of the disc domain is then initiated on the user's stack without a process switch. After the fetch is initiated, it completes in an unblocked manner so that this process (if no-wait I/O) or another process can proceed in parallel with the cache fetch.

In general, when writing, a process will not wait for completion of the physical I/O. Instead, the process will be awakened as soon as the transfer has completed between the process's data area and the mapped disc domain (i.e. no-wait-for-post). The physical I/O will then be posted at background priority while the process continues. (Users can specify wait-for-post on a file by file basis in place of the default no-wait-for-post with the FSETMODE intrinsic. This can be done on a global basis via :CACHECONTROL.) If the access request is a write and there is a current write pending against the specified mapped disc domain, the process request is queued until the pending write is posted to disc. If the disc domain to be written is not currently cached in memory, a free piece of memory will be obtained to map the corresponding disc image and then the "write" takes place from the process' data area to the mapped disc domain. This prevents data from having to be read before being written. After that, a post to disc is initiated (on any write only the portion of a mapped disc domain that is modified will be posted to disc). After the move to the mapped disc domain is complete and the post to disc is initiated, the process performing the "write" is allowed to continue to run without having to wait for the post to complete. Writes that must be posted to disc in a certain order use the Global Serial Write Queue. These

ordered writes include things like updating disc free space maps for a new file extent before updating the file extent map in the file label.

There are two disc request entries used for disc caching requests. The first entry is a Logical Disc Request (LDR) entry and is used to manage the data moves to/from the user's data area and the disc domain (i.e. the logical I/O). The second entry is a regular Disc Request (DRQ) entry and is used to perform the physical I/O necessary to map a disc domain (for a read "miss") or to perform the physical post (on write requests). The disc domain will remain mapped until both the logical and physical I/O completes. If a request is not completely described by one disc domain already in memory or a Mapped Domain CDT entry (i.e. the requested disc area falls into more than one disc domain) then the overlapping disc domain(s) will be flushed to disc and the new complete disc domain will be fetched (if read) and mapped - no partial mappings are allowed.

The DST number of the Cache Directory Table (CDT) is at %1273 and the bank and offset are kept in %1274-%1275. The Caching Sir (2) is used when starting and stopping caching (via :STARTCACHE/:STOPCACHE) and by the LOADER when loading a program file (this sir is only used when updating the STT at load time).

When caching is enabled for a disc, a bit in the flags word of the DIT is set. Also, the Global Serial Write queue can be found by examining the header entry of the Disc Request Table. See Chapter 13 for a more detailed explanation of both the DIT and the Disc Request Table header. See Chapter 2 for a description of the Memory Region Header for a disc domain (cached region).

Disc Caching Tables Overview



Memory Regions



Cache Directory Table

The Cache Directory Table (CDT) is the bookkeeping structure for managing cached disc domains. This table is divided into 3 parts:

CDT Header Entry
This entry contains all information necessary to manage the entire table and also contains global caching related information.

CDT Device Entry
There will be one of these entries for every disc ldev that currently has caching enabled. These entries keep track of all cached disc domains in memory for this device. In addition, these entries contain statistics regarding the number of I/Os performed to the ldev.

CDT Mapped Domain Entry
These entries describe disc domains that are currently "mapped" into memory. This means that there is logical I/O (cache move) and/or physical I/O (fetch or post) pending. These entries keep track of the state of the cached disc domain (IMI, RDC, etc.) just as the DST Table keeps track of data segments.

The following low core cells contain the address of the CDT:

%1273	contains the DST Number of the CDT
%1274	contains the Bank Number of the CDT
%1275	contains the Offset within the bank of the CDT

Header Entry

0	# Entries	CDT'ENTRIES
1	Entry Size (%30)	CDT'SIZE
2	# Free Entries	CDT'FREE'COUNT
3	1st Free Entry (table offset)	CDT'FREE'HERD
4	Last Free Entry (table offset)	CDT'FREE'TRIL
5	Max # Entries Used	CDT'MAX'USED
6	# Ldevs cached	CDT'NUM'LDEVS
7	1st Cache device entry (entry number)	CDT'DISC'HERD
%10	# Words this DST	CDT'DST'WORDS
%11	TRUE if stopcache pending	CDT'STOP'PND
%12	# Sectors sequential fetch	CDT'SEQ'MIN'FTCH
%13	# Sectors random fetch	CDT'RND'MIN'FTCH
%14	TRUE if wait for physical post	CDT'FORCE'POST
%15	Head of impeded queue (PIN)	CDT'STOP'QUEUE
%16	. . .	
%27		

CDT'ENTRIES
The total number of CDT entries configured in this table (i.e. includes all three types of entries). The number of entries in the table will be:
1 entry for the header
+ 1 entry for each disc ldev configured.
(CDT Device entries)
+ 1 entry for each DRQ configured.
(CDT Mapped Domain entries)

This scheme insures that this table can never overflow (since an entry in the DRQ table is always obtained before an entry in this table).

CDT'SIZE
Size of each entry in the table.

CDT'FREE'COUNT
Total number of entries currently unassigned.

CDT'FREE'HEAD
Table relative offset (i.e. Entry number * entry size) of the first available entry.

CDT'FREE'TAIL
Table relative offset of the last available entry.

CDT'MAX'USED
The maximum number of entries in use at one time.

CDT'NUM'LDEVS
The number of ldevs currently cached.

CDT'DISC'HERD
The entry number of the first Device Entry.

CDT'DST'WORDS
The total number of words in this data segment.

CDT'STOP'PND
This value will be TRUE if there is a pending :STOPCACHE.

CDT'SEQ'MINFTCH
If there is a prefetch for a sequential read ("miss"), the size of the prefetch is delimited by the extent size of the file. Within this limitation, the prefetch is equal to the greater of two sizes:
1) Requested size.
2) The largest integer multiple of the request size that is smaller than the value found in this cell.

The default value is 96 sectors. (This value may be changed via :CACHECONTROL).

CDT'RND'MINFTCH
This is the same as CDT'SEQ'MINFTCH except that it's for random access. The default value is 16 sectors. (This value may be changed via :CACHECONTROL).

CDT'FORCE'POST
When this value is TRUE, all writes will 'block' until the physical update on disc completes. The system default is FALSE. (Can be altered via :CACHECONTROL).

CDT'STOP'QUEUE
If CDT'STOP'PENDING is TRUE this will be the PIN number of the head pin of the processes impeded until the :STOPCACHE completes.

Device Entry

0	Next ldev entry (entry number)	CDT'DE'NXT'LDEV
1	Prev ldev entry (entry number)	CDT'DE'PREV'LDEV
2	Ldev for this disc	CDT'DE'LDEV
3	# Pages in device's domain	CDT'DE'MAPD'PAGES
4	# Disc domains currently mapped	CDT'DE'MAPD'CNT
5	Head of mapped domain (entry number)	CDT'DE'MAPD'HEAD
6	Tail of mapped domain (entry number)	CDT'DE'MAPD'TAIL
7	# Disc domain regions for this device	CDT'DE'REGIONS
X10	Memory address of head cached disc domain	CDT'DE'REG'HD
X12	Memory address of tail cached disc domain	CDT'DE'REG'TL
X14	# Read hits	CDT'DE'RHIT
X16	# Write hits	CDT'DE'WHIT
X20	# Read misses	CDT'DE'RMISS
X22	# Write misses	CDT'DE'WMISS
X24	# Stops	CDT'DE'STOP
X26	Memory address of last referenced domain	CDT'DE'SCANPT

CDT'DE'NEXT'LDEV
The entry number of the next Device Entry.

CDT'DE'PREV'LDEV
The entry number of the previous Device Entry.

CDT'DE'LDEV
The Ldev number for this cached device.

CDT'DE'MAPD'PAGES
Total number of main memory pages allocated to disc domains for this cached device. This includes mapped and unmapped regions. (1 main memory page = 128 words).

CDT'DE'MAPD'CNT
The total number of Mapped Domain entries associated with this Device Entry.

CDT'DE'MAPD'HEAD
The entry number of the first Mapped Domain entry for this device.

CDT'DE'MAPD'TAIL
The entry number of the last Mapped Domain entry for this device.

CDT'DE'REGIONS
The total number of disc domain regions for this ldev (includes mapped and unmapped regions).

CDT'DE'REG'HD
Memory address to the head region of the disc domain linked list. Disc domain regions are linked in order based on the disc address they represent (i.e. small disc address at head, large disc address at tail). This address will not point to the region base (RB), but to the next domain (ND) field of the region header. (This is to facilitate the use of the LLSH instruction).

CDT'DE'REG'TL
Memory address of the tail region of the disc domain linked list. This address will be of the previous domain (PD) field of the region header.

CDT'DE'RHIT
Total number of times that a read was requested and the requested disc domain was present in memory - i.e. a read "hit". This means that the read completed without performing any I/O (to fetch the domain). Thus this is actually the number of read I/Os eliminated. This value will reset to zero on overflow.

CDT'DE'WHIT
Total number of times that a write was requested and the requested disc domain was present in memory - i.e. a write "hit". If there was no other write pending to the "hit" domain, then the process would continue as soon as the cache move completes - thus eliminating a block for I/O. Otherwise, the process would block waiting for the first write to complete. This value will reset to zero on overflow.

CDT'DE'RMISS
Total number of times that a read was requested and the requested disc domain was not in memory - i.e. a read "miss". This means that the requested disc domain had to be fetched into memory before the read could complete - thus potentially blocking the process. This value will reset to zero on overflow.

CDT'DE'WMISS
Total number of times that a write was requested and the requested disc domain was not in memory - i.e. a write "miss". This does not mean that the process would block until the disc domain is fetched as is the case for reads. Rather, a free memory region would be obtained to be the destination of the cache move. This disc domain would then be posted in the background (unless overridden via :CACHECONTROL or RSEMODE) allowing the process to continue without blocking. This value will reset to zero on overflow.

CDT'DE'STOP
Total number of times that a process had to block on a cache transfer. Will reset to zero on overflow.

CDT'DE'SCANPT
The memory address of the last region looked at on a search. This address will be of the next domain (ND) field of the region header. This value will be used along with CDT'DE'REG'HD to determine where to start the next search for a cached disc domain. At times it will be more efficient to start with this address since the disc domain requested may be of a higher disc address than found in this region header, rather than always starting the search with CDT'DE'REG'HD.

Mapped Domain Entry



CDT'MD'PREV
Entry number of the previous mapped domain entry for this device.

CDT'MD'NEXT
Entry number of the next mapped domain entry for this device.

CDT'MD'SECTOR
The starting disc sector address representing this mapped domain entry.

CDT'MD'END'SECTOR
The ending disc sector address representing this mapped domain entry.

CDT'MD'FLAGS
Flags describing the state of this mapped domain entry and the region associated with it:

(0:1) - Absent.
Region is not present in memory.
(1:1) - INI.
Region is already In-Motion-In. (Set when the fetch for this cached region is initiated).
(2:1) - IMO.
Region is In-Motion-Out. (Set by STARTOBJWRITE when performing the background post of a cached region).
(3:1) - MISS.
This disc domain was not present and had to be prefetched.
(4:1) - LOCK. Not used.
(5:1) - FWIP.
Forced Write In Progress. Region was forced out of memory to make room for another object.
(6:1) - ROC.
Recover Overlay Candidate. Region may be forced out of memory to make room for another object. However, if this region is referenced again it can be recovered.
(7:1) - VIRGIN.
Clean region in the write state. Cleared as soon as a move completes. (I.e. if this bit is on, then a write can complete immediately. Otherwise the write will have to wait until the current write completes the physical post).
(8:1) - NOPOST.
Set when the CDT is being posted out as a result of a write request that did not want to wait for the physical post to complete. This will be cleared by the cache completor when the physical post completes. (This is used to insure that a cache move for any subsequent write request will not be serviced until the physical post completes.)
(9:1) - SEQ.
Set if doing sequential I/O. When the request for the last area of this disc domain is complete, this domain will be made a ROC.
(10:3) - Not used.
(13:3) - STATE
0 - AVAIL. CDT is an available entry.

1 - READ. Only read LDR(s) are attached.
2 - WRITE. Write LDR(s) and possibly read LDR(s) are attached.
3 - FLUSH. CDT is being flushed out.
4 - LOCK. Unused.

CDT'MD'READ'CNT
The number of LDRs attached that are for reads (move not complete).

CDT'MD'WRITE'CNT
The number of LDRs attached that are for writes. NOTE: This count will not be decremented until both the cache move and the physical write completes. However, as soon as the cache move completes, the LDR will be dequeued from the CDT.

CDT'MD'LKD'CDT
Not used.

CDT'MD'IMPED'HD
The first LDR that is impeded. (I.e. the CDT is in a write state already and another write is attached. The second write will be placed in this queue until the first write completes.)

CDT'MD'LDR'HEAD
The first LDR that is on the active list for this CDT.

CDT'MD'MEM'ADDR
The memory address (region base) for this mapped disc domain, if present.

CDT'MD'DISCREQ
The disc request table index associated with this mapped disc domain. This will be used to fetch this region in, or to post this region after any logical I/Os (writes) have completed. (I.e. this DRQ is used for the physical I/O.)

CDT'MD'LK'CNT
Not used.

CDT'MD'LDEV
The ldev number for this mapped domain.

CDT'MD'IMPEDED
The PIN for the first process impeded on this mapped disc domain. Processes get impeded here when they do WRITFORID when their LDR is on the CDT impeded queue and the Mapped Domain is currently being written out. (This will also happen upon a :STOPCACHE to force all LDRs to complete.) As soon as the physical post of the Mapped Domain is complete, all processes impeded here will be awakened.

CDT'MD'DE
The entry number for the Device entry that this Mapped Domain entry is associated with.

Logical Disc Request Table

X1017 Pointer to Logical Disc Request Table

NOTE:
This table is really part of the DRQ (Chapter 13). Any entry with the logical request bit set in the flags will conform to this format and not the format of the standard DRQ.

Logical disc requests entries are used to manage requests between the requesting process and a mapped disc domain. They are the counterpart of disc requests entries used to manage physical I/O requests between a process and a disc. These entries are kept as part of the DRQ Table, but will never be queued to the disc's DIT, instead they will be queued to the mapped disc domain CDT entry. LDR entries may only be placed onto the following queues:

1) The CDT active list.
2) The CDT impeded LDR list.
3) The Disabled Disc Request. (This will only happen if the buffer segment is absent when the logical I/O (cache move) is attempted.)

NOTE:
LDRs are singly linked onto the CDT queues and doubly linked onto the disabled disc request queue.

Logical Disc Request Entry



LDR'FLAGS
Flags.

(0:3) - Not used.
(3:1) - SBUF.
Set if request is to/from a System Buffer.
(4:1) - IOWAKE.
Set if system should wake up the process when the logical I/O completes.
(5:1) - BLOCKED.
Set if the process wants to wait for the logical disc request to complete.
(6:1) - DONE.
Set when the logical disc request is complete and the process will be awakened (if IOWAKE is set)
(7:1) - DO'POST.
Set if the caller wants to be waited until the physical post to disc completes. Only valid for write requests.
(8:1) - SERIAL'POST.
Set when the physical post should be through the Global Serial Write queue.
(9:1) - CDT'QUEUED.
This request has been queued - either onto the CDT active queue (see CDT Mapped Domain entries) or onto the disabled disc request list.
(10:1) - MOVE'DONE.
The move has been completed, but the process won't be awakened until the DONE bit is set.
(11:1) - Not used.
(12:1) - CUR'REQ.
Set if this request is the current/active request.
(13:1) - DISABLE.
Set if the request is disabled.
(14:1) - LDR'REQ.
Set if this is a logical disc request.
(15:1) - LDR'INLOC.
Set if Mapped Domain CDT entry is in process's locality list.

LDR'L'MODA
The High Order Disc Address of the extent linit. (See note with LDR'B'MODA).

LDR'LDEV
The ldev for this request.

LDR'CDT
The CDT number for the Mapped Domain entry associated with this request.

LDR'BUFDST
Data Segment number for the target of the logical I/O request. If bit zero is set, then this is the process's stack.

LDR'BUFADR
Offset within the DST (above) for the target address. If the DST is the process's stack, then this address will be DB relative.

LDR'STRAT'FUNC
(0:8) - Strategy
0 - Unknown caller
1 - Unknown File Systen
2 - Spooler
3 - Directory
4-7- Unknown caller
8 - Gennessage
9 - File Systen, Quiesce I/O
10 - File Systen, Sequential, No Buf
11 - File Systen, Direct, No Buf
12 - File Systen, Sequential, Buffered
13 - File Systen, Direct, Buffered
14 - File Systen, KSAM
15 - File Systen, IMAGE

(8:8) - Function
0 - Read
1 - Write

LDR'COUNT
On initiation, this specifies the requested transfer count (+words, -bytes). At completion of the request, this contains the actual transmission count (+words, -bytes).

LDR'PARM1
This is the High Order Disc Address of the requested disc sector.

LDR'PARM2
This is the Low Order Disc Address of the requested disc sector.

LDR'STATQ
Uniform status returns.

LDR'PCB
PIN of the requesting process.

LDR'PREVQ
Table relative index of the previous LDR in the queue. (NOTE: LDRs are singly linked on the CDT queues, and doubly linked on the disabled disc request queue).

LDR'NEXTQ
Table relative index of the next LDR in the queue.

LDR'B'MODA
The High Order Disc Address of the extent base. (Used when the logical disc request is through the file systen. Caching uses this information when searching memory for a "hit" on a cached domain).

LDR'B'LODA
The Low Order Disc Address of the extent base. (See note above).

LDR'L'LODA
The Low Order Disc Address of the extent limit. (See note above).

READER COMMENT SHEET

MPE V Tables Manual for MPE V/E, Version G.00.00

32033-90010 September 1984

We welcome your evaluation of this manual. It is one of several that serve as a reference source for HP 3000 Computer Systems. Your comments and suggestions help us to improve our publications and will be reviewed by appropriate technical personnel. HP may make any use of the submitted suggestions and comments without obligation.

Is this manual technically accurate?	Yes [] No []	(If no, explain under Comments, below.)
Are the concepts and wording easy to understand?	Yes [] No []	(If no, explain under Comments, below.)
Is the format of this manual convenient in size, arrangement and readability?	Yes [] No []	(If no, explain or suggest improvements under Comments, below.)

Comments:

We appreciate your comments and suggestions. This form requires no postage stamp if mailed in the U.S. For locations outside the U.S., your local HP representative will ensure that your comments are forwarded.

Date: _____

FROM:

Name _____

Company _____

Address _____

_____

_____

FOLD FOLD

NO POSTAGE
NECESSARY
IF MAILED
IN THE
UNITED STATES

BUSINESS REPLY MAIL

FIRST CLASS PERMIT NO. 1070 CUPERTINO, CALIFORNIA

POSTAGE WILL BE PAID BY ADDRESSEE

Documentation Manager/47U-91
Hewlett-Packard Company
Computer Systems Division
19447 Pruneridge Avenue
Cupertino, California 95014

FOLD FOLD

Part No. 32033-90010
Printed in U.S.A. 09/84
E2412

HEWLETT PACKARD